

Request for Quotation

Date:	21 Nov 2023	Project Number:	IE-230025
Contact:		Project Description:	Power Transformer Procurement

1 SCOPE

1. The specification (RFQ) covers the supply of new liquid-filled electricity pad-mounted transformers.
2. Manufacturer shall specify the transformer warranty
3. Transformers are expected to be supplied ASAP, supplier shall specify an approximate time of drawing submission in weeks after receipt of order (ARO).
4. Transformers are expected to be supplied ASAP, supplier shall specify an approximate time of delivery in weeks after receipt of approved drawings.
5. Supplier shall specify transformers' NO-LOAD LOSS AND LOAD LOSS. 需列出空载和负载损耗
6. All losses to be quoted at 100% rated voltage for three phase transformer and corrected to 85 °C.
所有损耗在三相变压器100%额定电压下报价，并校正到85°C。
7. All units have to be built as per the following specifications:
Current version of ANSI C57.12.00, C57.12.10, C57.12.20, C57.12.22, C57.12.38, C57.12.26, C57.12.70, C57.12.80, C57.12.90, . 需符合这些标准
8. Routine tests on the transformer shall be made as specified in Section 8 of the ANSI C57.12.00 latest revision thereof. ANSI Test Code C57.12.90 shall be followed for all testing procedures. Testing report shall be supplied. 变压器的常规试验应按照ANSI C57.12.00第8节的规定进行
9. Dielectric test shall be in accordance with ANSI Standard C57.12.26. 介电试验应符合ANSI标准C57.12.26。

2 PAD-MOUNTED TRANSFORMER SPECIFICATION:

Pad-mounted, 150 kVA, ONAN, PCB free (Qty: 1)

150kva 三相美变

- 3-phase, 60Hz
- Primary voltage: 13,200GrdY/7620 V
- Secondary voltage: 480GrdY/277 V
- Loop feed
- Five-legged core.
- Color: Munsell 7GY 3.29/1.5
- HV BIL: 95 kV
- LV BIL: 30 kV
- HV tap changer: 4-2.5% 2 Up, 2 Down

频率：60hz
一次电压：13,200GrdY/7620 V
二次电压：480GrdY/277 V
环网
五心柱铁芯
颜色：孟塞尔7GY 3.29/1.5
HV BIL: 95 kV
LV BIL: 30 kV
高压侧分接开关：±2*2.5%
冷却：ONAN
无PCB

- HV winding material: Copper 高压绕组材料：铜
- LV winding material: Aluminum 低压绕组材料：铝
- 65 °C on temperature rise 温升：65°C
- High voltage bushing: externally clamped, dead front with dust caps, 3 well, 15kV class, 200A 高压套管: 外夹紧, dead front带防尘帽, 3井, 15kV等级, 200A
- Low voltage bushing: externally clamped, 4 epoxy 4 hole spades 低压套管:外部夹紧, 4个环氧4孔铲式
- Bayonet fuses and current limiting fuses 刺刀熔断器和限流熔断器
- One (1) 2 position load break switch 一个(1)2位负载断开开关
- Oil level gauge, Thermometer, 1-inch drain valve with sampler 油位计, 温度计, 带采样器的1英寸放油阀

3

PAD-MOUNTED TRANSFORMER CONSTRUCTION:

1. Construction of the unit shall be such that it can be lifted, skidded, or slid into place on the mounting pad without disturbing previously installed entrance cable. (Unit must have removable doorsills).
2. A corrosion preventive undercoating over the regular finish shall be applied to all surfaces that are in contact with the pad to minimize corrosion. Paint shall be of such quality as to resist rust, fading, etc. for a minimum 10-15 years period.
3. Lifting provision shall be in accordance with ANSI C57.12.2.

1、变压器的构造应使其能够被提升、滑动或滑入安装垫上的适当位置，而不会干扰先前安装的入口电缆。(必须是可拆卸的门)。

2、所有与焊盘接触的表面都应在常规表面上涂防腐底漆，以尽量减少腐蚀。油漆的质量应能防止生锈、褪色等至少10-15年的期限。

3、起重装置应符合ANSI C57.12.2的要求。