GD54/74LS245

OCTAL BUS TRANSCEIVER; NON-INVERTED 3-STATE OUTPUTS

Feature

- Bidirectional Bus Transceiver in a High-Density 20-Pin Package
- · 3-State Outputs Dirve Bus Lines Directly
- . P-N-P Inputs D-C Loading on Bus Lines
- · Hysteresis at Bus Inputs Improve Noise Margins
- Typical Propagation Delay Times; Port to Port ...
 8 ns


Description

These octal bus transceiver are designed for asynchronous two-way communication between data buses. The control function implementation minimizes external timing requirements.

The device allows data transmission from the A bus to the B bus or from the B bus to the A bus depending upon the logic level at the directional control (DIR) input. The enable input (\overline{G}) can be used to disable the device so that the buses are effectively isolated.


Function Table

ENABLE G	DIRECTION CONTROL DIR	OPERATION				
L	L	B data to A bus				
L	Н	A data to B bus				
Н	X	Isolation				



Schematics of Inputs and Outputs

EQUIVALENT OF EACH INPUT TYPICAL OF ALL OUTPUTS



Absolute Maximum Ratings

•	Supply voltage, Vcc		/ V
•	Input voltage		7V
•	Off-state output voltage		5.5V
•	Operating free-air temperature range	54LS	-55°C to 125°C
		74LS	0°C to 70°C
•	Storage temperature range		-65°C to 150°C ▶

2-107

Recommended Operating Conditions

SYMBOL	PARAMETER		MIN	NOM	MAX	UNIT
v_{cc}	Const. college	54	4 5	5	5.5	
	Supply voltage	74	4.75	5	5.25	٧
Гон	High-level output current	54			-12	
		74			-15	mA
l _{OL}	Low-level output current	54			12	_
		74			24	mA
T _A	Operating free-air temperature	54	-55		125	
		74	0		70	۰c

Electrical Characteristics over recommended operating free-air temperature range (unless otherwise noted)

SYMBOL	PARAMETER			TEST CONDITIONS			MIN (Note 1)		МАХ	UNIT
V _{IH}	High-level input voltage						2			٧
V _{IL}	Low-level inp	Low-level input voltage				54 74			0.7	v
V _{IK}	Input clamp voltage			V _{CC} =Min, I _I =-18mA					-1.5	v
V _{T+} -V _{T-}	Hysteresis			V _{CC} =Min,			0.2	0.4		V
V _{OH}	High-level ou	utout voltage		V _{CC} =Min, V _I V _{IL} =Max, I _O		74	2.7	-		
				V _{CC} =Min, V _{IH} =Min V _{IL} =Max, I _{OH} =-3mA		2.4	3.4		v	
				V _{CC} =Min, V _I V _{IL} =0.5V, I _C		54,74	2			
.,				V _{CC} =Min	I _{OL} =12m	A 54, 74		0.25	0.4	
V _{OL}	Low-level ou	tput voltage		V _{IL} =Max V _{IH} =Min	I _{OL} =24m	A 74		0.35	0.5	V
l _{ozh}	Off-state out high-level vo	tput current litage applied		V _{CC} =Max, V V _{IH} =Min, V _{IL}		<i>x</i>			20	μΑ
I _{OZL}	1			V _{CC} =Max, V V _{IH} =Min, V _{IL}		G at 2V		·•	-200	μΑ
l ₁	1 *	Input ourrent of movimum A D		V _{CC} =Max		V ₁ =5.5V V ₁ =7V			0.1	mA
I _{IH}	High-level in	put current		V _{CC} =Max, V _I =2.7V				20	μΑ	
I _{IL}	Low-level input current		V _{CC} =Max, V _i =0.4V				-0.2	mA		
los	Short-circuit output current		V _{CC} =Max (Note 2)		-40		-225	mA		
	Supply Outputs high					48	70			
Icc	Current	Outpute low		V _{CC} =5.25V, Outputs open			62	90	mA	
		All outputs disabled						64	95	

Note 1. All typical values are at $V_{CC}=5V$, $T_A=25$ °C

Note 2. Not more than one output should be shorted at a time, and duration of the short-circuit should not exceed one second

Switching Characteristics, $V_{CC} = 5V$, $T_A = 25$ °C

SYMBOL	PARAMETER	TEST CONDITION#	MIN	TYP	MAX	UNIT
t _{PLH}	Propagation delay time, low-to-high-level output			8	12	ns
t _{PHL}	Propagation delay time, high-to-low-level output	$C_L = 45pF, R_L = 667\Omega$		8	12	ns
t _{PZL}	Output enable time to low level			27	40	ns
t _{PZH}	Output enable time to high level			25	40	ns
t _{PLZ}	Output disable time from low level	0 -5-5 D -0070		15	25	ns
t _{PHZ}	Output disable time from high level	$C_L=5pF, R_L=667\Omega$		15	25	ns

[#] For load circuit and voltage waveforms see page 3-11