Launch Control XL 3 — Track 006 (lean, mix)

Two custom modes: Mode 16 (channel 16) plays the stems, Mode 2 the melodies (all CCs + 48). Column 8 is global in both modes and controls the same thing: the fader takes the last moved value, the knobs are coupled (every turn shifts the shared value relatively).

Filter knobs are exponential, so the whole travel is audible. Density (knob row 3) is a crossfade: 0 = main layer only, 0.5 = both, 1 = extra layer only.

Knob | Fader | Button | global (all modes) | unused

Mode 16 — Stems

	1 Kick	2 Sub	3 Bass	4 Hats	5 Clap	6 Bongos	7 Space	8 Global
Row 1 HPF	CC 13 **HPF** 20–2000 Hz. Fully open: only the click is left.	CC 14 **HPF** 20–300 Hz	CC 15 **HPF** 20–600 Hz	CC 16 **HPF** 300–8000 Hz	CC 17 **HPF** 150–3000 Hz	CC 18 **HPF** 60–600 Hz	CC 19 **HPF** 80–1200 Hz	CC 20 / 68 **Global HPF** 0–1000 Hz (quadratic), added to kick, sub, bass, bongos, space. Not to hats, clap, melodies.
Row 2 LPF	CC 21 **LPF** 100–12800 Hz (+1.5 kHz with softness)	CC 22 **LPF** 80–2000 Hz	CC 23 **LPF / Cutoff** 150–4000 Hz. Together with acid the 303 cutoff.	CC 24 **LPF** 2–16 kHz	CC 25 **LPF** 1.5–15 kHz	CC 26 **LPF** 1–10 kHz	CC 27 **LPF sweep** upper limit of the slow filter sweep, 0.8–12 kHz	CC 28 / 76 **Global LPF** 100–12800 Hz (exp.), melodies only (not baselines).
Row 3 Character	CC 29 **Softness** 0 = 909. 1 = soft sine kick + 808, slightly driven.	CC 30 **Density** quarter-note saw + sine sub → pulsing 8ths	CC 31 **Acid** 0 = warm saw. 1 = 303: resonance, filter envelope, accents, drive.	CC 32 **Density** open hats → 16th hats	CC 33 **Density** backbeat → ghosts + double taps	CC 34 **Density** low/high taps → ghosts, rolls, fingers	CC 35 **Feedback** delay feedback 0.23–1.14. Above ~0.9 it builds up!	CC 36 / 84 **Swing** offbeat 8ths later: 0 straight … 1 heavy shuffle.
Fader Level	CC 5 **Level** 0–1	CC 6 **Level** 0–2	CC 7 **Level** 0–2, drops slightly with acid	CC 8 **Level** 0–0.4	CC 9 **Level** 0–1.4	CC 10 **Level** 0–0.8	CC 11 **Level** 0–0.7	CC 12 / 60 **Master Level** volume of everything.
Buttons 1	CC 37 —	CC 38 —	CC 39 —	CC 40 —	CC 41 **Clap Room** off / 0.5	CC 42 —	CC 43 —	CC 44 —
Buttons 2	CC 45 —	CC 46 —	CC 47 —	CC 48 —	CC 49 —	CC 50 —	CC 51 —	CC 52 —

Mode 2 — Melodies (CC + 48)

	Melody 1	Melody 2	Melody 3	Melody 4	Melody 5	Melody 6	Melody 7	8 Global
Row 1 Character	CC 61 **Wobble** 0 = dry. 0.5 = organic: drift + vibrato. 1 = acid: 303 envelope, accents, drive. Also affects the baseline.	CC 62 **Wobble** as Melody 1	CC 63 **Wobble** as Melody 1	CC 64 **Wobble** as Melody 1	CC 65 **Wobble** as Melody 1	CC 66 **Wobble** as Melody 1	CC 67 **Wobble** as Melody 1	CC 20 / 68 **Global HPF** 0–1000 Hz (quadratic), added to kick, sub, bass, bongos, space. Not to hats, clap, melodies.
Row 2 Baseline	CC 69 **Baseline LPF** 0–800 Hz. At 0 the baseline is silent; turning up fades it in.	CC 70 **Baseline LPF** as Melody 1	CC 71 **Baseline LPF** as Melody 1	CC 72 **Baseline LPF** as Melody 1	CC 73 **Baseline LPF** as Melody 1	CC 74 **Baseline LPF** as Melody 1	CC 75 **Baseline LPF** as Melody 1	CC 28 / 76 **Global LPF** 100–12800 Hz (exp.), melodies only (not baselines).
Row 3 Density	CC 77 **Overtones** fades voices in, in 3 stages (0–0.3, 0.3–0.6, 0.6–0.9). Which ones is set by the button below.	CC 78 **Overtones** as Melody 1	CC 79 **Overtones** as Melody 1	CC 80 **Overtones** as Melody 1	CC 81 **Overtones** as Melody 1	CC 82 **Overtones** as Melody 1	CC 83 **Overtones** as Melody 1	CC 36 / 84 **Swing** offbeat 8ths later: 0 straight … 1 heavy shuffle.
Fader Level	CC 53 **Level** melody + overtones (not baseline). E F G A in Oktaven	CC 54 **Level** melody + overtones (not baseline). D E C F B G A	CC 55 **Level** melody + overtones (not baseline). 16 notes, half tempo	CC 56 **Level** melody + overtones (not baseline). C♯ F♯ A G / E	CC 57 **Level** melody + overtones (not baseline). D♭ F B E	CC 58 **Level** melody + overtones (not baseline). C♯ F A/G E	CC 59 **Level** melody + overtones (not baseline). D♭ E♭ B F	CC 12 / 60 **Master Level** volume of everything.
Buttons 1	CC 85 **Overtone mode** every press: major → minor → octaves	CC 86 **Overtone mode** as Melody 1	CC 87 **Overtone mode** as Melody 1	CC 88 **Overtone mode** as Melody 1	CC 89 **Overtone mode** as Melody 1	CC 90 **Overtone mode** as Melody 1	CC 91 **Overtone mode** as Melody 1	CC 92 —
Buttons 2	CC 93 —	CC 94 —	CC 95 —	CC 96 —	CC 97 —	CC 98 —	CC 99 —	CC 100 —