Launch Control XL 3 — House Keys Lab 10 (lab/keys, round 10 for 009: sway)

Columns 1-4 = accent before gaps (the longer the rest after a hit, the harder it is played). Columns 5-8 = 2nd rhythm soft (in the overlays the second rhythm half as loud and darker). In each half: same timing, same touch, new timing, new touch. Same = the deviation repeats in every bar; new = it changes every bar. Timing = hits a little early or late; touch = a little harder or softer. Shift + the column's fader = how much (0 = exact). All columns equally loud; pull up one fader at a time.

Sound: hold any column's button 2 and turn its knobs: 1 = piano → Rhodes, 2 = B3 → M1, 3 = vibraphone → marimba. Each knob: 0 silent, first third the first sound fades in, middle third blends into the second at equal loudness, last third the second fades out. In Mode 2: faders 1-4 = grand, Rhodes, organ, vibraphone layers; knob 3 above each changes its character; faders 6 and 7 = drums and bass.

"? LC groß" in the status box opens the dashboard: every control, its value, the pattern and the beat.

Knob | Fader | Button | unused

Mode 16 — Rhythms

	1 Accent same timing	2 Accent same touch	3 Accent new timing	4 Accent new touch	5 2nd soft same timing	6 2nd soft same touch	7 2nd soft new timing	8 2nd soft new touch
Row 1 Brightness	CC 13 **Brightness** dull ↔ bright (lpf 250 Hz – 12 kHz, a little resonance): the filter sweep; brighter also plays a little harder (±2 dB, a softer attack at the dark end).	CC 14 **Brightness** as 1 Accent same timing	CC 15 **Brightness** as 1 Accent same timing	CC 16 **Brightness** as 1 Accent same timing	CC 17 **Brightness** as 1 Accent same timing	CC 18 **Brightness** as 1 Accent same timing	CC 19 **Brightness** as 1 Accent same timing	CC 20 **Brightness** as 1 Accent same timing
Row 2 Space	CC 21 **Space** 0 = dry; a 1/8 echo is there from the first turn (full at half), from about a third on the room joins (full at the top).	CC 22 **Space** as 1 Accent same timing	CC 23 **Space** as 1 Accent same timing	CC 24 **Space** as 1 Accent same timing	CC 25 **Space** as 1 Accent same timing	CC 26 **Space** as 1 Accent same timing	CC 27 **Space** as 1 Accent same timing	CC 28 **Space** as 1 Accent same timing
Row 3 Length	CC 29 **Length** 0 = short stab ↔ hits ring four times longer.	CC 30 **Length** as 1 Accent same timing	CC 31 **Length** as 1 Accent same timing	CC 32 **Length** as 1 Accent same timing	CC 33 **Length** as 1 Accent same timing	CC 34 **Length** as 1 Accent same timing	CC 35 **Length** as 1 Accent same timing	CC 36 **Length** as 1 Accent same timing
Fader Level	CC 5 **Level** accent before gaps; timing sway, the same in every bar.	CC 6 **Level** accent before gaps; touch sway, the same in every bar.	CC 7 **Level** accent before gaps; timing sway, new in every bar.	CC 8 **Level** accent before gaps; touch sway, new in every bar.	CC 9 **Level** 2nd rhythm soft; timing sway, the same in every bar.	CC 10 **Level** 2nd rhythm soft; touch sway, the same in every bar.	CC 11 **Level** 2nd rhythm soft; timing sway, new in every bar.	CC 12 **Level** 2nd rhythm soft; touch sway, new in every bar.
Button 1 Change	CC 37 **Change** 8 patterns: chain → shifted chain → pairs → 3-3-2 → Kerri syncope → Kerri riff → chain + shifted chain → chain + pairs.	CC 38 **Change** as 1 Accent same timing	CC 39 **Change** as 1 Accent same timing	CC 40 **Change** as 1 Accent same timing	CC 41 **Change** as 1 Accent same timing	CC 42 **Change** as 1 Accent same timing	CC 43 **Change** as 1 Accent same timing	CC 44 **Change** as 1 Accent same timing
Button 2 Shift (hold)	CC 45 **Shift** press = on / off: the 3 knobs mix the sound (piano → Rhodes, B3 → M1, vibraphone → marimba); the fader = how much sway (0 = exact).	CC 46 **Shift** as 1 Accent same timing	CC 47 **Shift** as 1 Accent same timing	CC 48 **Shift** as 1 Accent same timing	CC 49 **Shift** as 1 Accent same timing	CC 50 **Shift** as 1 Accent same timing	CC 51 **Shift** as 1 Accent same timing	CC 52 **Shift** as 1 Accent same timing

Mode 2 — Sound + global

	1 Grand	2 Rhodes	3 Organ	4 Vibraphone	5	6 Drums	7 Bass	8
Row 1	CC 61 —	CC 62 —	CC 63 —	CC 64 —	CC 65 —	CC 66 **Swing** 50 % straight ↔ 70 %; 55–58 % = house.	CC 67 —	CC 68 —
Row 2	CC 69 —	CC 70 —	CC 71 —	CC 72 —	CC 73 —	CC 74 —	CC 75 —	CC 76 —
Row 3	CC 77 **M1** 0 = plain grand ↔ the 90s house piano (detuned, e-piano octave, a little grit).	CC 78 **Phaser** 0 = plain ↔ slow, deep phaser swirl.	CC 79 **M1** 0 = B3 ↔ M1, blended at equal loudness.	CC 80 **Marimba** 0 = vibraphone ↔ woody marimba, blended at equal loudness.	CC 81 —	CC 82 —	CC 83 —	CC 84 —
Fader Level	CC 53 **Grand** layer level: dry grand piano.	CC 54 **Rhodes** layer level: warm electric piano.	CC 55 **Organ** layer level: B3 and M1 organ.	CC 56 **Vibraphone** layer level: soft, jazzy mallets.	CC 57 —	CC 58 **Drums** 909 kick, off-beat hat, clap, shaker.	CC 59 **Bass** off-beat bass on the chord root.	CC 60 —
Buttons 1	CC 85 —	CC 86 —	CC 87 —	CC 88 —	CC 89 —	CC 90 —	CC 91 —	CC 92 —
Buttons 2	CC 93 —	CC 94 —	CC 95 —	CC 96 —	CC 97 —	CC 98 **Drums out** keys and bass alone while held.	CC 99 —	CC 100 —

Guide

Changing the sound

Three levels, from quick to deep. 1. Brightness (row 1): the house filter sweep, the most used move of all; it also plays a little harder. Space (row 2): echo, then room. Length (row 3): a short, dry stab ↔ ringing chords. 2. The sound mix (shift knobs, or Mode 2 faders 1-4): grand + organ = the thick 90s piano, Rhodes + vibraphone = soft and deep. 3. Each layer's character (Mode 2 knob 3): grand → M1 piano, Rhodes → phaser, organ B3 → M1, vibraphone → marimba.

Why off the kick

Stab rhythms that avoid the kick and sit on the off-16ths pull against the beat; hits on the kick double it and sound like a band. Two hits and 3-3-2 do start on the one: that is their weight.

Constancy

Every pattern repeats unchanged (one or two bars long); only the “new” sway (columns 3, 4, 7, 8) differs a little from bar to bar. Change comes from you: filter, length, layers, another pattern.

Sway

A player never hits exactly on the grid or equally hard. Timing sway moves each hit up to ±30 ms; touch sway makes it up to ±4 dB harder or softer (and a little brighter or darker). Same: the deviation repeats in every bar, so the loop keeps its shape. New: it changes in every bar. Shift + the column's fader sets how much (0 = exact, start at half).

Harmony

One chord only: Am9 in Kerri Chandler's shape (the 7th at the bottom, the 9 instead of the root). Chord changes have their own board: house-harmony-lab.