# Launch Control XL 3 — Track 009 — house (one controller)

Happy, jazzy, dry house in A minor, 124 BPM. Jojo plays the rhythm (kick, bass, drums, percussion), Jonas the harmony with the chord progressions (column 1), the keys (column 2), the vibraphone (column 3), the flute (column 4; 5-7 empty for now) and the global column 8.

Every row means the same everywhere: row 1 = brightness, row 2 = space, row 3 = character, fader = level, button 1 = next pattern (at the next bar), button 2 = a moment while held.

Start with all faders down. Nothing sounds until Jonas' master fader (column 8) is up. Chapter (Jonas, column 8) switches between one chord (Vamp) and the progression chosen on Jonas 1 (Wechsel) at the next 4-bar phrase.

One controller: Mode 1 = Jojo (foundation, columns 1–7; Jojo's column 8 (Tamb / Ride) stays off; Mode 1 sends the same CCs as Mode 16), Mode 2 = Jonas (colour). Column 8 is global on both pages.

Knob | Fader | Button | global (all modes) | unused

## Mode 1 — Jojo: Foundation (beat + bass) · same CCs as Mode 16

| | 1 Kick | 2 Noise Pump | 3 Sub | 4 Bass | 5 Clap | 6 Hats / Shaker | 7 Congas | 8 Global |
|---|---|---|---|---|---|---|---|---|
| **Row 1 Brightness** | CC 13 **Brightness** 0 = round and tight ↔ extra click on top (lpf 4–16 kHz). | CC 14 **Brightness** soft whoosh ↔ airy hiss (lpf 2–14 kHz). | CC 15 **Brightness** 0 = sine with a few overtones (audible on small speakers) ↔ warm and full. | CC 16 **Brightness** dull ↔ bright (low-pass over each sound's own range); brighter also a little louder. | CC 17 **Brightness** natural ↔ sharp crack (lpf 3.5–14 kHz). | CC 18 **Brightness** soft hiss ↔ crisp and sharp (lpf 4–16 kHz). | CC 19 **Brightness** soft and woody ↔ crisp slap (lpf 1–12 kHz). | CC 20 **Fog** 0 = clear, up = every filter pulled down to ~6 %: muffled, as if from outside the club. |
| **Row 2 Space** | CC 21 **Space** dry and close ↔ in a room (reverb). | CC 22 **Space** dry ↔ far away (reverb + echo). | CC 23 **Space** dry ↔ a little room (reverb). | CC 24 **Space** dry ↔ a little room (reverb). | CC 25 **Space** dry ↔ far away (reverb + echo). | CC 26 **Space** dry ↔ far away (reverb + echo). | CC 27 **Space** dry ↔ far away (reverb + echo). | CC 28 **Room** 0 = each sound's own room (row 2), up = everything drowns in reverb. |
| **Row 3 Character** | CC 29 **Punch** 0 = tight 909 kick ↔ harder: bigger pitch drop, more body. | CC 30 **Motion** still ↔ the filter breathes and the noise wanders left and right. | CC 31 **Length** long, pumping notes ↔ short, bouncing ones. | CC 32 **Sound** FM (Daft Punk) → M1 organ → warm analog. | CC 33 **Ghost notes** plain ↔ a quiet rim before beat 3 ↔ + small double taps. | CC 34 **Hats ↔ Shaker** 0 = 909 hats ↔ middle = both ↔ 1 = shaker (same rhythm). | CC 35 **Density** steady pattern ↔ + fingertip ghost notes. | CC 36 **Tension** build-up: echo grows, filters open, from the middle a snare roll (clap fader). 0 = release. |
| **Fader Level** | CC 5 **Level** 0 = gone. Four on the floor, tuned to A. | CC 6 **Level** noise that pumps with the kick. | CC 7 **Level** sub on the root, follows the chapter. | CC 8 **Level** bass line, follows the chords. | CC 9 **Level** clap on 2 and 4. Also the level of Tension's snare roll. | CC 10 **Level** off-beat hat + swung 16ths. | CC 11 **Level** congas and bongos, in the background. | CC 12 **Master Level** volume of everything, both controllers. 0 = silence. |
| **Button 1 Change** | CC 37 **Change** 4/4 → a gap every 4th bar → a gap every 8th bar. | CC 38 **Change** pump → off-beat → 16ths. | CC 39 **Change** pump → off-beat → half bars. | CC 40 **Change** 6 lines: around the 1 + dead notes → dead notes → around the 1 → beat 4 open → pluck → Alright. | CC 41 **Change** 2 + 4 → with a pickup → a fill every 4th bar. | CC 42 **Change** off-beat → + swung 16ths → driving 16ths. | CC 43 **Change** pillow → rolling → latin. | CC 44 **Chapter** Vamp (Am9) ↔ Wechsel (col. 1 chords). |
| **Button 2 Moment** | CC 45 **Drop** kick, noise pump and sub pause while held. | CC 46 **Riser** a noise sweep rises over 2 bars while held. | CC 47 **Slide** every note bends up into its pitch while held. | CC 48 **Octave** one octave up while held. | CC 49 **Roll** snare roll, growing over the bar, while held. | CC 50 **Open** open hats on every 8th while held. | CC 51 **Fill** a conga run over the bar while held. | CC 52 **Break / Drop** 1st: beat out. 2nd: all back on the one. |

## Mode 2 — Jonas: Colour (chords + melodies) · CC + 48

| | 1 Harmony | 2 Keys | 3 Vibraphone | 4 Flute | 5 Brass | 6 Strings | 7 Guitar | 8 Global |
|---|---|---|---|---|---|---|---|---|
| **Row 1 Brightness** | CC 61<br>**Brightness**<br>dull ↔ bright (low-pass over the sound's range). | CC 62<br>**Brightness**<br>dull ↔ bright over each sound's own range (lpf from 250 Hz); top third: a presence peak; brighter also plays a little harder (±2 dB). | CC 63<br>**Brightness**<br>dull ↔ bright (low-pass). | CC 64<br>**Brightness**<br>dull ↔ bright (low-pass). | CC 65<br>**Brightness**<br>dull ↔ bright (low-pass 0.9–8 kHz). | CC 66<br>**Brightness**<br>dull ↔ bright (low-pass 1.2–12 kHz). | CC 67<br>**Brightness**<br>dull ↔ bright (low-pass 0.8–7 kHz). | CC 20<br>**Fog**<br>0 = clear, up = every filter pulled down to ~6 %: muffled, as if from outside the club. |
| **Row 2 Space** | CC 69<br>**Space**<br>echo and room. | CC 70<br>**Space**<br>0 = dry; a 1/8 echo is there from the first turn (full at half), from about a third on the room joins (full at the top). | CC 71<br>**Soft**<br>dry and short ↔ long notes, echo and room. | CC 72<br>**Space**<br>echo and room (a little at 0). | CC 73<br>**Space**<br>room at 0 ↔ hall and dotted-8th echo. | CC 74<br>**Space**<br>room at 0 ↔ hall and dotted-8th echo. | CC 75<br>**Space**<br>dry ↔ a 1/8 echo, then room. | CC 28<br>**Room**<br>0 = each sound's own room (row 2), up = everything drowns in reverb. |
| **Row 3 Character** | CC 77<br>**Strings ↔ B3**<br>strings → both → B3 alone. | CC 78<br>**Length**<br>0 = short stab ↔ hits ring four times longer. | CC 79<br>**Complexity**<br>core notes → figure → fills → doubles. | CC 80<br>**Playful**<br>core motif → + neighbour notes → + a short trill. | CC 81<br>**Complexity**<br>core figure → + pickups and answers → + small extra hits. | CC 82<br>**Build-up**<br>unison → + octave → + thirds under the runs → + celli two octaves down. | CC 83<br>**Complexity**<br>line → + dead notes → + slides, bar 4/8 variation → + 16th motor and a fill in bar 8. | CC 36<br>**Tension**<br>build-up: echo grows, filters open, from the middle a snare roll (clap fader). 0 = release. |
| **Fader Level** | CC 53<br>**Level**<br>held chords, follow the progression. | CC 54<br>**Level**<br>keys: Steinway (VCSL) and Rhodes Mark I (jRhodes3d), organs, mallets. | CC 55<br>**Level**<br>vibraphone phrases, follow the chords. | CC 56<br>**Level**<br>flute melody from real flute notes, follows the chords. | CC 57<br>**Level**<br>full brass section, follows the chords. | CC 58<br>**Level**<br>string section, disco figures on the chords. | CC 59<br>**Level**<br>plucked guitar lines on the chords. | CC 12<br>**Master Level**<br>volume of everything, both controllers. 0 = silence. |
| **Button 1 Change** | CC 85<br>**Progression**<br>next of 10, at the next 8-bar phrase (plays in Wechsel). | CC 86<br>**Change**<br>8 stab rhythms (chain, shifted, pairs, 3-3-2, two Kerri, two overlays). | CC 87<br>**Phrase**<br>off-beat → tresillo → echo of the call, next bar. | CC 88<br>**Motif**<br>hopping → call and answer → turn, next bar. | CC 89<br>**Figure**<br>push → 3-3-2 → shout → double push → 3-3-2 long → swell + push, next bar. | CC 90<br>**Figure**<br>echo stab → run up → long run → stab + swell → 16th figure, next bar. | CC 91<br>**Line**<br>Stardust → e & a 4 → call + answer → repeated note → lick → dead-note groove → off-16th pairs → pickup. | CC 44<br>**Chapter**<br>Vamp (Am9) ↔ Wechsel (col. 1 chords). |
| **Button 2 Moment** | CC 93<br>**Echo throw**<br>held: long dotted-8th echo. | CC 94<br>**Sound**<br>on / off: knobs = sound mix (piano → Rhodes, B3 → M1, vibes → marimba); fader = overtones. | CC 95<br>**Echo throw**<br>held: long dotted-8th echo. | CC 96<br>**Echo throw**<br>held: long dotted-8th echo. | CC 97<br>**Lift**<br>held: the section grows over 2 bars (voices, brightness, +3 dB); back over 1 bar after. | CC 98<br>**Lift**<br>held: octave and voices come in over 2 bars, brighter, +3 dB; back over 1 bar after. | CC 99<br>**Lift**<br>held: phaser, brighter, echo, +3 dB over 2 bars; back over 1 bar after. | CC 52<br>**Break / Drop**<br>1st: beat out. 2nd: all back on the one. |

## Guide

### Building it up

One layer after the other, not all at once: drums (kick, hats, clap), then bass and sub, then the keys, then percussion (congas, tambourine). Start in Vamp.

### Harmony

Button 1 of column 1 picks the progression (at the next 8-bar phrase); it plays when Chapter is Wechsel. Row 3 fades strings ⟶ strings + B3 ⟶ B3.

### Keys

1:1 from the keys lab (round 19, column 2): brightness, space, length; button 1 = stab rhythm (8); button 2 = sound: the knobs mix the sound (piano ⟶ Rhodes, organ B3 ⟶ M1, vibraphone ⟶ marimba), the fader sets how strongly the overtones follow the accent.

### Break and drop

Jonas presses Break: the whole rhythm goes out at the next bar, only the keys keep playing. Jojo holds the riser (noise pump, button 2). Jonas switches Chapter to Wechsel and presses Break again: everything is back on the one, now with the progression.

### Every position sounds good

All knobs at 0 is dry, close and clear, as the track is meant to be. Space adds room, it does not repair. Every column has its own fader: each layer can be muted on its own.

### Status box

The status box at the bottom right of the Strudel page shows chapter, break and each stem's pattern. Its button “als Fenster” opens it as a small window that stays on top (Chrome/Edge).

### Playing alone

A run is: build the beat in Mode 1, switch to Mode 2, add colour, use column 8 for the drop. Mode 1 is set up in Components with the same CCs as Mode 16.

Faders are shared hardware: after a mode switch each sound keeps its value until you touch its fader, then it jumps to where the fader physically is. Move faders gently after switching.