

# Day 4 connecting and testing peripherals

1. Connect a USB webcam to your computer, install any required drivers, and verify that the webcam works by opening the default camera app and capturing a photo.

SO here are the steps of connect usb webcam with computer

- 1 Connect the **USB webcam** to your computer.
  - 2 Wait for Windows to detect it automatically.
  - 3 If Windows asks for a driver, allow it to install. If needed, install the driver provided by the webcam manufacturer.
  - 4 Open the **Camera** app from the Windows Start menu.
  - 5 If you have multiple cameras, select the USB webcam.
  - 6 Make sure the webcam displays a live video preview.
  - 7 Click the **Capture/Take Photo** button.
  - 8 Open the captured photo to verify that the webcam is working correctly.
2. Set up a local printer (USB or network), install the correct driver, and print a test page to confirm successful installation.

## Setting Up a Local Printer

First, connect the printer to the computer using a USB cable. Turn on the printer and wait for Windows to detect the connected device. A notification may appear indicating that the printer has been connected.

Next, check the printer's **company and model number**. Windows may automatically install the required driver. If the driver is not installed automatically, visit the printer manufacturer's official website, find the driver for the exact printer model and Windows version, download it, and complete the installation.

After installing the driver, open a PDF file and press **Ctrl + P** to open the print settings. Select the connected printer and choose the option to print. Print a page and check whether the printer produces the document correctly. If the page prints successfully, the printer has been installed and configured correctly.

3. Simulate a connectivity issue by unplugging the printer's USB cable, then use Windows Device Manager to identify and resolve the 'printer not detected' problem.
- Unplug the printer's USB cable from the computer.
  - Open **Device Manager** by right-clicking the Start button and selecting **Device Manager**.

- Expand **Printers, Print queues, or Universal Serial Bus controllers** and check for the printer or a device with a warning/error icon.
  - Reconnect the printer's USB cable.
  - In Device Manager, click **Action** → **Scan for hardware changes**.
  - Wait for Windows to detect the printer again and confirm that the error icon has disappeared.
  - Open **Settings** → **Bluetooth & devices** → **Printers & scanners** and verify that the printer is listed and available.
    - Print a test page to confirm that the connectivity problem has been resolved.
4. A user reports that their webcam video is not displaying in Zoom, but it works in the default camera app. Troubleshoot and resolve the issue so the webcam works in both applications.

First, close the Camera app and any other application that may be using the webcam, as another application can prevent Zoom from accessing it. Open Zoom and go to **Settings** → **Video** and make sure the correct webcam is selected. Check whether the camera preview is visible in Zoom.

If the webcam still does not work, open **Windows Settings** → **Privacy & security** → **Camera** and make sure **Camera access** and **Let desktop apps access your camera** are enabled. Restart Zoom and test the camera again. If the problem continues, open **Device Manager** → **Cameras**, update the webcam driver, restart the computer, and test the webcam in both Zoom and the Camera app to confirm that it works correctly in both applications.