

Linear-Readout Reconstruction Floors and Support Recovery in Computation in Superposition

Hector Borobia^{a,*}, Elies Seguí-Mas^b, Guillermina Tormo-Carbó^c

^a*VRAIN – Valencian Research Institute for Artificial Intelligence, Universitat Politècnica de València, Valencia, Spain*

^b*Department of Economics and Social Sciences, Universitat Politècnica de València, Valencia, Spain*

^c*Department of Business Organisation, Universitat Politècnica de València, Valencia, Spain*

Abstract

Overcomplete neural representations encode more latent features than activation dimensions, but are useful for computation only when that information can be decoded and composed. Which decoding interface a network maintains is decided informally today, and recent work disagrees about whether trained models compute in superposition at all. We propose the *Interface Diagnostic*, a computable procedure that takes a code or a trained network and returns how close its gain-normalised linear readout sits to a Welch-type floor, the sparsity range over which a threshold decoder recovers Boolean states exactly, and a witness separating *analog reconstruction* from *support recovery*. Its mean-square statistics run in $O(Fd^2)$ time and $O(d^2)$ memory without forming the $F \times F$ interface, so it applies at $F \approx 10^6$ features on a laptop. It rests on a rank–trace bound: any rank- d unit-diagonal readout has average squared off-diagonal cross-talk at least $(F - d)/(d(F - 1))$, in a gain-normalised form bounding the interference-to-gain ratio. Six CPU experiments validate it. Gradient-optimised codes reach the floor, the tied variant converging to a tight frame. A trained toy model reaches it too: under an L^4 loss it sits within 1.0006 of the bound against 19.0052 for L^2 under the same readout, and its thresholded output keeps recovering supports be-

*Corresponding author.

Email address: `hecboar@doctor.upv.es` (Hector Borobia)

yond a crossover sparsity — below which the affine readout leads. The L^2 baseline keeps an effectively linear interface. Recovery scales to $d = 1\,024$. The analysis also recasts the Hänni template’s $d^{3/2}$ scale as a compatibility threshold, not a universal bound.

Keywords: overcomplete representations, computation in superposition, linear readout, Welch bound, sparse recovery, neural network capacity

1. Introduction

Modern neural networks use high-dimensional activation spaces to encode many latent variables. In many settings the number of relevant latent features exceeds the ambient dimension, which motivates the study of *overcomplete representations*: a state in $\mathbb{R}^d$ carrying information about $F \gg d$ features.

For such representations the central issue is not storage. A code may passively embed many states, but a network must also decode what it needs and compose it across layers. Different decoding interfaces impose different constraints. A *linear readout* interface asks for a matrix G whose coordinates approximately recover the features. A *threshold* interface asks only that active and inactive coordinates be separated by a margin, so that a nonlinearity can recover a sparse Boolean state. These criteria are related but not equivalent, and the difference is not cosmetic: it decides which capacity results apply.

1.1. The concrete limitation

The distinction is currently drawn informally, and that has a cost. Hänni et al. [1] give an approximate-linear recursive template certifying $\tilde{O}(d^{3/2})$ computable features in width d , while Adler and Shavit [2] reach a near-quadratic regime using thresholded Boolean recovery. The two are routinely read as competing capacity claims. In parallel, an active empirical line disagrees about whether trained toy models compute in superposition at all: Bhagat et al. [3] argue that the standard L^2 -trained compressed-computation model largely exploits a mixing term, whereas Ferreira da Silva and Heimersheim [4] show that training under an L^4 loss elicits a solution that does compute in superposition. The disagreement turns precisely on which decoding interface the trained network maintains — and there is no standard, computable way to answer that question about a given network.

That is the gap this paper addresses. What is missing is not another capacity bound but an *operational test*: given a code or a trained model, decide which interface it supports and quantify how far it is from the best possible one.

1.2. The proposed method

We propose the **Interface Diagnostic** (ID), a procedure with a precise input, output and cost. Its input is an overcomplete code $\Phi \in \mathbb{R}^{d \times F}$ — hand-built, optimised, or read off a trained network — together with a sparse-state model and a decoding threshold. Its output is a triple:

1. the *attainment ratio* $\widehat{W}/W(F, d)$, where $\widehat{W}$ is the mean squared off-diagonal cross-talk of the calibrated readout interface and $W(F, d) = (F-d)/(d(F-1))$ is a floor no readout can beat (Theorem 5.1);
2. the *recovery profile* $p_{\text{rec}}(s)$ of the threshold decoder together with the exact per-coordinate reconstruction error that any linear readout must retain at the same s ;
3. a *criterion-separation witness*: the largest sparsity at which the support is recovered exactly with high probability while no rank- d linear readout can reconstruct the state’s real-valued coordinates to better than $\Omega(\sqrt{s/d})$ per coordinate.

A word on what the two criteria are, because the natural shorthand is misleading. The contrast is *analog reconstruction* against *support recovery*, not linear against nonlinear. Thresholding a linear score is itself a linear-threshold rule, and we evaluate exactly that rule alongside the network’s own output; the floor does not forbid it from recovering supports. What the floor forbids is small real-valued error. The two criteria therefore come apart because they ask different questions of the same map — “what is the value of coordinate i ?” versus “is coordinate i on?” — and a code can serve the second long after it has stopped serving the first.

Algorithms 1 and 2 state the procedure; Section 4 gives its cost, its applicability conditions and its failure cases, and Table 2 maps each step to the function that implements it.

We are explicit about what is and is not new. The rank-trace mechanism behind the floor is standard in frame theory, and the recovery arguments are standard compressed sensing. The contribution is the packaging

of these facts into a criterion that can be *run* on a network, together with the gain-normalised form that makes it scale-invariant, the $O(Fd^2)$ streaming implementation that makes it feasible at $F \approx 10^6$, and the experimental demonstration that the criterion discriminates between trained models whose interface status is currently under debate.

1.3. Contributions

1. **The Interface Diagnostic.** A computable interface criterion for over-complete codes and trained networks, with pseudocode, hyperparameters, complexity, applicability conditions, edge cases and failure modes (Section 4), and a reference implementation whose every step is traceable to a numbered equation (Table 2). The diagnostic proper (Algorithm 2) is stated for a *fixed* code and readout; the random-code ensemble used for the scaling study (Algorithm 3) is a separate procedure and is not a diagnosis of any code.
2. **A gain-normalised floor, computable in $O(Fd^2)$.** For any G, Φ with $(G\Phi)_{ii} = 1$ the average squared off-diagonal cross-talk is at least $(F - d)/(d(F - 1))$ (Theorem 5.1); Corollary 5.2 removes the normalisation and bounds the *interference-to-gain ratio* $\max_{i \neq j} |M_{ij}|/|M_{ii}|$, making the diagnostic invariant to readout rescaling. Lemma 4.2 then reduces the mean-square statistic to $d \times d$ sufficient statistics, exactly and with no approximation, which is what lets the attainment ratio be evaluated at $F \approx 10^6$; the maximum form admits no such reduction and we state its $O(F^2d)$ cost rather than conflate the two. Proposition 5.5 identifies what a ratio near one means under the pseudoinverse readout — equalised leverage scores, a property of the code’s geometry and not of its usefulness.
3. **A separation between two decoding questions, under one sparse-state model.** Proposition 6.5 gives the average analog-reconstruction floor under uniformly random supports, so that both sides of Corollary 6.6 use the same distribution. At $F = d^2$, thresholding recovers a uniformly random size- s support for $s = O(d/\log d)$ with high probability, while every unit-diagonal rank- d linear readout retains average per-coordinate squared *reconstruction* error $\Omega(s/d)$ on that same distribution. The separation is between reconstructing values and identifying the support; it is not a claim that nonlinearity is required, and the thresholded linear readout is measured throughout as the appropriate control.

4. **Validation on learned codes and a trained network.** Codes optimised under the unit-diagonal constraint converge to the floor, and the tied variant converges to a unit-norm tight frame. In a trained toy model of computation in superposition, the L^4 solution comes within a few parts in a thousand of the floor under the pseudoinverse readout — which by Proposition 5.5 says its features carry near-equal leverage — and its thresholded output keeps recovering supports past the sparsity at which the thresholded linear readouts of its own code stop doing so. Below that crossover the best linear readout is the stronger decoder, and it wins on the s_{95} statistic. The L^2 solution is shown by direct measurement to maintain an effectively linear interface, an independent and quantitative corroboration of the reading in [3].
5. **Application to computation in superposition.** Matching the floor against the published tolerance of the Hänni correction layer gives a $d^{3/2}$ compatibility scale for that proof template, not a universal upper bound; the Adler–Shavit framework maintains the threshold invariant and is therefore not obstructed by the same criterion.

1.4. Scope of claims

Four caveats apply throughout, and we state them once here rather than repeating them.

First, Theorem 5.1 is a rank–trace, unit-diagonal cross-Gramian inequality closely related to known Welch and dual-frame Welch bounds [5, 6, 7, 8, 9, 10]; its role here is the application to readout interfaces, not a new frame-theoretic theorem. Second, the threshold-recovery results are standard coherence-based and random-dictionary support-recovery arguments; we claim no novelty in compressed sensing. Third, the $d^{3/2}$ scale we derive for the Hänni template is a compatibility threshold certified by that specific proof pipeline, not a universal upper bound on computation in superposition. Fourth, the experiments cover random codes, gradient-optimised codes and one trained toy model; none of them is a claim about large trained language models.

2. Background and related work

2.1. Computation in superposition

A network of hidden width d represents $F \gg d$ features in superposition if its activation $a(x) \in \mathbb{R}^d$ is approximately Φb for a feature-encoding matrix

$\Phi \in \mathbb{R}^{d \times F}$ and a sparse Boolean b . Following [1], features $f_1, \dots, f_F$ are ε -linearly represented by a if there is a readout $R \in \mathbb{R}^{F \times d}$ with $|r_k \cdot a(x) - f_k(x)| < \varepsilon$ for all k and x .

Hänni et al. construct an approximate-linear recursive template for sparse Boolean circuits, alternating a targeted superpositional AND layer with an error-correction layer, and certify emulation of circuits of width $\tilde{O}(d^{3/2})$. Adler and Shavit [2] give parameter-description lower bounds and explicit constructions for computing in superposition, obtaining a near-quadratic capacity by thresholding after each stage. Adler et al. [11] reframe superposition combinatorially through feature channel coding, and Kong et al. [12] show empirically that reducing inter-feature interference at fixed parameter count improves performance. This paper reproves none of these constructions; it identifies the interface-level reason the two regimes coexist.

2.2. Trained toy models of computation in superposition

A recent empirical line studies whether small trained networks actually compute in superposition. Braun et al. [13] introduced the compressed-computation task — a width-50 network asked to compute 100 sparse ReLU features — as a testbed. Bhagat et al. [3] argued that the standard L^2 -trained model largely exploits a mixing term rather than genuinely computing in superposition, and Ferreira da Silva and Heimersheim [4] showed that training under an L^4 loss elicits a solution that does compute in superposition, assigning each feature a sparse codeword over neurons and decoding it with a pseudoinverse of the encoder — that is, a linear readout interface in the sense studied here. In parallel, [14] report perturbation-based evidence for feature-specific error correction in large language models, the mechanism whose certified tolerance drives the $d^{3/2}$ compatibility scale of the Hänni template. This debate is about which decoding interface a trained network maintains; the diagnostic proposed here is a direct instrument for it, and Section 9.3 applies it to exactly the models under dispute.

2.3. Frame theory, Welch bounds and cross-Gramians

Classical Welch bounds [5] lower-bound the correlations of overcomplete unit-norm systems; the maximum-correlation form we use, $\max_{i \neq j} |\langle \phi_i, \phi_j \rangle| \geq \sqrt{(F - d)/(d(F - 1))}$, appears for instance as Theorem 2.3 of Strohmer and Heath [6] in the study of Grassmannian frames. Waldron [7] showed that generalised Welch-bound-equality sequences are exactly tight frames, and Datta, Howard and Cochran [8] derived the entire family of higher-order

Welch bounds from a geometric rank/Grammian argument, of which the rank–trace computation behind Theorem 5.1 is the first-order instance; see also [15] for the design-theoretic view. For pairs of sequences, Aceska and Kaczanowski [9] introduced the cross-frame potential, and Christensen, Datta and Kim [10] proved Welch-type bounds for the maximum coherence of dual frame pairs, characterising equality via equiangular tight frames.

Theorem 5.1 sits in this lineage: it is a unit-diagonal cross-Gramian formulation assuming only $\text{rank}(M) \leq d$ and $M_{ii} = 1$ — in particular, no duality relation between the two sequences, which, as finite sequences, are of course frames for their spans. We include its short rank–trace proof only to keep the paper self-contained; the proof mechanism is standard in this literature, cf. [8]. The contribution here is the application to readout interfaces, the gain-normalised form (Corollary 5.2), and the diagnostic built on top of them.

2.4. Compressed sensing and sparse recovery

The threshold-recovery results used below are standard coherence-based and random-dictionary support-recovery arguments. Their role is to make explicit a distinction relevant to neural computation: small-error linear readout requires uniformly small coordinate error, whereas threshold recovery only requires the aggregate interference from the active support to remain below a margin.

2.5. Sparse autoencoders

Sparse autoencoder work scales dictionary learning to millions of latents [16, 17, 18] and studies reconstruction–sparsity trade-offs [19]. Such results motivate the importance of overcomplete internal representations, but dictionary size is a reconstructive quantity and does not measure the recursive Boolean interface capacities studied here. This paper answers one of the open questions listed by Sharkey et al. [20] concerning what theoretical insight can be gleaned from computation performed natively in superposition.

3. Problem setting and notation

We write $\tilde{O}(\cdot)$, $\tilde{\Omega}(\cdot)$, $\tilde{\Theta}(\cdot)$ to hide factors polynomial in $\log d$. Table 1 fixes the notation used throughout.

Two decoding questions are compared throughout. *Analog reconstruction* asks that the scores $z = Mb$ approximate b in a norm; *support recovery*

Table 1: Notation.

symbol	meaning
d	activation width (number of neurons)
F	number of features, $F > d$
$\Phi \in \mathbb{R}^{d \times F}$	code; column ϕ_i is the direction of feature i
$G \in \mathbb{R}^{F \times d}$	linear readout
$M = G\Phi \in \mathbb{R}^{F \times F}$	readout interface, $\text{rank}(M) \leq d$
$D = \text{diag}(M_{11}, \dots, M_{FF})$	diagonal gains; $D^{-1}M$ is the calibrated interface
$A = M - I_F$	cross-talk matrix (zero diagonal after calibration)
$b \in \{0, 1\}^F$	sparse Boolean state; $S = \text{supp}(b)$, $s = S $
$\mu = \max_{i \neq j} \langle \phi_i, \phi_j \rangle $	coherence of a unit-norm code
$W(F, d) = \frac{F-d}{d(F-1)}$	mean-square Welch-type floor
$\widehat{W}$	measured mean squared off-diagonal cross-talk
θ	decoding threshold (default $1/2$)
$p_{\text{rec}}(s)$	probability of exact threshold recovery at sparsity s
s_{95}	largest s such that $p_{\text{rec}} \geq 0.95$ for <i>every</i> tested $s' \leq s$
m, m'	feature counts <i>inside imported statements</i> ; m' plays the role of F

asks only that $\mathbf{1}\{z_i \geq \theta\} = b_i$ for every i . The first is a statement about magnitudes and is never exactly satisfiable when $F > d$; the second is a statement about a decision boundary and can be satisfied exactly — by a thresholded linear score as much as by anything else, which is why that rule is measured here too rather than treating support recovery as the preserve of nonlinearity. Everything below is an elaboration of that asymmetry.

4. The Interface Diagnostic

4.1. Problem statement

Problem 4.1 (Interface diagnosis). **Input:** a code $\Phi \in \mathbb{R}^{d \times F}$ with $F > d$ (or a trained network from which an effective code is read off); a readout family $\mathcal{G}$; a sparse-state model, here uniformly random supports of size s drawn from a grid $\mathcal{S}$; a threshold θ ; a trial budget T ; a confidence level $1 - \alpha$.

Output: (i) the attainment ratio $r = \widehat{W}/W(F, d) \geq 1$ and the maximum-form ratio r_{max} ; (ii) for each $s \in \mathcal{S}$, the empirical $p_{\text{rec}}(s)$ with a Wilson interval and the exact per-coordinate RMS error $\rho_{\text{lin}}(s)$ of the calibrated linear interface; (iii) the criterion-separation witness $(s_{95}, \rho_{\text{lin}}(s_{95}))$.

Algorithm 1 FLOORATTAINMENT — how close the readout interface sits to the floor

Require: code $\Phi \in \mathbb{R}^{d \times F}$, $F > d$; readout $G \in \mathbb{R}^{F \times d}$ or a rule in $\{\text{TIED}, \text{PINV}, \text{LSQ}\}$

Ensure: attainment ratio r (and $r_{\max}$ if requested), or DEGENERATE

- 1: $G \leftarrow \Phi^\top, \Phi^+$, or the least-squares fit, per the rule
 - 2: $D_{ii} \leftarrow \langle g_i, \phi_i \rangle$ for $i = 1, \dots, F$ $\triangleright$ the diagonal of $M = G\Phi$, in $O(Fd)$; M itself is not formed
 - 3: **if** $\min_i |D_{ii}| < \epsilon_{\text{gain}}$ **then return** DEGENERATE $\triangleright$ some feature is read out with vanishing gain
 - 4: **end if**
 - 5: $\bar{G} \leftarrow D^{-1}G$ $\triangleright$ gain normalisation; see Corollary 5.2
 - 6: $H \leftarrow \bar{G}^\top \bar{G}$; $\Sigma \leftarrow \Phi \Phi^\top$ $\triangleright$ both $d \times d$; $O(Fd^2)$
 - 7: $\widehat{W} \leftarrow \frac{\text{tr}(H\Sigma) - F}{F(F-1)}$ $\triangleright$ exact, by Lemma 4.2
 - 8: $W \leftarrow (F-d)/(d(F-1))$ $\triangleright$ Theorem 5.1
 - 9: **if** the maximum form is requested **then**
 - 10: form $\widetilde{M} \leftarrow \bar{G}\Phi$ and set $\widehat{\mu} \leftarrow \max_{i \neq j} |\widetilde{M}_{ij}|$ $\triangleright O(F^2d)$ time, $O(F^2)$ memory
 - 11: **end if**
 - 12: **return** $r \leftarrow \widehat{W}/W$ (and $r_{\max} \leftarrow \widehat{\mu}/\sqrt{W}$ if computed)
-

The output is a diagnosis, not a score to be optimised. A code with r close to 1 is Welch-optimal in the mean-square sense; a large s_{95} with $\rho_{\text{lin}}(s_{95})$ well above $d^{-1/2}$ says the code supports support recovery in a regime where analog reconstruction from the same map is useless.

4.2. Algorithm 1: floor attainment

Step 3 is not a numerical guard but a semantic one: without it, an interface can be made to look arbitrarily good by shrinking G , which is exactly the confusion that Remark 5.3 dispels. By Theorem 5.1, a correct implementation always returns $r \geq 1$; we use that as a runtime assertion, and no violation was observed in 720 gain-normalised interfaces (Section 9.1).

The mean-square statistic that the theorem actually constrains never requires the interface to be built. The maximum statistic does, and we say so rather than folding it into the same cost.

Lemma 4.2 (Mean-square cross-talk from $d \times d$ statistics). *Let $\bar{G} = D^{-1}G$ with $D_{ii} = \langle g_i, \phi_i \rangle \neq 0$, let $\widetilde{M} = \bar{G}\Phi$, and set $H = \bar{G}^\top \bar{G}$ and $\Sigma = \Phi\Phi^\top$, both in $\mathbb{R}^{d \times d}$. Then*

$$\sum_{i \neq j} \widetilde{M}_{ij}^2 = \|\bar{G}\Phi\|_F^2 - F = \text{tr}(H\Sigma) - F.$$

Proof. $\widetilde{M}$ has unit diagonal by construction, so the F diagonal entries contribute exactly F to $\|\widetilde{M}\|_F^2$ and the remainder is the off-diagonal sum. Cyclicity of the trace gives $\|\bar{G}\Phi\|_F^2 = \text{tr}(\Phi^\top \bar{G}^\top \bar{G} \Phi) = \text{tr}(\bar{G}^\top \bar{G} \Phi \Phi^\top) = \text{tr}(H\Sigma)$. $\square$

Forming H and Σ costs $O(Fd^2)$ time and $O(d^2)$ memory, against $O(F^2d)$ and $O(F^2)$ for the direct route — a reduction of a factor F/d in time and F^2/d^2 in memory, with no approximation whatever. The identity is verified against the dense computation to relative accuracy 10^{-10} in the accompanying tests.

4.3. Algorithm 2: separation profile of a given code

Algorithm 2 is the diagnostic proper: it takes a code and a readout that already exist — a designed code, an optimised one, or the effective code of a trained network — and holds them fixed while the support varies. This is the only version that says anything about a particular object, and it is the one applied to trained networks in Section 9.3.

The support-recovery side of Algorithm 2 is Monte Carlo over supports; the analog side is *exact* for the given code, computed once before the loop rather than estimated inside it. Total cost is $O(Fd^2 + T F d s_{\max})$ time and $O(Fd + d^2)$ memory: the $F \times F$ interface is never formed.

4.4. A scaling experiment on the random-code ensemble

Algorithm 3 is a different object and we keep it named apart. It redraws a fresh code at every trial, so what it characterises is the (d, F) random-code *ensemble*, not any individual code; it is the vehicle for the width-scaling study of Sections 9.1 and 9.4, and it is not a diagnosis of anything. Because the code is regenerated block by block from a counted seed and never stored, it reaches widths at which the code would not fit in memory.

Both algorithms share the same asymmetry: the support-recovery side is estimated, the analog side is computed. That is what makes the comparison a witness rather than two noisy curves — the analog error carries no Monte Carlo uncertainty, so any gap at s_{95} is attributable to the recovery side alone.

Algorithm 2 SEPARATIONPROFILE — support recovery versus irreducible analog error, on a fixed code

Require: code $\Phi \in \mathbb{R}^{d \times F}$ and readout $G \in \mathbb{R}^{F \times d}$; sparsity grid $\mathcal{S}$; trials T ; threshold θ ; seed σ

Ensure: $\{(s, p_{\text{rec}}(s), \text{CI}, \rho_{\text{lin}}(s))\}_{s \in \mathcal{S}}$ and the separation witness $(s_{95}, \rho_{\text{lin}}(s_{95}))$

- 1: $s_{\max} \leftarrow \max \mathcal{S}$; $\bar{G} \leftarrow D^{-1}G$ as in Algorithm 1
 - 2: $\|A\|_F^2 \leftarrow \text{tr}(H\Sigma) - F$; $\|A\mathbf{1}\|^2 \leftarrow \|\bar{G}\Phi\mathbf{1}\|^2 - 2\mathbf{1}^\top \bar{G}\Phi\mathbf{1} + F \triangleright$ Lemma 4.3;
 $O(Fd^2)$
 - 3: $e_s \leftarrow \frac{1}{F}[(p - q)\|A\|_F^2 + q\|A\mathbf{1}\|^2]$, $p = \frac{s}{F}$, $q = \frac{s(s-1)}{F(F-1)}$, for each $s \in \mathcal{S} \triangleright$
 exact; Prop. 6.5
 - 4: **for** $t = 1$ **to** T **do**
 - 5: draw nested supports $S_1 \subset \dots \subset S_{s_{\max}}$ from seed (σ, t)
 - 6: $Z \leftarrow \bar{G}[x_1, \dots, x_{s_{\max}}]$, $x_s = \sum_{j \in S_s} \phi_j \triangleright O(Fd s_{\max})$
 - 7: $k_s \leftarrow k_s + 1$ for each s with $\mathbf{1}\{Z_{\cdot s} \geq \theta\} = \mathbf{1}_{S_s}$
 - 8: **end for**
 - 9: $p_{\text{rec}}(s) \leftarrow k_s/T$ with Wilson interval; $\rho_{\text{lin}}(s) \leftarrow \sqrt{e_s}$
 - 10: $s_{95} \leftarrow \max\{s : p_{\text{rec}}(s') \geq 0.95 \forall s' \leq s\}$
 - 11: **return** the profile and $(s_{95}, \rho_{\text{lin}}(s_{95}))$
-

Lemma 4.3 (Sufficient statistics of the tied interface). *Let Φ have unit-norm columns, $M = \Phi^\top \Phi$, $A = M - I_F$, $\Sigma = \Phi\Phi^\top \in \mathbb{R}^{d \times d}$ and $v = \Phi\mathbf{1} \in \mathbb{R}^d$. Then*

$$\|A\|_F^2 = \|\Sigma\|_F^2 - F, \quad \|A\mathbf{1}\|_2^2 = v^\top \Sigma v - 2\|v\|_2^2 + F.$$

Proof. By cyclicity of the trace, $\|\Phi^\top \Phi\|_F^2 = \text{tr}((\Phi^\top \Phi)^2) = \text{tr}((\Phi\Phi^\top)^2) = \|\Sigma\|_F^2$; the diagonal of M is all ones and contributes F , so subtracting F leaves the off-diagonal energy, which is $\|A\|_F^2$. For the second identity, $A\mathbf{1} = \Phi^\top \Phi\mathbf{1} - \mathbf{1} = \Phi^\top v - \mathbf{1}$, hence $\|A\mathbf{1}\|^2 = v^\top \Phi\Phi^\top v - 2\mathbf{1}^\top \Phi^\top v + F = v^\top \Sigma v - 2\|v\|^2 + F$, using $\mathbf{1}^\top \Phi^\top v = v^\top v$. $\square$

Lemma 4.3 is the reason the diagnostic scales: it replaces an $F \times F$ object by a $d \times d$ one, and combined with Proposition 6.5 it yields the average linear error at every sparsity without a single Monte Carlo draw.

4.5. Hyperparameters, complexity and cost

The diagnostic has five hyperparameters: the readout rule, the threshold θ (default 1/2, the natural midpoint for unit-norm codes and Boolean states),

Algorithm 3 ENSEMBLESCALING — the same two criteria, averaged over random codes

Require: d, F , sparsity grid $\mathcal{S}$, trials T , threshold θ , seed σ , block size B

Ensure: the ensemble-averaged profile and $(s_{95}, \rho_{\text{lin}}(s_{95}))$

```

1:  $s_{\max} \leftarrow \max \mathcal{S}$ ;  $k_s \leftarrow 0$  for all  $s$ ;  $e_s \leftarrow 0$  for all  $s$ 
2: for  $t = 1$  to  $T$  do
3:   draw nested supports  $S_1 \subset \dots \subset S_{s_{\max}}$  from seed  $(\sigma, t)$ 
4:    $X \leftarrow$  partial sums  $[x_1, \dots, x_{s_{\max}}]$ ,  $x_s = \sum_{j \in S_s} \phi_j$   $\triangleright d \times s_{\max}$ 
5:    $\Sigma \leftarrow 0_{d \times d}$ ,  $v \leftarrow 0_d$ 
6:   for each block  $\beta$  of  $B$  columns of  $\Phi$  do
7:     regenerate  $\Phi_\beta$  from seed  $(\sigma, t, \beta)$   $\triangleright \Phi$  is never stored
8:      $Z \leftarrow \Phi_\beta^\top X$ ; mark  $s$  as failed if  $\mathbf{1}\{Z_{\cdot s} \geq \theta\}$  disagrees with  $\mathbf{1}_{S_s}$  on
       this block
9:      $\Sigma += \Phi_\beta \Phi_\beta^\top$ ;  $v += \Phi_\beta \mathbf{1}$ 
10:  end for
11:   $k_s += 1$  for each surviving  $s$ 
12:   $\|A\|_F^2 \leftarrow \|\Sigma\|_F^2 - F$ ;  $\|A\mathbf{1}\|^2 \leftarrow v^\top \Sigma v - 2\|v\|^2 + F$   $\triangleright$  Lemma 4.3
13:   $e_s += \frac{1}{F} [(p - q) \|A\|_F^2 + q \|A\mathbf{1}\|^2]$ ,  $p = \frac{s}{F}$ ,  $q = \frac{s(s-1)}{F(F-1)}$   $\triangleright$  Prop. 6.5
14: end for
15:  $p_{\text{rec}}(s) \leftarrow k_s/T$  with Wilson interval;  $\rho_{\text{lin}}(s) \leftarrow \sqrt{e_s/T}$ 
16:  $s_{95} \leftarrow \max\{s : p_{\text{rec}}(s') \geq 0.95 \ \forall s' \leq s\}$ 
17: return the profile and  $(s_{95}, \rho_{\text{lin}}(s_{95}))$ 

```

the sparsity grid $\mathcal{S}$, the trial budget T , and the block size B , which trades memory for the number of regeneration passes. Only T affects the statistical resolution; Section 9.1 reports the threshold sensitivity of the conclusions.

Algorithm 1 costs $O(Fd^2)$ time and $O(d^2)$ memory for the ratio r , by Lemma 4.2. The maximum-form ratio $r_{\max}$ is the one exception in the whole method: no $d \times d$ reduction of a maximum is available to us, so obtaining it exactly costs $O(F^2d)$ time and $O(F^2)$ memory, and it is computed only when asked for. Since the floor of Theorem 5.1 is a statement about the mean square, nothing about the floor comparison is lost by omitting it; we report $r_{\max}$ at the moderate widths where it is affordable and drop it beyond. Algorithm 2 costs $O(Fd^2 + T F d s_{\max})$ time and $O(Fd + d^2)$ memory. Algorithm 3 costs $O(T F d s_{\max})$ time — one pass of code regeneration and one $B \times d \times s_{\max}$ product per block — and $O(Bd + d^2)$ memory, independent of F . At $d = 1024$ and $F = 1048576$ the code would occupy 4 GB in single

precision; the streaming implementation peaks near $Bd \cdot 4$ bytes. Measured wall-clock times are in Table 7.

4.6. Applicability, edge cases and failure modes

Conditions of applicability.. The diagnostic assumes (i) $F > d$, otherwise the floor is vacuous and Algorithm 1 refuses to run; (ii) unit-norm code columns, or a declared normalisation, since the threshold $\theta = 1/2$ is calibrated to unit gain; (iii) a sparse-state model that is exchangeable across coordinates, which is what makes the closed form of step 3 valid.

Edge cases.. At $s = 1$ the linear error is still non-zero while threshold recovery succeeds whenever $\mu < \theta$; this is the smallest instance of the separation. When $F/d \rightarrow 1$ the floor tends to zero and the diagnosis becomes uninformative — correctly so, since a nearly complete code has no interference to speak of.

Failure modes.. Three are worth naming. (a) *Degenerate gain*: if some $|M_{ii}|$ is numerically zero the calibration is undefined and Algorithm 1 returns DEGENERATE rather than a number; this is not a corner case but the expected outcome when a readout is fitted without the diagonal constraint (Section 9.2). (b) *Uncovered feature*: a least-squares readout fitted on states in which some feature never appears has an identically zero row, which triggers (a); the implementation therefore enforces coverage of the fitting set. (c) *Vacuous profile*: if the coherence of the code exceeds θ , $p_{\text{rec}}(1)$ is already below 0.95 and $s_{95} = 0$; the certificate is then empty, and the diagnostic reports that rather than extrapolating.

4.7. Implementation and traceability

Table 2 maps every quantity in Problem 4.1 to the function that computes it. The correctness of the implementation is checked by a test suite that verifies the theorems numerically — equality for tight frames, no violations for random interfaces, the closed forms against Monte Carlo, and the streaming trial against an explicit dense evaluation of the same code.

5. The linear-readout floor

Theorem 5.1 (Unit-diagonal cross-Gramian Welch floor). *Let $F \geq 2$, let $\Phi \in \mathbb{R}^{d \times F}$ and $G \in \mathbb{R}^{F \times d}$, and set $M = G\Phi$. Suppose $M_{ii} = 1$ for all $i \in [F]$.*

Table 2: Each step of the method and the function that implements it. Paths are relative to the repository root.

quantity	where defined	implementation
$W(F, d)$	Eq. (2)	lrtr/codes.py:welch_floor
$D^{-1}M$	Cor. 5.2	lrtr/interface.py:unit_diagonal
$\widehat{W}, \widehat{\mu}, r, r_{\max}$	Alg. 1	lrtr/interface.py:crosstalk_stats
Algorithm 1	Sec. 4	lrtr/diagnostic.py:interface_floor_dia
$\Sigma, v \mapsto \ A\ _F^2, \ A\mathbf{1}\ ^2$	Lem. 4.3	lrtr/diagnostic.py:tied_energy_moments
$\frac{1}{F} \mathbb{E}_S \ A\mathbf{1}_S\ ^2$	Prop. 6.5	lrtr/interface.py:linear_energy_uniform
energy floor	Eq. (3)	lrtr/interface.py:energy_floor_uniform
threshold decoder Q	Thm. 6.1	lrtr/threshold.py:threshold_decode
fixed-code trial	Alg. efalg:two, l. 5–7	lrtr/threshold.py:recovery_trial_fixed
streaming trial	Alg. efalg:ensemble, l. 6–10	lrtr/threshold.py:recovery_trial_strea
Algorithm efalg:two	Sec. efsec:method	lrtr/diagnostic.py:fixed_code_separati
Algorithm efalg:ensemble	Sec. efsec:alg-ensemble	lrtr/diagnostic.py:random_code_scaling
$\text{tr}(H\Sigma) - F$	Lem. eflem:suffstat	lrtr/interface.py:crosstalk_mean_sq
leverage form of r	Prop. efprop:leverage	lrtr/interface.py:crosstalk_mean_sq_pi
s_{95}	Alg. efalg:two, l. 9	lrtr/threshold.py:s95_from_curve

Then

$$\sum_{i \neq j} |M_{ij}|^2 \geq \frac{F(F-d)}{d}. \quad (1)$$

Consequently, if $F > d$,

$$\frac{1}{F(F-1)} \sum_{i \neq j} |M_{ij}|^2 \geq W(F, d) := \frac{F-d}{d(F-1)}, \quad (2)$$

and hence $\max_{i \neq j} |M_{ij}| \geq \sqrt{W(F, d)}$. In particular, if $F/d \rightarrow \infty$ then $\max_{i \neq j} |M_{ij}| \geq (1 - o(1)) d^{-1/2}$.

Proof. Since $M = G\Phi$ with $G \in \mathbb{R}^{F \times d}$ and $\Phi \in \mathbb{R}^{d \times F}$ we have $\text{rank}(M) \leq d$, and the unit diagonal gives $\text{tr}(M) = F$. For any matrix of rank at most d , $|\text{tr}(M)| \leq \|M\|_* \leq \sqrt{d} \|M\|_F$ (Appendix D), so $F^2 \leq d \|M\|_F^2$. Expanding $\|M\|_F^2 = F + \sum_{i \neq j} |M_{ij}|^2$ gives (1), and dividing by $F(F-1)$ gives (2). For the maximum, note that $\max_{i \neq j} |M_{ij}|^2 \geq \frac{1}{F(F-1)} \sum_{i \neq j} |M_{ij}|^2$, and take square roots. $\square$

The argument is the standard rank–trace mechanism, cf. [8]; we give it in full only for self-containedness. The next corollary is what the diagnostic actually uses, because it removes the normalisation hypothesis.

Corollary 5.2 (Gain-normalised form). *Let $F > d$ and let $M = G\Phi$ satisfy $\text{rank}(M) \leq d$ and $M_{ii} \neq 0$ for all i . Then*

$$\max_{i \neq j} \frac{|M_{ij}|}{|M_{ii}|} \geq \sqrt{\frac{F - d}{d(F - 1)}}.$$

Proof. Apply Theorem 5.1 to $D^{-1}M$ with $D = \text{diag}(M_{11}, \dots, M_{FF})$: this matrix has rank at most d , unit diagonal, and entries M_{ij}/M_{ii} . $\square$

Remark 5.3 (Why the gain normalisation is essential). Without a diagonal normalisation the absolute off-diagonal entries of $G\Phi$ can be made arbitrarily small by shrinking G , and the floor appears to fail. A concrete instance: take Φ to be the three unit vectors at 120° in $\mathbb{R}^2$ — an equiangular tight frame — and $G = D\Phi^\top$ with $D = \text{diag}(1/10, 1/20, 1/20)$. Then $G\Phi$ has diagonal $(1/10, 1/20, 1/20)$ and maximum off-diagonal entry $1/20$, ten times *below* $\sqrt{(F - d)/(d(F - 1))} = 1/2$. There is no contradiction: this interface reads out its own coordinates with gains far below one, and after recalibrating each row to unit gain the maximum off-diagonal entry becomes exactly $1/2$ — the floor, attained with equality. Corollary 5.2 isolates the scale-invariant content: what is bounded below is the interference-to-gain ratio. This example is verified in the test suite, and Section 9.2 shows that a gradient optimiser left free of the constraint exploits exactly this degree of freedom.

Proposition 5.4 (Equality within the tied family). *Let $\Phi \in \mathbb{R}^{d \times F}$ have unit-norm columns and let $G = \Phi^\top$, so that $M = \Phi^\top \Phi$ has unit diagonal. Then $\sum_{i \neq j} |M_{ij}|^2 \geq F(F - d)/d$, with equality if and only if $\Phi\Phi^\top = (F/d)I_d$, that is, iff Φ is a unit-norm tight frame.*

Proof. The diagonal entries are $\|\phi_i\|^2 = 1$. By cyclicity, $\|M\|_F^2 = \text{tr}((\Phi\Phi^\top)^2) = \|\Sigma\|_F^2$ with $\Sigma = \Phi\Phi^\top \succeq 0$ and $\text{tr } \Sigma = F$. Cauchy–Schwarz on the eigenvalues of Σ gives $\|\Sigma\|_F^2 \geq (\text{tr } \Sigma)^2/d = F^2/d$, with equality iff all d eigenvalues coincide, i.e. $\Sigma = (F/d)I_d$. Subtracting the diagonal contribution F gives the claim. $\square$

Within this family — unit-norm columns read out by their own transpose — equality therefore characterises tight frames, consistent with [7, 8]. We

stress the scope: it is a statement about the tied Gram matrix, not about every rank- d unit-diagonal interface. Other readouts attain the same floor under different conditions, and the next proposition identifies the condition for the pseudoinverse. Whether learned codes find such configurations is an empirical question, answered in Section 9.2.

Proposition 5.5 (The pseudoinverse ratio is a leverage statistic). *Let $\Phi \in \mathbb{R}^{d \times F}$ have full row rank, let $G = \Phi^+$, and write $P = \Phi^+ \Phi$ for the orthogonal projector onto the row space, with leverage scores $h_i = P_{ii} \in (0, 1]$. Then the gain-normalised interface $\widetilde{M} = D^{-1}P$ satisfies*

$$\sum_{i \neq j} \widetilde{M}_{ij}^2 = \sum_{i=1}^F \frac{1}{h_i} - F, \quad \text{so} \quad r = \frac{d}{F(F-d)} \left(\sum_{i=1}^F \frac{1}{h_i} - F \right).$$

Since $\sum_i h_i = \text{tr } P = d$, Cauchy-Schwarz gives $\sum_i h_i^{-1} \geq F^2/d$ with equality iff $h_i = d/F$ for every i . Hence $r \geq 1$, and $r = 1$ exactly when leverage is equalised across features.

Proof. P is symmetric idempotent, so row i obeys $\sum_j P_{ij}^2 = P_{ii} = h_i$ and $D_{ii} = h_i$. Dividing row i by h_i and removing the unit diagonal entry leaves $(h_i - h_i^2)/h_i^2 = h_i^{-1} - 1$; summing over i gives the identity. The inequality is Cauchy-Schwarz applied to $\sum_i h_i \cdot \sum_i h_i^{-1} \geq F^2$, and dividing by $F(F-1)$ and by $W(F, d) = (F-d)/(d(F-1))$ turns it into $r \geq 1$. $\square$

This is worth stating because it deflates a natural over-reading of a ratio close to one under the pseudoinverse readout. Attaining the floor with $G = \Phi^+$ says that the code spreads its features evenly over the row space — nothing more. It is a statement about the geometry of the code, not about whether the code is a good representation for any task; a code can have perfectly equalised leverage and still be useless. We use this to scope the empirical claims of Section 9.3.

Corollary 5.6 (No better-than-floor ε -linear readout). *Let $F > d$ and suppose G satisfies $\|Gy_i - e_i\|_\infty \leq \delta$ for singleton states y_i , with $\delta < 1/2$. Then $\delta/(1-\delta) \geq \sqrt{(F-d)/(d(F-1))}$; in particular $\delta = \Omega(d^{-1/2})$ when $F/d \rightarrow \infty$.*

Proof. Let $M = G[y_1, \dots, y_F]$. The hypothesis gives $|M_{ii} - 1| \leq \delta$ and $|M_{ji}| \leq \delta$ for $j \neq i$. Calibrating, $|\widetilde{M}_{ij}| \leq \delta/(1-\delta)$, and Theorem 5.1 applies to $\widetilde{M}$. $\square$

6. Threshold recovery and the separation

The floor rules out small-error ε -linear readout with $\varepsilon = o(d^{-1/2})$ when $F \gg d$. It does not rule out thresholded Boolean recovery, because thresholding does not require every inactive score to be small — only that the aggregate interference stay below the margin.

Theorem 6.1 (Threshold recovery under coherent superposition). *Let Φ have unit-norm columns with coherence μ , let b be s -sparse, let $x = \Phi b + \eta$ with $\|\Phi^\top \eta\|_\infty \leq \nu$, and let $Q(z)_i = \mathbf{1}\{z_i \geq 1/2\}$. If $s\mu + \nu < 1/2$ then $Q(\Phi^\top x) = b$, with margin $\tau = \frac{1}{2} - (s\mu + \nu) > 0$.*

Proof. For $i \in S = \text{supp}(b)$ we have $z_i = 1 + \sum_{j \in S, j \neq i} \langle \phi_i, \phi_j \rangle + \langle \phi_i, \eta \rangle \geq 1 - (s-1)\mu - \nu \geq \frac{1}{2} + \tau$. For $i \notin S$, $z_i \leq s\mu + \nu = \frac{1}{2} - \tau$. $\square$

Corollary 6.2 (Random codes at quadratic load). *Let $F = \lfloor d^2 \rfloor$ and let $\phi_1, \dots, \phi_F$ be independent uniform unit vectors in $\mathbb{R}^d$. Then $\mu \leq 6\sqrt{\log d/d}$ with probability at least $1 - d^{-5}$ for all sufficiently large d , and on that event the threshold decoder recovers every s -sparse Boolean state whenever $\|\Phi^\top \eta\|_\infty < \frac{1}{2} - 6s\sqrt{\log d/d}$.*

Proof. For independent uniform unit vectors u, v , the inner product $\langle u, v \rangle$ has the law of the first coordinate of a uniform point on S^{d-1} , whose tail satisfies $\Pr\{|\langle u, v \rangle| > t\} \leq 2\exp(-(d-1)t^2/2)$ for $0 < t < 1$ (see e.g. [21, Thm. 3.4.6]). Taking a union bound over the $\binom{F}{2}$ unordered pairs and using $2\binom{F}{2} \leq F^2 \leq d^4$,

$$\Pr\{\mu > t\} \leq d^4 \exp\left(-\frac{(d-1)t^2}{2}\right).$$

With $t = 6\sqrt{\log d/d}$ we have $\frac{(d-1)t^2}{2} = 18(1 - 1/d)\log d \geq 9\log d$ for $d \geq 2$, so $\Pr\{\mu > t\} \leq d^4 e^{-9\log d} = d^{-5}$. The recovery claim is then Theorem 6.1 with $\mu \leq t$. $\square$

The worst-case coherence bound is pessimistic for a *random* support, which is the case the diagnostic measures. The following average-case statement is the one used in Algorithms 2 and 3.

Theorem 6.3 (Random-support threshold recovery). *Let Φ have independent uniform unit-vector columns and let S be a uniformly random support*

of size s , independent of Φ . For $\delta \in (0, 1)$ there is a universal $C > 0$ such that, with probability at least $1 - \delta$,

$$\max_{i \in [F]} \left| \sum_{j \in S, j \neq i} \langle \phi_i, \phi_j \rangle \right| \leq C \sqrt{\frac{s \log(F/\delta)}{d}},$$

and on that event thresholding $\Phi^\top(\Phi \mathbf{1}_S + \eta)$ at $1/2$ recovers $\mathbf{1}_S$ whenever $\|\Phi^\top \eta\|_\infty + C \sqrt{s \log(F/\delta)/d} < 1/2$.

Proof. Conditionally on S and on ϕ_i , the summands are independent and each is distributed as the first coordinate of a uniform point on S^{d-1} , hence sub-Gaussian with variance proxy $O(1/d)$ [21, Thm. 3.4.6]. The sum of at most s of them is sub-Gaussian with proxy $O(s/d)$, so $\Pr\{|I_i| > t \mid S\} \leq 2 \exp(-c_0 d t^2 / s)$. A union bound over $i \in [F]$ and the stated choice of t give the claim; the recovery statement follows as in Theorem 6.1. Full details are in Appendix C. $\square$

Remark 6.4 (Which randomness the probability is over). The guarantee of Theorem 6.3 is *annealed*: the probability is taken over the joint draw of the code Φ and the support S . It is therefore the right statement for Algorithm 3, which redraws the code at every trial, and it is not directly the statement for Algorithm 2, which holds one code fixed. A quenched version — Φ fixed, probability over S alone — follows from concentration for sampling without replacement, but it is not free: it needs hypotheses on the particular Φ (bounded coherence and bounded row sums of $|\Phi^\top \Phi| - I$), which a given trained code may or may not satisfy. We do not assume them. What the fixed-code diagnostic reports is therefore an empirical recovery rate with a Wilson interval, and the theorem is quoted as the ensemble-level expectation it is, not as a guarantee about the code in hand. The analog side has no such caveat: Proposition 6.5 is exact for every fixed Φ .

We now give the average linear-readout error under the *same* distribution, which is what allows the two criteria to be compared without a distributional mismatch.

Proposition 6.5 (Average linear energy floor, uniform random supports). *Let $F > d$, let $M = G\Phi \in \mathbb{R}^{F \times F}$ satisfy $\text{rank}(M) \leq d$ and $M_{ii} = 1$ for all i , and set $A = M - I_F$. Let $S \subseteq [F]$ be a uniformly random support of size s with $1 \leq s \leq F/2$ and let $b = \mathbf{1}_S$. Then*

$$\mathbb{E}_S \|Ab\|_2^2 \geq \frac{s(F-s)}{F(F-1)} \|A\|_F^2 \geq \frac{s(F-s)(F-d)}{d(F-1)}. \quad (3)$$

In particular $\frac{1}{F}\mathbb{E}_S \|Ab\|_2^2 \geq \frac{s(F-d)}{2d(F-1)}$, which is $\Omega(s/d)$ whenever $F/d \rightarrow \infty$.

Proof. For a uniformly random size- s support, $\mathbb{E}[b_i] = s/F$ and $\mathbb{E}[b_i b_j] = \frac{s(s-1)}{F(F-1)}$ for $i \neq j$. Hence $\mathbb{E}[bb^\top] = (p - q)I_F + q\mathbf{1}\mathbf{1}^\top$ with $p = s/F$ and $q = \frac{s(s-1)}{F(F-1)}$, and

$$p - q = \frac{s(F-1) - s(s-1)}{F(F-1)} = \frac{s(F-s)}{F(F-1)}.$$

Therefore $\mathbb{E}_S \|Ab\|_2^2 = \text{tr}(A^\top A \mathbb{E}[bb^\top]) = (p - q) \|A\|_F^2 + q \|A\mathbf{1}\|_2^2 \geq (p - q) \|A\|_F^2$. Since A has zero diagonal and $\text{rank}(M) \leq d$ with unit diagonal, Theorem 5.1 gives $\|A\|_F^2 \geq F(F-d)/d$, which yields the second inequality. For $s \leq F/2$ we have $F-s \geq F/2$, and dividing by F gives the per-coordinate form. $\square$

Corollary 6.6 (Separation at quadratic load, one sparse-state model). *Let $F = d^2$ and let Φ have independent uniform unit-vector columns. There is a universal $c > 0$ such that, for $1 \leq s \leq cd/\log d$ and a uniformly random support S of size s , thresholding $\Phi^\top \Phi \mathbf{1}_S$ at $1/2$ recovers $\mathbf{1}_S$ exactly with probability at least $1 - d^{-10}$ for all sufficiently large d . For the same sparse-state model, every unit-diagonal rank- d linear readout has average per-coordinate squared error at least $\frac{s(F-d)}{2d(F-1)} = \Omega(s/d)$, and hence RMS error $\Omega(\sqrt{s/d})$.*

Proof. Apply Theorem 6.3 with $\delta = d^{-10}$, so $\log(F/\delta) = 12 \log d$; the interference bound is $C\sqrt{12s \log d/d}$, which is below $1/2$ as soon as $s \leq cd/\log d$ with $c < 1/(48C^2)$. The second statement is Proposition 6.5 with $F = d^2$. $\square$

Remark 6.7 (What the separation compares). The two sides compare different *interface criteria* on the same input distribution: expected squared linear readout error versus exact-recovery probability of a threshold decoder. Neither criterion dominates the other in general. The content of Corollary 6.6 is that at quadratic feature load one of them is attainable exactly and the other is provably not, in the same regime — which is precisely the quantity Algorithm 2 reports. Corollary 6.6 is stated for uniform supports; the Bernoulli variant, with the same conclusion, is in Appendix C.

7. Application: two frameworks, two invariants

We now apply the interface distinction to the two frameworks whose apparent tension motivated this work. All statements imported from the source

papers were checked against arXiv:2408.05451v1 and arXiv:2409.15318v3; the audit is recorded in Appendix [Appendix B](#).

Lemma 7.1 (Computation-layer interface; restated from [1, Thm. 11]). *Fix $s = O(1)$ and suppose the targeted superpositional AND primitive of Hänni et al. is applied in a regime satisfying its stated graph-balancing, sparsity, norm and incoming-interference hypotheses. Then the computation layer produces outgoing readout error $\varepsilon_{\text{comp}}(d) = \tilde{O}(\sqrt{s^2/d}) = \tilde{O}(d^{-1/2})$.*

Lemma 7.2 (Correction-layer tolerance; restated from [1, Thm. 21]). *The correction layer admits incoming error $\varepsilon_{\text{in}} < K(d) d^{1/4}/(F^{1/2} s^{1/4})$ with $K(d) = \text{polylog}(d)$, and produces $\varepsilon_{\text{out}} = O((\log d) \sqrt{s/d})$ and $\mu_{\text{out}} = \tilde{O}(\sqrt{s/d})$.*

Proposition 7.3 (Template compatibility threshold; derived from Lemmas 7.1–7.2). *Fix $s = O(1)$. The published Hänni computation–correction template is certified in the regime $F \lesssim \tilde{O}(d^{3/2})$, and its recursive construction emulates circuits of width m using width $d = \tilde{O}(m^{2/3} s^2)$, giving a matching certified scale $\tilde{\Theta}(d^{3/2})$. This is a template-specific certificate, not an impossibility result for other implementations.*

Proof. The correction theorem applies after the computation layer when $\varepsilon_{\text{comp}}(d) \lesssim \varepsilon_{\text{corr,max}}(F, d, s)$, i.e. $\tilde{O}(d^{-1/2}) \lesssim K(d) d^{1/4}/F^{1/2}$ for $s = O(1)$. Suppressing polylogarithmic factors, $F^{1/2} \lesssim d^{3/4}$, hence $F \lesssim \tilde{O}(d^{3/2})$. Conversely, inverting $d = \tilde{O}(m^{2/3} s^2)$ at $s = O(1)$ gives $m = \tilde{\Omega}(d^{3/2})$. $\square$

In the Adler–Shavit framework, exact Boolean state is restored by thresholding after every stage. Their parameter-description lower bound $\Omega(m' \log m')$, converted to neurons under their architectural assumption of $\Theta(n^2)$ parameters with $O(1)$ average description length each, gives $F_{\text{rec}}^{\text{AS}}(n) \leq O(n^2/\log n)$; their explicit construction uses $n = O(\sqrt{m'} \log m')$ neurons, giving $F_{\text{rec}}^{\text{AS}}(n) \geq \Omega(n^2/\log^2 n)$. The remaining logarithmic gap is open.

The two regimes do not contradict each other, and the reason is now precise. The Hänni template maintains an approximate ε -linear interface, so it must feed its residual error into a correction theorem whose tolerance is $\tilde{O}(d^{1/4}/F^{1/2})$; matching that tolerance to the unavoidable $d^{-1/2}$ cross-talk scale of Theorem 5.1 gives the $d^{3/2}$ threshold. Adler–Shavit instead threshold, leaving the small-error class entirely, so Corollary 5.6 does not apply to them. In the vocabulary of Section 4: the first framework operates where the diagnostic’s attainment ratio matters, the second where its criterion-separation witness does.

8. Experimental setup

Six campaigns validate the diagnostic, from controlled random codes to a trained network. E1–E3 establish that the implementation measures what the theory describes; E4 tests whether *learned* codes attain the floor; E5 applies the diagnostic to trained models; E6 tests how the recovery threshold scales.

Environment. All experiments run on CPU only, with no CUDA device. Python 3.12.10, NumPy 2.4.4, SciPy 1.17.1, PyTorch 2.13.0+cpu on a 14-core machine; thread counts are pinned and two cores are reserved for the system. Every campaign writes a run record with the exact command, seeds, configuration, environment, wall-clock duration and exit status. Total measured compute is 343.8 minutes (Table 7).

E1 — floor on random codes. $d \in \{16, 32, 64, 128\}$, $F/d \in \{2, 4, 8, 16\}$, 15 independent codes per configuration, three readouts (tied, pseudoinverse and an i.i.d. Gaussian readout as an adversarial control), and a harmonic tight frame at each (d, F) as the equality witness.

E2 — recovery and separation at $F = d^2$. $d \in \{64, 128, 256\}$, 200 trials per configuration, thresholds $\theta \in \{0.4, 0.5, 0.6\}$ (3 values) as a sensitivity ablation.

E3 — average linear energy. $d \in \{32, 64, 128\}$ at $F = 8d$, sparsities $s \in \{1, 2, 4, 8, 16, 32, 64, 128\}$, energies computed in closed form under both the Bernoulli and the uniform-support model, with a 20 000-draw Monte Carlo cross-check of the closed form.

E4 — optimised codes. $d \in \{16, 32, 64\}$, $F/d \in \{2, 4, 8, 16\}$ (12 configurations), Adam at learning rate 10^{-2} for 20 000 steps, 168 runs in total across four variants: *free* (G and Φ independent), *tied* ($G = \Phi^\top$), *smooth-max*, and the *uncalibrated* ablation in which the diagonal constraint is removed.

E5 — trained toy model. The compressed-computation task of [13]: $d = 50$, $F = 100$, inputs with each coordinate active with probability $p \in \{0.01, 0.02\}$ and value $\sim U[-1, 1]$, target $\text{ReLU}(x)$, $\hat{y} = W_{\text{out}}\text{ReLU}(W_{\text{in}}x)$ trained by Adam for 50 000 steps under an L^2 and an L^4 loss, 5 seeds each, plus an i.i.d. random-code control at the same (d, F) . Diagnosis uses 400 evaluation trials per sparsity and three linear readouts, including a least-squares readout fitted

on the evaluation distribution — deliberately the strongest linear baseline we can give the competing criterion.

E6 — scaling.. $d \in \{128, 256, 512, 1024\}$ at $F = d^2$, up to $F = 1\,048\,576$ features. The code is never materialised: each trial regenerates it in blocks from a counted seed sequence and evaluates every sparsity in one pass using nested supports.

Statistics.. Recovery probabilities carry Wilson 95% intervals. Group comparisons in E5 use a two-sided exact Mann–Whitney U test with Cliff’s δ as effect size. The scaling law in E6 is a one-parameter least-squares fit of $s_{95} = cd/\ln d$, the shape being predicted by the theory and only the constant free; with 4 points the fit is reported as a consistency check, not as an estimate with inferential force.

Reproducibility.. Every figure and table in this paper is generated from the raw result files by a script, and every measured number in the text is a macro emitted from those same files; a checker regenerates the macros, compares them against the file on disk, and fails the build on any mismatch, on a macro the text uses but does not define, and on a macro defined but never used. We are explicit about the limit of that guarantee: it certifies that the *values* match the saved results, not that the sentences around them draw the right conclusion. Prose claims still need a reader. Commands are in Appendix [Appendix A](#).

A note on E6’s linear side.. To keep the cost of the largest widths manageable, the exact linear-energy statistic is computed on every fifth trial rather than every trial, so its averages rest on fewer samples than the recovery curves (10 trials against 50 at $d = 1\,024$). The recovery probabilities use the full budget.

9. Results

9.1. E1–E3: the diagnostic measures what the theory describes

Across 16 configurations, 15 trials each and three readouts — 720 calibrated interfaces in total — the floor was violated 0 times. This is a correctness check on the implementation rather than evidence for Theorem [5.1](#), and we report it as such.

The attainment ratio of the tied readout falls from 1.999 at the lowest feature load to 1.063 at the highest (Table 3, Fig. 1a): a random code is close to Welch-optimal in the mean-square sense once F/d is large, since $\mathbb{E}\langle\phi_i, \phi_j\rangle^2 = 1/d$ while $W(F, d) \rightarrow 1/d$ from below. At $d = 128$, $F = 2048$ the tied ratio is 1.0662 and the pseudoinverse ratio is 1.0010, the latter being the closer of the two at high load. In all 16 configurations the harmonic tight frame attains the floor to within 4e-16 of exact equality, confirming Proposition 5.4 at machine precision. The Gaussian control, by contrast, reaches ratios as large as 3.4e+08: the bound holds for it too, but nothing forces an arbitrary readout to be anywhere near the floor, and the diagnostic’s attainment ratio is therefore informative across seven orders of magnitude rather than a formality.

Fig. 1b shows threshold recovery at $F = d^2$. The transition moves right with d , from $s_{95} = 1$ at $d = 64$ to $s_{95} = 2$ at $d = 256$. At $d = 256$ and $s = s_{95}$, thresholding is exact in at least 95% of trials while the calibrated linear interface retains a per-coordinate RMS error of 0.0884, which is 1.41 times the $d^{-1/2}$ scale and above its own theoretical floor of 0.0882. That pair of numbers is the criterion-separation witness of Problem 4.1, measured.

The threshold is a hyperparameter, and $\theta = 1/2$ is not a privileged choice. At $d = 256$ the recovery threshold moves from $s_{95} = 1$ at $\theta = 0.4$ to $s_{95} = 2$ at $\theta = 0.5$ and $s_{95} = 4$ at $\theta = 0.6$. Raising it helps here because, with unit-norm codes and Boolean states, active scores concentrate near one while inactive scores concentrate near zero, so a higher cut trades false positives for false negatives favourably in this regime; the individual interference terms are of course signed. Two limits on how far this ablation goes: the three thresholds re-decode the *same* trials rather than independent replications, so they show the sensitivity of the decision rule and not of the sampling; and at the smallest width the effect is not merely numerical — at $d = 64$, $\theta = 0.4$ no sparsity reaches the 95% level at all, so no certificate exists there.

E3 confirms the energy scale (Fig. 1c). Over 24 configurations the ratio $E/(s/d)$ lies in $[0.9735, 1.0088]$ — the s/d reference scale is essentially exact for random codes — with 0 violations of either energy floor, and the closed forms agree with a 20 000-draw Monte Carlo estimate to within a relative 0.0013.

Measured against the *proved* uniform-support floor of Proposition 6.5, however, the ratio lies in $[1.1395, 2.2165]$: the bound is correct but conservative by a factor between one and two in this regime. That is expected and worth stating plainly, since it bounds what the diagnostic can certify. Two




Figure 1: **The Interface Diagnostic on random codes.** (a) Attainment ratio $\widehat{W}/W(F, d)$ of the calibrated tied readout versus feature load; shaded bands are the min-max range over trials, the dashed line is the floor of Theorem 5.1. (b) Exact threshold recovery at $F = d^2$ with Wilson 95% intervals; the dotted line marks the 0.95 level defining s_{95} . (c) Average per-coordinate linear energy under uniformly random supports against the s/d reference. Generated by `scripts/make_figures.py` from `results/e1`, `results/e2` and `results/e3`.

Table 3: E1: attainment ratio $\widehat{W}/W(F, d)$ of the calibrated tied readout for random unit-norm codes, averaged over 15 trials. Values above one are required by Theorem 5.1; the approach to one with growing feature load is the content of the measurement.

d	F/d			
	2	4	8	16
16	1.899	1.298	1.130	1.063
32	1.966	1.327	1.141	1.065
64	1.972	1.329	1.141	1.066
128	1.999	1.332	1.141	1.066

steps of the proof give the slack: the non-negative $q \|A\mathbf{1}\|^2$ term is discarded, and $\|A\|_F^2$ is replaced by its worst case $F(F - d)/d$ rather than the value realised by the code at hand. The looser the feature load, the larger the second effect — here $F = 8d$, so $(F - d)/F = 7/8$ alone accounts for part of the gap. Algorithm 2 therefore reports the *exact* energy computed from the code’s own frame operator, and uses the floor only as the guarantee that the quantity can never be zero.

9.2. E4: learned codes attain the floor

Gradient descent under the unit-diagonal constraint drives the interface to the floor (Table 4, Fig. 2). Over 60 runs of the free variant, spanning all

12 configurations, the attainment ratio reaches a mean of 1.0006 and never exceeds 1.0176, with 0 runs below the floor. The tied variant is sharper still: over 36 runs, mean ratio 1.0000 with a maximum of 1.0000 (0 below the floor), and a relative tight-frame residual of 0.0013 on average (worst case 0.0016). In other words, the optimiser recovers the equality case of Proposition 5.4: a unit-norm tight frame emerges from gradient descent rather than being constructed.

The smooth-max variant is the one that does *not* reach its target, and the reason is structural rather than a tuning failure. Over 36 runs it attains a mean mean-square ratio of 1.5050 (worst case 3.5230, 0 below the floor) and drives the maximum off-diagonal entry only to 3.125 times $\sqrt{W(F, d)}$. Equality in the maximum form requires an equiangular tight frame, and those exist only for special (d, F) — none of our 12 configurations is guaranteed to admit one. The maximum form of the bound is therefore approached but not attained here, which is the expected outcome and not evidence against the bound.

The uncalibrated ablation is the most informative of the four, and its outcome is more extreme than we expected. Removing the diagonal constraint does not lead the optimiser to a code with low interference: it leads it to the trivial solution. Across all 36 runs the *raw* off-diagonal energy collapses to 6.61e-09 — the readout is driven to zero — and with it the diagonal gains, whose smallest absolute value reaches 0 in single precision. In 25 of the 36 runs the calibration is therefore undefined and Algorithm 1 returns DEGENERATE; in the remaining runs the calibrated interface still respects the floor, and in no run did it fall below (0 violations). An unconstrained optimiser reports spectacular apparent cross-talk while destroying the interface it was supposed to build. This is Remark 5.3 as an experiment, and it is the reason step 4 of Algorithm 1 exists and reports a status rather than a number.

9.3. E5: the separation inside a trained network

Table 5 and Fig. 3 report the diagnostic applied to the compressed-computation models. Three findings stand out; one of them we did not anticipate, and one prediction we had made was not borne out.

The L^4 -trained network attains the floor.. Its calibrated linear interface has attainment ratio 1.0006 under the pseudoinverse readout (range [1.0005, 1.0006] over 5 seeds) and 1.0216 under the fitted least-squares readout (range [1.0206, 1.0223]), against a floor of $W = 0.01010$. The L^2 baseline sits at 28.8135 and the




Figure 2: **Optimised codes attain the Welch floor.** (a) Attainment ratio during optimisation of the free variant; bands are min-max over configurations and seeds. (b) Final cross-talk against the floor across every configuration and variant; the dashed line is equality. Generated by `scripts/make_figures.py` from `results/e4`.

Table 4: E4: attainment of the floor by gradient-optimised codes, 168 runs over 12 configurations. “Below floor” counts runs whose calibrated interface fell under the theoretical bound; it must be zero. The uncalibrated ablation has no meaningful calibrated ratio by construction.

variant	runs	mean $\widehat{W}/W$	max $\widehat{W}/W$	below floor	
free (G, Φ independent)	60	1.0006	1.0176	0	
tied ($G = \Phi^\top$)	36	1.0000	1.0000	0	
smooth-max	36	1.5050	3.5230	0	
uncalibrated (ablation)	36	n/a	n/a	0	raw ratio $\geq 1.5e - 16$, min $ M $

random-code control at 1.0550. E4 had shown the floor to be reachable by direct optimisation of the cross-talk; here it is approached by a network optimising a task loss that never mentions interference.

Two caveats on the statistics, both cutting against reading too much into them. First, the comparison with the random code is readout-dependent: L^4 is closer to the floor than an i.i.d. code of the same shape under the pseudoinverse (1.0006 versus 1.0170) and under least squares, but its own trained decoder is *farther* from the floor (1.0260) than either. That last figure has no counterpart in the control and we do not pair it with one: the random code has no trained decoder, so its W_{out} column is by construction the pseudoinverse and would be compared against a different object. Across the readouts that do admit a matched comparison, the trained code is comparable to a random one on this axis, not better. Second, every pairwise test returns

$p = 0.0079$ with $|\delta| = 1$, which is exactly the smallest two-sided p an exact Mann–Whitney can produce at $n = 5$ per group: within-group variance is negligible, so the test reports “no overlap” and nothing more. The effect sizes are what separate the cases, and they differ by orders of magnitude — 28.8135 versus 1.0216 for L^2 against L^4 , a few percent for L^4 against random. No multiplicity correction is applied across the nine tests, and at this n none would survive one.

The separation is real but much narrower than we predicted, and the s_{95} statistic runs against us.. Our pre-registered expectation was that the network’s thresholded output would remain exact over a strictly wider sparsity range than its best linear readout. The measurement contradicts that at the sparsities where both work. Ranking the three linear readouts by exact-recovery rate at each s and taking the best of them, the network is behind up to $s = 4$: at $s = 3$ both are exact, and at $s = 4$ the network recovers in 0.844 of trials while the calibrated W_{out} interface recovers in 0.985. On the s_{95} statistic the linear readout is strictly ahead — $s_{95} = 4$ against the network’s 3 on all 5 seeds at $p = 0.010$, and ahead on 3 of 5 seeds (tied on the remainder) at $p = 0.020$ (Table 5). The preregistered comparison is not supported.

The network only leads further out, where both decoders are already unreliable: at $s = 5$, 0.745 versus 0.294, and at $s = 6$, 0.426 versus 0.136. E5 therefore shows the network extending the usable sparsity range past the point where the thresholded linear readouts of its own code have collapsed, not dominating them everywhere.

The floor statement is on firmer ground, but it is worth being exact about what it is. At every sparsity analog reconstruction carries irreducible error: at $s = 3$, where the network is exact in 1.000 of trials, the best linear readout still has per-coordinate RMS error 0.1733 against its floor of 0.1714. That non-zero error is Theorem 5.1 restated for this code, not an independent measurement — any rank- d unit-diagonal interface has it by construction. What E5 measures is its *size* for a code that gradient descent actually produced, and how far the thresholded decoder gets before that error stops it.

The L^2 model is maintaining a linear interface.. This is the finding we did not plan for. In the L^2 models the ReLU is active on only 4.6% of preactivations, the learned decoder sits at relative distance 0.011 from the pseudoinverse of the encoder, and the network’s thresholded decision agrees with

that of a plain linear readout on 99.1% of evaluation states. The L^4 models are elsewhere: ReLU active on 48.6% of preactivations, decoder at relative distance 0.726, and agreement with the linear readout down to 21.8%. The diagnostic thus reproduces, from interface measurements alone and without any mechanistic reverse-engineering, the distinction that [3] and [4] reached by other means. It also explains why the L^2 model is bound by Theorem 5.1 at all: a network that keeps an effectively linear readout *is* a linear readout for these inputs, and its measured ratio of 28.8135 says how far from optimal that readout is. Its thresholded output recovers even a single active feature only 0.491 of the time.

The finding replicates at a second training sparsity.. Everything above is measured at $p = 0.010$. Repeating the whole campaign at $p = 0.020$ (ablation A5, 5 fresh seeds per condition) reproduces both halves: the L^4 models sit at 1.0217 against the floor and agree with a linear readout on only 22.3% of states, while the L^2 models sit at 45.1973 and agree 99.7% of the time. The interface distinction is therefore not an artefact of one input sparsity.

What does not favour our hypothesis.. Three things. The L^4 models have a worse mean squared error on the training task than the L^2 models (1.19e-03 versus 8.30e-04), as expected since they optimise a different objective: the interface advantage is not a task-performance advantage, and we do not claim it is. The s_{95} prediction above failed. And the random-code control is a reminder that a good interface is not by itself evidence of computation: its *linear* readout recovers exactly with probability 0.698 at $s = 3$, better than the L^2 network, simply because an i.i.d. code is already near-Welch-optimal (ratio 1.0550). What the random control lacks is the nonlinear stage; the “network” column for that row is not meaningful and is reported only for completeness.

9.4. E6: how the recovery threshold scales

Scaling to $d = 1024$ at $F = 1048576$ features lets the recovery threshold be traced over a factor of eight in width (Table 6, Fig. 4). On the grid, s_{95} grows from 1 at $d = 128$ to 8 at $d = 1024$.

That grid statistic needs care, because it floors the crossing and floors it unevenly. The true 95% crossing lies between grid points, and the gap is proportionally largest where the transition is sharp relative to the spacing — at $d = 128$ the interpolated crossing is 1.18 against a reported 1. Interpolating instead of flooring changes the headline: growth over the sweep falls




Figure 3: **Interface separation inside a trained toy model of computation in superposition.** A width-50 network trained to compute 100 sparse ReLU features (setup of [13]; L^4 variant of [4]); one point per seed. (a) Attainment ratio of the learned calibrated interface against the floor of Theorem 5.1. (b) Exact recovery by the network’s thresholded output (solid) versus the best linear readout of the same code (dotted). (c) Per-coordinate RMS error of the best linear readout against the energy floor of Proposition 6.5. Generated by `scripts/make_figures.py` from `results/e5`.

Table 5: E5: the diagnostic applied to trained models, averaged over 5 seeds at training sparsity $p = 0.010$. “Agrees with linear” is the fraction of evaluation states on which the network’s thresholded decision coincides with that of a plain linear readout — the quantity that identifies which interface the model maintains.

model	$\widehat{W}/W$	s_{95} (network)	s_{95} (best linear)	ReLU clipped (%)	agrees with linear (%)
L^4 -trained	1.022	3.0	4.0	48.6	21.8
L^2 -trained	28.814	0.0	0.0	4.6	99.1
random code	1.055	0.0	2.0	50.0	13.8

from 8.00 to 6.89, against 5.60 for an exact $d/\ln d$ law. The floored figure therefore overstates the growth by roughly a third, purely as an artefact of the grid, and we quote the interpolated values from here on.

On the interpolated crossings a one-parameter fit of $s_{95} = cd/\ln d$ gives $c = 0.0563$ with $R^2 = 0.9882$ over 4 points. This is consistent with the predicted shape but does not establish it: a plain linear law cd reaches $R^2 = 0.9636$ and $cd/\ln^2 d$ reaches $R^2 = 0.9630$ on the same four points. Four widths cannot separate these, and the base of the logarithm is not identifiable at all. We report the fit as a consistency check on a shape the theory predicts, not as evidence for it over the alternatives.

Two further qualifications. The reference curve $d/(16\ln d)$ drawn in Fig. 4b sits *above* the measured thresholds at every width (9.23 against 8




Figure 4: **Threshold recovery at quadratic feature load, up to $d = 1024$ ($F = 1\,048\,576$).** (a) Empirical exact-recovery probability with Wilson 95% intervals; a fresh random code is drawn per trial. (b) The empirical threshold $s_{95}(d)$ against the fitted $c d / \ln d$ law and the conservative union-bound reference $d / (16 \ln d)$. Generated by `scripts/make_figures.py` from `results/e6`.

Table 6: E6: recovery threshold and measured cost by width.

d	$F = d^2$	trials	s_{95}	$d / (16 \ln d)$	wall clock (min)
128	16 384	200	1	1.65	1.5
256	65 536	200	2	2.89	2.2
512	262 144	100	5	5.13	4.9
1024	1 048 576	50	8	9.23	21.3

at $d = 1024$): recovery fails somewhat earlier than that curve suggests, so it is not the conservative lower reference its form implies. The constant 16 is inherited from the earlier literature and is not derived anywhere here — Corollary 6.6 fixes only the shape $s \leq c d / \log d$ for an unspecified universal c — so the curve should be read as a visual landmark, nothing more. And s_{95} is a point estimate: at $d = 1024$ the campaign runs 50 trials, so even a flawless 50-for-50 result gives a Wilson lower bound of only 0.929. No sparsity at that width can be certified at the 95% level with 95% confidence on this budget; the reported thresholds are best estimates, and a claim at confidence would need more trials.

The whole campaign took 29.9 minutes on CPU, with $d = 1024$ accounting for 21.3 of them over 50 trials. Materialising the code at that size would have required 4 GB; the streaming implementation of Algorithm 3 keeps the peak footprint proportional to Bd .

Table 7: Measured computational cost. All campaigns are CPU-only; no GPU is used anywhere in this work.

campaign	question	jobs	workers	wall clock (min)
E1	floor on random codes	–	1	0.6
E2	recovery at $F = d^2$	–	1	67.5
E3	average linear energy	–	1	0.2
E4	optimised codes	168	12	169.6
E5	trained toy model	25	6	76.1
E6	scaling to $d = 1024$	–	4	29.9
total				343.8

9.5. Cost and traceability

Every campaign ran on CPU alone; Table 7 reports the measured wall clock, which totals 343.8 minutes across the six. Table 8 closes the loop between the claims above and the artefacts behind them: for each experimental claim it names the figure or table that shows it, the raw result file the numbers come from, and the script and configuration that produce that file. Together with the automatic check that every measured number in this manuscript matches the saved results (Appendix [Appendix A](#)), this is what makes the reported quantities auditable rather than merely stated.

Table 8: Traceability: each experimental claim, the figure or table that shows it, the raw result file it comes from, and the script and configuration that produce it. Reproduction commands are in Appendix [Appendix A](#).

claim	figure / table	raw result file	script (config)
The floor is respected by every calibrated interface	Tab. 3, Fig. 1a	results/e1/raw/e1_results	experiments/e1_welch_floor.py (configs/e1.json)
Threshold recovery succeeds where linear readout cannot be exact	Fig. 1b	results/e2/raw/e2_results	experiments/e2_threshold_recovery.py (configs/e2.json)
Average linear energy follows the s/d scale	Fig. 1c	results/e3/raw/e3_results	experiments/e3_linear_energy.py (configs/e3.json)
Learned codes attain the floor	Tab. 4, Fig. 2	results/e4/raw/e4_results	experiments/e4_optimized_codes.py (configs/e4.json)
A trained network attains the floor and separates the two criteria	Tab. 5, Fig. 3	results/e5/raw/e5_results	experiments/e5_trained_toy.py (configs/e5.json)
$s_{95}(d)$ grows with the $d/\ln d$ scale	Tab. 6, Fig. 4	results/e6/raw/e6_results	experiments/e6_threshold_scaling.py (configs/e6.json)

10. Discussion

The results support a simple reading. The floor is not an obstacle that networks struggle against; it is a target that both direct optimisation and ordinary task training reach. E4 shows that gradient descent under the unit-diagonal constraint converges to a unit-norm tight frame, and E5 shows that a network trained on a task, with no interference objective at all, lands within 1.0006 of the same bound. What distinguishes models is not whether they approach the floor but whether the floor *binds* them — that is, whether they maintain a linear readout interface in the first place. The L^2 model does, measurably; the L^4 model does not, and it is the latter whose thresholded output keeps working past the sparsity at which the thresholded linear readouts of its own code have collapsed. The margin is narrow, and below that point the linear readout is the better decoder — so this is evidence that leaving the linear class buys headroom at the hard end, not that it dominates.

This gives the debate in [3, 4] an instrument. The question “does this network compute in superposition?” becomes two measurements: how far the network’s decision function is from a linear readout of its own code, and how far that code is from the floor. Neither requires reverse-engineering the mechanism.

For capacity theory, the interface distinction explains why the Hänni and Adler–Shavit results coexist rather than compete (Section 7). It also cautions against reading sparse-autoencoder dictionary sizes as computation capacities: those are reconstructive quantities, and the diagnostic makes explicit that reconstruction and recursive Boolean decoding are governed by different criteria.

10.1. Limitations

1. **One trained setting.** E5 covers a single toy task at $d = 50$, $F = 100$, with 5 seeds per condition. Nothing here is a claim about large trained language models.
2. **Out-of-distribution evaluation.** The diagnostic is defined on Boolean sparse states, while the toy models are trained on continuous sparse inputs. It therefore measures which interface the learned code *supports*, not what the network does on its native distribution.
3. **Constant sparsity in the application.** The Hänni-template comparison assumes $s = O(1)$, whereas the distributional results allow s up to $O(d/\log d)$; real features are continuous with heterogeneous sparsity.
4. **The floor bounds linear readouts only.** Nonlinear decoders and distribution-specific average-case mechanisms are outside its scope — which is the point of the separation, but also a limit on what the diagnostic can certify.
5. **Fit with few points.** The $cd/\ln d$ fit in E6 rests on 4 widths, on which a plain linear law fits nearly as well ($R^2 = 0.9636$ against 0.9882). The data are consistent with the predicted shape and do not discriminate it from the alternatives; the logarithm’s base is not identifiable at all.
6. **s_{95} is a point estimate, not a certified threshold.** The trial budget shrinks with width, and at $d = 1024$ even a perfect run gives a Wilson lower bound of 0.929— below the 95% level being estimated. The reported thresholds are best estimates; certifying them at confidence would need more trials at the large widths.

7. **The linear side’s non-exactness is the theorem, not a measurement.** Wherever we report that a linear readout “cannot be exact”, that follows from Theorem 5.1 by construction for any rank- d unit-diagonal interface. What the experiments measure is the *magnitude* of that error for codes that were actually learned, and how far a threshold decoder gets before it bites.
8. **Correlated curve points.** The nested-support trick makes each point of $p_{\text{rec}}(s)$ marginally unbiased but correlates points within a trial; the Wilson intervals are per-point and should not be read as a joint confidence band.
9. **Open log gap.** The Adler–Shavit capacity bracket retains a single logarithmic factor of slack, which is not resolved here.

10.2. Open problem

Corollary 5.6 shows that no reset staying inside the small-error ε -linear class can improve the worst-case cross-talk scale beyond $d^{-1/2}$ when $F \gg d$, while Theorem 6.3 shows thresholded recovery survives to $s = O(d/\log d)$ at quadratic load. Any interpolation beyond the Hänni template must therefore leave the small-error linear class. This makes one question concrete.

Conjecture 10.1 (Generic robust threshold reset). Fix $s = O(1)$. There are constants $c, C, K > 0$ such that for every d and every $F \leq c d^2 / \log^C d$ there exist a code $\Phi \in \mathbb{R}^{d \times F}$, an input readout R_{in} , a width- $\tilde{O}(d)$ reset module $\mathcal{R}_{\Phi} : \mathbb{R}^d \rightarrow \mathbb{R}^d$ and a scoring map S such that, for every s -sparse b and every x with $\|R_{\text{in}}x - b\|_{\infty} \leq K d^{1/2} / (F^{1/2} s^{1/4})$, the output $z = \mathcal{R}_{\Phi}(x)$ is composable with the next stage and satisfies $b_i = 1 \Rightarrow (Sz)_i \geq 3/4$ and $b_i = 0 \Rightarrow (Sz)_i \leq 1/4$.

The incoming-error tolerance is the essential clause: a reset theorem for clean inputs $x = \Phi b$ alone would not support recursive composition. By Corollary 5.6 any proof must use an explicitly nonlinear or thresholded decoding mechanism, as Adler–Shavit do.

11. Conclusion

We proposed the Interface Diagnostic, a computable procedure that decides which decoding interface an overcomplete code or a trained network maintains, and how far it is from the best possible one. The procedure rests on a rank–trace floor for unit-diagonal linear readouts, in a gain-normalised

form that bounds the interference-to-gain ratio, and on a separation between the linear and threshold criteria proved under one and the same sparse-state model. It runs in $O(Fd^2)$ time and $O(d^2)$ memory and scales to $F \approx 10^6$ features on a laptop CPU.

Six campaigns validate it. Codes optimised under the unit-diagonal constraint reach the floor, with the tied variant converging to a unit-norm tight frame. A network trained on the compressed-computation task under an L^4 loss attains the floor to within 1.0006 and separates the two criteria, while the L^2 baseline is shown by direct measurement to maintain an effectively linear interface and to sit a factor 28.8135 above the floor. Threshold recovery scales to $d = 1\,024$ with an empirical threshold consistent with a $cd/\ln d$ law.

The broader lesson is that capacity questions for overcomplete representations are not settled by counting features. They depend on which decoding interface is maintained across computation, and that is now something one can measure.

Acknowledgements

The authors thank the VRAIN institute and the Universitat Politècnica de València for institutional support, and two frame-theory researchers who, after reading the preprint, pointed out prior work containing the proof mechanism of Theorem 5.1 and raised the calibration question that became Corollary 5.2 and Remark 5.3.

Funding

H.B. acknowledges support from the UPV doctoral programme. No additional external funding was received for the submitted work.

CRedit authorship contribution statement

Hector Borobia: Conceptualization, Methodology, Software, Formal analysis, Investigation, Validation, Visualization, Writing – original draft. **Elies Seguí-Mas:** Supervision, Methodology, Writing – review & editing. **Guillermina Tormo-Carbó:** Supervision, Methodology, Writing – review & editing.

Declaration of competing interest

The authors declare that they have no known competing financial interests or personal relationships that could have appeared to influence the work reported in this paper.

Data availability

No human-subject, biological, clinical or proprietary data were generated or analysed. All data underlying the figures and tables are synthetic, generated by the released code from recorded seeds, and are included as raw JSON result files in the public repository.

Code availability

All code, configurations, logs, raw results and the sources of this manuscript are publicly available at <https://github.com/hechoar/linear-readout-threshold-recovery>, together with a single entry point that reproduces every experiment, table and figure (Appendix [Appendix A](#)).

Declaration of generative AI and AI-assisted technologies in the writing process

During the preparation of this work the authors used AI-assisted tools for exploratory mathematical checking, drafting support, language editing and literature-search assistance. After using these tools the authors reviewed and edited the content as needed and take full responsibility for the content of the publication. AI tools are not listed as authors and did not determine the research questions, proof strategy or final claims. All mathematical statements, proofs, citations and comparisons with source papers were verified by the authors.

References

- [1] K. Hänni, J. Mendel, D. Vaintrob, L. Chan, Mathematical models of computation in superposition, version v1, 10 August 2024 (2024). [arXiv:2408.05451](#).
- [2] M. Adler, N. Shavit, On the complexity of neural computation in superposition, version v3, 26 February 2026 (2024). [arXiv:2409.15318](#).

- [3] J. Bhagat, S. Molas-Medina, G. Giguemiani, S. Heimersheim, Compressed computation is (probably) not computation in superposition (2026). [arXiv:2606.14673](#).
- [4] F. Ferreira da Silva, S. Heimersheim, Compressed computation under l^4 loss is likely computation in superposition (2026). [arXiv:2607.04800](#).
- [5] L. R. Welch, Lower bounds on the maximum cross correlation of signals, IEEE Transactions on Information Theory 20 (3) (1974) 397–399.
- [6] T. Strohmer, R. W. Heath, Grassmannian frames with applications to coding and communication, Applied and Computational Harmonic Analysis 14 (3) (2003) 257–275.
- [7] S. Waldron, Generalized Welch bound equality sequences are tight frames, IEEE Transactions on Information Theory 49 (9) (2003) 2307–2309.
- [8] S. Datta, S. D. Howard, D. Cochran, Geometry of the Welch bounds, Linear Algebra and its Applications 437 (10) (2012) 2455–2470, preprint [arXiv:0909.0206](#).
- [9] R. Aceska, M. Kaczanowski, Cross frame potential, Numerical Functional Analysis and Optimization 43 (14) (2022) 1663–1678, preprint [arXiv:2205.05613](#).
- [10] O. Christensen, S. Datta, R. Y. Kim, Equiangular frames and generalizations of the Welch bound to dual pairs of frames, Linear and Multilinear Algebra 68 (12) (2020) 2495–2505.
- [11] M. Adler, D. Alistarh, N. Shavit, Towards combinatorial interpretability of neural computation (2025). [arXiv:2504.08842](#).
- [12] L. Kong, I. Subramanian, Y. Shavit, M. Adler, D. Alistarh, N. Shavit, Expand neurons, not parameters (2025). [arXiv:2510.04500](#).
- [13] D. Braun, L. Bushnaq, S. Heimersheim, J. Mendel, L. Sharkey, Interpretability in parameter space: Minimizing mechanistic description length with attribution-based parameter decomposition (2025). [arXiv:2501.14926](#).

- [14] F. Ferreira da Silva, S. Heimersheim, Evidence for feature-specific error correction in LLMs (2026). [arXiv:2606.24964](#).
- [15] A. Klappenecker, M. Rötteler, Mutually unbiased bases are complex projective 2-designs, in: Proceedings of the IEEE International Symposium on Information Theory (ISIT), 2005, pp. 1740–1744.
- [16] H. Cunningham, A. Ewart, L. Riggs, R. Huben, L. Sharkey, Sparse autoencoders find highly interpretable features in language models (2023). [arXiv:2309.08600](#).
- [17] L. Gao, T. D. la Tour, H. Tillman, et al., Scaling and evaluating sparse autoencoders (2024). [arXiv:2406.04093](#).
- [18] T. Lieberum, S. Rajamanoharan, A. Conmy, et al., Gemma scope: Open sparse autoencoders everywhere all at once on Gemma 2 (2024). [arXiv:2408.05147](#).
- [19] E. J. Michaud, L. Gorton, T. McGrath, Understanding sparse autoencoder scaling in the presence of feature manifolds (2025). [arXiv:2509.02565](#).
- [20] L. Sharkey, B. Chughtai, J. Batson, et al., Open problems in mechanistic interpretability (2025). [arXiv:2501.16496](#).
- [21] R. Vershynin, High-Dimensional Probability: An Introduction with Applications in Data Science, Cambridge University Press, 2018.
- [22] W. B. Johnson, J. Lindenstrauss, Extensions of Lipschitz mappings into a Hilbert space, in: Contemporary Mathematics, Vol. 26, American Mathematical Society, 1984, pp. 189–206.
- [23] H. Borobia, E. Seguí-Mas, G. Tormo-Carbó, How pruning reshapes features: Sparse autoencoder analysis of weight-pruned language models (2026). [arXiv:2603.25325](#).
- [24] Y. Liu, Z. Liu, J. Gore, Superposition yields robust neural scaling (2025). [arXiv:2505.10465](#).
- [25] N. Elhage, T. Hume, C. Olsson, et al., Toy models of superposition (2022). [arXiv:2209.10652](#).

Appendix A. Reproduction

From a clean checkout:

```
python -m venv .venv && . .venv/bin/activate      # Windows: .venv\Scripts\activate
python -m pip install -r requirements.txt
python -m pytest -q tests/                        # 104 tests
bash scripts/run_all.sh                          # Windows: scripts\run_all.ps1
```

Individual campaigns, each of which writes `results/<id>/run_record.json` with the exact command, seeds, environment, duration and exit status:

```
python experiments/e1_welch_floor.py
python experiments/e2_threshold_recovery.py
python experiments/e3_linear_energy.py
python experiments/e4_optimized_codes.py
python experiments/e5_trained_toy.py
python experiments/e6_threshold_scaling.py
```

Adding `-smoke` to any of them runs a reduced configuration end to end in seconds. Figures, tables and the generated numbers are rebuilt with `scripts/make_figures.py`, `scripts/make_tables.py` and `scripts/make_numbers.py`; `scripts/check_manuscript_numbers.py` verifies that every measured number in this manuscript matches the saved results and exits non-zero otherwise. E6 writes results per width and per chunk and resumes an interrupted campaign without recomputing completed trials.

Appendix B. Verification of imported statements

Every statement imported from the two source frameworks was checked against the published version. Table B.9 records the audit.

Appendix C. Auxiliary proofs

Appendix C.1. Sub-Gaussian interference

Let $u, u_1, \dots, u_m$ be independent uniform unit vectors in $\mathbb{R}^d$. Conditionally on u , each $X_j = \langle u, u_j \rangle$ is distributed as the first coordinate of a uniform point on S^{d-1} , hence has mean zero and is sub-Gaussian with variance proxy C_0/d for a universal C_0 [21, Thm. 3.4.6]. The X_j are conditionally independent, so their sum is sub-Gaussian with proxy $C_0 m/d$ and $\Pr\{|\sum_j X_j| > t\} \leq 2 \exp(-c_0 d t^2/m)$ with $c_0 = 1/(2C_0)$. This is the estimate used in Theorem 6.3.

Appendix C.2. The Bernoulli variant of the energy floor

Under $b_i \sim \text{Bernoulli}(p)$ independently, $\mathbb{E}[bb^\top] = p(1-p)I_F + p^2\mathbf{1}\mathbf{1}^\top$, so $\mathbb{E}_b \|Ab\|^2 = p(1-p) \|A\|_F^2 + p^2 \|A\mathbf{1}\|^2 \geq p(1-p)F(F-d)/d$ by Theorem 5.1. With $p = s/F$ and $s \leq F/2$ this gives $\frac{1}{F}\mathbb{E}_b \|Ab\|^2 \geq \frac{s(F-d)}{2dF} = \Omega(s/d)$, matching Proposition 6.5 up to the $(F-1)$ versus F denominator. Both variants are computed by the released code and both are reported in E3.

Appendix D. The nuclear-norm inequality

For $M \in \mathbb{R}^{F \times F}$ with singular value decomposition $M = \sum_{k=1}^r \sigma_k u_k v_k^\top$,

$$|\text{tr}(M)| = \left| \sum_k \sigma_k u_k^\top v_k \right| \leq \sum_k \sigma_k |u_k^\top v_k| \leq \sum_k \sigma_k = \|M\|_*,$$

and by Cauchy–Schwarz on $(\sigma_1, \dots, \sigma_r)$, $\|M\|_*^2 \leq r \sum_k \sigma_k^2 = r \|M\|_F^2$. With $r \leq d$ this gives $|\text{tr}(M)|^2 \leq d \|M\|_F^2$, as used in Theorem 5.1. Note that the identity $\text{tr}(M) = \sum_k \sigma_k$ holds only for positive semidefinite matrices and is *not* used.

Appendix E. Reference scales

The scales appearing in this literature count different objects and should not be read as a capacity ordering. Writing $F_{\text{CS}}(d, \alpha) = d g(\alpha)$ with $g(\alpha) = 1/((1-\alpha) \ln(1/(1-\alpha)))$ for compressed-sensing-style linearly decodable storage, $F_{\text{cert}}^{\text{H}}(d) = \tilde{\Theta}(d^{3/2})$ for the Hänni template certificate, $L_{\text{AS}}(d) = d^2/\log^2 d$ and $U_{\text{AS}}(d) = d^2/\log d$ for the two sides of the Adler–Shavit bracket, and $N_{\text{JL}}(d; \varepsilon) = \exp(\Theta(d\varepsilon^2))$ for Johnson–Lindenstrauss packing [22], one has

$$F_{\text{CS}} \ll F_{\text{cert}}^{\text{H}} \ll L_{\text{AS}} \lesssim F_{\text{rec}}^{\text{AS}} \lesssim U_{\text{AS}} \ll N_{\text{JL}}$$

as $d \rightarrow \infty$. This does not mean that recursive computation beats storage: N_{JL} counts passively packable states, F_{CS} counts linearly decodable features through a compressed bottleneck, and the middle two count recursively computable Boolean features under two different published frameworks. Michaud et al. [19] give a complementary reason why an observed dictionary size may fall below the template scale: if feature manifolds consume capacity, the relevant comparison is the effective dimension rather than the raw feature count.

Appendix F. Sparse-autoencoder context

As background only, our companion study [23] trains TopK sparse autoencoders ($k = 64$, expansion $8d$) on three language models and observes no dead features at $F = 8d$, placing those dictionaries well below both the $d^{3/2}$ template scale and the near-quadratic Adler–Shavit scale. Sparse-autoencoder dictionary size is a reconstructive quantity and is not a measurement of recursive computation capacity; these numbers are not used in any proof or experiment of the present paper, and are mentioned only to indicate where current empirical dictionaries sit relative to the scales of Appendix [Appendix E](#). Liu et al. [24] and Elhage et al. [25] provide further context on why strong superposition regimes are of interest.

Table B.9: Audit of imported statements.

source	as printed there	as used here
[1, Thm. 11]	targeted superpositional AND, precision $\varepsilon_{\text{in}} \rightarrow \varepsilon_{\text{out}}$ with $\varepsilon_{\text{out}} = \tilde{O}(\sqrt{s^2/d})$	Lemma 7.1, $\varepsilon_{\text{comp}}(d) = \tilde{O}(d^{-1/2})$ at $s = O(1)$
[1, Thm. 14]	$\varepsilon^{(1)} = \tilde{O}(\max\{s\mu, \sqrt{s\varepsilon}, \sqrt{s/d}\})$, $\mu^{(1)} = \tilde{O}(\max\{\sqrt{1/d}, \mu\})$	quoted in Sec. 7 only to note it does not by itself preserve the $\tilde{O}(d^{-1/2})$ invariant
[1, Cor. 15]	relaxes the near-sphere hypothesis of Thm. 14 at the cost of depth $1 \rightarrow 3$	not used for a capacity claim
[1, Thm. 21]	tolerance $\varepsilon < K d^{1/4}/(m^{1/2}s^{1/4})$, output $\varepsilon^{(1)} = O(\log(d)\sqrt{s}/\sqrt{d})$, $\mu^{(1)} = \tilde{O}(\sqrt{s}/\sqrt{d})$	Lemma 7.2 with m in the role of F
[1, Thm. 8]	width $d = \tilde{O}(m^{2/3}s^2)$, depth $2L$	Proposition 7.3, inverted at $s = O(1)$
[2]	$\Omega(\sqrt{m'} \log m')$ neurons and $\Omega(m' \log m')$ parameters; construction with $O(\sqrt{m'} \log m')$ neurons; at most $O(n^2/\log n)$ features with n neurons	Sec. 7; the parameter-to-neuron conversion is flagged as an architectural assumption of that model
[6, Thm. 2.3]	$\max_{i \neq j} \langle \phi_i, \phi_j \rangle \geq \frac{\sqrt{(F-d)/(d(F-1))}}{\sqrt{(F-d)/(d(F-1))}}$ for unit-norm systems	the Gram case of Theorem 5.1; the reduction is noted in Sec. 2.3