Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

OIL TEST SET · TRANSFORMER OIL BDV TESTER

CIE/7100

Transformer oil BDV tester · manual / motorised · IS 6792:1992

01 KEY FEATURES

- Memory device retains breakdown reading
- Zero-start interlocking
- Interlocked H.T. door cutout
- Manual or motorised drive
- Analog moving-iron kV meter
- Standard test vessel, IS 6792:1992

02 WHAT'S IN THE BOX

- ✓ Instruction manual with circuit diagram
- ✓ Input supply cable, minimum 2 metres, 3-pin plug
- ✓ Test vessel (oil cell) with electrode and gap-setting gauge

03 OPTIONS & ACCESSORIES (extra cost)

- + Alternate tripping current set point
- + Digital metering in place of analog
- + 2-unit housing
- + Magnetic stirrer



CIE/7100 · OIL TEST SET

04 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION
ELECTRICAL	
Output Voltage	0–100 kV (continuously variable)
Capacity	1000 VA
Input	230 V ±10%, 50 Hz, 1 phase A.C.
Duty	Intermittent
H.V. Winding	Cast-resin, graded insulation, centre point grounded
METERING & TEST VESSEL	
Metering	96 mm² A.C. moving-iron voltmeter, L.T. side, scaled in kV (analog)
Motorised Rate	Approx. 2 kV/second (motorised variant)
Test Vessel	Two brass spheres, 12.5–13 mm dia., 4mm or 2.5mm gap, per IS 6792:1992
GENERAL	
Warranty	12 months against manufacturing defects only

05 CIE/7000 SERIES - OUTPUT VOLTAGE & CAPACITY

OUTPUT VOLTAGE	CAPACITY	MANUAL MODEL	MOTORISED MODEL
0–50 kV	500 VA	CIE/7050	CIE/7050 MOT
0–60 kV	600 VA	CIE/7060	CIE/7060 MOT
0–70 kV	700 VA	CIE/7070	CIE/7070 MOT
0–75 kV	750 VA	CIE/7075	CIE/7075 MOT
0–80 kV	800 VA	CIE/7080	CIE/7080 MOT
0–90 kV	900 VA	CIE/7090	CIE/7090 MOT
0–100 kV	1000 VA	CIE/7100	CIE/7100 MOT
0–120 kV	1200 VA	CIE/7120	CIE/7120 MOT

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/7100 Product Catalogue.