Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL INSULATION TESTER

# DIT-2500

Up to 2500 V · 50 GΩ · True-RMS multimeter · CAT III 1000 V / CAT IV 600 V

| Up to 2500V | 50 GΩ | CAT III / IV | 380 g |
|---|---|---|---|
| MAX TEST VOLTAGE | MAX RESISTANCE (2500 V) | 1000 V / 600 V | WEIGHT, INCL. BATTERY |

## 01 KEY SPECIFICATIONS

| | |
|---|---|
| INSULATION TEST | 100 / 250 / 500 / 1000 / 2500 V |
| IR RANGE | Up to 50 GΩ (at 2500 V) |
| DAR / PI | Built-in · 15 s / 30 s / 1 min / 10 min |
| MULTIMETER | True-RMS · AC/DC to 1500 V |
| SAFETY | CAT III 1000 V · CAT IV 600 V |
| POWER | Li-ion 3.7 V × 2, rechargeable |




DIT-2500 · INSULATION TESTER

## 02 TECHNICAL SPECIFICATIONS

| PARAMETER | SPECIFICATION |
|---|---|
| **INSULATION RESISTANCE RANGE, BY TEST VOLTAGE** | |
| 100 V | 0.1 MΩ – 2 GΩ |
| 250 V | 0.25 MΩ – 5 GΩ |
| 500 V | 0.5 MΩ – 10 GΩ |
| 1000 V | 1 MΩ – 20 GΩ |
| 2500 V | 2.5 MΩ – 50 GΩ |
| **INSULATION TEST** | |
| Accuracy | ±(3% + 5) to 399.9 MΩ · ±(5% + 5) 0.4–2 GΩ · ±(10% + 5) 2.001–50 GΩ |
| Open-circuit voltage | 90% – 110% of rated |
| Short-circuit current | ≥ 1 mA |
| DAR | 1 min : 15 s and 1 min : 30 s |
| PI | 10 min : 60 s |
| **MULTIMETER (TRUE-RMS)** | |
| DC voltage | 6 V – 600 V ±(0.5% + 5) · 1500 V ±(1% + 5) |
| AC voltage | 6 V – 600 V ±(1.2% + 5) · 1500 V ±(2% + 5), 40 Hz – 1 kHz |
| Resistance | 600 Ω – 60 MΩ |
| Capacitance | 10 nF – 100 mF |
| Frequency | 10 Hz – 20 kHz (ACV 1 – 600 V) |
| Diode / continuity | Diode test · buzzer below approx. 50 Ω |
| **GENERAL** | |
| Safety category | CAT III 1000 V / CAT IV 600 V |
| Terminals | LINE, EARTH, GUARD (insulation) · VΩ, COM (multimeter, max. 1500 V) |
| Battery | Li-ion 14500, 3.7 V × 2, rechargeable |
| Operating temperature | 0 – 40 °C, below 75% RH |
| Dimensions (L × W × H) | 189 × 89 × 55 mm |
| Weight | Approx. 380 g (incl. battery) |
| Warranty | 12 months |

## 03 APPLICATIONS

- Insulation resistance: motors, transformers, cables
- DAR / PI insulation quality assessment
- Switchgear, panel and cable commissioning

## 04 WHAT'S IN THE BOX

✓ Test leads ✓ Charging set ✓ Instruction manual



All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DIT-2500 Product Catalogue.