Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN, BATTERY-FREE

# CIE/444

## 1000 V / 0–100 MΩ

Hand-driven insulation tester · centrifugal governor · cross-coil indicator

## 01 KEY FEATURES

- Hand-cranked generator, no battery
- Centrifugal governor
- Cross-coil indicator
- Anti-parallax mirror scale
- Anti-magnetic aluminium, die-cast body
- Collapsible generator handle

Supplied as base instrument only - carrying case, test leads, and range options available at extra cost.




CIE/444 · INSULATION TESTER · ILLUSTRATIVE IMAGE

## 02 TECHNICAL SPECIFICATIONS

| PARAMETER | SPECIFICATION |
|---|---|
| **CONFIGURATION** | |
| Rated Test Voltage | 1000 V D.C. |
| Insulation Resistance Range | 0–100 MΩ |
| **MEASUREMENT** | |
| Scale Length | 90 mm (approx.) |
| Accuracy | Conforms to IS: 2992-1987 |
| Response Time | 3 seconds |
| **GENERATOR** | |
| Generator Type | Hand-driven generator, centrifugal governor |
| Rotation Speed | 160 r.p.m. or more |
| **TEST & SAFETY** | |
| High Voltage Test | Min. 2000V or (rated V + 1000)V A.C. r.m.s., 1 min |
| Insulation Resistance Test | Better than 50 MΩ at 500V D.C. |
| **GENERAL** | |
| Body | Anti-magnetic aluminium |
| Dimensions (L×W×H) | 110 × 128 × 195 mm (approx.) |
| Weight | 2.5 kg (approx.) |
| Warranty | 12 months against manufacturing defects only |

*Dual-voltage, dual-range and continuity options, and custom ranges, are available against specific requirements - enquire.*

## 03 APPLICATIONS

- Motors, generators, and other rotating machinery
- Insulation control and switching equipment checks
- Distribution network and cable insulation testing
- Transformer, insulator, and installation checks
- Locating shorts, defects, and insulation failures

## 04 OPTIONAL ACCESSORIES

+ Carrying case
+ Test leads, 1m/2m
+ H.V. test leads, 2m
+ Dual voltage/range option



All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/444 1000 V, 0-100 MΩ Product Catalogue.