Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL INSULATION TESTER · COMPACT, RECHARGEABLE

DIT-5005

1000 V / 0–2000 MΩ

3½-digit LCD · rechargeable Ni-Cd · IS 10656-1983

01 KEY FEATURES

- 3½-digit LCD, direct readout
- Rechargeable Ni-Cd cells
- Bench-top or hand-held use
- Lo-Bat indication
- Rugged ABS body



DIT-5005 · DIGITAL INSULATION TESTER · ILLUSTRATIVE IMAGE

02 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION
CONFIGURATION	
Rated Test Voltage	1000 V D.C.
Insulation Resistance Range	0–2000 MΩ
MEASUREMENT	
Display	3½ digits, L.C.D.
Accuracy - Insulation	±3% of F.S. ±5 digits
Accuracy - Output Voltage (DC)	±10% at rated resistance
Confirms To	IS 10656-1983
TEST & SAFETY	
H.V. Test	2 kV A.C. (r.m.s.), 1 min., circuit to containing case
Insulation Resistance Test	More than 50 MΩ at 500V D.C.
GENERAL	
Dimensions (L×W×H)	172 × 98 × 38 mm (approx.)
Weight	550 g (approx.)
Warranty	12 months against manufacturing defects only

Other ranges can be built against specific requirements - enquire.

03 APPLICATIONS

- Insulation measurement of electrical equipment (motors, transformers, machines)
- Household appliances (mixers, toasters, washing machines)
- Industrial, commercial, and residential installations
- Electrical cables for distribution and communication networks

04 WHAT'S IN THE BOX

- ✓ Carrying case
- ✓ Charging cord
- ✓ Testing lead, 1m
- ✓ Instruction manual

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DIT-5005 1000 V, 0-2000 MΩ Product Catalogue.