Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, WOODEN BODY

# CIE/666/MR

Multirange insulation tester · selectable voltage · continuity range · wooden body

## 01 KEY FEATURES

- Selectable multi-voltage operation
- Built-in continuity range
- Seasoned wooden body, sunmica finish




CIE/666/MR · INSULATION TESTER

## 02 TECHNICAL SPECIFICATIONS

| PARAMETER | SPECIFICATION |
|---|---|
| Body | Seasoned wooden, sunmica finish |
| Generator Type | Hand-driven |
| Series Available | MR-1 to MR-8 (full range, incl. HV series MR-5–8) |
| Continuity Range | Built-in as standard on all MR series |
| Warranty | 12 months against manufacturing defects only |

*Any configuration apart from the standard MR series above can be built to order.*

## 03 AVAILABLE SERIES - VOLTAGE, RANGE & CONTINUITY

| SERIES | VOLTAGE & RESISTANCE RANGES | CONTINUITY RANGE |
|---|---|---|
| MR-1 | 1000V/0–2000MΩ · 500V/0–1000MΩ · 250V/0–500MΩ | 0–20 KΩ |
| MR-2 | 1000V/0–200MΩ · 500V/0–100MΩ · 250V/0–50MΩ | 0–1 KΩ |
| MR-3 | 500V/0–1000MΩ · 250V/0–500MΩ · 100V/0–200MΩ | 0–5 KΩ |
| MR-4 | 500V/0–100MΩ · 250V/0–50MΩ · 100V/0–20MΩ | 0–1 KΩ |
| MR-5 | 2500V/0–5000MΩ · 1000V/0–2000MΩ · 500V/0–1000MΩ | 0–20 KΩ |
| MR-6 | 2500V/0–1000MΩ · 1000V/0–200MΩ · 500V/0–100MΩ | 0–1 KΩ |
| MR-7 | 5000V/0–20000MΩ · 2500V/0–10000MΩ | 0–20 KΩ |
| MR-8 | 5000V/0–5000MΩ · 2500V/0–2500MΩ | 0–5 KΩ |

## 04 APPLICATIONS

- High-voltage multi-voltage field insulation testing
- Multi-voltage transformer and cable testing to 5000V
- Both low- and high-voltage testing in one instrument

## 05 OPTIONAL ACCESSORIES

+ Carrying case
+ Test leads, 1m
+ H.V. test leads, 2m (general)
+ H.V. test leads, 2m (special)



All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666/MR Product Catalogue.