



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN, UP TO 10KV

CIE/666

Hand-cranked analog insulation tester in seasoned wooden body - available in single-range configurations from 100V to 10,000V, wider range than metal-body CIE/444.

100–10000V

AVAILABLE RANGES, SPECIFY AT ORDER

Battery-Free

HAND-CRANKED GENERATOR

3 Seconds

RESPONSE TIME

Insulation Tester - Wooden Body, Hand-Driven

A hand-driven generator-type insulation tester in a seasoned wooden cabinet - wider voltage range than the metal-body CIE/444, suited to HV switchgear and higher-class transformer testing up to 10,000 V.

- **No batteries required** - hand-cranked generator
- **Centrifugal governor** - holds output voltage constant
- **Seasoned wooden body** - detachable lid, handle, lock
- **3-second response** - quick direct reading

Supplied as base instrument only - carrying case, test leads, and range options available at extra cost.

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



CIE/666 · INSULATION TESTER

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	Seasoned wooden, sunmica finish, detachable lid & lock
Generator Type	Hand-driven generator, centrifugal governor
Scale Length	100 mm (approx.)
Accuracy	Conforms to IS: 2992-1987
Rotation Speed	160 r.p.m. or more
High Voltage Test	Min. 2000V or (rated V + 1000)V A.C. r.m.s., 1 min
Insulation Resistance Test	Better than 50 M Ω at 500V D.C.
Guard Terminal & Infinity Adjuster	Provided on instruments with insulation range 1000 M Ω and above
Response Time	3 seconds
Range Configuration	Multiple range options available - specify at order
Dimensions (L×W×H)	265 × 165 × 185 mm (approx.)
Weight	4.1 kg (approx.)
Warranty	12 months against manufacturing defects

Custom ranges and configurations can also be built against specific requirements.

02 Typical Applications

- Motors, generators, and other rotating machinery
- Insulation control and switching equipment checks
- HV switchgear and transformer testing to 10,000V
- Locating shorts, defects, and insulation failures

03 Optional Accessories

- + Carrying case
- + Test leads, 1m/2m
- + H.V. test leads, 2m
- + Dual voltage/range option

Cambridge Instruments & Engg. Co.

cieinstruments.in

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Product Catalogue.