



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · TRUE-RMS MULTIMETER

DIT-2500

Insulation resistance testing up to 2500 V, 50 GΩ max, combined with a full True-RMS digital multimeter.

Up to **2500V**

MAX TEST VOLTAGE

50 GΩ

MAX RESISTANCE

CAT III/IV

SAFETY RATING

380 g

WEIGHT, HANDHELD

Digital Insulation Tester + Multimeter

One handheld instrument for insulation-resistance testing up to 2500 V and full True-RMS multimeter duty - built for motor, transformer, cable and switchgear commissioning.

- **Insulation test to 2500V** - 100/250/500/1000/2500V, 50 GΩ max
- **Built-in DAR & PI** test mode - 15s/30s/1min/10min timer
- **True-RMS multimeter** - AC/DC to 1500V, 60 MΩ, 100 mF
- **CAT III 1000V / CAT IV 600V** safety rated
- **Rechargeable Li-ion** battery, 3.7V × 2
- **Backlit LCD**, data hold, auto power-off
- Compact **189×89×55 mm**, 380 g

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



DIT-2500 · INSULATION TESTER

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Insulation Test Voltage	100V / 250V / 500V / 1000V / 2500V
Insulation Resistance Range	0.1 MΩ - 50 GΩ
Short Circuit Current	≥ 1 mA
DAR	1 min : 15 s and 1 min : 30 s
PI	10 min : 60 s
DC / AC Voltage	1 mV - 1500 V
Resistance	0.1 Ω - 60 MΩ
Capacitance	0.001 nF - 100 mF
Measurement Type	True-RMS
Battery	Li-ion 3.7 V × 2 (rechargeable)
Safety Category	CAT III 1000 V / CAT IV 600 V
Dimensions (L×W×H)	189 × 89 × 55 mm
Weight	Approx. 380 g
Warranty	12 months against manufacturing defects

02 Typical Applications

- Insulation resistance testing on motors, transformers, and cables
- DAR and PI testing for insulation quality assessment
- Switchgear, panel, and cable commissioning

03 What's in the Box

- ✓ Test leads
- ✓ Charging set
- ✓ Instruction manual