Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, METAL BODY

# CIE/444/MR

Multirange · series MR-1 to MR-4 · built-in continuity range

**MR-1 to MR-4**
SERIES AVAILABLE, METAL BODY

**Built-In**
CONTINUITY RANGE, STANDARD

**Battery-Free**
HAND-CRANKED GENERATOR

## 01 KEY SPECIFICATIONS

| | |
|---|---|
| SERIES | MR-1 to MR-4 (metal body) |
| RANGES | 3 selectable ranges per series |
| CONTINUITY | Built-in, all series |
| GENERATOR | Hand-driven · no battery |
| BODY | Anti-magnetic aluminium, die-cast |

MR-5 to MR-8 are wooden-body only (see **CIE/666/MR**) - not available in this metal-body configuration.




CIE/444/MR · INSULATION TESTER

## 02 TECHNICAL SPECIFICATIONS

| PARAMETER | SPECIFICATION |
|---|---|
| Body | Anti-magnetic aluminium |
| Generator Type | Hand-driven |
| Series Available (Metal Body) | MR-1 to MR-4 only |
| Continuity Range | Built-in as standard on all MR series |
| Warranty | 12 months against manufacturing defects |

*Any configuration apart from the standard MR series above can be built to order.*

## 03 AVAILABLE SERIES - VOLTAGE, RANGE & CONTINUITY

| SERIES | VOLTAGE & RESISTANCE RANGES | CONTINUITY RANGE |
|---|---|---|
| MR-1 | 1000V/0–2000MΩ · 500V/0–1000MΩ · 250V/0–500MΩ | 0–20 KΩ |
| MR-2 | 1000V/0–200MΩ · 500V/0–100MΩ · 250V/0–50MΩ | 0–1 KΩ |
| MR-3 | 500V/0–1000MΩ · 250V/0–500MΩ · 100V/0–200MΩ | 0–5 KΩ |
| MR-4 | 500V/0–100MΩ · 250V/0–50MΩ · 100V/0–20MΩ | 0–1 KΩ |

## 04 APPLICATIONS

- Multi-voltage insulation testing on a single instrument
- Utilities needing flexible voltage selection
- Cable and transformer testing at varying voltages
- Substation and EPC commissioning

## 05 OPTIONAL ACCESSORIES

+ Carrying case
+ Test leads, 1m
+ H.V. test leads, 2m (general)
+ H.V. test leads, 2m (special)



All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/444/MR Product Catalogue.