Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL MULTIMETER · 3½-DIGIT, MANUAL RANGING

DM 235

3½-digit · manual ranging · 1000 V · 20 A · 200 MΩ · hFE

1000V DC / 750V AC	Up to 20A	200 MΩ
VOLTAGE RANGE	DC/AC CURRENT	MAX RESISTANCE

01 KEY SPECIFICATIONS

DC VOLTAGE	Up to 1000 V
AC VOLTAGE	Up to 750 V
DC / AC CURRENT	Up to 20 A
RESISTANCE	Up to 200 MΩ
DISPLAY	3½-digit, manual ranging
TESTS	Continuity, diode, hFE



DM 235 · DIGITAL MULTIMETER

02 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION
DISPLAY & RANGING	
Display	3½-digit
Ranging	Manual
VOLTAGE & CURRENT	
DC Voltage	200 mV / 2 V / 20 V / 200 V / 1000 V
AC Voltage	2 V / 20 V / 200 V / 750 V
DC Current	2 mA / 20 mA / 200 mA / 20 A
AC Current	20 mA / 200 mA / 20 A
OTHER MEASUREMENTS	
Resistance	200Ω / 2KΩ / 20KΩ / 200KΩ / 2MΩ / 20MΩ / 200MΩ
Capacitance	2000 pF / 20 nF / 200 nF / 2 µF / 20 µF
Additional Functions	Continuity, diode, transistor (hFE) test, auto power-off, low battery
GENERAL	
Power Supply	9 V battery
Dimensions (L×W×H)	170 × 87 × 35 mm
Weight	Approx. 210 g (incl. battery)
Warranty	12 months against manufacturing defects

03 APPLICATIONS

- General electrical measurement
- Panel testing
- Workshop and field use

04 WHAT'S IN THE BOX

✓ Test leads ✓ User manual ✓ Battery ✓ Holster

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DM 235 Product Catalogue.