Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, WOODEN BODY

CIE/666/MR

Series MR-1 · 1000 / 500 / 250 V

Multirange insulation tester · selectable voltage · continuity range

01 KEY FEATURES

- Selectable multi-voltage operation
- Built-in continuity range
- Seasoned wooden body, sunmica finish



CIE/666/MR · INSULATION TESTER · ILLUSTRATIVE IMAGE

02 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION
Body	Seasoned wooden, sunmica finish
Generator Type	Hand-driven
Series	MR-1
Continuity Range	Built-in as standard on all MR series
Warranty	12 months against manufacturing defects only

Any other configuration can be built to order - enquire.

03 SERIES SPECIFICATION - VOLTAGE, RANGE & CONTINUITY

SERIES	VOLTAGE & RESISTANCE RANGES	CONTINUITY RANGE
MR-1	1000V/0–2000MΩ · 500V/0–1000MΩ · 250V/0–500MΩ	0–20 KΩ

04 APPLICATIONS

- High-voltage multi-voltage field insulation testing
- Multi-voltage transformer and cable testing to 5000V
- Both low- and high-voltage testing in one instrument

05 OPTIONAL ACCESSORIES (extra cost)

+ Carrying case
+ Test leads, 1m
+ H.V. test leads, 2m (general)
+ H.V. test leads, 2m (special)

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666/MR MR-1 Product Catalogue.