



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, WOODEN BODY

CIE/666/MR

Selectable multi-voltage insulation tester in wooden body — full series MR-1 to MR-8, including HV series MR-5 to MR-8.

MR-1 TO MR-8

Multirange Insulation Tester — Wooden Body

A multirange version of the hand-driven wooden-body CIE/666, covering the full MR-1 to MR-8 series — including HV series MR-5 to MR-8, not available in the metal-body CIE/444/MR — with continuity range built in as standard.

- **Full MR-1 to MR-8 series** — including HV series MR-5–8
- **Continuity range built-in** — standard on all MR series
- **Hand-driven** — no batteries required
- **Seasoned wooden body** — sunmica finish
- **MR-7 / MR-8 to 5000V** — widest single-instrument coverage



- M** **MR-1 to MR-8** Full series, wooden body
- ✓** **Built-In** Continuity range, standard
- V** **Up to 5000V** MR-7/MR-8 widest coverage

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	Seasoned wooden, sunmica finish
Generator Type	Hand-driven
Series Available	MR-1 to MR-8 (full range, incl. HV series MR-5–8)
Continuity Range	Built-in as standard on all MR series
Warranty	12 months against manufacturing defects

BUILD TO ORDER Specify required MR series (MR-1 to MR-8 in wooden body) — other configurations built to order

02 Available Series — Voltage, Range & Continuity

SERIES	VOLTAGE & RESISTANCE RANGES	CONTINUITY RANGE
MR-1	1000V/0–2000M Ω · 500V/0–1000M Ω · 250V/0–500M Ω	0–20 K Ω
MR-2	1000V/0–200M Ω · 500V/0–100M Ω · 250V/0–50M Ω	0–1 K Ω
MR-3	500V/0–1000M Ω · 250V/0–500M Ω · 100V/0–200M Ω	0–5 K Ω
MR-4	500V/0–100M Ω · 250V/0–50M Ω · 100V/0–20M Ω	0–1 K Ω
MR-5	2500V/0–5000M Ω · 1000V/0–2000M Ω · 500V/0–1000M Ω	0–20 K Ω
MR-6	2500V/0–1000M Ω · 1000V/0–200M Ω · 500V/0–100M Ω	0–1 K Ω
MR-7	5000V/0–20000M Ω · 2500V/0–10000M Ω	0–20 K Ω
MR-8	5000V/0–5000M Ω · 2500V/0–2500M Ω	0–5 K Ω

03 Typical Applications

- High-voltage multi-voltage field insulation testing
- Multi-voltage transformer and cable testing to 5000V
- Both low- and high-voltage testing in one instrument

04 Optional Accessories

- + Carrying case
- + Test leads, 1m
- + H.V. test leads, 2m (general)
- + H.V. test leads, 2m (special)

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 71101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.