



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN, BATTERY-FREE

CIE/444

Hand-cranked analog insulation tester in anti-magnetic aluminium body — no batteries required, 100V to 5000V.

BATTERY-FREE

Insulation Tester — Metal Body, Hand-Driven

A hand-driven generator-type insulation tester for direct-reading insulation resistance on machines, switchgear, cables and transformers — power is generated entirely by the operator, no batteries or external supply required.

- **No batteries required** — hand-cranked A.C. generator
- **Centrifugal governor** — holds output voltage constant
- **Anti-magnetic aluminium body** — die-cast, rugged
- **Cross-coil indicator** — anti-parallax mirror scale
- **3-second response** — quick direct reading
- **6 rated voltages** — 100V to 5000V, build-to-order

Supplied as base instrument only — carrying case, test leads, and range options available at extra cost.

Manufactured in India since 1963 — trusted by MSEB, Indian Railways, WBSETCL, etc.



- V 100-5000V** Rated voltage range
- 0 Battery-Free** Hand-cranked generator
- 3 3 Seconds** Response time

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	Anti-magnetic aluminium (pressure die-cast)
Generator Type	Hand-driven A.C. generator, centrifugal governor
Scale Length	90 mm (approx.)
Accuracy	Conforms to IS: 2992-1987
Rotation Speed	160 r.p.m. or more
High Voltage Test	Min. 2000V or (rated V + 1000)V A.C. r.m.s., 1 min
Insulation Resistance Test	Better than 50 M Ω at 500V D.C.
Response Time	3 seconds
Rated Voltages	100V / 250V / 500V / 1000V / 2500V / 5000V
100V Range Options	0-20 · 0-50 · 0-100 M Ω
250V Range Options	0-50 · 0-100 · 0-250 M Ω
500V Range Options	0-100 · 0-200 · 0-500 · 0-1000 · 0-2000 M Ω
1000V Range Options	0-100 · 0-200 · 0-500 · 0-1000 · 0-2000 M Ω
2500V Range Options	0-1000 · 0-2000 · 0-2500 · 0-5000 · 0-10000 · 0-20000 · 50-50000 M Ω
5000V Range Options	0-5000 · 0-10000 · 0-20000 · 50-50000 M Ω
Dimensions (L×W×H)	110 × 128 × 195 mm (approx.)
Weight	2.5 kg (approx.)
Warranty	12 months against manufacturing defects

BUILD TO ORDER Standard voltage & resistance ranges above — need something different? We can build it.

02 Typical Applications

- Rotating plant and stationary apparatus maintenance
- Insulation control and switching equipment checks
- Distribution network and cable insulation testing
- Transformer, insulator, and installation checks
- Locating shorts, defects, and insulation failures

03 Optional Accessories

- + Carrying case
- + Test leads, 1m/2m
- + H.V. test leads, 2m
- + Dual voltage/range option

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 71101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.