



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

DIGITAL EARTH RESISTANCE TESTER · BUILD-TO-ORDER

DET-2000

4-terminal digital earth resistance tester, built to order in dual or triple range configurations.

BUILD-TO-ORDER

Digital Earth Resistance Tester

A digital earth resistance tester with 4 terminals (E1, P1, P2, E2) for 3-terminal earth-resistance testing or 4-terminal soil-resistivity measurement — rugged ABS body, convertible from handheld to bench-top use.

- **4-terminal design** — earth resistance & soil resistivity
- **Build-to-order range** — dual or triple, specify at order
- **Rugged ABS body** — handheld or bench-top use
- **Rechargeable Ni-Cd** battery, 230V/50Hz charging cord
- **3½-digit LCD**, with Lo-Bat indicator
- **±1.5% accuracy** (10–90% of range), per IS 9223

Testing kit (spikes, cables, hammer) available at extra cost — not included standard.

Manufactured in India since 1963 — trusted by MSEB, Indian Railways, WBSETCL, etc.



- 4 **4-Terminal** E1 / P1 / P2 / E2 design
- ± **±1.5%** Accuracy, 10–90% of range
- R **Custom Range** Dual or triple, build-to-order

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Display	3½-digit LCD, with Lo-Bat indicator
Terminals	4-terminal (E1, P1, P2, E2)
Power	Rechargeable Ni-Cd cells, 230 V/50 Hz charging cord
Accuracy	±3% (0–10%, 90–100%); ±1.5% (10–90% of range)
High Voltage Test	2kV A.C. r.m.s., 1 min, circuit to containing case
Insulation Resistance Test	More than 25 M Ω at 500V D.C.
Dual Range Options	0–5–500 Ω · 0–10–100 Ω · 0–20–200 Ω · 0–10–1000 Ω · 0–20–2000 Ω · 0–200–2000 Ω
Triple Range Options	0–5–50–500 Ω · 0–10–100–1000 Ω · 0–20–200–2000 Ω
Dimensions (L×W×H)	172 × 98 × 38 mm
Weight	Approx. 575 g
Warranty	12 months against manufacturing defects

BUILD TO ORDER Standard dual & triple ranges above — need something different? We can build it.

02 Typical Applications

- Earth resistance testing — power, telecom, railway
- Domestic and industrial installation earthing checks
- Soil resistivity surveys for electrode positioning
- General non-inductive/non-capacitive resistance testing

03 What's in the Box

- ✓ Carrying case
- ✓ Charging cord
- ✓ Instruction manual

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 711101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.