



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

HV TEST SET · A.C. BREAKDOWN / WITHSTAND

CIE/5050A

Robust powder-coated AC HV breakdown/withstand test set — 0–3 kV or 0–5 kV, 25/50 mA selectable. Analog moving-iron metering, memory device.

UP TO 5kV

AC High Voltage Test Set

An A.C. high-voltage breakdown/withstand test set for fast, accurate testing of electrical and electronic materials, components, equipment, and panel boards — housed in a robust powder-coated M.S. cabinet, with a cast-resin H.V. transformer built to withstand frequent sparkover and momentary short-circuit conditions.

- **0–3kV or 0–5kV output** — continuously variable
- **25/50mA tripping current** — toggle-switch selectable, standard
- **Memory device** — retains breakdown reading after HV trips off
- **Zero-start interlocking** — HV circuit can't energise off-zero
- **Analog moving-iron metering** — kV meter + milliammeter, IS 1248:1983
- **Cast-resin HV transformer** — withstands frequent sparkover



- V Up to 5kV** 0–3kV or 0–5kV variant
- A 25/50mA** Toggle-selectable tripping current
- M Memory Device** Retains breakdown reading

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors across India.

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Input	230 V $\pm 10\%$, 50 Hz, 1 phase A.C.
Capacity	50 mA maximum on H.V. side
Tripping Current	25 mA & 50 mA — toggle switch selectable (standard)
Duty Cycle	Intermittent — 5 min ON, 10 min OFF
Mode of Operation	Manual
Metering	Analog moving-iron — kV meter & milliammeter, per IS 1248:1983 (not digital)
Memory Device	Push-button switch retains breakdown reading after H.V. trip
Warranty	12 months against manufacturing defects

Any tripping current setting apart from the standard 25mA/50mA above can be built to order.

02 Available Variants

VARIANT	OUTPUT RANGE	TRIPPING CURRENT
CIE/5050A (3 kV)	0–3 kV A.C.	25 mA & 50 mA, toggle selectable
CIE/5050A (5 kV)	0–5 kV A.C.	25 mA & 50 mA, toggle selectable

03 Typical Applications

- Breakdown/withstand testing of electrical and electronic components and materials
- Equipment and panel board dielectric strength testing
- HV withstand testing in production and site environments

04 What's in the Box

- ✓ One pair of H.V. probe with cable

05 Optional Accessories

- + Alternate tripping current set point

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 711101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.