



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

DIGITAL EARTH RESISTANCE TESTER

DET-2000

4-terminal digital earth resistance tester with dual or triple range configurations.

DUAL & TRIPLE RANGE

Digital Earth Resistance Tester

A digital earth resistance tester with 4 terminals (E1, P1, P2, E2) for 3-terminal earth-resistance testing or 4-terminal soil-resistivity measurement — rugged ABS body, convertible from handheld to bench-top use.

- **4-terminal design** — earth resistance & soil resistivity
- **Dual or triple range** — specify at order
- **Rugged ABS body** — handheld or bench-top use
- **Rechargeable Ni-Cd** battery, 230V/50Hz charging cord
- **3½-digit LCD** , with Lo-Bat indicator
- **±1.5% accuracy** (10–90% of range), per IS 9223

Testing kit (spikes, cables, hammer) available at extra cost — not included standard.

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- 4 **4-Terminal** E1 / P1 / P2 / E2 design
- ± **±1.5%** Accuracy, 10–90% of range
- R **Dual/Triple Range** Specify configuration at order

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Display	3½-digit LCD, with Lo-Bat indicator
Terminals	4-terminal (E1, P1, P2, E2)
Power	Rechargeable Ni-Cd cells, 230 V/50 Hz charging cord
Accuracy	±3% (0–10%, 90–100%); ±1.5% (10–90% of range)
High Voltage Test	2kV A.C. r.m.s., 1 min, circuit to containing case
Insulation Resistance Test	More than 25 MΩ at 500V D.C.
Range Configurations	Dual or triple range (any ONE configuration per unit, specify at order)
Dual Range	0–2,000Ω
Triple Range	0–2,000Ω
Dimensions (L×W×H)	172 × 98 × 38 mm
Weight	Approx. 575 g
Warranty	12 months against manufacturing defects

Any range apart from the standard dual & triple ranges above can be built to order.

02 Typical Applications

- Earth resistance testing — power, telecom, railway
- Domestic and industrial installation earthing checks
- Soil resistivity surveys for electrode positioning
- General non-inductive/non-capacitive resistance testing

03 What's in the Box

- ✓ Carrying case
- ✓ Charging cord
- ✓ Instruction manual

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 711101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.