



Cambridge Instruments  
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, MOTORISED, DUAL-SCALE

# CIE/777/MR

Dual-scale motorised insulation tester — inner and outer scale readings cover two ranges per voltage. Series MR-A to MR-E.

MR-A TO MR-E

## Multirange Motorised Insulation Tester

A motorised multi-voltage insulation tester with a dual-scale (inner/outer) reading arrangement — the inner scale covers a standard resistance range and the outer scale an extended range, at each rated voltage, so the operator can read either range without switching instruments. Five series (MR-A to MR-E) cover different voltage and range combinations.

- **Motorised drive** — mains, 230V/50Hz A.C.
- **Dual-scale display** — inner & outer ranges, no switching
- **5 series, MR-A to MR-E** — different range combinations
- **5000V maximum** — standard on every series
- **Sustained PI & DAR testing** — full motor-driven capability



- M** **Motorised** Mains, 230V/50Hz A.C.
- ✓** **Dual-Scale** Inner + outer range, no switch
- V** **5000V Maximum** Standard on all 5 series

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.

### 01 Full Specification Sheet

| PARAMETER        | SPECIFICATION                                                          |
|------------------|------------------------------------------------------------------------|
| Drive            | Motorised (mains, 230 V, 50 Hz A.C.)                                   |
| Series Available | MR-A to MR-E                                                           |
| Display          | Dual-scale inner/outer (MR-A, MR-B, MR-D) or single-scale (MR-C, MR-E) |
| Physical Specs   | Varies by series – contact us to confirm                               |
| Warranty         | 12 months against manufacturing defects                                |

Any configuration apart from the standard MR series above can be built to order.

### 02 Available Series — Voltage, Inner Scale & Outer Scale

| SERIES | VOLT.  | INNER         | OUTER        |
|--------|--------|---------------|--------------|
| MR-A   | 5000 V | 0–5000 MΩ     | 50–100000 MΩ |
| MR-A   | 2500 V | 0–2500 MΩ     | 25–50000 MΩ  |
| MR-A   | 1000 V | 0–1000 MΩ     | 10–20000 MΩ  |
| MR-B   | 5000 V | 0–2000 MΩ     | 10–10000 MΩ  |
| MR-B   | 2500 V | 0–1000 MΩ     | 5–5000 MΩ    |
| MR-B   | 1000 V | 0–500 MΩ      | 2–2000 MΩ    |
| MR-C   | 5000 V | 100–100000 MΩ | —            |
| MR-C   | 2500 V | 50–50000 MΩ   | —            |
| MR-D   | 5000 V | 0–5000 MΩ     | 50–100000 MΩ |
| MR-D   | 2500 V | 0–2500 MΩ     | 25–50000 MΩ  |
| MR-E   | 5000 V | 50–50000 MΩ   | —            |
| MR-E   | 2500 V | 25–25000 MΩ   | —            |
| MR-E   | 1000 V | 10–10000 MΩ   | —            |

### 03 Typical Applications

- Transformer and HV switchgear insulation testing requiring both standard and extended resistance range
- PI and dielectric absorption testing across multiple voltage classes
- Industrial and utility insulation maintenance programs

### 04 Optional Accessories

- + Carrying case + Test leads, 1m
- + H.V. test leads, 2m (general)
- + H.V. test leads, 2m (special) + Timer
- + Any other range — on request

#### OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,  
Kolkata 700001, West Bengal, India

#### WORKS

23/2, Maulana Abul Kalam Azad  
Road, Howrah 711101, West  
Bengal, India

#### CONTACT

+91 98300 91260  
+91 98300 92117  
cieinstruments@gmail.com

#### ONLINE

cieinstruments.in  
Instruments for accuracy and  
reliability since 1963.