



Cambridge Instruments  
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL MULTIMETER · 3½-DIGIT, MANUAL RANGING

# DM 235

3½-digit manual-ranging DMM - DC/AC voltage, DC/AC current, resistance, capacitance, continuity, diode, hFE. 9V battery.

20A AC/DC

## Digital Multimeter

A 3½-digit manual-ranging digital multimeter for general electrical and electronic measurement - DC voltage to 1000V, AC voltage to 750V, DC/AC current to 20A, resistance to 200MΩ, and capacitance, plus continuity, diode, and transistor (hFE) test.

- **DC voltage to 1000V** - AC voltage to 750V
- **DC/AC current to 20A** - manual ranging
- **Resistance to 200MΩ** - plus capacitance measurement
- **hFE transistor test** - built-in socket, PNP/NPN
- **Continuity & diode test** - audible buzzer
- **Auto power-off** - 9V battery, low-batt indication

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- V **1000V DC / 750V AC** Voltage range
- A **Up to 20A** DC/AC current
- Ω **200 MΩ** Max resistance

### 01 Full Specification Sheet

| PARAMETER            | SPECIFICATION                                                         |
|----------------------|-----------------------------------------------------------------------|
| Display              | 3½-digit                                                              |
| Ranging              | Manual                                                                |
| DC Voltage           | 200 mV / 2 V / 20 V / 200 V / 1000 V                                  |
| AC Voltage           | 2 V / 20 V / 200 V / 750 V                                            |
| DC Current           | 2 mA / 20 mA / 200 mA / 20 A                                          |
| AC Current           | 20 mA / 200 mA / 20 A                                                 |
| Resistance           | 200Ω / 2KΩ / 20KΩ / 200KΩ / 2MΩ / 20MΩ / 200MΩ                        |
| Capacitance          | 2000 pF / 20 nF / 200 nF / 2 μF / 20 μF                               |
| Additional Functions | Continuity, diode, transistor (hFE) test, auto power-off, low battery |
| Power Supply         | 9 V battery                                                           |
| Dimensions (L×W×H)   | 170 × 87 × 35 mm                                                      |
| Weight               | Approx. 210 g (incl. battery)                                         |
| Warranty             | 12 months against manufacturing defects                               |

### 02 Typical Applications

- General electrical measurement
- Panel testing
- Workshop and field use

### 03 What's in the Box

- ✓ Test leads
- ✓ User manual
- ✓ Battery
- ✓ Holster

Cambridge Instruments & Engg. Co.

[cieinstruments.in](http://cieinstruments.in)

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DM 235 Product Catalogue.