



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, WOODEN BODY

CIE/666/MR

Selectable multi-voltage insulation tester in wooden body - full series MR-1 to MR-8, including HV series MR-5 to MR-8.

MR-1 TO MR-8

Multirange Insulation Tester - Wooden Body

A multirange version of the hand-driven wooden-body CIE/666, covering the full MR-1 to MR-8 series - including HV series MR-5 to MR-8, not available in the metal-body CIE/444/MR - with continuity range built in as standard.

- **Full MR-1 to MR-8 series** - including HV series MR-5-8
- **Continuity range built-in** - standard on all MR series
- **Hand-driven** - no batteries required
- **Seasoned wooden body** - sunmica finish
- **MR-7 / MR-8 to 5000V** - widest single-instrument coverage

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- M** **MR-1 to MR-8** Full series, wooden body
- ✓** **Built-In** Continuity range, standard
- V** **Up to 5000V** MR-7/MR-8 widest coverage

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	Seasoned wooden, sunmica finish
Generator Type	Hand-driven
Series Available	MR-1 to MR-8 (full range, incl. HV series MR-5-8)
Continuity Range	Built-in as standard on all MR series
Warranty	12 months against manufacturing defects

Any configuration apart from the standard MR series above can be built to order.

02 Available Series - Voltage, Range & Continuity

SERIES	VOLTAGE & RESISTANCE RANGES	CONTINUITY RANGE
MR-1	1000V/0-2000M Ω · 500V/0-1000M Ω · 250V/0-500M Ω	0-20 K Ω
MR-2	1000V/0-200M Ω · 500V/0-100M Ω · 250V/0-50M Ω	0-1 K Ω
MR-3	500V/0-1000M Ω · 250V/0-500M Ω · 100V/0-200M Ω	0-5 K Ω
MR-4	500V/0-100M Ω · 250V/0-50M Ω · 100V/0-20M Ω	0-1 K Ω
MR-5	2500V/0-5000M Ω · 1000V/0-2000M Ω · 500V/0-1000M Ω	0-20 K Ω
MR-6	2500V/0-1000M Ω · 1000V/0-200M Ω · 500V/0-100M Ω	0-1 K Ω
MR-7	5000V/0-20000M Ω · 2500V/0-10000M Ω	0-20 K Ω
MR-8	5000V/0-5000M Ω · 2500V/0-2500M Ω	0-5 K Ω

03 Typical Applications

- High-voltage multi-voltage field insulation testing
- Multi-voltage transformer and cable testing to 5000V
- Both low- and high-voltage testing in one instrument

04 Optional Accessories

- + Carrying case + Test leads, 1m
- + H.V. test leads, 2m (general)
- + H.V. test leads, 2m (special)