



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

DIGITAL INSULATION TESTER · AUTO-RANGE

DIT-5000

Auto-ranging insulation resistance testing up to 5000 V, 200 GΩ max, with an HV live-output indicator.

5000V · 200 GΩ

Digital Insulation Tester - up to 5000 V

A dedicated digital insulation tester for testing at voltages up to 5000 V, with resistance measurement to 200 GΩ - auto-ranging with automatic zero calibration and polarity display for fast field use.

- **Output voltage to 5000V** - 500/1000/2500/5000V
- **Insulation resistance to 200 GΩ** - tiered accuracy
- **Auto-range** - auto zero calibration & polarity display
- **HV LED indicator** - warns when output is live
- **Large backlit LCD** - 3½-digit, 35mm characters
- **AC voltage to 750V** - secondary function
- Powered by **6×AA batteries** (replaceable)

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



- V Up to 5000V** Max output voltage
- Ω 200 GΩ** Max insulation resistance
- A Auto-Range** Auto zero + polarity

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Output Voltage	500 V / 1000 V / 2500 V / 5000 V
Insulation Resistance	1 MΩ – 200 GΩ
Short Circuit Current	1 mA
AC Voltage Measurement	Up to 750 V (secondary function)
Display	3½-digit LCD, 68×55 mm, 35 mm characters, backlit
Ranging	Auto-range, auto zero calibration, auto polarity
HV Indicator	High-voltage LED - lights when output is live
Acc. 1M–200MΩ	±(3% × reading + 5 digits)
Acc. 200M–10GΩ	±(5% × reading + 5 digits)
Acc. 10G–200GΩ	±(10% × reading + 5 digits)
Power Supply	6×1.5 V AA batteries (replaceable)
Dimensions (L×W×H)	218 × 122 × 75 mm
Weight	Approx. 900 g
Warranty	12 months against manufacturing defects

02 Typical Applications

- Motor and rotating-machinery insulation testing at higher voltages
- HV transformer and cable insulation testing up to 5000 V
- Utilities and large industrial plants requiring 5000V class testing

03 What's in the Box

- ✓ Test leads
- ✓ 6×AA batteries
- ✓ User manual
- ✓ Carrying box