

ILUTWIST Ambient Lamp

Description

This spiral lampshade creates a soft ambient glow while highlighting the twisted surface pattern. The light diffuses through the layered lines and gives the lamp a calm, warm atmosphere.

The lamp is designed to fit the **Bambu Lab LED Lamp Kit 001 (or alternatives found online)**.

Overall dimensions of the lampshade

- Diameter: **187 mm**
- Height: **220 mm**

The lamp consists of three printed parts:

- Lampshade
- Inner insert (light diffuser)
- Base

Important Notes

⚠ **Not a beginner-friendly print.**

The lampshade requires specific slicer settings. Please follow the instructions carefully, otherwise the print may fail or the walls may become too thin.

⚠ **The lampshade must be printed in Vase Mode only.**

Filaments Used in Photos

- **Bambu Lab PETG Translucent Clear**
- **Bambu Lab PETG Translucent Orange**

Alternative materials shown in the photos:

- **Bambu Lab PLA Matte White**
- **Bambu Lab PLA Matte Brown**

Print Settings

Lampshade

Vase Mode only

Settings:

- Layer height: **0.2 mm**
- Outer wall line width: **0.65 – 0.7 mm**
- Vase Mode: **enabled**
- Smooth Vase: **enabled**
- Bottom shell layers: **5-6**
- **Slow down** your print if you struggle with print quality (for example, I print translucent PETG on max volumetric speed 5-6 mm³/s).

The **line width is very important**.

If it is smaller than recommended, the lampshade will be **too thin** and can cause surface issues such as shifting or uneven layers.

Inner Insert (Light Diffuser)

This part helps distribute the light and can be printed in a different color to create a different glow.

Settings:

- Layer height: **0.2 mm**
- Outer wall line width: **0.65 – 0.7 mm**
- Vase Mode: **enabled**
- Smooth Vase: **enabled**
- Bottom shell layers: **0**

Setting the bottom shell layers to **0** keeps the top and bottom open.

Also make sure your **print bed is clean before printing**.

The lampshade has a **small contact area**, so good bed adhesion is important.

Lamp Base

The base holds the **Bambu Lab LED Lamp Kit 001**.

Settings:

- Standard print mode
- Infill: **~12% gyroid**
- Walls: **2-3**
- Seam: **Back (Rear)**

 Questions or Feedback?

 simonauhrova3d@gmail.com

 Join the Community:

<https://discord.gg/SagnAaCgHF>