Computationally Efficient Predictions for Multi-Output Spatiotemporal Dynamical Systems

Joey Hotz
joey.hotz@mail.utoronto.ca

Supervisor: Dr. Meredith Franklin
Examiners: Dr. Ricardo Baptista & Dr. Joshua Speagle

Department of Statistical Sciences
University of Toronto

October 26, 2026

Abstract

Over the past decade, several groups of machine learning researchers have demonstrated promising computational algorithms and mathematical results which utilize Gaussian process (GP) regression and Kalman filtering (KF) to derive estimates and predictions for the future states of spatiotemporal dynamical systems in a more computationally-efficient manner.

This paper builds on previous results in this research area by adapting and extending the results of previous work on univariate outputs towards dynamical systems with vector-valued outputs. In this paper, we introduce the mathematical background necessary to understand Gaussian processes and Kalman filtering, and cover prior results in these areas. We then formally describe the multi-output spatiotemporal dynamics problem, and depict the assumptions required for similar computational speedups to exist in the multi-output spatiotemporal dynamics setting. Lastly, we apply these algorithms to both synthetic and real-world datasets to evaluate their performance.

Contents

1 Introduction **1**

2 Background **2**

2.1 Gaussian Processes 2

2.2 Multi-Output Gaussian Processes 3

2.3 Kalman Filtering 7

3 Problem Formulation **8**

3.1 Single-Output Dynamical System 9

3.2 Multi-Output Dynamical System 11

4 Methods **11**

4.1 Simulations 11

5 Results **12**

6 Discussion **12**

6.1 Conclusions 12

6.2 Limitations 12

6.3 Future Work 12

A AI Usage Statement **15**

B Definitions and Technical Details **15**

C Code **15**

1 Introduction

Gaussian processes (GPs) are an 'industry standard' procedure for modelling the values of unknown functions, especially in scenarios where there are noisy or otherwise unreliable measurements and/or correlations in the data which must be accounted for (Rasmussen and Williams, 2006).

Gaussian process regression, also commonly referred to in the literature as *kriging* after the South African geostatistician Danie G. Krige (Cressie, 1990), is a statistical modelling procedure wherein a finite collection of observations are used for learning the form of an unknown real-valued function. Gaussian processes are particularly useful when there are correlations among observations, as these models can leverage information from correlated data to reduce the variance of outputs in the estimated function. Furthermore, the equations for fitting a GP to a dataset have computable closed-form solutions. Due to these convenient properties, Gaussian processes are frequently used in a variety of practical statistical applications involving spatiotemporal datasets, ranging from geostatistics and climatology to fields such as electrical engineering and signal processing (Särkkä and Hartikainen, 2012; Huang et al., 2025).

Although Gaussian processes are mathematically tractable and convenient to use, there is one major drawback to these models: exact inference with Gaussian processes has a cubically-scaling computational overhead. Fitting a Gaussian process on a set of N observations is a process which requires $\mathcal{O}(N^3)$ operations (Rasmussen and Williams, 2006), making these regression problems infeasible for many large-scale datasets (Guhaniyogi and Banerjee, 2018; Pförtner et al., 2025; Salari and Zeinali, 2025).

Due to these computational difficulties, many statisticians and machine learning researchers have sought to develop algorithms for fitting a Gaussian process with reduced computational overhead. Prominent well-studied and broadly applicable methods for accomplishing this task include approximations using induced latent variables (Quiñonero-Candela and Rasmussen, 2005), sparse variational Gaussian processes (Titsias, 2009), and Vecchia approximations (Katzfuss and Guinness, 2021). However, these methods all require some degree of approximation, trading the exactness of a solution for increased algorithmic efficiency.

In their 2020 paper *Efficient spatio-temporal Gaussian regression via Kalman filtering*, Todescato et al. introduce a new algorithm for efficiently deriving estimates of the future states in a spatio-temporal dynamical system under certain assumptions for the covariance structure between observations. The algorithm proposed by the authors utilizes Gaussian process regression in tandem with the Kalman filter, providing the ability to account for both the spatial and temporal aspects which guide the 'evolution' of the dynamical system while simultaneously reducing the overall computational load.

This paper provides a detailed overview of the results in Todescato et al. (2020) and subsequently builds upon the scaffolding in the authors' work by amending their proposed algorithm to operate with vector-valued outputs instead of being confined to scalar responses. This extension to multivariate response vectors provides many practical benefits, as there are many scientific research areas which utilize spatiotemporal models to account for the relationships between a set of correlated response variables.

2 Background

In order to properly describe the algorithm devised by Todescato et al. (2020), we must first separately discuss Gaussian processes and Kalman filtering.

2.1 Gaussian Processes

A Gaussian process (GP) is a real-valued stochastic process indexed over some P-dimensional *state space* $\mathcal{X} \subseteq \mathbb{R}^P$ which satisfies the following key property:

Definition 1 (Gaussian Process)**.** *The real-valued function $f : \mathcal{X} \to \mathbb{R}$ follows a Gaussian process on $\mathcal{X}$ if for every finite collection (N-tuple) of states $\{\mathbf{x}_1, \cdots, \mathbf{x}_N\} \subset \mathcal{X}$, the joint distribution of the random vector $\big(f(\mathbf{x}_1), \cdots, f(\mathbf{x}_N)\big)^\mathsf{T}$ is a multivariate Gaussian distribution on $\mathbb{R}^N$.*

Furthermore, every Gaussian process on the state space $\mathcal{X}$ is *uniquely* specified by two real-valued functions: a mean function $m : \mathcal{X} \to \mathbb{R}$ and a *positive-definite* covariance (kernel) function $k : \mathcal{X} \times \mathcal{X} \to \mathbb{R}^{\geq 0}$, which respectively describe the mean and covariance of the underlying process (Rasmussen and Williams, 2006). Any function $f : \mathcal{X} \to \mathbb{R}$ which is a realization of a Gaussian process with mean $m(\cdot)$ and kernel $k(\cdot, \cdot)$ is endowed with the following structure:

$$\textbf{Mean:} \quad m(\mathbf{x}) = \mathbb{E}[f(\mathbf{x})] \text{ for all } \mathbf{x} \in \mathcal{X} \tag{1a}$$

$$\textbf{Covariance:} \quad k(\mathbf{x}, \mathbf{x}') = \mathrm{Cov}(f(\mathbf{x}), f(\mathbf{x}')) \text{ for all } (\mathbf{x}, \mathbf{x}') \in \mathcal{X} \times \mathcal{X} \tag{1b}$$

We denote a function $f : \mathcal{X} \to \mathbb{R}$ which is drawn from a Gaussian process with mean $m(\cdot)$ and kernel $k(\cdot, \cdot)$ as $f \sim \mathcal{GP}(m, k)$. Note that the kernel function $k(\cdot, \cdot)$ in Equation (1b) must be symmetric in its arguments, as this function describes the covariance between the Gaussian process outputs at these two locations. In addition to describing the covariance between function observations, the kernel function $k(\cdot, \cdot)$ serves another complementary purpose, as sample paths have continuous mean-square derivatives up to the order of the kernel $k(\cdot, x)$ (Rasmussen and Williams, 2006).

Suppose that $f \sim \mathcal{GP}(m, k)$ is a realization of some Gaussian process on $\mathcal{X} \subseteq \mathbb{R}^P$, and let $\{\mathbf{x}_1, \ldots, \mathbf{x}_N\} \subset \mathcal{X}$ be a set of queried locations. For ease of notation, we define the data matrix $\mathbf{X} := \big[\, \mathbf{x}_1^\mathsf{T} \cdots \mathbf{x}_N^\mathsf{T} \,\big]^\mathsf{T} \in \mathbb{R}^{N \times P}$, and define the corresponding vectors $f(\mathbf{X}) := \big[\, f(\mathbf{x}_1^\mathsf{T}) \cdots f(\mathbf{x}_N^\mathsf{T}) \,\big]^\mathsf{T} \in \mathbb{R}^N$ and $m(\mathbf{X}) := \big[\, m(\mathbf{x}_1^\mathsf{T}) \cdots m(\mathbf{x}_N^\mathsf{T}) \,\big]^\mathsf{T} \in \mathbb{R}^N$. Lastly, let $k(\mathbf{X}, \mathbf{X}) \in \mathbb{R}^{N \times N}$ represent the *Gram matrix* for the observed locations which is induced by the kernel $k(\cdot, \cdot)$:

$$k(\mathbf{X}, \mathbf{X}) := \begin{bmatrix} k(\mathbf{x}_1, \mathbf{x}_1) & k(\mathbf{x}_1, \mathbf{x}_2) & \cdots & k(\mathbf{x}_1, \mathbf{x}_N) \\ k(\mathbf{x}_2, \mathbf{x}_1) & k(\mathbf{x}_2, \mathbf{x}_2) & \cdots & k(\mathbf{x}_2, \mathbf{x}_N) \\ \vdots & \vdots & \ddots & \vdots \\ k(\mathbf{x}_N, \mathbf{x}_1) & k(\mathbf{x}_N, \mathbf{x}_2) & \cdots & k(\mathbf{x}_N, \mathbf{x}_N) \end{bmatrix} \tag{2}$$

One of the key properties which allows Gaussian processes to be so widely-applicable is that under the conditions described above, the vector $f(\mathbf{X})$ follows a multivariate Gaussian distribution:

$$f(\mathbf{X}) \sim \mathcal{N}\Big(m(\mathbf{X}), k(\mathbf{X}, \mathbf{X})\Big) \tag{3}$$

Furthermore, consider the same setting as above, and suppose that we have some (potentially) noisy measured observations given by $y_i = f(\mathbf{x}_i) + \epsilon_i$, for independent normally-distributed measurement errors $\epsilon_1, \ldots, \epsilon_N \overset{\text{i.i.d.}}{\sim} \mathcal{N}(0, \sigma^2)$. Equivalently, we assume that $y_i \sim \mathcal{N}\big(f(\mathbf{x}_i), \sigma^2\big)$ for each queried

location $\mathbf{x}_i$ (Rasmussen and Williams, 2006). Defining the response vector $\mathbf{y} := \begin{bmatrix} y_1 & \cdots & y_N \end{bmatrix}^\mathsf{T} \in \mathbb{R}^N$ yields the following distributional result:

$$\mathbf{y} \sim \mathcal{N}\Big(m(\mathbf{X}), k(\mathbf{X}, \mathbf{X}) + \sigma^2 \mathbf{I}_N\Big) \tag{4}$$

Gaussian processes are often incorporated in a Bayesian setting as a prior distribution which one can place on the space of real-valued functions on $\mathcal{X}$ (Titsias, 2009; Álvarez et al., 2012). For example, for a *black-box* function $f : \mathcal{X} \to \mathbb{R}$, we may place a prior of the form $f \sim \mathcal{GP}(m, k)$, for specified functions $m : \mathcal{X} \to \mathbb{R}$ and $k : \mathcal{X} \times \mathcal{X} \to \mathbb{R}$ as described by Equations (1a) and (1b). If observations of the black-box function $f(\cdot)$ are taken with normally-distributed measurement error (as described by Equation (4)), then the posterior predictive distribution for $f(\cdot)$ will be a Gaussian process whose mean and kernel are altered by conditioning on the observed data. In particular, for a data matrix $\mathbf{X} \in \mathbb{R}^{N \times P}$ with the response vector $\mathbf{y} \in \mathbb{R}^N$, the posterior predictive distribution for f evaluated at any points $\mathbf{x}, \mathbf{x}' \in \mathcal{X}$ is given by the following:

$$\textbf{Mean:} \quad m_{\text{post}}(\mathbf{x}) = m(\mathbf{x}) + k(\mathbf{x}, \mathbf{X})\big[k(\mathbf{X}, \mathbf{X}) + \sigma^2 \mathbf{I}_N\big]^{-1}\big(\mathbf{y} - m(\mathbf{X})\big) \tag{5a}$$

$$\textbf{Kernel:} \quad k_{\text{post}}(\mathbf{x}, \mathbf{x}') = k(\mathbf{x}, \mathbf{x}') - k(\mathbf{x}, \mathbf{X})\big[k(\mathbf{X}, \mathbf{X}) + \sigma^2 \mathbf{I}_N\big]^{-1} k(\mathbf{X}, \mathbf{x}') \tag{5b}$$

In the equations above, $k(\mathbf{x}, \mathbf{X})$ represents the 1-by-N Gram matrix with entries $k(\mathbf{x}, \mathbf{x}_i)$ and similarly, $k(\mathbf{X}, \mathbf{x}')$ is the N-by-1 Gram matrix with entries $k(\mathbf{x}_i, \mathbf{x}')$. Setting $\mathbf{x} = \mathbf{x}'$ in Equation (5b) yields the posterior predictive variance for $f(\mathbf{x})$. Furthermore, when the observations $y_1, \ldots, y_N$ are assumed to be exact (i.e. $\sigma^2 = 0$), then Equations (5a) and (5b) will perfectly interpolate every observation. To be precise, if $\sigma^2 = 0$, the posterior Gaussian process satisfies that $m_{\text{post}}(\mathbf{x}_i) = y_i$ and $k_{\text{post}}(\mathbf{x}_i, \mathbf{x}_i) = 0$, implying that each $f(\mathbf{x}_i)$ is *exactly* equal to the corresponding y_i.

2.2 Multi-Output Gaussian Processes

Thus far, we have focused solely on the description of single-output Gaussian processes, whose realizations are described by functions of the form $f : \mathcal{X} \to \mathbb{R}$. However, there is a natural extension from these univariate processes to *multi-output* (also called *multi-task*) Gaussian processes: a higher-dimensional form of a Gaussian process, whose outputs are vectors in $\mathbb{R}^D$ (Álvarez et al., 2012; Bonilla et al., 2007).

Definition 2 (Multi-Output Gaussian Process)**.** *The vector-valued function* $\mathbf{f} = (f_1, \ldots, f_D)^\mathsf{T} : \mathcal{X} \to \mathbb{R}^D$ *follows a multi-output Gaussian process on* $\mathcal{X}$ *if for every finite collection of states* $\{\mathbf{x}_1, \ldots, \mathbf{x}_N\} \subset \mathcal{X}$*, the joint distribution of the* ND *random variables* $\big(f_1(\mathbf{x}_1), \cdots, f_D(\mathbf{x}_N)\big)^\mathsf{T}$ *is a multivariate Gaussian distribution on* $\mathbb{R}^{ND}$*.*

Multi-output GPs (MOGPs) are naturally applicable whenever there are several (potentially) correlated quantities which are measured over some common domain. These processes include both *auto-correlations* within the same output and *cross-correlations* between outputs, allowing for information about one output to reduce the uncertainty of other response variables in the model. Conceptually, a multi-output GP is analogous to simultaneously modelling D single-output Gaussian processes, while also modelling the covariance between these processes.

Given states $\mathbf{X} = \begin{bmatrix} \mathbf{x}_1^\mathsf{T} & \cdots & \mathbf{x}_N^\mathsf{T} \end{bmatrix}^\mathsf{T} \in \mathbb{R}^{N \times P}$, we define the matrix $\mathbf{f}(\mathbf{X}) \in \mathbb{R}^{N \times D}$ by concatenating the vectorized columns, i.e. $\mathbf{f}(\mathbf{X}) = \begin{bmatrix} f_1(\mathbf{X}) & \cdots & f_D(\mathbf{X}) \end{bmatrix}$, and we can analogously define the matrix $\mathbf{m}(\mathbf{X}) \in \mathbb{R}^{N \times D}$ as a concatenation of the respective N-dimensional mean vectors

$m_1(\mathbf{X}), \ldots, m_D(\mathbf{X})$. In order to work with a multi-output GP, we must also construct a Gram matrix $\mathbf{K}(\mathbf{X}, \mathbf{X}) \in \mathbb{R}^{ND \times ND}$ which defines the covariance structure between both the queried locations and the output dimensions. In its most general form, the Gram matrix providing the covariance for a multi-output GP has the following structure:

$$\mathbf{K}(\mathbf{X}, \mathbf{X}) := \begin{bmatrix} \mathbf{K}(\mathbf{x}_1, \mathbf{x}_1) & \mathbf{K}(\mathbf{x}_1, \mathbf{x}_2) & \cdots & \mathbf{K}(\mathbf{x}_1, \mathbf{x}_N) \\ \mathbf{K}(\mathbf{x}_2, \mathbf{x}_1) & \mathbf{K}(\mathbf{x}_2, \mathbf{x}_2) & \cdots & \mathbf{K}(\mathbf{x}_2, \mathbf{x}_N) \\ \vdots & \vdots & \ddots & \vdots \\ \mathbf{K}(\mathbf{x}_N, \mathbf{x}_1) & \mathbf{K}(\mathbf{x}_N, \mathbf{x}_2) & \cdots & \mathbf{K}(\mathbf{x}_N, \mathbf{x}_N) \end{bmatrix} \tag{6}$$

The covariance matrix in Equation (6) is overall quite similar to the Gram matrix in the univariate setting which is shown in Equation (2). However, the multi-output Gram matrix consists of N^2 covariance matrix sub-blocks $\mathbf{K}(\mathbf{x}_i, \mathbf{x}_j) = \mathrm{Cov}(\mathbf{f}(\mathbf{x}_i), \mathbf{f}(\mathbf{x}_j))$ of size $D \times D$, each of which has entries of the form $[\mathbf{K}(\mathbf{x}_i, \mathbf{x}_j)]_{(d,d')} = \mathrm{Cov}(f_d(\mathbf{x}_i), f_{d'}(\mathbf{x}_j))$ (Álvarez et al., 2012). Vectorizing the matrix $\mathbf{f}(\mathbf{X})$ yields the following distributional result:

$$\mathrm{vec}\big(\mathbf{f}(\mathbf{X})\big) \sim \mathcal{N}\Big(\mathrm{vec}\big(\mathbf{m}(\mathbf{X})\big), \mathbf{K}(\mathbf{X}, \mathbf{X})\Big) \tag{7}$$

Additionally, suppose that we have observations of the form $\mathbf{y}_i = \mathbf{f}(\mathbf{x}_i) + \boldsymbol{\epsilon}_i$ with independent measurement error vectors $\boldsymbol{\epsilon}_1, \ldots, \boldsymbol{\epsilon}_N \overset{\text{i.i.d.}}{\sim} \mathcal{N}(\mathbf{0}, \boldsymbol{\Sigma}_\epsilon)$, for some positive-definite covariance matrix $\boldsymbol{\Sigma}_\epsilon \in \mathbb{R}^{D \times D}$. The joint distribution of these observed values is given by

$$\mathrm{vec}\big(\mathbf{f}(\mathbf{X})\big) \sim \mathcal{N}\Big(\mathrm{vec}\big(\mathbf{m}(\mathbf{X})\big), \mathbf{K}(\mathbf{X}, \mathbf{X}) + \mathbf{I}_N \otimes \boldsymbol{\Sigma}_\epsilon\Big) \tag{8}$$

Again, the full distribution in Equation (8) closely echoes the univariate result from Equation (4), with a slight adjustment to account for covariances between outputs.

From a purely theoretical standpoint, multi-output Gaussian processes are defined quite analogously to the single-output processes discussed in Section 2.1. However, by solely introducing the theory and notation regarding MOGPs, we have obscured the major practical implications of these models; namely, the extreme cost for computational inference. In the (general) single-output Gaussian process regime, the cost of inference scales cubically with the size of the matrix $k(\mathbf{X}, \mathbf{X})$, giving a computational cost of the order $\mathcal{O}(N^3)$. In the setting where the responses are vector-valued, statistical inference still requires the inversion of the Gram matrix $\mathbf{K}(\mathbf{X}, \mathbf{X})$, whose cost balloons to the order of $\mathcal{O}(N^3 D^3)$. Even when $D \ll N$, this is a significant increase in the computational requirement for an already-expensive operation. We will now turn our attention towards three specific cases of multi-output Gaussian processes, which give simpler forms for the Gram matrix $\mathbf{K}(\mathbf{X}, \mathbf{X})$.

Fully Independent Model: The simplest form of a multi-output Gaussian process is one in which each output dimension is assumed to be an independent univariate Gaussian process: $f_d \sim \mathcal{GP}(m_d, k_d)$. Under this assumption, the Gram matrix $\mathbf{k}(\mathbf{X}, \mathbf{X})$ is a block-diagonal matrix with D $N \times N$ sub-blocks. This model is computationally quite cheap, as it can be simply decoupled into D separate single-output regression problems. However, this model makes the strong assumption that the targeted outputs are fully independent, and it shares no information across the output dimensions, which hampers its applicability in many practical contexts.

This model is computationally cheap, since it decouples into D separate single-output prob-

lems, but it shares no information across outputs whatsoever. The models below reintroduce dependencies between the outputs by expressing them as the linear combinations of latent Gaussian processes.

Linear Model of Coregionalization (LMC): The LMC model for a Gaussian process with a vector-valued output is predicated on the assumption that the output functions are built from a linear combination of some set of independent mean-zero univariate Gaussian processes (Álvarez et al., 2012). Suppose that the latent Gaussian processes $u_1, \ldots, u_R$ are independent, with $\mathbb{E}[u_i(\mathbf{x})] = 0$ and $\text{Cov}(u_r(\mathbf{x}), u_{r'}(\mathbf{x}')) = \mathbf{1}_{\{r=r'\}} \times k_r(\mathbf{x}, \mathbf{x}')$, so that the covariance is nonzero if and only if $r = r'$.

Following the description given by Álvarez et al. (2012), we can sort these latent GPs based on their covariance function, giving us Q groups of size $\{R_q\}_{q=1}^{Q}$. By sorting the latent processes in this manner, each group q (for $q = 1, \ldots, Q$) consists of R_q independent univariate Gaussian processes of the form $u_q^1, \ldots, u_q^{R_q} \overset{\text{i.i.d.}}{\sim} \mathcal{GP}(0, K^{(q)})$. Note that even though the covariance structures are shared for latent functions in the same group, the respective Gaussian processes are still entirely independent. As such, $\text{Cov}(u_q^i(\mathbf{x}), u_{q'}^{i'}(\mathbf{x}')) = \mathbf{1}_{\{q=q'\}} \times \mathbf{1}_{\{i=i'\}} \times K^{(q)}(\mathbf{x}, \mathbf{x}')$ under this regrouping of the latent functions.

In the LMC model, we assume that the desired functions $\{f_d(\cdot)\}_{d=1}^{D}$ for the multivariate process are constructed via a linear combination of the latent Gaussian processes $u_1, \ldots, u_R$. Each function is therefore described by the following latent model:

$$f_d(\mathbf{x}) = m_d(\mathbf{x}) + \sum_{r=1}^{R} \alpha_{d,r} u_r(\mathbf{x}) \tag{9}$$

Grouping the latent functions by their kernel, this can be written in the form

$$f_d(\mathbf{x}) = m_d(\mathbf{x}) + \sum_{q=1}^{Q} \sum_{i=1}^{R_q} \alpha_{d,q}^i u_q^i(\mathbf{x}) \tag{10}$$

The functions $\{m_d(\cdot)\}_{d=1}^{D}$ in Equations (9) and (10) ensure that each function in the observable multi-output process can have a non-zero mean. Using the latent form given in Equation (10), we can represent the covariance between two outputs by the following:

$$\text{Cov}(f_d(\mathbf{x}), f_{d'}(\mathbf{x}')) = \sum_{q=1}^{Q} \sum_{q'=1}^{Q} \sum_{i=1}^{R_q} \sum_{i=1}^{R_{q'}} \alpha_{d,q}^i \alpha_{d',q'}^{i'} \text{Cov}\left(u_q^i(\mathbf{x}), u_{q'}^{i'}(\mathbf{x})\right) \tag{11a}$$

In the summation above, the covariance is non-zero if and only if $q = q'$ and $i = i'$.

$$= \sum_{q=1}^{Q} \sum_{i=1}^{R_q} \alpha_{d,q}^i \alpha_{d',q}^i \text{Cov}\left(u_q^i(\mathbf{x}), u_q^i(\mathbf{x})\right) \tag{11b}$$

$$= \sum_{q=1}^{Q} \sum_{i=1}^{R_q} \alpha_{d,q}^i \alpha_{d',q}^i K^{(q)}(\mathbf{x}, \mathbf{x}') \tag{11c}$$

For each group $q = 1, \ldots, Q$, and each pair of dimensions (d, d'), we define the value $b_{d,d'}^{(q)} := \sum_{i=1}^{R_q} \alpha_{d,q}^i \alpha_{d',q}^i$. We can then concatenate these values into a $D \times D$ *coregionalization* matrix $\mathbf{B}^{(q)}$ such that the (d, d') entry of $\mathbf{B}^{(q)} = b_{d,d'}^{(q)}$. Using these coregionalization matrices yields the kernel

function for the linear model of coregionalization, which is given by

$$\mathbf{K}(\mathbf{x}, \mathbf{x}') = \sum_{q=1}^{Q} K^{(q)}(\mathbf{x}, \mathbf{x}')\mathbf{B}^{(q)}, \quad \text{with } \mathbf{K}(\mathbf{x}, \mathbf{x}') \in \mathbb{R}^{D \times D}, \tag{12}$$

and the overall Gram matrix for the linear model of coregionalization is given by

$$\mathbf{K}(\mathbf{X}, \mathbf{X}) = \sum_{q=1}^{Q} K^{(q)}(\mathbf{X}, \mathbf{X}) \otimes \mathbf{B}^{(q)}, \quad \text{with } \mathbf{K}(\mathbf{X}, \mathbf{X}) \in \mathbb{R}^{ND \times ND} \tag{13}$$

The linear model of coregionalization is commonly used for describing the kernels of multi-output Gaussian processes in scientific modelling settings such as inference among sensor networks, geostatistical applications, and robot dynamics (Álvarez et al., 2012; Liu et al., 2018).

Intrinsic Coregionalization Model (ICM): The intrinsic coregionalization model (ICM) for a multi-output Gaussian process is a special case of the LMC kernel, where the number of distinct kernel functions (Q) is equal to one. The ICM kernel is a more restrictive simplification of the LMC kernel, but the Gram matrix will be significantly less expensive to decompose as a result of this simplifying assumption.

The ICM kernel can be derived in the same format as the LMC kernel, with all latent functions $u_1, \ldots, u_R \overset{\text{i.i.d.}}{\sim} \mathcal{GP}(0, k)$. The covariances generated by the ICM kernel are described by the following relations:

$$\text{Cov}(f_d(\mathbf{x}), f_{d'}(\mathbf{x}')) = k(\mathbf{x}, \mathbf{x}') \times \mathbf{B}(d, d') \tag{14}$$

The covariance given in Equation (14) corresponds to a kernel which is similar to that in Equation (13), with only one spatial kernel $k(\mathbf{X}, \mathbf{X}) \in \mathbb{R}^{N \times N}$ and one corresponding coregionalization matrix $\mathbf{B} \in \mathbb{R}^{D \times D}$ for the outputs.

$$\mathbf{K}(\mathbf{X}, \mathbf{X}) = k(\mathbf{X}, \mathbf{X}) \otimes \mathbf{B}, \quad \text{with } \mathbf{K}(\mathbf{X}, \mathbf{X}) \in \mathbb{R}^{ND \times ND} \tag{15}$$

The ICM kernel is an example of a *separable* kernel, as the Gram matrix in 15 can be written as the Kronecker product of one purely spatial Gram matrix and another purely output-related Gram matrix. Similarly, the individual terms of the form $k(\mathbf{X}, \mathbf{X}) \otimes \mathbf{B}^{(q)}$ in the summation in 13 are separable kernels.

Semiparametric Latent Factor Model (SLFM): Another special case of the LMC kernel is the *semiparametric latent factor model* (SLFM) (Bonilla et al., 2007), in which there is exactly one kernel corresponding to each group, i.e. $R_q = 1$ for each $q \in \{1, \ldots, Q\}$ in the equation in Equation (10). Under this scenario, each matrix $\mathbf{B}^{(q)}$ is a rank-one matrix generated by the coefficients $\alpha_{d,q}$, which also allows for the resulting matrix decomposed in a less expensive manner than the traditional LMC kernel.

Other Constructions: Many valid MOGP kernels do not satisfy the sum of separable kernels form which was depicted above, such as *process convolution* approaches (Boyle and Frean, 2004) and other invariant forms of kernels which incorporate lags or spatial shifts (Álvarez et al., 2012). In this paper, we focus on multi-output kernels which can be represented via a sum of separable kernels, as the Kronecker product structure combines naturally with the separability requirements

considered by Todescato et al. (2020). This produces a convenient structure for the Gram matrices which we consider in Section 3.

2.3 Kalman Filtering

The Kalman filter (KF), introduced and eponymously named for Rudolf E. Kálmán (1960), is a technique for recursively estimating the unobserved (latent) states of a linear dynamical system from a sequence of noisy and indirect measurements of the system. Kálmán originally derived the filter as the means to solving an optimal linear estimation problem via orthogonal projections. However, the Kalman filter also lends itself to a statistical interpretation, as the filter is equivalent to the solution of a Bayesian inference problem for a *linear Gaussian state-space model* whose posterior distribution is updated sequentially as new observations are recorded (Särkkä and Svensson, 2023).

In this subsection of the paper, we will formally describe the Kalman filter, and the linear Gaussian state-space model which underpins the statistical viewpoint for the Kalman filter. These statistical properties of interest are central to the algorithm presented by Todescato et al. (2020).

Definition 3 (State Space Model)**.** *Let $t_0 < t_1 < t_2 < \cdots < t_J$ be an indexed sequence of time points. A state space model is a dynamical system describing the joint behaviour of two stochastic processes: a latent state process $\{\mathbf{s}_j\}_{j=0}^J$ for states $\mathbf{s}_j \in \mathbb{R}^n$ which evolves over time according to some Markovian dynamics, and an observation (or measurement) process $\{\mathbf{y}_j\}_{j=1}^J$, where each measurement $\mathbf{y}_j \in \mathbb{R}^m$ is a (potentially) noisy observation of some deterministic function of the current latent state $\mathbf{s}_j$.*

One particularly convenient form of a state space model is the *linear Gaussian* state space model. In this setting, the dynamics which guide the evolution of the system over time and the observation model are both linear functions of the underlying states, and the random terms in the model follow multivariate Gaussian distributions.

Definition 4 (Linear Gaussian State Space Model)**.** *A linear Gaussian state space model is a dynamical state space model whose latent state and observation model are described by the following equations:*

$$\textbf{Initial state:} \quad \mathbf{s}(0) \sim \mathcal{N}\big(\mathbf{m}(0), \mathbf{\Sigma}(0)\big) \tag{16a}$$

$$\textbf{Dynamic model:} \quad \mathbf{s}(j+1) = \mathbf{A}(j)\mathbf{s}(j) + \mathbf{w}(j), \qquad \mathbf{w}(j) \sim \mathcal{N}\big(\mathbf{0}, \mathbf{Q}(j)\big) \tag{16b}$$

$$\textbf{Observation model:} \quad \mathbf{y}(j) = \mathbf{C}(j)\mathbf{s}(j) + \mathbf{v}(j), \qquad \mathbf{v}(j) \sim \mathcal{N}\big(\mathbf{0}, \mathbf{R}(j)\big) \tag{16c}$$

In the definition above, $\{\mathbf{s}(j)\}_{j=0}^J$ are the latent states within the dynamical model. The evolution of the dynamical system over time is guided by the *state transition matrix* $\mathbf{A}(j)$ and the random Gaussian noise $\mathbf{w}(j)$, and the observation process is influenced by the *observation matrix* $\mathbf{C}(j)$ and observation noise $\mathbf{v}(j)$. The initial state $\mathbf{s}(0)$, process noise terms $\{\mathbf{w}(j)\}_{j=0}^{J-1}$ and observation noise terms $\{\mathbf{v}(j)\}_{j=1}^J$ are all assumed to be mutually independent. Furthermore, the parameters $\mathbf{m}(0), \mathbf{\Sigma}(0), \{\mathbf{Q}(j)\}_{j=0}^{J-1}$, and $\{\mathbf{R}(j)\}_{j=1}^J$, and the transition and observation matrices are assumed to have fixed, known values.

A key property of the multivariate Gaussian distribution is that *any* linear transformation – including affine linear transformations – of a Gaussian-distributed random vector will still follow a Gaussian distribution, as does the sum of any pair of *independent* Gaussian-distributed vectors.

Consequently, in the linear Gaussian state space model described by Definition 4, every latent state $\{\mathbf{s}(j)\}_{j=0}^{J}$ and measurement $\{\mathbf{y}(j)\}_{j=1}^{J}$ is a random vector drawn from a Gaussian distribution with mathematically tractable parameters (Särkkä and Svensson, 2023).

In such cases, the standard method for recovering the parameters describing the distribution of each random vector is to utilize the Kalman filter (Kálmán, 1960), which iteratively computes the respective conditional mean and covariance for each latent state and observation. This is accomplished by iterating between two steps; the *prediction* step and the *update* step.

Algorithm 1 The Kalman Filter (Kálmán, 1960)

Require:
$\widehat{\mathbf{m}}(0 \mid -1)$: expected value of the initial state $\mathbf{s}(0)$
$\boldsymbol{\Sigma}(0 \mid -1)$: variance of the initial latent state $\mathbf{s}(0)$

for $j = 1$ to J **do**
`Prediction Step:`
$\widehat{\mathbf{m}}(j \mid j-1) = \mathbf{A}(j-1)\widehat{\mathbf{m}}(j-1 \mid j-1)$
$\boldsymbol{\Sigma}(j \mid j-1) = \mathbf{A}(j-1)\boldsymbol{\Sigma}(j-1 \mid j-1)\mathbf{A}(j-1)^{\mathsf{T}} + \mathbf{Q}(j-1)$
`Update Step:`
$\mathbf{d}(j) = \mathbf{y}(j) - \mathbf{C}(j)\widehat{\mathbf{m}}(j \mid j-1)$
$\mathbf{S}(j) = \mathbf{C}(j)\boldsymbol{\Sigma}(j \mid j-1)\mathbf{C}(j)^{\mathsf{T}} + \mathbf{R}(j)$
$\mathbf{K}(j) = \boldsymbol{\Sigma}(j \mid j-1)\mathbf{C}(j)^{\mathsf{T}}\mathbf{S}(j)^{-1}$ ▷ Kalman gain
$\widehat{\mathbf{m}}(j \mid j) = \widehat{\mathbf{m}}(j \mid j-1) + \mathbf{K}(j)\mathbf{d}(j)$
$\boldsymbol{\Sigma}(j \mid j) = \boldsymbol{\Sigma}(j \mid j-1) - \mathbf{K}(j)\mathbf{S}(j)\mathbf{K}(j)^{\mathsf{T}}$
end for

The prediction and update steps in the Kalman filtering algorithm (Algorithm 1) are so named as they correspond to specific conditional distributions of $\mathbf{s}(j)$ and $\mathbf{y}(j)$ before and after conditioning on the latest observation. In particular, for the linear Gaussian state space model described by Definition 4, we have the following distributional relationships:

$$\mathbf{s}(j) \mid \mathbf{y}(1), \ldots, \mathbf{y}(j-1) \sim \mathcal{N}\big(\widehat{\mathbf{m}}(j \mid j), \widehat{\boldsymbol{\Sigma}}(j)\big) \tag{17a}$$

$$\mathbf{y}(j) \mid \mathbf{y}(1), \ldots, \mathbf{y}(j-1) \sim \mathcal{N}\big(\mathbf{C}(j)\widehat{\mathbf{m}}(j), \mathbf{S}(j)\big) \tag{17b}$$

$$\mathbf{s}(j) \mid \mathbf{y}(1), \ldots, \mathbf{y}(j) \sim \mathcal{N}\big(\mathbf{m}(j), \boldsymbol{\Sigma}(j)\big) \tag{17c}$$

Each of the J iterations of Algorithm 1 requires both multiplying and inverting matrices. In total, the computational complexity per iteration in the Kalman filtering loop is $\mathcal{O}(m^3 + n^3)$ (Raitoharju and Piché, 2019), with each of these steps occurring J times in the total run of the algorithm. Thus, a 'naive' implementation of this algorithm would have a total computational complexity on the order of $\mathcal{O}\big(J(m^3 + n^3)\big)$. Overall, the computational complexity of the Kalman filtering algorithm is *linear* with respect to the number of iterations J, which is far quicker than the cubically-scaling $\mathcal{O}(J^3)$ runtime required for Gaussian process regression on a set of J observations. This algorithm also has a much lower storage requirement, as the updates are based strictly on the previous state, allowing for overwriting of earlier estimators.

3 Problem Formulation

Now that we have discussed the pre-requisite information regarding Gaussian process regression and Kalman filtering, we may begin to describe the setting considered by Todescato et al..

First, we will describe the initial univariate Gaussian process regression problem posed by

the authors, and the algorithm which they propose as a means of more efficiently deriving their desired estimates. Following this, we will explain how the algorithm by Todescato et al. can be extended for use with multi-output spatiotemporal dynamical systems, while maintaining similar computational benefits in comparison to related MOGP-based methods.

3.1 Single-Output Dynamical System

Suppose that we have some *compact* state space $\mathcal{X} \subseteq \mathbb{R}^P$ which represents a set of all possible locations of interest, such as the latitudes and longitudes of a bounded geographical region, or the coordinates of pixels in an image. Within the state space $\mathcal{X}$, we have a *finite* set of "observable" locations $\mathcal{I} := \{x_1, \ldots, x_M\} \subset \mathcal{X}$.

We wish to perform inference on the values of some function $f : \mathcal{X} \times \mathbb{R}^+ \to \mathbb{R}$, which we assume to be a realization of some zero-mean Gaussian process $f \sim \mathcal{GP}(0, K)$, for some kernel function K. Furthermore, at times $t_0 < t_1 < \ldots$, we record noisy observations of the form

$$y_i(t_j) = f(x_i, t_j) + v_i(t_j), \quad v_i(t_j) \sim \mathcal{N}(0, \sigma^2) \tag{18}$$

Importantly, the set of observations which are recorded at each time instant t_j may differ. For each time instant t_j, we let $\mathcal{M}_j \subseteq \mathcal{I}$ represent the observations recorded at time t_j, with $M_j := |\mathcal{M}_j|$.

The ultimate goal of the algorithm proposed by Todescato et al. is to develop estimates of the *entire* function $f(x, t)$ at any $x \in \mathcal{X}$ and $t \in \mathbb{R}^+$ based solely on statistical inference on observations from the set of pre-specified locations $\mathcal{I} \subset \mathcal{X}$.

Assumption 1. *The kernel function K representing the covariance of the univariate GP $f(x, t)$ can be separated into the product of a temporal and spatial kernel,*

$$K((x, t), (x', t')) = K_s(x, x')\gamma(\tau), \quad \textit{where } \tau := |t - t'| \tag{19}$$

Assumption 2. *The power spectral density $S(\omega)$ (see Definition 7) of $\gamma(|t - t'|)$ can be written as a rational function (with respect to ω) of order $2r$.*

The separability requirement enforced by Assumption 1 restricts the class of kernel functions which can be used for describing the covariance structure of the Gaussian process. However, this assumption is not overly restrictive in practice, and the family of kernels meeting this criterion remains quite flexible. Similarly, Assumption 2 does not excessively confine the options for temporal kernels in the Gaussian process, as many commonly-used kernels such as the Matérn covariance family satisfy this requirement of the power spectrum (Rasmussen and Williams, 2006).

In order to apply the Kalman filter, the algorithm proposed by Todescato et al. relies on a discretized state-space representation of the dynamical process which guides the evolution of the function $f(x, t)$. In many applied settings, the dynamical system which is desired evolves according to a continuous-time process. However, the measurement model is based on discrete-time observations. To overcome this distinction, the authors introduce a discretized state-space representation of the underlying continuous-time dynamics which guide the 'true' growth of the system.

For any time instance t_j where measurements are recorded, let $\tau_j := t_j - t_{j-1}$. Additionally, let the three matrices $F \in \mathbb{R}^{r \times r}, G \in \mathbb{R}^{r \times 1}$ and $H \in \mathbb{R}^{1 \times r}$ be the model matrices which collectively form a state-space representation for the spectral density $S(\omega)$ (Carron et al., 2016; Särkkä and

Svensson, 2023), and let $\overline{K}_s \in \mathbb{R}^{M \times M}$ be the Gram matrix for the spatial kernel K_s applied to $\mathcal{I}$. The spatiotemporal dynamics for the desired system are discretized by the following pair of equations, which guide the evolution from one observation time to the next:

$$\mathbf{s}(j+1) = A(j)\mathbf{s}(j) + \mathbf{w}(j), \quad \mathbf{w}(j) \sim \mathcal{N}(\mathbf{0}, Q(j)) \tag{20a}$$

$$\mathbf{y}(j) = C(j)\mathbf{s}(j) + \mathbf{v}(j), \quad \mathbf{v}(j) \sim \mathcal{N}(0, R(j)) \tag{20b}$$

The Markovian dynamics which impact Equations (20a) and (20b) are parametrized by the following matrices. These matrices are indexed by the observations, but the only manner in which they differ across observation times is through changes to the location set $\mathcal{M}_j \subset \mathcal{I}$.

$$A(j) = e^{T_j(\mathbf{I} \otimes F)} \in \mathbb{R}^{rM \times rM} \tag{21a}$$

$$C(j) = I_j \overline{K}_s^{1/2}(\mathbf{I} \otimes H) \in \mathbb{R}^{M_j \times rM} \tag{21b}$$

$$Q(j) = \mathbf{I} \otimes \left(\int_{t_{j-1}}^{t_j} \left(e^{\tau F}\right) G G^{\mathsf{T}} \left(e^{\tau F}\right) \mathrm{d}\tau \right) \in \mathbb{R}^{rM \times rM} \tag{21c}$$

$$R(j) = \sigma^2 \mathbf{I} \in \mathbb{R}^{M_j \times M_j} \tag{21d}$$

Algorithm 2 Kalman-based GP regression on $\mathcal{I}$ at query time $t \in \mathbb{R}^+$

Require:
- (F, G, H): state-space representation of $S_r(\omega)$
- σ^2: measurement noise variance
- $\mathcal{I}$: set of input locations
- $K_s(\cdot, \cdot)$: spatial kernel function
- $\gamma(\cdot)$: temporal kernel function
- $\mathbf{\Sigma}_0$: solution of Lyapunov equation $FX + XF^{\mathsf{T}} + GG^{\mathsf{T}} = 0$

Initialize $\widehat{\mathbf{s}}(0 \mid -1) = \mathbf{0}$ and $\mathbf{\Sigma}(0 \mid -1) = \mathbf{I} \otimes \mathbf{\Sigma}_0$.
`Kalman estimates:`
while $t_{j+1} \leq t$ **do**
  Compute $A(j), C(j), Q(j), R(j)$ using Equations (21a) to (21d)
  Apply the Kalman filter (Algorithm 1) to compute $\widehat{\mathbf{s}}(j+1 \mid j+1)$ and $\mathbf{\Sigma}(j+1 \mid j+1)$
  $\widehat{\mathbf{s}}(t) = \widehat{\mathbf{s}}(j+1 \mid j+1)$
  $\mathbf{\Sigma}^{\mathbf{s}}(t) = \mathbf{\Sigma}(j+1 \mid j+1)$
end while
`Open-loop prediction:`
$\tau = t - t_j$
$\widehat{\mathbf{s}}(t) = e^{\tau(\mathbf{I} \otimes F)} \widehat{\mathbf{s}}(j \mid j)$
$\mathbf{\Sigma}^{\mathbf{s}}(t) = \left(e^{\tau(\mathbf{I} \otimes F)}\right) \mathbf{\Sigma}(j|j) \left(e^{\tau(\mathbf{I} \otimes F)}\right)^{\mathsf{T}}$
`Process Estimate:`
$\widehat{\mathbf{f}}(t) = \overline{K}_s^{1/2}(\mathbf{I} \otimes H)\widehat{\mathbf{s}}(t)$
$\mathbf{\Sigma}^{\mathbf{f}}(t) = \overline{K}_s^{1/2}(\mathbf{I} \otimes H)\mathbf{\Sigma}^{\mathbf{s}}(t)(\mathbf{I} \otimes H)^{\mathsf{T}}\overline{K}_s^{1/2}$
return $\widehat{\mathbf{f}}(t)$ and $\mathbf{\Sigma}^{\mathbf{f}}(t)$

Algorithm 2 is a cleaned-up representation of the first algorithm presented by Todescato et al. in their paper. Instead of presenting the algorithm as a continuous, non-terminating function which 'loops' over all $t \in \mathbb{R}^+$, we have altered the formulation of the algorithm to explicitly demonstrate the Kalman filtering aspect, and the subsequent estimation of the change in the process post-filtering.

As part of their paper, Todescato et al. describe and prove a *Dynamic Representer Theorem*;

a form of the classic 'Representer Theorem' for Gaussian processes (see Theorem 1) which is amenable to the presumed spatiotemporal dynamics in their model. The key practical result of their Dynamic Representer Theorem is that for any time t beyond the final observation time t_J, the mean and variance estimates returned by Algorithm 2 can be used to derive a minimum-variance estimator of the function $f(x,t)$ at *any* location $x \in \mathcal{X}$.

Furthermore, the authors demonstrate that the computational complexity of Algorithm 2 is of the order $\mathcal{O}(rMM_J + rM_J^3)$ to derive the mean and covariance $\widehat{\mathbf{f}}(t_J)$ and $\mathbf{\Sigma}^{\mathbf{f}}(t_J)$, with an additional $\mathcal{O}(MP)$ cost to compute predictions of the form $f(x_i,t)$ at the P locations $\{x_1,\ldots,x_P\} \in \mathcal{X}$.

3.2 Multi-Output Dynamical System

Now, we may focus on the adaptation of the Kalman-enhanced regression algorithm for a multi-output Gaussian process. In addition to the two previously-stated assumptions on the nature of the dynamical system, we must make one additional assumption regarding the observations in the dynamical model.

Assumption 3 (Missingness of Vector-Valued Observations)**.** *For any location $\mathbf{x}_i \in \mathcal{X}$ and time $t_k \in \mathbb{R}^+$, the D entries of the response vector $\mathbf{y}_{i,j} = f(\mathbf{x}_i, t_j) + \mathbf{v}_{i,j} \in \mathbb{R}^D$ will either all be recorded, or all be missing.*

Assumption 3 is a simplifying assumption which ensures that there are not any partially-recorded or partially-unrecorded vectors of information. Such an assumption was absent from the prior paper on this topic, as their algorithm focused solely on scalar-valued responses, so it would not be possible for the measurement $\mathbf{y}_i(t_j)$ to be partially observed.

Algorithm 3 Kalman-based MOGP regression on $\mathcal{I}$ at query time $t \in \mathbb{R}^+$

1: **return** $\widehat{\mathbf{f}}(t)$ and $\mathbf{\Sigma}^{\mathbf{f}}(t)$

4 Methods

A major theoretical benefit of the algorithm proposed by Todescato et al. – and our multi-output extension in Algorithm 3 – is that under the necessary assumptions presented above, these algorithms provide minimum variance estimators with a significant reduction in the required computational resources. In order to determine if this goal is met in a practical setting, it is necessary to assess the efficacy of the proposed algorithm based on testable, reproducible results.

To evaluate the performance of Algorithm 3 we compare the accuracy and speed of Algorithm 1 to a 'naive' multi-output Gaussian process regression algorithm. The code for comparing these algorithms are created in Python, and utilize the `GPyTorch` library (Gardner et al., 2018) for the implementation of computational tasks involving Gaussian processes.

4.1 Simulations

The focus of our practical simulation study is to compare Algorithm 3 to a 'traditional' multi-output Gaussian process regression method.

To accomplish this, we generate synthetic data according to a multivariate Gaussian process model, and compare the predictive accuracy and overall runtime of these algorithms using a set

of four multi-output Gaussian process kernels. The four kernels which are compared are described by the following equations:

$$\textbf{Independent:} \quad K((x,t,d),(x',t',d')) = \gamma(|t-t'|)K_s(x,x')\mathbf{1}_{\{d=d'\}}\sigma_d^2 \tag{22a}$$

$$\textbf{ICM:} \quad K((x,t,d),(x',t',d')) = \gamma(|t-t'|)K_s(x,x')\mathbf{B}(d,d') \tag{22b}$$

$$\textbf{LMC:} \quad K((x,t,d),(x',t',d')) = \gamma(|t-t'|)\sum_{q=1}^{Q} K_s^{(q)}(x,x')\mathbf{B}^{(q)}(d,d') \tag{22c}$$

$$\textbf{Temporal LMC:} \quad K((x,t,d),(x',t',d')) = \sum_{q=1}^{Q} \gamma^{(q)}(|t-t'|)K_s^{(q)}(x,x')\mathbf{B}^{(q)}(d,d') \tag{22d}$$

These four kernels describe similar, but distinct, covariance structures for a multi-output Gaussian process. The first two kernels are fully separable into the product of covariances across the temporal, spatial, and output dimensions, whereas the two LMC kernels are a finite sum of such separable kernels.

5 Results

6 Discussion

6.1 Conclusions

In this paper, we focus on developing a method for deriving estimates of a spatiotemporal multi-output Gaussian process by incorporating a Kalman filter to sequentially update the mean and covariance functions.

6.2 Limitations

6.3 Future Work

References

Álvarez, M. A., Rosasco, L., and Lawrence, N. D. (2012). Kernels for Vector-Valued Functions: A Review. *Foundations and Trends in Machine Learning*, 4(3):195–266.

Bonilla, E., Chai, K., and Williams, C. (2007). Multi-task Gaussian Process Prediction. In Platt, J., Koller, D., Singer, Y., and Roweis, S., editors, *Advances in Neural Information Processing Systems*, volume 20. Curran Associates, Inc.

Boyle, P. and Frean, M. (2004). Dependent Gaussian Processes. In Saul, L., Weiss, Y., and Bottou, L., editors, *Advances in Neural Information Processing Systems*, volume 17. MIT Press.

Carron, A., Todescato, M., Carli, R., Schenato, L., and Pillonetto, G. (2016). Machine learning meets Kalman Filtering. In *2016 IEEE 55th Conference on Decision and Control (CDC)*, pages 4594–4599.

Cressie, N. (1990). The origins of kriging. *Mathematical Geology*, 22(3):239 – 252.

Gardner, J. R., Pleiss, G., Bindel, D., Weinberger, K. Q., and Wilson, A. G. (2018). GPyTorch: Blackbox Matrix-Matrix Gaussian Process Inference with GPU Acceleration. In *Advances in Neural Information Processing Systems*.

Guhaniyogi, R. and Banerjee, S. (2018). Meta-Kriging: Scalable Bayesian Modeling and Inference for Massive Spatial Datasets. *Technometrics*, 60(4):430–444. PMID: 31007296.

Huang, H., Blake, L. R., Katzfuss, M., and Hammerling, D. M. (2025). Nonstationary Spatial Modeling of Massive Global Satellite Data. *Journal of Computational and Graphical Statistics*, 34(4):1226–1239.

Kálmán, R. E. (1960). A New Approach to Linear Filtering and Prediction Problems. *Journal of Basic Engineering*, 82(1):35–45.

Katzfuss, M. and Guinness, J. (2021). A General Framework for Vecchia Approximations of Gaussian Processes. *Statistical Science*, 36(1):124 – 141.

Liu, H., Cai, J., and Ong, Y.-S. (2018). Remarks on multi-output Gaussian process regression. *Knowledge-Based Systems*, 144:102–121.

Pförtner, M., Wenger, J., Cockayne, J., and Hennig, P. (2025). Computation-Aware Kalman Filtering and Smoothing. In Li, Y., Mandt, S., Agrawal, S., and Khan, E., editors, *Proceedings of The 28th International Conference on Artificial Intelligence and Statistics*, volume 258 of *Proceedings of Machine Learning Research*, pages 2071–2079. PMLR.

Quiñonero-Candela, J. and Rasmussen, C. E. (2005). A Unifying View of Sparse Approximate Gaussian Process Regression. *Journal of Machine Learning Research*, 6(65):1939–1959.

Raitoharju, M. and Piché, R. (2019). On Computational Complexity Reduction Methods for Kalman Filter Extensions. *IEEE Aerospace and Electronic Systems Magazine*, 34(10):2–19.

Rasmussen, C. E. and Williams, C. K. I. (2006). *Gaussian Processes for Machine Learning*. The MIT Press.

Salari, A. and Zeinali, M. (2025). Kalman-Enhanced Dynamic Spatiotemporal Gaussian Process Regression for Real-Time Wind Turbine Power Estimation. In *2025 15th Smart Grid Conference (SGC)*, pages 1–4.

Särkkä, S. and Hartikainen, J. (2012). Infinite-Dimensional Kalman Filtering Approach to Spatio-Temporal Gaussian Process Regression. In Lawrence, N. D. and Girolami, M., editors, *Proceedings of the Fifteenth International Conference on Artificial Intelligence and Statistics*, volume 22 of *Proceedings of Machine Learning Research*, pages 993–1001, La Palma, Canary Islands. PMLR.

Särkkä, S. and Svensson, L. (2023). *Bayesian Filtering and Smoothing*. Institute of Mathematical Statistics Textbooks. Cambridge University Press, 2 edition.

Titsias, M. K. (2009). Variational Learning of Inducing Variables in Sparse Gaussian Processes. In van Dyk, D. and Welling, M., editors, *Proceedings of the Twelfth International Conference on Artificial Intelligence and Statistics*, volume 5 of *Proceedings of Machine Learning Research*, pages 567–574, Hilton Clearwater Beach Resort, Clearwater Beach, Florida USA. PMLR.

Todescato, M., Carron, A., Carli, R., Pillonetto, G., and Schenato, L. (2020). Efficient spatio-temporal Gaussian regression via Kalman filtering. *Automatica*, 118:109032.

Appendix

A AI Usage Statement

Two large language models – Claude Opus 5.5 (Anthropic) and GPT-5.6 Luna (OpenAI) – were used in the creation of this project.

Claude Opus 5.5 was employed for the creation and testing of Python code used for the simulations and replication of results. Claude Opus 5.5 was additionally used for assistance with the mathematical derivations and guarantees. GPT-5.6 Luna assisted with LaTeXtypesetting and formatting. Both models were also used in searching for relevant background literature.

All written text in this document has been both verified and re-written by the author. None of the text in the written document is the output of a large language model.

B Definitions and Technical Details

Definition 5 (Reproducing Kernel Hilbert Space (RKHS))**.** *Let $\mathcal{X}$ be an indexing set, and let $\mathcal{H}$ be a Hilbert space of real-valued functions $f : \mathcal{X} \to \mathbb{R}$ equipped with the inner product $\langle \cdot, \cdot \rangle_{\mathcal{H}}$ and induced norm $\|\cdot\|_{\mathcal{H}}$.*

For every $x \in \mathcal{X}$, define the evaluation functional $L_x : \mathcal{H} \to \mathbb{R}$ such that $L_x[f] = f(x)$ for all $f \in \mathcal{H}$. $\mathcal{H}$ is an RKHS over $\mathcal{X}$ if for all $x \in \mathcal{X}$, the evaluation functional $L_x[f] := f(x)$ is a bounded and continuous functional on $\mathcal{H}$.

Definition 6 (Reproducing Kernel)**.** *Let $\mathcal{H}$ be an RKHS over $\mathcal{X}$ with $\langle \cdot, \cdot \rangle_{\mathcal{H}}$ and norm $\|\cdot\|_{\mathcal{H}}$. The function $k : \mathcal{X} \times \mathcal{X} \to \mathbb{R}$ is the reproducing kernel for $\mathcal{H}$ if it satisfies the reproducing property:*

$$f(x) = \langle f, k(x, \cdot) \rangle_{\mathcal{H}}, \quad \forall x \in \mathcal{X} \tag{23}$$

Theorem 1 (Representer Theorem)**.** *Suppose that we have some dataset $\mathcal{D} := \{(x_i, y_i)\}_{i=1}^n$.*

$$J[f] := \frac{\lambda}{2} \|f\|_{\mathcal{H}}^2 + \sum_{i=1}^{n} L\big(y_i, f(x_i)\big), \tag{24}$$

where λ is a regularization parameter, and L is some loss function. Let $\mathcal{H}_k$ be an RKHS with reproducing kernel k. The Representer Theorem states that the minimizer $f^*(x)$ satisfies

$$f^*(x) = \underset{f \in \mathcal{H}_k}{\arg\min}\, J[f] = \sum_{i=1}^{n} \alpha_i k(x, x_i) \tag{25}$$

Definition 7 (Power Spectral Density)**.** *The power spectral density (PSD) of a univariate real-valued function $z(\tau)$ is given by*

$$S(\omega) = \int z(\tau) e^{-2\pi i \omega \tau} \mathrm{d}\tau \tag{26}$$

C Code

All of the code used for this project is available in a public GitHub repository, located at https://github.com/hotz1/Dynamical-Multitask-Prediction.