

Kluge Machine

Pre-Operation & Run Procedure

This document outlines the standard pre-operation setup and run procedure for the Kluge machine. Follow all steps in order before each production run to ensure safe and optimal machine performance.

1. Pre-Operation Setup

A. Lubrication

Proper lubrication is critical to machine longevity and safe operation. Complete all oiling steps before starting the machine.

- i Oil all points marked with **red paint**.
- ii Oil all other moving parts at bearings where accessible.

 **Do not operate the machine if any lubrication points are dry or inaccessible. Contact a supervisor before proceeding.**

B. Load & Prepare Machine

Configure the machine for the current job before power-on. Ensure all settings are verified and test runs are completed.

- i Load paper to the desired position and quantity.
- ii Set foil and heating plates to the desired setting (*if foil is required for the job*).
- iii Set creasing blocks to the desired setting (*if creasing is required for the job*).
- iv Perform a test run of foil and/or creasing before full production.

2. Running the Machine

Once pre-operation setup is complete, follow the startup sequence below in order. Do not skip steps.

- i Set the job counter to **0**.
- ii Turn on the **power switch**.

Immediately check for any undesired or irregular machine operation. Stop the machine and consult a supervisor if anything is abnormal.

iii Turn on the **air supply**.

■ **Never leave the machine unattended during the initial startup sequence. Observe the first several cycles before stepping away.**

Quick Reference Checklist

1a-i	Oil red-marked lubrication points	Always
1a-ii	Oil all bearing points	Always
1b-i	Load paper	Always
1b-ii	Set foil / heating plates	If foil job
1b-iii	Set creasing blocks	If creasing job
1b-iv	Test foil / creasing	If applicable
2-i	Reset counter to 0	Always
2-ii	Power on & inspect	Always
2-iii	Turn on air supply	Always

For questions regarding this procedure, contact your floor supervisor or the Keith Merrick maintenance team.