

# Instruction manual

Carry the screen wireless 2D scanner

V1.2

Dear users, thank you for choosing our products. We will serve you with high-quality products, in order to ensure that you use this product better, please read this manual carefully before use!

**Description**

Storage count    Wireless connection    Electricity

Inventory mode    Bluetooth connection

**Bluetooth connection**

After the code scanner is powered on, open the Bluetooth search at the receiving end, find the device with the Bluetooth name "BARCODE SCANNER", click to connect, and the icon will be displayed on the display after success. (Applicable to Bluetooth version)

**Bluetooth settings**

Bluetooth HID    Bluetooth SPP

Bluetooth BLE    Clear the pairing information

**System settings**

Factory reset    Software version number

All barcodes can be read

**Communication mode settings**

\*\*USB HID mode    Virtual serial port mode

**Common ending character settings**

\*\* Enter    Carriage return to wrap

Tab    No terminator

**Reading mode settings**

\*\* Manual reading mode    Induction mode

Continuous mode

**Tone settings**

\*\*Turn on the prompt sound    Turn off the tone

\*\* Turn on your voice    Turn off speech

\*\* Turn on vibration    Turn off the vibration

**Wireless function settings**

\*\* Normal mode    Storage mode

Data uploads    Clear data

Illustrate:

1. Normal mode: Scan the barcode to enter the normal mode, in which the scanning results will be uploaded to the computer in time (this mode is the default mode).
2. Inventory mode: scan the barcode to enter the inventory mode, in this mode will store the scanning results in the internal memory, and the inventory mode icon will be displayed on the screen (when the internal memory is occupied, the buzzer will "beep" as a prompt).
3. Data upload: Scan the barcode to upload the data stored in the internal memory to the computer in turn (applicable in inventory mode, please ensure that the wireless signal is normal when uploading data, there will be voice prompts when data upload is successful, and there will be voice prompts when data upload fails.)
4. Storage Count: The screen of the barcode scanner will display the total number of stored data.
5. Clear data: Scanning the barcode will erase all the data in the internal memory.

**One-click pairing function**

pairing

Scan the pairing code above, the scanner will continuously send out a pairing voice prompt, insert the receiver into the USB port of the computer, the voice prompt pairing is successful, and the screen will display the icon when the connection is successful

**Sleep time setting**

Note: Scan the sleep time SET first, and then scan the time you want to set

Sleep time SET    30 seconds    \*\*60 seconds

2 minutes    5 minutes    No dormancy

**Language settings**

\*\* United States    France    Germany

Italy    Spain    Japanese

**Reverse reading settings**

Inverted color recognition is turned on    \*\* Inverted color recognition is turned off