Rockchip Solutions DDR SDRAM Reference List

Ver 3.01

2025/10/20

Do not download or use this document (“Document”) unless carefully reviewed and accepted the following notice (“Notice”). By downloading or using this Document, customers acknowledge that they have read and agreed to be bound by the Notice. If customers don’t agree to all of the Notice, please do NOT download or use this Document, and destroy any downloaded or saved copies.

NOTICE

THIS DOCUMENTIS IS PROVIDED “AS IS", AND ROCKCHIP FLFCTRONICS CO., LTD.("ROCKCHIP") DOES NOT PROVIDE ANY WARRANTY OF AND KIND, WHETHER EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY,COMPLETENESS,MERCHANTABILITY.FITNESS FOR ANY PARTICULAR PURPOSE OR NON INERINGEMENT OF ANY REPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY,AND ROCKHIP DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THIS DOCUMENT. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME FOR SOME REASONS.

GUIDANCE

Symbol	Description
S/A	Sample Tested and Applicable, but there is a risk of small margins or others that require mass production to validation.
N/A	Not Applicable
Empty	Not be evaluated

- Rockchip only validates limited pieces of each sample from vendors and has no mass production experience with the DDR products on this list, so we do not guarantee any DDR quality provided to customers by vendors. Customers are solely responsible for the validating and testing DDR products ensure such product meets applicable standards and any safety, security or other reguirements.
- The DRAM Part Number usually consists of two parts divided by '-', the first part contains memory type, density, orgainization, package, and the second part usually means data rate. It should be noticed that some vendors like ESMT, RAYSON, CXMT, BIWIN, Kingston, Foresee, Goldkey, the second part contains other important information. We don't care about the part represented of data rate.
- Rockchip platform can support all the chips that match the first part of Part Number which marks '√', 'T/A' or 'S/A', and do not need to care the second part. If you want your system running more effective, you may need to find out the exact data rate in DRAM datasheet and config in kernel menuconfig.
- Please copy the Rockchip reference design model of DRAM area PCB Layout directly without any modification and follow the PCB layout rules from Rockchip. Contact information: fae@rock-chips.com
- THIS DOCUMENT IS PROVIDED “AS IS”. ROCKCHIP ELECTRONICS CO., LTD. (“ROCKCHIP”) DOES NOT PROVIDE ANY WARRANTY OF ANY KIND, EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY, COMPLETENESS,MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANY REPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME DUE TO THE UPGRADES OF THE PRODUCT OR ANY OTHER REASONS.
- Every times update will be highlighted by yellow.
- For DDR products on this list, except for specific products marked with application note, they can be used without any software modification.
- For DDR products on this list, each platform corresponds to each testing separately and the test results of different platforms CANNOT BE REFERENCED.

◆Application Note:

[1] On RK3568/RK3566, loader should be updated to rk3568_ddr_xxxMHz_v1.09.bin / rk3566_ddr_xxxMHz_v1.09.bin or later version.
[2] For LPDDR4 and LPDDR4X unified product, platform only approve LPDDR4 mode, not guarantee LPDDR4X mode can work stably. So VDDQ must provide 1.1V not 0.6V.
[3] On RV1126/RV1109, the performance of LPDDR4/LPDDR4X is not enough, please use it after evaluation.
[4]For some DDR products whose frequencies are lower than the maximum frequency of the platform, it is necessary to modify the frequency to a matching one by yourself.Refer to "修改DDR bin文件" in the "Rockchip_Developer_Guide_DDR_CN" or "Modify the DDR bin file" in "Rockchip_Developer_Guide_DDR_EN".

◆ Revision History

Revision No.	History	Date
2.00	ORG.	2012.12.24
2.44	Add some supporting messages, modify IMD256M16R4ABD8LY, IMD512M16R4AZD8JY to N/A. Add "Product Status".	2020.09.02
2.53	Add some supporting messages, modify T/A QN4LPD512M32M-32H to N/A on RK3399, modify T/A of GE8062666ND to N/A on RK3568.	2022.05.30
2.61	Add some supporting messages, modify S/A of GD82B32MJ0-41M2 to N/A.	2024.06.05
2.65	Add some supporting messages, modify S/A of DD4N08GBCDSO2-C2,DS4D82FBFCENY,KAD4N3M46GUT,GSD08GHGB6-S3L3C,BI4D8G1666-DL1,BI4D8G1666-DL2 to N/A.	2025.03.17
3.00	Add some supporting messages, modify new version, delete RK290x RK2918.	2025.08.08
3.01	Add some supporting messages.	2025.10.20

See Infocenter, https://redmine.rock-chips.com/documents/49, for access to the latest support list.

Consumer

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S/	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G / RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
																						CPU_RAM	NPU_RAM					
GCAI	GDF08G16LP0-M12		8G bit	512M×16	DDR4	96ball							S/A															
	GDT42A32BF0-T3E		8G bit	256M×32	LPDDR3	178ball													N/A	N/A								
	GD81B32MJ0-41M2	EOL	8G bit	256M×32	LPDDR4	200ball								S/A [3]														
	GD82B32MJ0-41M2	EOL	16G bit	512M×32	LPDDR4	200ball		N/A	N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A						
	GD82D32MJ0-42C2		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		N/A	N/A	N/A	N/A	N/A	N/A	N/A			N/A		N/A			N/A						
	GD82D32MJ0-42M3		16G bit	512M×32	LPDDR4X	200ball							S/A															
	GDA2D32MJ0-42M6		24G bit	768M×32	LPDDR4X	200ball				S/A		S/A	S/A	N/A					N/A									
	GDB2D32MJ0-42M7		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A [1][2]		S/A [1][2]	S/A [1][2]	N/A					N/A									
	GD84D32MJ0-42C2		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
Dli	DD4N08GBCDSO2-C2		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	DN4H16GCCPDI4-D2		16G bit	512M×32	LPDDR4X	200ball		S/A	N/A	N/A	S/A	N/A	N/A	N/A			N/A		N/A			N/A						
	DN4H16GCBPDI4-C7		16G bit	512M×32	LPDDR4X	200ball			N/A	N/A	S/A [4]	N/A	N/A	N/A			N/A		N/A			N/A						
	DN4H32GCCPQI4-D2		32G bit	1024M×32	LPDDR4X	200ball		S/A	N/A	N/A	S/A	N/A	N/A	N/A			N/A		N/A			N/A						
	DN4H32GVBPQI4-C7		32G bit	1024M×32	LPDDR4X	200ball			N/A	N/A		N/A	N/A	N/A			N/A		N/A			N/A						
YEESTOR	SGA128M16A8HC-G03		2G bit	128M×16	DDR3L	96ball								S/A														
ICMAX	IMD128M16R322J8LY		2G bit	128M×16	DDR3L	96ball													S/A	S/A								
	IMD256M16R30HG8GNF-107		4G bit	256M×16	DDR3	96ball								S/A			S/A		N/A	N/A		S/A						
	IMD256M16R324J8LY		4G bit	256M×16	DDR3L	96ball								S/A			S/A		S/A	S/A		S/A		S/A				
	IMD512M16R31AG8GPF		8G bit	512M×16	DDR3	96ball											S/A					S/A						
	IMD256M16R4ABD8LY		4G bit	256M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A			
	IMD256M16R4ZAD8TB		4G bit	256M×16	DDR4	96ball							S/A															
	IMD512M16R4DBD8LY		8G bit	512M×16	DDR4	96ball							S/A															
	IMD512M16R4AZD8JY		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A	N/A			
	IMD512M16R4FCD8TB		8G bit	512M×16	DDR4	96ball													S/A	S/A								
	IMH256M32Z1D1DNP		8G bit	256M×32	LPDDR4	200ball								S/A [3]			S/A					S/A						
	IMH512M32H2D2ENA		16G bit	512M×32	LPDDR4X	200ball					S/A [4]	S/A	S/A															
	IMH512M32Z2D2ENP		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
TMTC	TN4G16D3CSEP-EK		4G bit	256M×16	DDR3	96ball											S/A					S/A						
	TN8G16D4DSA4-GZ		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	TM8G32MD4LSA1-I4		8G bit	256M×32	LPDDR4	200ball											S/A					S/A						
	TH16G32MD4LQM1-I4		16G bit	512M×32	LPDDR4	200ball											N/A					N/A						

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229/PX5	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G / RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
																						CPU_RAM	NPU_RAM					
Goldkey	GH4061600HRL-1833		4G bit	256M×16	DDR3L	96ball										S/A		S/A	S/A	S/A								
	GE4062666HD		4G bit	256M×16	DDR4	96ball								S/A														
	GE8062666ND		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	GE8062400HD-1833		8G bit	512M×16	DDR4	96ball															S/A		S/A					
	L4D32H71-06242		32G bit	1024M×32	LPDDR4	200ball				N/A		N/A	N/A															
Eorex	EM47DM1688SBA		2G bit	128M×16	DDR3	96ball																						
	EM47EM0888SBA-150		2G bit	256M×8	DDR3	78ball																		S/A		N/A	N/A	S/A
	EM47EM1688SBA-150		4G bit	256M×16	DDR3	96ball																						
	EM47EM1688SBB-150A		4G bit	256M×16	DDR3	96ball																		S/A		S/A	S/A	S/A
	EM47FM0888SBA-150		4G bit	512M×8	DDR3	78ball																				S/A	S/A	
	EM47FM0888SBA-150A		4G bit	512M×8	DDR3	78ball																				S/A	S/A	
	EM47EM3288MBA-125		8G bit	256M×32	DDR3	136ball																		S/A				S/A
	EM49FM1688PBA-075		8G bit	512M×16	DDR4	96ball							S/A						S/A									
	EM45FM3288LBA-187F		16Gb/2Channel	256M×32×2Ch	LPDDR2	220ball																		S/A				N/A
axeme	H2A301G1656BC6C		1G bit	64M×16	DDR2	84ball									S/A	N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A	N/A
	H2A401G1666BFBC		1G bit	64M×16	DDR3	96ball									S/A													
	H2A402G1666BFBC		2G bit	128M×16	DDR3	96ball																				S/A	S/A	
	H2A404G1666CFMC		4G bit	256M×16	DDR3	96ball										S/A		S/A	S/A	S/A								
	H2A404G0866CD8C		4G bit	512M×8	DDR3	78ball																		S/A				S/A
Sinker	SNB2816S21PS13		2G bit	128M×16	DDR3L	96ball								S/A														
	SNB5616S21PS13		4G bit	256M×16	DDR3L	96ball								S/A					S/A	S/A								
ProMOS	V59C1G01168QBASXJ25		1G bit	64M×16	DDR2	84ball										N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A	N/A
	V73CAG01808RA JI9		1G bit	128M×8	DDR3	78ball																						
	V59C1G02168QB		2G bit	128M×16	DDR2	84ball										N/A	N/A	N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A	N/A
QCHP	QN3B128M16H-13A		2G bit	128M×16	DDR3	96ball									S/A													
	QN3R256M16M-16G		4G bit	256M×16	DDR3	96ball																		S/A				
	QN4A256M16M-26G		4G bit	256M×16	DDR4	96ball							S/A															
	QN4A512M16M-26E		8G bit	512M×16	DDR4	96ball							S/A						S/A									
	QN4A1GM16S-32J		16G bit	1024M×16	DDR4	96ball						S/A																
	QN4LPD512M32M-32H		16G bit	512M×32	LPDDR4	200ball											N/A					N/A						
	QNLP4D512M32S-32I		16G bit	512M×32	LPDDR4	200ball			S/A	N/A		N/A	N/A				S/A					S/A						
	QNLP4D512M32T-37I		16G bit	512M×32	LPDDR4X	200ball					S/A [4]																	
	QNLP4D1GM32T-42I		32G bit	1024M×32	LPDDR4X	200ball		S/A			S/A																	
	QN4LPXD1GM32SP-32H		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				N/A		N/A	N/A															
	QN4XLPE32GM16H-42I		32G bit	1024M×32	LPDDR4X	200ball		S/A			S/A																	
	QN4LPXD1536M32SP-32H		48G bit	1536M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
	QN4XLPE64GM16H-42J		64G bit	2048M×32	LPDDR4X	200ball				N/A		N/A	N/A															

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229 /PX5	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G2 / RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
																						CPU_RAM	NPU_RAM					
XINCUN	XCCB128M16FP-EKNAH		2G bit	128M×16	DDR3	96ball														S/A								
	XCCC128M16FP-EKNAB		2G bit	128M×16	DDR3L	96ball																		S/A				
	XCCC256M16FP-EKNAY		4G bit	256M×16	DDR3L	96ball																		S/A				
	XCCB256M16DP-EKNAH		4G bit	256M×16	DDR3	96ball														S/A								
	XCCC256M16EP-EKNAY		4G bit	256M×16	DDR3L	96ball																		S/A				
HIKSEMI	HSED4HB04G-JD3		4G bit	256M×16	DDR4	96ball							S/A															
	HSED4HB08G-JD4		8G bit	512M×16	DDR4	96ball				S/A		S/A	S/A															
	HSEL4XSA2G-HD8		16G bit	512M×32	LPDDR4X	200ball					S/A [8]	S/A	S/A															
	HSEL4XFA4G-CA9M		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
	HSEL4XFA4G-HD9		32G bit	1024M×32	LPDDR4X	200ball		S/A			S/A	S/A	S/A															
	HSEL4XFA4G-CA8M		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
DBTC	DS4D82FBFCENY		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	DS4D162FBFCENY		16G bit	1024M×16	DDR4	96ball							S/A															
	DL4008E2FSCE2GHY		8G bit	256M×32	LPDDR4	200ball							S/A															
	DL4X16E3FDEE2GHY		16G bit	512M×32	LPDDR4X	200ball						S/A	S/A															
	DL4X16E3FSEE2GMR		16G bit	512M×32	LPDDR4X	200ball				S/A	N/A	S/A	S/A															
	DL4X32E3CQEE2GCX		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				N/A		N/A	N/A															
KEYMOS	KL4X162BD-C2B		16G bit	512M×32	LPDDR4X	200ball				N/A	N/A	N/A	N/A															
	KL4X164CD-C7A		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		S/A		S/A	S/A	S/A	S/A															
	KL4X322BQ-C7B		32G bit	1024M×32	LPDDR4X	200ball				N/A	N/A	N/A	N/A															
	KL4X321CD-D2B		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A	S/A	S/A															
Netsol	S5RG2G20CMS-MGCJ		32G bit	512M×64	LPDDR4	366ball											N/A					N/A						
MT.MOSET	ED3E25608CE-P9		2G bit	256M×8	DDR3	78ball																		S/A		S/A	N/A	S/A
sMART	S4B2G0846C-HYH9		2G bit	256M×8	DDR3	78ball																		S/A				S/A
	S4B2G0846D-HYK0		2G bit	256M×8	DDR3	78ball																		S/A				S/A
WINS	VP5TQ2G1635FFP-F9		2G bit	128M×16	DDR3	96ball																				N/A	N/A	
ISDT	IL2BR20E8H		16Gb/2Channel	256M×32×2Ch	LPDDR2	220ball																		S/A				
YXSC	YX3H2816AB-M9LC		2G bit	128M×16	DDR3L	96ball								S/A										S/A				
	YX3H4816AB-M9LC		4G bit	256M×16	DDR3L	96ball								S/A										S/A				
	YX4H8A16AB-NCMC		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	YX4LA816BC-MGPE		16G bit	512M×32	LPDDR4X	200ball				S/A		S/A	S/A															

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506/ RK2118	RK3576	RK3528	RK3562	RK3588/ RK3588S	RK3568	RK3566	RV1126/ RV1109	RV1108/ RK3308/ RK3308B-S	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3326/ PX30	RK1808/ RK1806	RK3399PRO		RK3288	RK3368/RK3228A/RK3228B/RK3229 /PX5	RK2928/ RK3028A/ RK3128/PX3-SE	RK2926/RK3026/ RK3036/RK3036G / RK3126	RK3066/RK3066A/ PX2/RK3168/ RK3188/PX3
																						CPU_RAM	NPU_RAM					
KOWIN	KAD3N2M33BNT		4G bit	256M×16	DDR3L	96ball																		S/A				
	KAD4N3M46GUT		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	KAL3S3C55FN2		8G bit	256M×32	LPDDR3	178ball														S/A								
	KALXX4S43AY2		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		S/A		S/A	S/A	S/A	S/A															
	KALXX5S43AY2		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
DW MICRO	DWCT536HLC0-OB		16G bit	512M×32	LPDDR4/LPDDR4X	200ball			S/A			S/A	S/A															
	DWCT536HLC0-OD		16G bit	512M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
	DWCTA36HLC0-OB		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A						N/A									
	DWCTA36HLC0-OD		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
	DWCTB36HLC0-OD		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
GSTO	GSD02GHFB3-E3N3C		2G bit	128M×16	DDR3L	96ball				N/A		N/A	N/A						N/A	N/A								
	GSD04GHFB4-E3N3C		4G bit	256M×16	DDR3L	96ball													S/A	S/A								
	GSD04GHGB5-S3L3C		4G bit	256M×16	DDR4	96ball				S/A		S/A	S/A															
	GSD08GHGB6-S3L3C		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
Artmem	ATL4X12324M102		12G bit	384M×32	LPDDR4/LPDDR4X	200ball													N/A									
BIIE	BI4D4G16M00-DL1		4G bit	256M×16	DDR4	96ball													S/A									
	BI4D4G16M00-DL2		4G bit	256M×16	DDR4	96ball				N/A		N/A	N/A															
	BI4D8G1666-DL1		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	BI4D8G1666-DL2		8G bit	512M×16	DDR4	96ball			N/A	N/A		N/A	N/A	N/A		N/A		N/A	N/A	N/A	N/A		N/A					
	BI16G32MD4PDC1-J1		16G bit	512M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
	BI32G32MD4PQC1-J1		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
Rocfour	MC4X1GM32BQ200A-32T		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A		S/A	S/A															
	MC4X1GM32BQ200A-42T		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
	MC4X2GM32CQ200A-42T		64G bit	2048M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
	MC5D1GM32DQ315B-64T		32G bit	1024M×32	LPDDR5	315ball		S/A			S/A																	
Yangtze Mason	MSP4C0D5I-032G		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A															
Barycn	SPMNBBQMCM-MJXU		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A	S/A															
JSC	JSL5HCG329TKA-03		32G bit	1024M×32	LPDDR5	315ball		S/A			S/A																	
	JSL5HDG32ATKA-03		64G bit	2048M×32	LPDDR5	315ball					S/A																	
TWSC	TEL4XCC32ACY-32G		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball						S/A																
	TEL4XMA32ACX-32G		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball				S/A																		
XUNSHAN	XSRGBQCA1MG-L		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	
TSEM	T5LC32BQBM-CP		64G bit	2048M×32	LPDDR5	315ball		N/A			N/A																	
PLUSE	PSX4S0D4S-32G		32G bit	1024M×32	LPDDR4/LPDDR4X	200ball		S/A			S/A																	

Industrial&Wide Temperature

Manufacturer	Part Number	Product Status	Density	Organization	Type	Package	RK3506J	RK3576J	RK3528	RK3562J	RK3588J	RK3568J	RK3566	RV1126K	RV1108K1 RK3308J	RK3228H	RK3399	RK3328	RK3326S/ PX30S	RK3358J	RK1808K	RK3399PRO		RK3288				
																						CPU_RAM	NPU_RAM					