2/10/24 Arms Signed
Competencies
Induction

burlodge

Method Statement

Cleaning food spillages inside the Multi-Cook oven chamber

Originator:	Lloyd Hunt
Position:	Technical Support Manager
Review Date:	01/02/2024
Expiry Date:	01/03/2025
Contract Manager:	N/A

Planned Task/ Activity Description:	Service and/or maintenance of Burlodge catering equipment. Cleaning instructions for all Multicook ovens.

This method statement is critical to the health and safety of the activity(ies) it relates to. It is to be strictly adhered to. Any deviation must first be authorised by the Technical Manager.

The Multicook oven is specifically designed to regenerate single plated meals provided the oven is used correctly and cleaned in the correct frequency. The use of any chemical cleaners is eliminated. We do not advise the use of any chemical cleaners other than soapy water and the use of any type of jet washer, water hose and steam cleaners are prohibited. Ensure that the correct PP work clothes are worn.

General Considerations:

Location and Access: (attached plan as appropriate)	Client site or warehouse:
Working Environment & Restrictions:	Trolley must be removed from sensitive areas to area more appropriate for use of detergents and other cleaning materials. All mechanical components and potentially sharp edges within the oven chamber should be treated with caution and care: use long-handled brush to minimise hand contact.

2/10/24 Rupert Seaman

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

Applicable legislation and standards	The Health and Safety at Work etc. Act 1974 Management of Health and Safety at Work Regulations 1999 Workplace (Health, Safety and Welfare) Regulations 1992 The Control of Noise at Work Regulations 2005 Manual Handling Operations Regulations 1992 The Controlled Waste (England & Wales) Regulations 2012 (Amended) The Provision and Use of Workplace Equipment Regulations 1998 (PUWER) Reporting of Injuries, Diseases and Dangerous Occurrences Regulations (RIDDOR) 2013 Control of Substances Hazardous to Health Regulations (CoSHH) 2002 The Personal Protective Equipment at Work Regulations 1992 EU fluorinated greenhouse gas (F gas) regulation 2014 ISO 9001:2008 Quality Management System See also: **Burlodge Electrical Safety Handbook**
Protection of others:	Trailing cables or spilt liquid present hazards to others: these should be avoided or cleared as quickly as possible.
Emergency Procedures:	If using any chemicals, ensure that safe handling procedures are followed and that access to cold running water is available.
Operatives/Competence:	Subject to training in cleaning and awareness of internal mechanical components

Preparation:

Personal Protective Equipment:	Overalls; Protective glasses; Heavy duty gloves; Oven gloves (only required if wash cycle is used); Other protective clothing appropriate to the working area;
Plant & Equipment:	Non-caustic detergents
Materials Handling/Storage and Safety Information:	All mechanical components within the oven chamber should be treated with caution. Refer to manufacturer's instructions for any chemicals used.

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

Procedure:

Isolation in Safe Mode	It is essential to ensure the Oven is in a safe condition before any cleaning or maintenance takes place. This is referred to in the manual as the **SAFE MODE**. The Oven is in the **SAFE MODE** under the following conditions: • Fully isolated from any power source • The cable, if supplied, is correctly secured in the holder • The oven chamber is at ambient temperature, i.e. below 30°C (86°F) • Oven fans are stopped
Frequency	Clean the oven after every cycle and all spillage should be cleaned and not left to dry. This will eliminate the use of any chemical cleaners.

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

Critical Stages: (must be undertaken in correct sequence	1. Ensure the oven disconnected from power and in **Safe Mode** (see **Safe Mode** below) 2. Ensure all required cleaning materials are available and to hand 3. Open oven door 4. Remove all the grids 5. Do not place hand or fingers into or through the central and vertical ventilation slots or grid supports. 6. Brush out and dispose of any loose debris; 7. Ensure the oven disconnected from power and in **Safe Mode** (see **Safe Mode** below) 8. Ensure all required cleaning materials are available and to hand 9. Open oven door 10. Remove all the grids 11. Do not place hand or fingers into or through the central and vertical ventilation slots or grid supports. 12. Brush out and dispose of any loose debris; 13. Wipe and clean all surfaces with non-caustic detergent with a soft cloth; 14. Rinse cleaned area; 15. Once cleaning has been completed, remove any excess water using sponge; 16. Wipe and clean all surfaces with non-caustic detergent with a soft cloth; 17. Rinse cleaned area; 18. Once cleaning has been completed, remove any excess water using sponge;
Critical Stages: (continued)	19. If a large amount of water is to be used, a receptacle must be placed under the waste outlet at the rear of the oven; 20. Allow to dry; 21. Insert the grids back into the oven; 22. Close oven door.
Exterior of the oven:	Wipe all surfaces and glass with slightly damp soft clean cloth. Always clean following the grain of the stainless steel in a straight line and not in rotation.

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073, VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

Final Clearance: (Work/Activity completed to satisfaction).	N/A

Signature:	
Name:	Lloyd Hunt
Position:	Technical Support Manager
Date:	1st February 2024

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073, VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

Method Statement

Equipment Isolation

Form:	**MS15**
Originator:	Lloyd Hunt
Position:	Technical Support Manager
Review Date:	01/02/2024
Expiry Date:	01/02/2025
Contract Manager:	N/A

Planned Task/ Activity Description:	Multigen Electrical Components **Inspection, repair and replacement of Multigen Electrical components**
Scope of works:	**Service and/or maintenance of Burlodge catering equipment.**

This method statement is critical to the health and safety of the activity(ies) it relates to. The first section relates to the risk assessment It is to be strictly adhered to. Any deviation must first be authorized by the Technical Manager.

Working Environment & Restrictions:	Where possible the trolley must be moved to a safe area where the repairs can be carried out safely. Do not carry out any electrical work in wet areas.
Protection of others:	Keep working area safe and clean at all times inform catering operatives that you are working in that specific area and do not leave any unfinished work unattended. Do not carry out work in a confined space.

Burlodge Limited
C 60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

Applicable legislation and standards	The Health and Safety at Work etc. Act 1974 Management of Health and Safety at Work Regulations 1999 Workplace (Health, Safety and Welfare) Regulations 1992 The Control of Noise at Work Regulations 2005 Manual Handling Operations Regulations 1992 The Controlled Waste (England & Wales) Regulations 2012 (Amended) The Provision and Use of Workplace Equipment Regulations 1998 (PUWER) Reporting of Injuries, Diseases and Dangerous Occurrences Regulations (RIDDOR) 2013 The Personal Protective Equipment at Work Regulations 1992 EU fluorinated greenhouse gas (F gas) regulation 2014 ISO 9001:2008 Quality Management System See also: **Burlodge Electrical Safety Handbook**

Burlodge Limited
C 60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

Emergency Procedures:

In case of electrical shock:

While **waiting for medical help, follow these steps:**

1. **Look first. Don't touch.** The person may still be in contact with the electrical source. Touching the person may pass the current through you.
2. **Turn off the source of electricity if possible.** If not, move the source away from you and the affected person, using a non-conducting object made of cardboard, plastic or wood.
3. **Check for signs of circulation (breathing, coughing or movement).** If absent, begin cardiopulmonary resuscitation (CPR) immediately.
4. **Prevent shock.** Lay the person down and, if possible, position the head slightly lower than the trunk, with the legs elevated.

In case of fire:

- Follow site specific procedures provided during your site induction. Otherwise:

1. Raise the alarm
2. Switch off electrical supply
3. Use close by firefighting equipment if competent and it is safe to do so

Caution

- **Don't touch the person with your bare hands** if he or she is still in contact with the electrical current.
- **Don't get near high-voltage wires** until the power is turned off. Stay at least 20 feet away — further if wires are jumping and sparking.
- **Don't move a person** with an electrical injury unless the person is in immediate danger.

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

Operatives/Competence:	Burlodge trained Engineers.
Emergency **Contact:**	Burlodge: 020 8879 5700 (during office hours). Technical Manager: 07747214688 (out of hours)
Personal **Protective Equipment:**	Safety shoes Other protective clothing appropriate to that working area.
Plant & Equipment:	Hand tools; VDE Insulated Tools GS38 Complaint Test Leads and meter Insulation Resistance tester; PAT Tester.
Materials Handling/Storage and Safety Information:	Risk Assessments: **RA2; RA8; RA9; RA16** The Electricity at Work Regulations 1989 require precautions to be taken against the risk of death or personal injury from electricity in work activities. The purpose of these notes is to provide guidance for competent staff on such precautions when there is any possibility of contact with live equipment. Regulation 14 states: no person shall be engaged in any work activity on or so near any live conductor (other than one suitably covered with insulating material so as to prevent danger) that danger may arise unless: a) it is unreasonable in all the circumstances for it to be dead; and b) it is reasonable in all the circumstances for him to be at work on or near it while it is live; and c) Suitable precautions (including, where necessary, the provision of suitable protective equipment) are taken to prevent injury.

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

Critical Stages: (must be undertaken in correct sequence)

Before beginning the work, all personnel involved should make themselves fully conversant equipment manuals. Make sure of the following before attempting the procedure:

a. *All personal protective equipment is available and being used correctly.*

b. *Work must be carried out in an area with adequate ventilation.*

Burlodge Limited
C/60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 407 236
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

1. Contact client's management/estates department to gain permission and to advise of work to be carried out. Identify work location, likely time frame, include post hot-work fire check. Provide your name and contact details.

2. Where required, complete site's Permit to Work and adhere to any rules printed thereon, follow these procedures.

3. Gather as much information on the fault as possible before starting work on the equipment.

4. Ensure that all circuits that are being worked on are isolated and locked and signage to denote that you are working on this circuit you must also comply with any other local or hospital requirements and this must be noted in your report

Portable equipment must be unplugged from all power sources. Remember that some equipment may have more than one power cable and plug.

5. Do not work on any live circuits as the specified work does not require this. Check equipment dead repair/replacement of electrical components and circuits.

6. Always use VDE approved fully insulated tools even though there is no working on live equipment everybody has a responsibility to make sure they keep themselves, and others safe.

7. Once the work have been completed the equipment should be tested under full load conditions, including the cord sets and that all safety circuits are working and have been tested never leave any equipment with any safety circuit disabled.

8. Carry out a full PAT and record the results on our standard forms.

10. After the work has been satisfactorily completed the equipment and area must be left clean and in good working order. All tools removed from equipment and work area.

11. If the equipment is unsafe to use all fuses must be removed and a notice place on the equipment that it is unsafe to use the client must be given the fuses and a sign the report you must inform the office immediately.

Burlodge Limited
C 60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 407 236
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

Final Clearance: (Work/Activity completed to satisfaction).	A full report should be made listing any advice, issues encountered or remedial action that may be required. This must be signed off by an authorised member of the client staff.

Signature:

Name: Lloyd Hunt

Position: Technical Support Manager

Date: 1st February 2024

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

RISK ASSESSMENT

TASK: **RA2**	Lone Working	**ASSESSMENT BY:**	LLOYD HUNT, TECHNICAL MANAGER
DATE OF ASSESSMENT:	15/02/2024	**REVIEW DATE:**	15/02/2025

What are the hazards?	Who might be harmed?	Where does the hazard occur?	How does the hazard occur?	Risk probability	Risk impact	Risk Rating	Current control measures	Further action required?
Injury/death through accident or illness.	Engineer. Office Worker. Warehouse	Accident or illness harm	Illness or injury causing incapacity being undetected	Possible	Severe	Medium/High	• Avoid working alone when possible. • Always inform others (site staff, colleagues) as to your working location. • Have a way of raising alarm, such as a fully charged phone. (Connect to wifi incase of signal loss before starting task). • Familiarise yourself with the tasks risk assessments, coshh assessments and method statements before work.	Review every 12 months
Injury/death From Breathing Difficulties	Engineer. Office Worker. Warehouse	Replacement of oxygen or release of toxic coshh substances	Poor ventilation. Incorrect use of coshh products.	Unlikely	Severe	Medium/High	• Avoid working alone when possible. • Always inform others (site staff, colleagues) as to	Review every 12 months

							your working location. • Have a way of raising alarm, such as a fully charged phone. (Connect to wifi incase of signal loss before starting task). • Familiarise yourself with the tasks risk assessments, coshh assessments and method statements before work. • Check that the ventalation is adaqute before working	
Injury through violence.	Engineer. Office Worker. Warehouse	Other personnel	Members of the public. Vulnerable persons.	Possible	Major	Medium/High	• Avoid working alone when possible. • Always inform others (site staff, colleagues) as to your working location. • Have a way of raising alarm, such as a fully charged phone. (Connect to wifi incase of signal loss before starting task). • Familiarise yourself with the tasks risk assessments, coshh assessments and method statements before work.	Review every 12 months

							• Check external doors locked at Burlodge locations	
Poor Mental Well Being/Stress	Engineer. Office Worker. Warehouse	Repeated lone worked. Performing new tasks	Little communicati on with others. Unfamiliarity, lack of skills for the tasks.	Possible	Moderate	Medium	• Avoid working alone when possible. • Request training if required. • Talk to colleagues regually, seek advice on tasks. • Discuss personnal/work concerns with line manager	Review every 12 months

IMPACT LEVEL	DESCRIPTION
NOT SIGNIFICANT	Negligible injuries not needing medical treatment
MINOR	Minor injuries causing temporary impairment needing medical treatment
MODERATE	Illness and/or injury requiring hospitalization
MAJOR	Illness and/or injury resulting in permanent impairment
SEVERE	Fatality

PROBABILITY LEVEL	DESCRIPTION
HIGHLY UNLIKELY	Rare chance of an occurrence
UNLIKELY	Not likely to occur under normal circumstances
POSSIBLE	May occur at some point under normal circumstances
LIKELY	Expected to occur at some point in time
HIGHLY LIKELY	Expected to occur regularly under normal circumstances

RISK SEVERITY MATRIX *based on Impact and Probability Levels*

burlodge

RISK ASSESSMENT

IMPACT x PROBABILITY	NOT SIGNIFICANT	MINOR	MODERATE	MAJOR	SEVERE
HIGHLY UNLIKELY	LOW	LOW	LOW / MED	MEDIUM	MEDIUM
UNLIKELY	LOW	LOW / MED	LOW / MED	MEDIUM	MED / HIGH
POSSIBLE	LOW	LOW / MED	MEDIUM	MED / HIGH	MED / HIGH
LIKELY	LOW	LOW / MED	MEDIUM	MED / HIGH	HIGH
HIGHLY LIKELY	LOW / MED	MEDIUM	MED / HIGH	HIGH	HIGH

burlodge

RISK ASSESSMENT

TASK: **RA15**	MULTI-COOK OPERATING, REPAIR AND SERVICING	**ASSESSMENT BY:**	LLOYD HUNT, TECHNICAL MANAGER
DATE OF ASSESSMENT:	15/02/2024	**REVIEW DATE:**	15/02/2025

What are the hazards?	Who might be harmed?	Where does the hazard occur?	How does the hazard occur?	Risk probability	Risk impact	Risk Rating	Current control measures	Further action required?
Burn	Engineer. Operator.	Inside the oven. Food	Handling hot surfaces and food	Low/ Medium	Possible	Medium	Gloves provided for food handling. Service to take place once oven is in safe mode (temp below 30°C)	Review every 12 months
Electrical shock	Engineer. Operator.	All metal parts and conductors	Contact with live conductor. Faulty parts.	Unlikely	Severe	High	Check plug/cable before use. Electrically isolate oven before repair/service of internal.	Review every 12 months
Crushing fingers in doors.	Engineer. Operator.	Oven doors opening/closing	Inserting fingers into tight recesses.	Unlikely	Minor	Low/Medium	Keep fingers clear of door.	Review every 12 months
Cuts and abrasions	Operator. Engineer.	Cleaning the internal oven.	Inserting fingers into tight recesses	Unlikely	Minor	Low/Medium	Follow correct procedure (Method statement for Cleaning the Oven Chamber)	Review every 12 months
Tripping	Operator. Engineer.	Mains Cable. Tools.	When oven is incorrectly positioned. Untidied tools.	Possible	Moderate	Medium	Correct positioning on oven. And cable/plug. No tools to be left loose on the floor. Always keep work area clear.	Review every 12 months
Slipping	Operator. Engineer.	Falling over from food spillage	Failure to clean up spillages	Possible	Moderate	Medium	Clean all spillages immediately. Use warning signs.	Review every 12 months

burlodge

RISK ASSESSMENT

Impacts from moving parts	Engineer.	Touching a moving fan blade	Servicing/repairs with oven baffle removed.	Low	Major	Medium	Only remove oven baffle after electrically isolating the oven.	Review every 12 months

IMPACT LEVEL	DESCRIPTION
NOT SIGNIFICANT	Negligible injuries not needing medical treatment
MINOR	Minor injuries causing temporary impairment needing medical treatment
MODERATE	Illness and/or injury requiring hospitalization
MAJOR	Illness and/or injury resulting in permanent impairment
SEVERE	Fatality

PROBABILITY LEVEL	DESCRIPTION
HIGHLY UNLIKELY	Rare chance of an occurrence
UNLIKELY	Not likely to occur under normal circumstances
POSSIBLE	May occur at some point under normal circumstances
LIKELY	Expected to occur at some point in time
HIGHLY LIKELY	Expected to occur regularly under normal circumstances

burlodge

RISK ASSESSMENT

RISK SEVERITY MATRIX *based on Impact and Probability Levels*

IMPACT x PROBABILITY	NOT SIGNIFICANT	MINOR	MODERATE	MAJOR	SEVERE
HIGHLY UNLIKELY	LOW	LOW	LOW / MED	MEDIUM	MEDIUM
UNLIKELY	LOW	LOW / MED	LOW / MED	MEDIUM	MED / HIGH
POSSIBLE	LOW	LOW / MED	MEDIUM	MED / HIGH	MED / HIGH
LIKELY	LOW	LOW / MED	MEDIUM	MED / HIGH	HIGH
HIGHLY LIKELY	LOW / MED	MEDIUM	MED / HIGH	HIGH	HIGH

burlodge

RISK ASSESSMENT

TASK: **RA16**	MULTIGEN OPERATING, REPAIR AND SERVICING	**ASSESSMENT BY:**	LLOYD HUNT, TECHNICAL MANAGER
DATE OF ASSESSMENT:	15/02/2024	**REVIEW DATE:**	15/02/2025

What are the hazards?	Who might be harmed?	Where does the hazard occur?	How does the hazard occur?	Risk probability	Risk impact	Risk Rating	Current control measures	Further action required?
Burn	Engineer. Operator.	Inside the oven. Food	Handling hot surfaces and food	Low/ Medium	Possible	Medium	Gloves provided for food handling. Service to take place once oven is in safe mode (temp below 30°C)	Review every 12 months
Electrical shock	Engineer. Operator.	All metal parts and conductors	Contact with live conductor. Faulty parts.	Unlikely	Severe	High	Check plug/cable before use. Electrically isolate oven before repair/service of internal.	Review every 12 months
Crushing fingers in doors.	Engineer. Operator.	Oven doors opening/closing	Inserting fingers into tight recesses.	Unlikely	Minor	Low/Medium	Keep fingers clear of door.	Review every 12 months
Cuts and abrasions	Operator. Engineer.	Cleaning the internal oven.	Inserting fingers into tight recesses	Unlikely	Minor	Low/Medium	Follow correct procedure (Method statement for Cleaning the Oven Chamber)	Review every 12 months
Tripping	Operator. Engineer.	Mains Cable. Tools.	When oven is incorrectly positioned. Untidied tools.	Possible	Moderate	Medium	Correct positioning on oven. And cable/plug. No tools to be left loose on the floor. Always keep work area clear.	Review every 12 months
Slipping	Operator. Engineer.	Falling over from food spillage	Failure to clean up spillages	Possible	Moderate	Medium	Clean all spillages immediately. Use warning signs.	Review every 12 months
Manual handling injury	Engineer.	Manoeuvring refrigeration equipment/bottles	Incorrect Manual handling	Possible	Moderate	Medium	Use correct manual handling methods	Review every 12 months

Burlodge Limited
C60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

burlodge

RISK ASSESSMENT

Impacts from moving parts	Engineer.	Touching a moving fan blade	Servicing/repairs with oven baffle removed.	Low	Major	Medium	Only remove oven baffle after electrically isolating the oven.	Review every 12 months

IMPACT LEVEL	DESCRIPTION
NOT SIGNIFICANT	Negligible injuries not needing medical treatment
MINOR	Minor injuries causing temporary impairment needing medical treatment
MODERATE	Illness and/or injury requiring hospitalization
MAJOR	Illness and/or injury resulting in permanent impairment
SEVERE	Fatality

PROBABILITY LEVEL	DESCRIPTION
HIGHLY UNLIKELY	Rare chance of an occurrence
UNLIKELY	Not likely to occur under normal circumstances
POSSIBLE	May occur at some point under normal circumstances
LIKELY	Expected to occur at some point in time
HIGHLY LIKELY	Expected to occur regularly under normal circumstances

Burlodge Limited
C 60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY, United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk

RISK SEVERITY MATRIX *based on Impact and Probability Levels*

IMPACT x PROBABILITY	NOT SIGNIFICANT	MINOR	MODERATE	MAJOR	SEVERE
HIGHLY UNLIKELY	LOW	LOW	LOW / MED	MEDIUM	MEDIUM
UNLIKELY	LOW	LOW / MED	LOW / MED	MEDIUM	MED / HIGH
POSSIBLE	LOW	LOW / MED	MEDIUM	MED / HIGH	MED / HIGH
LIKELY	LOW	LOW / MED	MEDIUM	MED / HIGH	HIGH
HIGHLY LIKELY	LOW / MED	MEDIUM	MED / HIGH	HIGH	HIGH

Burlodge Limited
C 60 Barwell Business Park, Leatherhead Road, Chessington, Surrey, KT9 2NY United Kingdom
T +44 0208 879 5700 F +44 0208 879 5701 E sales@burlodge.co.uk
Service phone +44 0208 879 5757 Service e-mail service@burlodge.co.uk
Company Reg. No.: 2196073. VAT Reg. No.: GB 493 4072 36
WEEE Reg. No.: WEE/CA0112XR
www.burlodge.co.uk