PLANT 2 · STANDARD OPERATING PROCEDURE

Line Shutdown and Shift Handover

SOP-102
Rev C

Effective	Owner	Prepared by	Approved by
2024-09-02	**Production**	**M. Alvarez**	**D. Whitfield**

PURPOSE

Leave the line clean, safe and documented for the next shift.

SCOPE

Lines 1, 2 and 3, at the end of every shift.

ROLES

ROLE	RESPONSIBILITY
Line Lead	Writes the handover and meets the incoming Line Lead.
Operator	Cleans and secures the machine.

PPE

- Safety glasses
- Safety shoes
- Chemical-resistant gloves when cleaning the filler

TOOLS

- Scraper
- Lint-free wipes

MATERIALS

- Sanitizer

PROCEDURE

Shutdown

STEP	WHO	ACTION
1	Operator	Run the line empty. Stop the filler, then the capper, labeler and case packer in that order.
2	Operator	Clean filler nozzles and the drip tray. Wipe the labeler rollers. Empty the case packer reject bin.
3	Operator	Count rejected bottles and write the count on the production report.
4	Operator	Move any product on hold to the hold cage as described in QP-315.

Handover

STEP	WHO	ACTION
5	Operator	Enter every stop of 3 minutes or longer in FRM-PR-09 Downtime Log Sheet with the cause and a short comment.
6	Line Lead	Fill in FRM-PR-02 Shift Handover Log: output against plan, open problems, materials short, safety concerns.
7	Line Lead	Walk the line with the incoming Line Lead. Both sign the log.
8	Line Lead	If the line will be down for more than 60 minutes, the next start follows SOP-101 in full.

RELATED DOCUMENTS

- SOP-101 Line Start-Up
- QP-315 Nonconforming Product and Hold

RECORDS

- FRM-PR-02 Shift Handover Log
- FRM-PR-09 Downtime Log Sheet

REVISION HISTORY

REV	DATE	CHANGE
C	2024-09-02	Stops of 3 minutes or longer must be logged (was 5).
B	2022-01-10	Added walk with incoming lead.