

STANDARD OPERATING PROCEDURE FOR ELECTRICAL CABLE JOINTING

Purpose

To ensure safe and reliable jointing of electrical cables in industrial environments while preventing electrical hazards, ensuring continuity, and maintaining compliance with safety standards.

Scope

Applicable to all electrical cable jointing works in the facility, covering both low-voltage (LV) and high-voltage (HV) cables.

Procedure for Cable Jointing

1. Identify and verify the cable type, size, and voltage rating.
2. Measure and cut the cable to the required length using an insulated cutter.
3. Remove dirt, moisture, and contaminants using a cleaning solvent.
4. Strip the outer sheath using a cable stripper while ensuring the inner insulation is not damaged.
5. Remove the armor (if applicable) and secure the metal shielding using earthen wire.
6. Strip the conductor insulation according to the jointing kit's specifications. Use mechanical connectors or crimping lugs to join conductors.
7. Apply heat shrink tubing over the joint and use a heat gun to shrink it.
8. If using a resin jointing kit, pour resin into the joint mold and let it cure.
9. Ensure the joint is fully insulated and sealed to prevent moisture ingress.
10. If the cable has more than two joints, the cable to be discarded.

PPE:

Ensure all technicians wear appropriate Personal Protective Equipment (PPE) including safety gloves, eye protection, high-visibility clothing, and insulated footwear.