

VoiceMail User Guide

Log On To the Voice Mail System

To Access Your Voicemail (From your Office Phone)

- Dial your 5 digit voice mail access number
- Enter your PIN (Password) followed by #

To Access Your Voicemail (From Any Other Phone)

- Internally dial your 5 digit voice mail access number
- Externally dial your full 10 digit voice mail access number
- Press the * (star) key
- Enter your ID (your 5 digit Extension) followed by the #
- Enter your PIN (Password) followed by #

Log Off the Voice Mail System

- Hang Up

Change Password

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 2 "Preference"
- Press 1 "PIN" (password)
- Enter your new PIN followed by #
- Enter your new PIN again to confirm then press #
- Your New PIN is active

Recorded Name

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 2 "Preference"
- Press 2 "Recorded Name"
- Your recorded name is. . . will play your recorded name
- To keep the recorded name press *
- To record a new name say Your first and last name at the tone then press #
- Help 0
- Exit *

Directory Listings

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 2 "Preference"
- Press 2 "Recorded Name"
- Will play "You are listed in the Directory"
- Press 3 "Directory Listing"

Personal Greetings

The voice mail system allows you to record up to six (Standard/Closed/Alternate/Busy/Internal/Holiday) personal greetings. You can turn on as many greetings as you want, and you can specify how long you want the greetings to say on.

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 3 for "Greeting"
- System will say your current greeting is a Standard Greeting (if this is what you have turned on)
- System will play your recorded Standard Greeting
- To re-record this greeting Press 1
- To turn on your alternate greeting (Extended Absence Greeting) Press 2
- To edit other greeting Press 3
- To play all your greetings Press 4
- Help 0
- Exit *

To Edit Other Greetings

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 3 for "Greeting"
- Press 3 to Edit other greetings
- To edit Standard Greeting Press 1
- Closed Greeting Press 2
- Alternate Greeting Press 3
- Busy Greeting Press 4
- Internal Greeting Press 5
- Holiday Greeting Press 6
- Help 0
- Exit *

Press 1 - for Standard Greeting - (This is your personal greeting) it plays during regular business hours or in other situations when no other greeting is on.

- After pressing 1 the System will play your Standard Greeting.
- To record this greeting Press 1
- To use the System Greeting Press 2
- Help Press 0
- Exit Press *

Press 2 – for Closed Greeting – Turn on this greeting when you want your callers to hear a recording from you during non business hours. (For example, "Sorry, I am not available to answer your call. Company office hours are <times>"). When it is on, the closed greeting overrides the standard greeting during non business hours.

- After pressing 2 your System will play your Closed Greeting.
- To record/re-record this greeting Press 1
- To use the System Greeting Press 2
- To turn on/off Press 3
 - To set a date and time for the greeting Press 1
 - For later today Press 0
 - For tomorrow Press 1
 - For 2 days from now Press 2
 - And so on
 - To enter month and day Press 9
- To leave on indefinitely Press #
- Help 0
- Exit *

Press 3 – for Alternate Greeting- (Replaces the Extended

Absence Greeting) – turn on this greeting for a specific time period when you want to provide information about special circumstances, such as when you are on vacation. (For example, "I will be out of the office until <date>."). When it is on, the alternate greeting overrides all other greetings.

Note: Caller's can not press "0" when you have this greeting in place. Please indicate in your greeting the alternate number you can be reached at or for callers to call in your absence, if one is necessary.

- After pressing 3 your System will play your Alternate Greeting.
- To record/re-record this greeting Press 1
- To use the System Greeting Press 2
- To turn on/off Press 3
 - To set a date and time for the greeting Press 1
 - For later today Press 0
 - For tomorrow Press 1
 - For 2 day from now Press 2, And so on
 - To enter month and day Press 9

- To leave on indefinitely Press #
- Help 0
- Exit *

Press 4 – for Busy Greeting – turn on this greeting when you want callers to know that you are on the phone. (For example, “I am currently on another line, please leave a message.”) When it is on, the busy greeting overrides the standard, closed, and internal greetings when your phone is busy.

- After pressing 4 the System will play your Busy Greeting.
- To record/re-record this greeting Press 1
- To use the System Greeting Press 2
- To turn on/off Press 3
 - To set a date and time for the greeting Press 1
 - For later today Press 0
 - For tomorrow Press 1
 - For 2 day from now Press 2
 - And so on
 - To enter month and day Press 9
- To leave on indefinitely Press #
- Help 0
- Exit *

Press 5 – for Internal Greeting – turn on this greeting when you want to provide information that coworkers might need to know. (For example, “I will be in conference room B until noon today.”) when it is on. The internal greeting overrides the standard and closed greetings, and plays only to callers within your organization when you do not answer your phone.

- After pressing 5 the System will play your Internal Greeting.
- To record/re-record this greeting Press 1
- To use the System Greeting Press 2
- To turn on/off Press 3
 - To set a date and time for the greeting Press 1
 - For later today Press 0
 - For tomorrow Press 1
 - For 2 day from now Press 2
 - And so on
 - To enter month and day Press 9
- To leave on indefinitely Press #
- Help Press 0
- Exit Press *

Press 6 – for Holiday Greeting – turn on this greeting when you want callers to hear your recording during a holiday. (For example, “Happy Holidays. I am not available to answer your call. I will be out of the office from <date> to <date>.”) When it is on, the holiday greeting overrides the standard greeting during non-business hours.

- After pressing 6 your System will play your Holiday Greeting.
- To record/re-record this greeting Press 1
- To use the System Greeting Press 2
- To turn on/off Press 3
 - To set a date and time for the greeting Press 1
 - For later today Press 0
 - For tomorrow Press 1
 - For 2 day from now Press 2
 - And so on
 - To enter month and a day Press 9
- To leave on indefinitely Press #
- Help 0
- Exit *

Playing Your Messages

Follow Log On Procedure

- Press 1 – to play messages
- Follow voice prompts

While listening to messages, the system will allow you to:

- Press 1 1 - Rewind to the start of the message
- Press 1 - Rewinds the message a few seconds
- Press 2 - Pauses/Restart the message
- Press 3 - Fast Forward message a few seconds
- Press 3 3 - Fast Forward to the end of the message
- Press 4 - Decrease the message's playback speed
- Press 5 – Message Properties Information gives the time and date message was left in mailbox and the caller's telephone number
- Press 6 - Increase the message's playback speed.
- Press 8 - Normal Volume control of message
- Press 9 – To increase the Volume control of message
- Press # - Skips to the next message
- Press 7 - to erase the message from your mailbox OR
- Press 9 - to save the message in your mailbox

Note: If you accidentally delete a message you can retrieve it from your deleted folder within 24 hours. Deleted messages are saved in your deleted folder in your mailbox for a 24 hour period until they are permanently deleted. Deleted messages stored can be permanently deleted by deleting the message a second time.

Deleted messages take up message space in your mailbox until they are permanently deleted in 24 hours or until you delete them from your mailbox prior to the 24 hour period. You can delete your deleted messages by pressing 3 from the main menu for your old messages, then press 2 for deleted messages and follow the prompts to permanently delete them. You should do this if you receive a lot of messages during the day or after hours to avoid getting the message that your mailbox is almost full.

Forward A Message

Follow Log On Procedure

- Press 6 to forward a message
- Record introduction at the tone when you are done press #
- Enter Extension and press #
- Or
- Switch between name or number press # #
- To add a name Press 9 1
- To Forward Press #
- To Mark Urgent Press 1
- For Return Receipt Press 2
- To Mark Private Press 3
- For Future Delivery Press 4
- To Review your recording Press 5
- To Record an introduction Press 6
- To add to message Press 7
- To hear all names and delete names Press 9 2
- To a copy to yourself Press 9 5
- Cancel Press *
- Help 0

Reply To Messages

Follow Log On Procedure

- Press 8 to reply
- Record your reply at the tone
- Press # when finished recording
- Press # to send your reply
- To Mark Urgent Press 1
- For Return Receipt Press 2
- To Mark Private Press 3
- For Future Delivery Press 4
- To Review your recording Press 5
- To re-record the message Press 6
- To add to the message Press 7
- To add a name Press 9 1
- To hear all names and delete names Press 9 2
- To a copy to yourself Press 9 5
- To Cancel Press *
- Help 0

Sending Voice Messages

You can send messages to other voice mail users without dialling their extensions. This can be helpful when you do not want to disturb a user or when you do not have time for a phone conversation. You can address a voice message to one or multiple recipients.

The following special options are available:

Urgent – Mark a message urgent so that the voice mail system sends it before regular message.

Return receipt – Request a return receipt so that the voicemail system notifies you when the recipient opens the message.

Private - Mark a message private so that the recipient knows to treat it confidentially. Voice mail users cannot forward private messages by phone

Future delivery - Deliver the message at the future date or time that you specify.

To send a message

Follow Log on Procedure

- At the Main Menu Press 2 to "Send a Message".
- Follow the prompts to record, address, and send the voice message. To Pause or resume recording, press 8. To end recording, press #.
 - While addressing the message, press ## to switch between spelling and number entry.
 - To address the message to a private list, enter the list number by using number entry.
 - When more than one user matches your addressing entries, the voice mail system plays a list of matches that you can navigate quickly. Press # to select a recipient from a list, press 7 to skip previous name and 9 to skip to the next name; and press 77 to skip to the beginning of list and 99 to skip to the end of a list.
- Then listen to the prompt for type of delivery.

Message Notification

The voice mail system can call a phone or pager number to notify you of new messages. **Note: you must enter a 9 first, then the 10 digit extension when forwarding to an external number, e.g. cellular phone or pager device**

Follow Log On Procedure

- Press 4 "Setup Options"
 - Press 1 for Message Settings
 - Press 1 to change Notification
- Message Notification – System will list what is on or off

- To set/change your Pager Press 1
- To set/change your Home phone Press 2
- To set/change your Work phone Press 3
- To set/change your Mobile phone Press 4
- Help 0
- Exit *
- To set up Settings (Note: Replace the destination in bold)
 - **Pager Settings**
 - To turn on **Pager** notification Press 1
 - To Play setting Press 2
 - To change your phone number Press 3
 - To Exit *

Creating Private List (Group Distribution Lists)

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 1 Message Settings
- Press 4 to Edit Private list

Select one of the options and follow the voice mail prompts

Edit a Private List

- Press 1 – to Create a list
 - The system will play the name on the list
 - To play the names on the list
- Select a Private list number
- To hear Private List Press 1
- To change a name on Private List Press 2

Create a Private List/Add or Delete

- Press 2 – to Create a list
- The System will prompt you:
 - Assign a private list number (1-15)
 - To add a name Press 1
 - To review names/delete names Press 2
 - To re-record name of the list itself Press 3
 - For Help 0
 - To Exit *

Call Transfer

Call Transfer rules controls how the voice mail system handles indirect calls, which are from callers who do not dial you directly (for example, callers who use the directory to reach you).

The three transfer rules are:

Standard Transfer Rule – is active during the business hours. If no other transfer rules are turned on, the standard transfer rule is active for non business hours as well.

Alternate Transfer Rule – is specific time period when you want to override the other transfer rule. For example, you may want to route all your calls immediately to voicemail while you are out of the office on vacation or you may want

to transfer your calls to a different extension if you are temporarily working from another location.

Closed Transfer Rule – to set how indirect calls to you are handled during non business hours. For example, you may want to route all your calls immediately to voicemail during non business hours. When it is turned on, the closed transfer rule is active during non business hours.

Follow Log On Procedure

- Press 4 "Setup Options"
- Press 4 for Call Transfer Setting
- Select the transfer rule whose setting you want to change
 - Standard Transfer Rule Press 1
 - Alternate Transfer Rule Press 2
 - Closed Transfer Rule Press 3

After the voice mail system announces your current transfer settings, follow the prompts to enable or disable the rule, to switch between transferring calls to a phone and to voicemail, or to change your transfer phone number.