

Hidden SU(2) in Spin-1 XY model

Jie Ren

I. ONSITE SU(2)

For spin-1 model, we can define another onsite SU(2) operator:

$$\begin{cases} \tilde{s}^\pm \equiv \frac{1}{2} (S^\pm)^2 \\ \tilde{s}^z \equiv \frac{1}{2} S^z \end{cases}, \quad (1)$$

where S_j^\pm is the regular $S = 1$ spin operator. For spin-1:

$$[\tilde{s}^+, \tilde{s}^-] = 2\tilde{s}^z, \quad (2)$$

$$[\tilde{s}^z, \tilde{s}^\pm] = \pm\tilde{s}^\pm, \quad (3)$$

$$\{\tilde{s}^+, \tilde{s}^-\} = (S^z)^2. \quad (4)$$

The Casimir invariant for this SU(2) is

$$C_2 = \frac{1}{2} (\tilde{s}^+ \tilde{s}^- + \tilde{s}^- \tilde{s}^+) + (\tilde{s}^z)^2 = \frac{3}{4} (S^z)^2. \quad (5)$$

So we have

$$[(S^z)^2, \tilde{s}^\pm] = 0. \quad (6)$$

Note that

$$[\tilde{s}_j^+, S_j^-] = S_j^- (1 - 2(S_j^z)^2), \quad (7)$$

$$[\tilde{s}_j^-, S_j^+] = S_j^+ (1 - 2(S_j^z)^2), \quad (8)$$

$$\{\tilde{s}_j^+, S_j^-\} = S_j^-, \quad (9)$$

$$\{\tilde{s}_j^-, S_j^+\} = S_j^+. \quad (10)$$

II. CHAIN OPERATOR

Define a chain operator

$$U_j = \prod_{l=1}^{j-1} (1 - 2(S_l^z)^2). \quad (11)$$

Note that

$$S_j^\pm U_k = \begin{cases} -U_k S_j^\pm & j < k \\ U_k S_j^\pm & j \geq k \end{cases}. \quad (12)$$

We introduce new operators

$$s_j^\pm = \tilde{s}_j^\pm U_j, \quad s_j = \tilde{s}_j. \quad (13)$$

Since $[U_j, s_k^\pm] = 0$, $\{s_j^z, s_j^\pm\}$ still satisfies su(2) algebra, and we can further define a global operator:

$$s_T^\pm = \sum_{j=1}^L s_j^\pm, \quad s_T^z = \sum_{j=1}^L s_j^z, \quad (14)$$

which also satisfies su(2) algebra.

III. COMMUTATION RELATION

The Hamiltonian for spin-1 XY model (with open boundary) is:

$$H_{XY} = \frac{1}{2} \sum_{j=1}^{L-1} (S_j^+ S_j^- + S_j^- S_j^+). \quad (15)$$

We first note that for $k \neq j, j+1$:

$$[s_k^+, S_j^+ S_{j+1}^- + S_j^- S_{j+1}^+] = 0. \quad (16)$$

While for $k = j$:

$$[s_j^+, S_j^+ S_{j+1}^- + S_j^- S_{j+1}^+] = S_{j+1}^+ [s_j^+, S_j^-] U_j \quad (17)$$

$$= S_j^+ S_{j+1}^+ U_{j+1}, \quad (18)$$

and for $k = j+1$:

$$[s_{j+1}^+, S_j^+ S_{j+1}^- + S_j^- S_{j+1}^+] = -S_j^+ \{s_{j+1}^+, S_{j+1}^-\} U_{j+1} \quad (19)$$

$$= -S_j^+ S_{j+1}^+ U_{j+1}. \quad (20)$$

In this way

$$[s_T^+, H_{XY}] = 0. \quad (21)$$

Similarly, we can show

$$[s_T^-, H_{XY}] = 0. \quad (22)$$