# Alesis Fusion OS Upgrade

## You assume all responibilty for performing this process.

For best results format your CF card using the Fusion. Most CF cards between 256 Mb & 4Gb will work with the Fusion. 256 Mb is fine for OS upgrades, 2 to 4 GB Gb is reccomended if you plan on using it to transfer or work with sound banks and/or songs on the Fusion.

Download the Fusion OS version 1.24 from the Alesis website to your computer.

Link for **Official Alesis Fusion dowloads as of 2-25-2013** http://www.alesis.com/fusion8hd

Unzip the OS image file on your computer and copy it to your CF card that you previously formatted using the Fusion.

With the Fusion turned off.

Insert the CF card containing the unzipped OS file **Fusion_Image_v124.bin** (about 62.5 mb in size) into the Fusion CF card slot.

Press and hold down the **B** & **7** keys while you power up the Fusion.

When you are asked if you want to proceed with the upgrade select **YES**

When the OS upgrade is complete, remove the CF card.

Press **GLOBAL,** select **ITEM, MARK** all items, select **PROCESS,** select **VERIFY.**

When verification is complete turn the Fusion off, wait a couple minutes then turn it on.

You should be good to go.

Note: If your computer does not have a CF card reader you can copy the unzipped OS image file on your computer to your CF card by installing the CF card in the Fusions CF card reader, with the Fusion turned on connect the Fusion to your computer using the USB cable and copy the file to Fusions CF card.

Once the file is copied to the CF card in the Fusion turn the Fusion off and proceed with the OS upgrade procedure highlighted above.