

5:DMX CHANNELS

13 DMX Channels

Channels	Numerical value	explanation
1	0-255	Y1 motor running
2	0-255	Y2 motor running
3	0-255	motor speed
4	0-255	total dimming
5	0-255	Red LED1-8 total dimming
6	0-255	Green LED1-8 total dimming
7	0-255	Blue LED1-8 total dimming
8	0-255	White LED1-8 total dimming
9	0	no strobe
	1-250	strobe
	251-255	no strobe
10	0	Dimming channel function
	1-7	Gradient effect
	8-140	Auto effect
	141-255	Soun Auto effect
11	0-15	other channels
	15-128	Auto effect
	129-255	Soun effect
12	0-255	Control the speed and sensitivity of the 6 7
13	250-255	Reset (stop for 3 seconds)

43 DMX Channels

Channels	Numerical value	explanation
1	0-255	Y1 motor running
2	0-255	Y1 Motor fine-tuning
3	0-255	Y2 motor running
4	0-255	Y2 Motor fine-tuning
5	0-255	motor speed
6	0-255	total dimming
7	0-255	Red 1 total dimming
8	0-255	Green 1 total dimming
9	0-255	Blue 1 total dimming
10	0-255	White 1 total dimming
11	0-255	Red 2 total dimming
12	0-255	Green 2 total dimming
13	0-255	Blue 2 total dimming

14	0-255	White 2 total dimming
15	0-255	Red 3 total dimming
16	0-255	Green 3 total dimming
17	0-255	Blue 3 total dimming
18	0-255	White 3 total dimming
19	0-255	Red 4 total dimming
20	0-255	Green 4 total dimming
21	0-255	Blue 4 total dimming
22	0-255	White 4 total dimming
23	0-255	Red 5 total dimming
24	0-255	Green 5 total dimming
25	0-255	Blue 5 total dimming
26	0-255	White 5 total dimming
27	0-255	Red 6 total dimming
28	0-255	Green 6 total dimming
29	0-255	Blue 6 total dimming
30	0-255	White 6 total dimming
31	0-255	Red 7 total dimming
32	0-255	Green 7 total dimming
33	0-255	Blue 7 total dimming
34	0-255	White 7 total dimming
35	0-255	Red 8 total dimming
36	0-255	Green 8 total dimming
37	0-255	Blue 8 total dimming
38	0-255	White 8 total dimming
39	0	no strobe
	1-250	strobe
	251-255	no strobe
40	0	Dimming channel function
	1-7	Gradient effect
	8-140	Auto effect
	141-255	Soun Auto effect
41	0-15	other channels
	15-128	Auto effect
	129-255	Soun effect
42	0-255	Control the speed and sensitivity of the 6 7
43	250-255	Reset (stop for 3 seconds)

This product can get the best results with Smoke Machine!