APC mini mk2 mapping

leddeck · port `APC mini mk2 Control` · channel 1 · mapping `apcmini-mk2.json`

	DECK A				DECK B				MASTER
EFFECTS	56 Rainbow	57 Blob	58 Starfield	59 Lightning	60 Rainbow	61 Blob	62 Starfield	63 Lightning	112 Tap tempo
	48 Electric	49 Solid	50 Shape	51 Line	52 Electric	53 Solid	54 Shape	55 Line	113 Crossfade auto
	40 Neon	41 Black	42 Rain	43 Pulse	44 Neon	45 Black	46 Rain	47 Pulse	114 Auto — 8 pulsations
PALETTES	32 Rainbow	33 Neon	34 Club	35 Fire	36 Rainbow	37 Neon	38 Club	39 Fire	115 Auto — 16 pulsations
	24 Ember	25 Ocean	26 Ice	27 Sunset	28 Ember	29 Ocean	30 Ice	31 Sunset	116 Auto — 32 pulsations
	16 Mint	17 Purple	18 White	19 Red	20 Mint	21 Purple	22 White	23 Red	117 Son réactif · bascule on/off
COLOURS	8 Red	9 Orange	10 Yellow	11 Green	12 Red	13 Orange	14 Yellow	15 Green	118 *libre*
	0 Cyan	1 Blue	2 Pink	3 White	4 Cyan	5 Blue	6 Pink	7 White	119 *libre*
	100 Électrique · tant qu'on appuie	101 Électrique · bascule on/off	102 Strobe · tant qu'on appuie	103 Strobe · bascule on/off	104 Flash · tant qu'on appuie	105 Flash · bascule on/off	106 Blackout · tant qu'on appuie	107 Blackout · bascule on/off	122 Shift
	CC 48 Deck A — réglage 1	CC 49 Deck A — réglage 2	CC 50 Deck A — réglage 3	CC 51 Luminosité master	CC 52 Deck B — réglage 1	CC 53 Deck B — réglage 2	CC 54 Deck B — réglage 3	CC 55 Vitesse globale	CC 56 Crossfader

THREE ZONES IN THE GRID

Rows 1 to 3 : effects. Rows 4 to 6 : palettes.
Rows 7 and 8 : eight solid colours, which stand in for the custom palette — one press puts the deck on that colour.

READING THE NUMBERS

Pads carry their note number, faders their CC number. On the grid : `note = row from the bottom × 8 + column`, and the bottom-left pad is `0`.

Measured on the hardware, not taken from the documentation.

COLOURS

- Effects
- Palettes
- Live and master functions

The bottom pads carry their real colour. Deck A left of the split, deck B right.

Effects light **dim white** at rest and **blinking white** while they play. Palettes take the deck colour, live functions their own colour, and the two bottom rows their own hue.

TWO WAYS TO PRESS

While held : the effect lasts as long as the press and stops on release. That is the strobe or kill gesture.

On/off latch : one press engages, another releases. Blackout exists in both forms — pick the gesture you want.

FADERS : SOFT TAKEOVER

A fader only takes over once it is back on the current value, and re-arms as soon as the value changes elsewhere (mouse, auto-mix).

Brushing a fader therefore never makes a setting jump.

KEYBOARD

- `S` strobe · `E` electric
- `space` flash · `B` blackout
- `Shift` + the same key : latch instead of hold

Generated by `leddeck midi sheet` from the mapping — slots with no effect and no palette are free and assignable.