

XSCT Commands 1

2019.03.05 | Erwin Ouyang

In Vivado 2016.4, the Xilinx Microprocessor Debugger (XMD) tool is deprecated, and it is removed in newer version of Vivado. The XMD is replaced by Xilinx Software Command-Line Tool (XSCT) [1]. The step-by-step for downloading the bitstream into the FPGA, and then debugging the processor using XSCT are described as follows:

1. Type `xsct` (instead of `xmd`) in the command line.
2. Connect to the Zynq using this command:
`connect`
3. Download the bitstream using this command:
`fpga -f design_1_wrapper_hw_platform_0/design_1_wrapper.bit`
4. Show the targets using this command:
`targets`
5. Connect to the processor core 0 using this command:
`targets 2`
6. Write data to the register using this command:
`mwr -force 0x41200000 0x8`
7. Read data from the register using this command:
`mwr -force 0x41210000`

Reference

[1] Xilinx Software Command-Line Tool (XSCT) Reference Guide, [ug1208-xsct-reference-guide.pdf](#)