

XSCT Commands 2

2019.03.08 | Erwin Ouyang

In Vivado 2016.4, the Xilinx Microprocessor Debugger (XMD) tool is deprecated, and it is removed in newer version of Vivado. The XMD is replaced by Xilinx Software Command-Line Tool (XSCT) [1]. The step-by-step for downloading the bitstream into the FPGA, and then downloading the elf file to the processor using XSCT are described as follows:

1. Type `xsct` (instead of `xmd`) in the command line.
2. Connect to the Zynq using this command:
`connect`
3. Download the bitstream using this command:
`fpga -f design_1_wrapper_hw_platform_0/design_1_wrapper.bit`
4. Show the targets using this command:
`targets`
5. Connect to the processor core 0 using this command:
`targets 2`
6. Download the elf file to the processor:
`dow axi_gpio/Debug/axi_gpio.elf`
7. Run the program:
`con`
8. Stop the program (before download a new elf file):
`stop`

Reference

[1] Xilinx Software Command-Line Tool (XSCT) Reference Guide, [ug1208-xsct-reference-guide.pdf](#)