















## The procedure for backup recovery seed

Seed store V07 Self test	⇐	Self test is running
↓		
Seed store V07 ALFA	⇐	Selected seed name, press ➡ button
↓		
Select seed name ALFA #1ab7	⇐	Selected seed name (Alfa for example), press 🔑 and ➡ button
↓		
Show BIP39 seed? Select=No Up=Yes	⇐	Press ➡ button (No)
↓		
Forgotten PIN? Select=No Up=Yes	⇐	Press ➡ button (No)
↓		
Setup? Select=No Up=Yes	⇐	Press 🔑 button (Yes)
↓		
Setup mode		
↓		
PIN for ALFA ***_	⇐	Default PIN is "123" Press 🔑 for enter PIN and ➡ button
↓		
PIN for ALFA is OK		
↓		
Change PIN? Select=No Up=Yes	⇐	Press 🔑 button (Yes)
↓		
PIN for ALFA ***_	⇐	Enter and remember your PIN Press 🔑 for enter PIN and ➡ button
↓		

Save?		
Select=No Up=Yes	⇐	Press  button (Yes)
↓		
Save?		
Saved		
↓		
Change name?		
Select=No Up=Yes	⇐	Press  button (Yes)
↓		
Setting		Rename the seed by the name of the wallet
Name 1: ALFA_	⇐	Press   for enter PIN and  button
↓		
Save?		
Select=No Up=Yes	⇐	Press  button (Yes)
↓		
Save?		
Saved		
↓		
Change words?		
Select=No Up=Yes	⇐	Press  button (Yes)
↓		
Words for ALFA	⇐	Your seed name
#1 ?	⇐	Press  button
↓		
Setting		Enter secret word (DIAMOND for example)
Word 1: ?_		Press   for enter PIN and  button
↓		
Words for ALFA	⇐	Your seed name
#1 DIAMOND	⇐	Press  button for next word
↓		
...		After saving all words, press  button
↓		
Save words?		
Select=No Up=Yes	⇐	Press  button (Yes)



Save words?  
Saved



Seed store    V07  
ALFA



Your seed name