



2-125

IERS

-125 is an ultra-compact 2-channel DSP amplifier delivering 125W per channel (250W in bridged Power Sharing Mode). Featuring analog and digital inputs for local zone audio, flexible mounting with a T-slot chassis, and easy setup via the SonARC for UA Series Amplifiers app, it's designed for performance and style in any space.

KEY FEATURES

- 2 Channel - 125wpc 8Ω|4Ω - Power Share in 4Ω to 250w
- Analog (RCA) and Digital (optical/coax) Inputs
- Analog (RCA) outputs with volume tracking
- Fully capable DSP
- Bluetooth-enabled app for setup
- Integrated Heatsink/Chassis with industry standard T-Slot Mounting
- Audio Sense and IR Control (with learning capability)
- Ultra-compact (5.25" x 1.875" x 7.825") designed for install in structured wiring can, TV back box, or outdoor enclosure

SPECIFICATIONS

SKU | Color

93550 (US), 93551 (INT)

Dimensions No Feet (WxHxD)

5.35" x 1.77" x 8.19" (135.89mm x 44.96mm x 208.03mm)

Mounting Bracket



2 x Surface Mounting Brackets (included), 20mm Series Industry Standard T-slots, Built into Chassis Design, Seismic Tether Mounting Hole

Inputs

Analog RCA, COAX S/PDIF Format, 2ch PCM, Optical TOSLINK S/PDIF Format, 2ch PCM

COPY ALL SPECS

DIMENSIONAL DRAWINGS



RELATED PRODUCTS



UA SERIES ACCESSORY KIT

SKU: 93759

MORE

DOWNLOADS

[SALES & DATA SHEETS](#)

[INSTRUCTIONS](#)

[UA2-125_UA2-125ARC SONANCE_Sell_Sheet.pdf](#)

DRAWINGS & IMAGES

[93550_UA_2-125_Front_CAD.pdf](#)

[93550_UA_2-125_Back_CAD.pdf](#)

[DOWNLOAD ALL](#)

[SHARE ALL](#)

LEARN MORE

NAME

MESSAGE

EMAIL

STATE /
PROVINCE

/

COUNTRY

[SUBMIT](#)

SIGN UP FOR EMAIL

EMAIL

[Subscribe](#)

CONTACT US

CAREERS

VIDEO RESOURCES

SPOTLIGHTS

SONANCE STUDIO360

SONANCE TECHNICAL RESOURCES

JAMES TECHNICAL RESOURCES

YOUR PRIVACY CHOICES