

RaspberryPi GPIO

- Black - Pin 1
- White - Pin 5
- Grey - Pin 7
- Purple - Pin 8

GPIO#	NAME		NAME	GPIO#
	3.3 VDC Power	1	5.0 VDC Power	
8	GPIO 8 SDA1 (I2C)	3	5.0 VDC Power	
9	GPIO 9 SCL1 (I2C)	5	Ground	
7	GPIO 7 GPClk0	7	GPIO 15 TXD (UART)	15
	Ground	9	GPIO 16 RXD (UART)	16
0	GPIO 0	11	GPIO 1 PCM_CLK/PWM0	1
2	GPIO 2	13	Ground	
3	GPIO 3	15	GPIO 4	4
	3.3 VDC Power	17	GPIO 5	5
12	GPIO 12 MOSI (SPI)	19	Ground	
13	GPIO 13 MISO (SPI)	21	GPIO 6	6
14	GPIO 14 SCLK (SPI)	23	GPIO 10 CE0 (SPI)	10
	Ground	25	GPIO 11 CE1 (SPI)	11
30	SDA0 (I2C ID EEPROM)	27	SCL0 (I2C ID EEPROM)	31
21	GPIO 21 GPCLK1	29	Ground	
22	GPIO 22 GPCLK2	31	GPIO 26 PWM0	26
23	GPIO 23 PWM1	33	Ground	
24	GPIO 24 PCM_FS/PWM1	35	GPIO 27	27
25	GPIO 25	37	GPIO 28 PCM_DIN	28
	Ground	39	GPIO 29 PCM_DOUT	29

Attention! The GPIO pin numbering used in this diagram is intended for use with WiringPi / Pi4J. This pin numbering is not the raw Broadcom GPIO pin numbers.

<http://www.pi4j.com>

