

Raspberry Pi 2 Model B (J8 Header)									
GPIO#	NAME		NAME	GPIO#					
	3.3 VDC Power	1	5.0 VDC Power						
8	GPIO 8 SDA1 (I2C)	3	5.0 VDC Power	4					
9	GPIO 9 SCL1 (I2C)	5	Ground						
7	GPIO 7 GPCLK0	7	GPIO 15 Tx0 (UART)	15					
	Ground	9	GPIO 16 Rx0 (UART)	16					
0	GPIO 0	11	GPIO 1 PCM_CLK/PWM0	1					
2	GPIO 2	13	Ground						
3	GPIO 3	15	GPIO 4	4					
	3.3 VDC Power	17	GPIO 5	5					
12	GPIO 12 MOSI (SPI)	19	Ground						
13	GPIO 13 MISO (SPI)	21	GPIO 6	6					
14	GPIO 14 SCLK (SPI)	23	GPIO 10 CE0 (SPI)	10					
	Ground	25	GPIO 11 CE1 (SPI)	11					
30	SDA0 (I2C ID EEPROM)	27	SCL0 (I2C ID EEPROM)	31					
21	GPIO 21 GPCLK1	29	Ground						
22	GPIO 22 GPCLK2	31	GPIO 26 PWM0	26					
23	GPIO 23 PWM1	33	Ground						
24	GPIO 24 PCM_FS/PWM1	35	GPIO 27	27					
25	GPIO 25	37	GPIO 28 PCM_DIN	28					
	Ground	39	GPIO 29 PCM_DOUT	29					

Attention! The GPIO pin numbering used in this diagram is intended for use with WiringPi / Pi4J. This pin numbering is not the raw Broadcom GPIO pin numbers.

<http://www.pi4j.com>

