

Radiotelephone (RATEL) Procedure

for Operators

in

WICEN

CONTENTS

CHAPTER 1. INTRODUCTION

	Paragraph
Aim	101
Phonetic Alphabet	102
Numerals	103
Mixed Groups	106
Punctuation	107

CHAPTER 2. RADIO NETS AND CALLS

Calling and Answering	201
Signal Strength and Readability	203
Abbreviated Procedure	206
Full Procedure	208
Arranging a Radiotelephone Conversation	209
Transmission of Messages	210
Long Message Procedure	212
Corrections during Transmission	214
Repetitions	217
Speed of Transmissions	218
Verifications	219
Acknowledgement of Messages	220
Cancelling Transmissions and Messages	221
Relay Procedure	223
Read Back Procedure	225
Words Twice	227
Change Frequency	228
Joining a Working Net	229
Location Reports	230
Unknown Station	232
Grid References	233
Times	234

CHAPTER 3. MESSAGE HANDLING SEQUENCE

Section

1.	Introduction	301
	Types of Messages	302

	Paragraph
2.	Use of Standard Message Forms
	Introduction 303
	Top Shaded Section 304
	Security Classification 305
	Precedence – Action 306
	Precedence – Info 307
	Date – Time Group 308
	Message Instructions 309
	Sig/Originator's 310
	From/To 311
	For Operator's Use 312
3.	Message Handling Sequence
	Introduction 313
	Messages Received for Transmission 314
	Message Serial Numbers 316
	Prowords 318
	Initial Call 319
	Transmission Sequence 320
	Sending a Long Message 323
	Messages Sent and Received 324

Annexes

- A. Sample Message Form
- B. Sample Log Sheet
- C. Prowords

CHAPTER 1.

INTRODUCTION

Aim

101. The aim of this pamphlet is to standardise the radiotelephone (RATEL) procedure for operators in WICEN in a form which provides maximum compatibility with Emergency Services.

Phonetic Alphabet

102. The standard phonetic alphabet is to be used. Difficult words or groups within the text of messages may be spelled using the phonetic alphabet and preceded by the proword I SPELL. If the operator can pronounce the word to be spelled, he will do so before and after the spelling to identify the word.

Example A: (A pronounceable word)
"Catenary - I SPELL Charlie Alpha etc. - Catenary"

Example B: (An unpronounceable abbreviation)
"Move to WA State HQ" is transmitted as:
"Move to - I SPELL - Whiskey Alpha - State - I SPELL - Hotel Quebec"

Numerals

103. To distinguish numerals from words similarly pronounced the proword FIGURES may be used before such numbers. Numbers will be transmitted digit by digit except that exact multiples of hundreds and thousands may be spoken as such.

Number	Spoken as	Number	Spoken as
44	Fo-wer Fo-wer	1478	Wun Fo-wer Seven Ate
90	Niner Zero	7000	Seven Thousand
136	Wun Thuh-ree Six	16000	Wun Six Thousand
500	Fi-yiv Hundred		

104. The figure Zero is written as Ø.

105. The decimal point is spoken as DAY-SEE-MAL.

Mixed Groups

106. When giving a mixed group of letters and figures the prowords FIGURES and I SPELL are used as in the example:

31AB7 is sent as:
FIGURES - Three One - I SPELL - Alpha Bravo - FIGURES - Seven.

Punctuation

107. Punctuation is sent as:

Symbol	Spoken as
Comma	COMMA
Full Stop	FULL STOP
Brackets	OPEN BRACKETS/CLOSE BRACKETS
Oblique stroke	SLANT
Hyphen	HYPHEN

CHAPTER 2

RADIO NETS AND CALLS

Calling and Answering

201. A call consists of the following parts:
Callsign - THIS IS - Callsign - Text - OVER.

Example A: VK6XX - THIS IS - VK6YY - Move now - OUT.
Note. An answer is not required.

Example B: VK6XX - THIS IS - VK6YY - Are you ready to move - OVER.
Note. An answer is required.

202. An answer consists of the following parts:
Callsign - THIS IS - Callsign - Text - Ending Sign.

Note: An ending sign may be:

- | | | |
|----|--------------|---|
| a. | OVER or OUT. | (But not together. They are contradictory) |
| b. | WAIT | I must pause for up to 5 seconds. No other station may transmit. |
| c. | WAIT OUT | I must pause for more than 5 seconds. Another station may transmit. |

Example:
VK6XX - THIS IS VK6YY - Are you ready to move - OVER.
VK6XX - WAIT - (pause of 5 secs max.) ROGER - OUT.

Signal Strength and Readability

203. A station is understood to have good signal strength and readability unless otherwise advised. A station that wishes to inform another of his signal strength is to do so by means of a short and concise report such as "weak but readable". The following prowords are for use when initiating and answering queries concerning signal strength and readability:

- | | |
|----------------------|-------------------------|
| a. ROGER | means loud and clear |
| b. READABLE | means satisfactory |
| c. WEAK | means with difficulty |
| d. WITH INTERFERENCE | means with interference |
| e. UNREADABLE | means unreadable |

204. Any combination of the above may be used.

205. A station requiring to know his signal strength will use the proword RADIO CHECK.

VK6XX - THIS IS - VK6YY - RADIO CHECK - OVER.

VK6XX - WEAK BUT READABLE - OVER.

(VK6YY) - You are READABLE - OUT.

Abbreviated Procedure

206. Under normal working conditions, use is made of abbreviated procedure to save time by omitting the callsign of the called station other than in the initial call, and any non-essential proword. In a single call, all callsigns may be omitted after the initial call and reply.

207. Those parts of a call or prowords which may be omitted are shown in brackets through the remainder of this pamphlet. The following example illustrates abbreviated procedure:

VK6AA - THIS IS - VK6BB - Move now - OVER.

VK6AA - I cannot move at this stage - OVER.

(VK6AA) - When can you move - OVER.

(VK6BB) - In ten minutes - OVER.

(VK6AA) - ROGER - OUT.

Full Procedure

208. When conditions deteriorate to such a degree that the use of abbreviated procedure is causing unnecessary repetitions, stations are to use full procedure. The use of callsigns and prowords that were previously optional, then become mandatory.

VK6AA - THIS IS VK6BB - Move now - OVER.

THIS IS - VK6AA - I cannot move at this stage - OVER.

THIS IS - VK6BB - When can you move - OVER.

THIS IS - VK6AA - In FIGURES one zero minutes - OVER.

THIS IS - VK6BB - ROGER - OUT.

Arranging a Radiotelephone Conversation

209. A person may speak to a specific individual at another station by calling the person concerned to the set. The operator can arrange this by asking for the name or title of the person.

Someone says to you, "I want to speak to the ambulance"

You say:

VK6XX - THIS IS - VK6YY - FETCH Ambulance Officer - OVER.

Assuming he is not at the set, the operator would say:

VK6XX - WAIT - OUT.

When he is available the operator would say:

VK6YY - THIS IS - VK6XX - Ambulance Officer SPEAKING - OVER.

Transmission of Messages

210. An offer is a preliminary call made to warn a station that a message follows. Messages are offered when:

- a. It is necessary to be written down,
- b. In difficult conditions it is necessary for the sender to satisfy himself that comms are sufficiently good for the message to be received.
- c. When a net is directed.

211. Messages may be offered by means of:

- a. The abbreviated offer which uses no proword,
- b. The proword MESSAGE or LONG MESSAGE.

a. Abbreviated Offer.

VK6AA - THIS IS - VK6BB - OVER.

VK6AA - OVER.

(THIS IS) - (VK6BB) - The aircraft has departed - OVER.

(THIS IS) - (VK6AA) - ROGER - OUT.

b. Use of proword.

VK6AA - THIS IS - VK6BB - MESSAGE - OVER.

(THIS IS) - VK6AA - SEND - OVER.

(THIS IS) - (VK6BB) - Move to etc. - OVER.

(THIS IS) - (VK6AA) - ROGER - OUT.

The use of the proword simply means the message is to be written down.

Long Message Procedure

212. If a message will take more than half a minute to send, the following procedure is to be used.

- a. Use the proword LONG MESSAGE.

- b. The message is to be sent in sections each lasting 30 seconds and terminating in the use of the proword MORE TO FOLLOW.
- c. Receiving stations are to acknowledge each section and if necessary request repeats.
- d. After receiving a receipt, the sender is to pause for several seconds to allow any other station to transmit urgent traffic.
- e. If there is no interruption the next section is sent by using the proword ALL AFTER followed by the last word or phrase of the section previously transmitted.
- f. The procedure is used until the complete message is sent.

213. More details on message handling procedure can be found in Chapter 3.

Corrections During Transmission

214. When an error is made by the transmitting operator, the proword CORRECTION is to be transmitted followed by the last word or group correctly transmitted; transmission then continues:

VK6AA - THIS IS - VK6BB - Convoy will arrive - CORRECTION - will depart at noon - OVER.

(THIS IS) - VK6AA - ROGER - OUT.

215. When an error in transmission is made and is not discovered immediately, but is discovered before the ending sign is transmitted, a correction is to be transmitted before the ending sign. When making a correction, the word or group to be corrected is to be properly identified as follows:

VK6AA - THIS IS - VK6BB - Move to Brown street - CORRECTION - WORD BEFORE street - Blue - OVER.

(THIS IS) - VK6AA - (ROGER) - OUT.

216. If a station has sent a message and later realises that a mistake has been made, a further message identifying the message and the portion to be corrected is transmitted as shown below:

VK6AA - THIS IS - VK6BB - Reference move - CORRECTION - Blue avenue - OVER.

(THIS IS) - VK6AA - (ROGER) - OUT.

Repetitions

217. When words are missed or are in doubt, repetitions are to be requested and given before receipt of the message. The proword SAY AGAIN used alone or in conjunction with ALL AFTER, ALL BEFORE, FROM...TO..., WORD AFTER, WORD BEFORE or other suitable word (e.g. CALLSIGN, TIME, GRID) is to be used for this purpose. In complying with requests for repetitions, the transmitting station is to identify that portion which is being repeated. It is normal

with short messages to use the proword SAY AGAIN rather than ask for one or two words to be repeated.

VK6AA - THIS IS - VK6BB - we require a re-supply of batteries at headquarters before tomorrow morning- OVER

(THIS IS) - VK6AA - SAY AGAIN ALL AFTER headquarters - OVER.

(THIS IS) - (VK6BB) - I SAY AGAIN ALL AFTER headquarters before tomorrow morning - OVER.

(VK6AA) - ROGER - OUT.

Speed of Transmission

218. If a receiving station has difficulty in recording a written message because the operator is speaking too rapidly, the receiving operator may request a reduction in the speed of the transmission by the use of the proword SPEAK SLOWER.

Verifications

219. When verification of all or part of a message has been requested, the originating station is to verify the accuracy with the originator and send the correct version. An example of verification is as follows:

VK6AA - THIS IS - VK6BB - reference your locstat - VERIFY - OVER.

VK6AA - WAIT - OUT.

The operator checks and establishes that the grid reference previously sent was incorrect, then transmits:

VK6BB - THIS IS - VK6AA - reference my locstat CORRECTION GRID 147857 - OVER.

VK6BB - ROGER - OUT.

Acknowledgement of Messages

220. An acknowledgement is a message from the addressee informing the originator that the message has been received. An acknowledgement should not be confused with a reply or receipt. A prompt reply referring to the message may serve instead of an acknowledgement. It is the prerogative of the originator to request an ACKNOWLEDGEMENT to a message. This request is usually included in the text of that message.

VK6AA - THIS IS - VK6BB - search area to the South - ACKNOWLEDGE - OVER.

VK6AA - WAIT - OUT.

The operator shows the message to the addressee who authorises him to acknowledge.

VK6BB - THIS IS - VK6AA - Reference your last - OUT.

Cancelling Transmissions and Messages

221. During the transmission of a message and prior to the transmission of the proword OVER or OUT, the transmission may be cancelled by the use of the prowords DISREGARD THIS TRANSMISSION - OUT.

VK6AA - THIS IS - VK6BB - MESSAGE - OVER

VK6AA - SEND - OVER

(VK6BB) - When the move to the new location is complete you are - DISREGARD THIS TRANSMISSION - OUT.

222. A message which has been completely transmitted may only be cancelled by another message.

VK6BB - THIS IS - VK6AA - CANCEL my movement instructions - OVER

VK6BB - ROGER - OUT

Relay Procedure

223. If communications between any two stations fail messages may be sent through a third station that is in contact with both of them. Prowords are RELAY THROUGH, RELAY TO, RELAY FROM, THROUGH ME.

VK6AA - THIS IS - VK6BB - move now - OVER
Communications cannot be established but VK6XX can communicate with both stations...

VK6XX - THIS IS VK6BB - RELAY TO VK6AA - move now - OVER

VK6XX - WAIT OUT TO YOU - VK6AA - THIS IS - VK6XX - FROM VK6BB -
move now - OVER

VK6AA - ROGER - OUT

VK6XX then goes back to VK6BB to inform him that the message has been passed.

VK6BB THIS IS - VK6XX - FROM VK6AA - ROGER - OVER

VK6BB - ROGER - OUT

224. The following example is of a station offering to relay by using the proword THROUGH ME

VK6AA - THIS IS - VK6BB - MESSAGE - OVER
No contact is made but VK6XX knows he is in contact with VK6AA so he offers to relay the message...

VK6BB - THIS IS - VK6XX - THROUGH ME - OVER

VK6BB - RELAY TO - VK6AA - move now - OVER

VK6XX - WAIT - OUT TO YOU - VK6AA - THIS IS - VK6XX - FROM - VK6BB -
move now - OVER

VK6AA - ROGER - OUT
VK6XX then goes back to VK6BB to tell him the message has been received.

VK6BB - THIS IS - VK6XX - FROM VK6AA - ROGER - OVER

VK6BB - ROGER - OUT

Read Back

225. Read Back procedure is used when a sender wishes to ensure that his message has been received correctly. This is necessary when the text is very complicated, when accuracy is very important or when conditions are poor.

226. If it is desired that a message be read back, the proword READ BACK is sent immediately following the call.

VK6AA - THIS IS - VK6BB - MESSAGE - OVER

VK6AA - SEND - OVER

(VK6BB) - READ BACK - move to GRID 123456 - OVER

(VK6AA) - I READ BACK - move to GRID 123456 - OVER

(VK6BB) - CORRECT - OUT

Words Twice

227. When conditions are poor, callsigns, words and phrases should be transmitted twice. This is indicated by the use of the prowords WORDS TWICE.

VK6AA - THIS IS - VK6BB - do you have any apples - OVER
Conditions are very poor.

VK6BB - THIS IS - VK6AA - SAY AGAIN - WORDS TWICE - OVER

VK6AA - VK6AA - THIS IS - VK6BB - THIS IS - VK6BB - do you have - do you have -
any apples - any apples - OVER - OVER

(VK6AA) - ROGER - OUT

Changing Frequency

228. Frequency changes may be ordered because of deteriorating conditions (atmospherics, interference) or to keep a call channel free (moving to a working frequency). The following procedure is to be used. Note that the change does not occur until the NCS gives the executive command.

VK6AA - THIS IS VK6BB - change to 7075 MHz - OVER

VK6AA - change to 7075 MHz - OVER

(VK6BB) - change now - OUT

It is very important that stations do not change on the preparatory command but wait for the executive.

Joining a Working Net

231. When joining a working net, the prowords REPORTING INTO NET are used.

VK6BB - THIS IS - VK6AA - REPORTING INTO NET - OVER

VK6BB - ROGER - OUT

Location Reports

230. It is often necessary to ascertain the position of a particular station. The proword LOCSTAT is used.

VK6AA - THIS IS - VK6BB - SEND LOCSTAT - OVER

VK6AA - LOCSTAT - turn off to Canning Dam - OVER

(VK6BB) - ROGER - OUT

231. A station may wish to report his position without being asked.

VK6BB - THIS IS - VK6AA - LOCSTAT - turn off to Canning Dam - OVER

VK6BB - ROGER - OUT

Unknown Station

232. Sometimes due to interference the callsign of the station calling is lost. The called station uses the prowords UNKNOWN STATION to reply.

VK6AA - THIS IS - crackle - OVER

UNKNOWN STATION - THIS IS - VK6AA - SAY AGAIN CALLSIGN - OVER

VK6AA - THIS IS - VK6BB - OVER

VK6AA - ROGER - OUT

Grid References

233. When transmitting a grid reference the proword GRID is used.

VK6AA - THIS IS - VK6BB - SEND LOCSTAT - OVER

VK6AA - LOCSTAT - GRID 123456 - OVER

(VK6BB) - ROGER - OUT

Times

234. Times are sent using the proword TIME.

VK6AA - THIS IS - VK6BB - I will be returning at TIME one four hundred hours - OVER

VK6AA - ROGER - OUT

CHAPTER 3

SECTION 1

Introduction

301. The aim of this chapter is to present all the information necessary for you to send and receive formal messages.

Types of Messages

302. There are three types of messages:

- a. Conversations.
These are a series of alternate voice transmissions between two users in which subjects may be discussed, questions answered and information exchanged.
- b. Informal messages.
A user may frequently wish to ask a question and send information without discussion. He can do this by giving his message verbally to the operator or by writing it down for transmission. An informal message consists simply of the user's text with an indication of the addressee.
- c. Formal messages.
A formal message is one which is written down on a message form, signed by a releasing officer, registered and passed to the operator for transmission and filing.

SECTION 2

USE OF STANDARD MESSAGE FORM

Introduction

303. The message form shown in Annex A to Section 3 is the form used by Emergency services and by WICEN. The following information will enable you to check/complete a message ready for transmission.

Top shaded section

304. This area is normally used by teletype operators in the armed services. We use it to write the message serial number in or out. e.g. 05/24

Security Classification

305. Not usually used. If it were it would probably be CONFIDENTIAL.

Precedence-Action

306. This is the precedence of the message. There are three precedences which you may encounter:

- a. ROUTINE. These are transmitted in order of receipt.
- b. PRIORITY. Transmitted in order of receipt before any Routine traffic not already being transmitted.
- c. IMMEDIATE. Transmitted in order of receipt before any Priority traffic not already being transmitted.

Precedence-Info Routine

307. This applies to any Info addressees, e.g. the message is sent to Albany but Bunbury needs to be aware of it. It is normally ROUTINE but it may be crossed out and a higher precedence inserted.

Date-Time Group

308. This is filled in by the originator when the message is written. It is written as a six figure number followed by a letter, e.g. 061800Z AUG 02. This is 1800 UTC on the 6 August 2002.

Message Instructions

309. Seldom used but handy if there are any.

Sig/Orig Number

310. They fill this in. It is their reference number.

From and To

311. Self explanatory.

For Ops Use

312. These blocks are important and must always be completed. The R blocks are used for an incoming message. The D blocks are used for outgoing messages.

SECTION 3

MESSAGE HANDLING SEQUENCE

Introduction

313. This section will detail the sequence of transmission and procedures with received messages.

Messages Received for Transmission

314. When a message is given to you for transmission you should check that:

- a. It can be read.
- b. It contains no obvious errors.
- c. It has all the necessary information for its transmission.
- d. The meaning of any abbreviations is clear.

315. It is given the next OUT serial number from the log book.

Message Serial Numbers

316. Messages are given serial numbers, either IN or OUT, so that some sort of filing system can exist. This number has no relationship to the Originators Number.

317. The number consists of two parts, the message number and the date, e.g. 05/15. The message number continues consecutively until the end of the exercise/event. The date changes at midnight. This could be UTC or local depending on the time zone being used. These numbers are entered into the log book in the appropriate columns. You generate the OUT numbers while the IN number is obtained from the incoming message.

Prowords

318. The most common prowords used during message transmission are listed below.

MESSAGE
LONG MESSAGE
WAIT
WAIT OUT
SEND
FULL STOP
BREAK
TIME
READ BACK TEXT
CORRECT
WRONG
MESSAGE ENDS

Initial Call

319. In the initial call you must indicate what is to follow e.g. message, long message, so that the receiving station can be prepared:

VK6AA - THIS IS - VK6BB - MESSAGE - OVER

VK6AA - SEND - OVER

Transmission Sequence

320. The message is transmitted in the following sequence. Any part not filled in is ignored:

- a. Transmission instructions, e.g. READ BACK TEXT, RELAY TO
- b. Message out number
- c. Precedence/s
- d. Date-Time group
- e. Security classification
- f. Originators number
- g. From
- h. To
- i. Text

321. The sample message shown in Annex A would be sent as:

VK6AA - THIS IS - VK6BB - MESSAGE - OVER

VK6AA - SEND - OVER

VK6BB - message number zero five slant one five, routine, TIME one five one one three zero hotel, OPS one six, from Bloggs, to Jones, BREAK, PARA ONE, do you have any batteries, FULL STOP, para two nil return required, FULL STOP, MESSAGE ENDS - OVER

VK6AA - ROGER - WAIT OUT.

322. This message is sent using abbreviated procedure and assumes good working conditions. The message contains only the information commonly sent.

Sending a Long Message

323. The offer LONG MESSAGE is used and the message is sent in short sections after which the prowords MORE TO FOLLOW are used. If no repetitions are necessary and after a short pause to allow other stations to send urgent traffic, the remainder of the message is sent.

Messages Sent/Received

324. Once a message given to you is sent, the D block at the bottom of the message is completed together with the Log Book. It is then filed in the OUT folder.

Messages Received via Radio

325. When a message is received over the radio, it is usually necessary to re-write it (This may be in duplicate depending on the situation). It is given an IN serial number (from the Log Book), the details are entered into the Log and the R block completed at the bottom of the message. The original is given to the addressee. If a carbon copy was kept it should be filed in the IN folder.

326. A sample Log Sheet is shown in Annex B.

Annex A

19

Annex B

Location

WICEN

Event Date

[illegible]

Page of

RATEL PROWORDS

Prowords

ACKNOWLEDGE	(a) Instruction to a station on the net to acknowledge that it has heard a message which was not specifically addressed to it. (b) When used in the text of a message, an instruction to the addressee that the message must be acknowledged.
ALL AFTER	The portion of the message that I have referenced is all that which follows.....
ALL BEFORE	The portion of the message that I have referenced is all that which precedes.....
ANSWER AFTER	The station called is to answer after callsign when answering transmissions.
ASSUME CONTROL	You will assume control of this net until further notice.
BREAK	The text is beginning or ending. Used only for formal messages.
CALLSIGN	That which follows is a callsign.
CHANGE NOW	Change frequency now
CHANGE TO	Change frequency to
CLOSE DOWN	Stations called are to close down when indicated. Acknowledgements are required.
CORRECT	You are correct, or, what you received is correct. This proword is used as a response in READBACK procedure.
CORRECTION	(a) An error has been made in this transmission. The message will continue with the last word correctly transmitted. (b) An error has been made in this transmission (or message indicated. The correct version is (c) That which follows is a corrected version in answer to your request for verification

DISREGARD THIS
TRANSMISSION

This transmission is in error. Disregard it. This proword shall not be used to cancel any message that has been transmitted and for which acknowledgment has been received.

DISTORTED

Your signals are distorted.

FADING

At times your signal strength fades to such an extent that continuous reception cannot be relied upon.

FETCH

The person indicated is to be called to the communications area to PERSONALLY communicate with the transmitting station.

FIGURES

Figures or numerals follow.

FORMAL MESSAGE

Formal message of precedence indicated follows.

FROM

The details of the originator follow.

FROM
TO

The portion of the message referred to is contained between the words indicated by FROM and TO.

GOOD

Your signal strength is good.

GRID

The portion following is a grid reference.

I AM ASSUMING
CONTROL

I am assuming control of this net.

INFO

The addressees immediately following are addressed for information (used in formal message procedure).

INTERFERENCE

Having trouble reading you due to interference.

I READ BACK

The following is the message as received at this station.

I SAY AGAIN

I am repeating all or portion of message indicated.

I SPELL

I shall spell the next word phonetically.

I VERIFY

The following has been verified at your request and is repeated. To be used only as a reply to VERIFY.

LONG MESSAGE

The message which follows is long, use attachment sheets of paper as required.

LOUD & CLEAR

The readability of your signals is of excellent quality.

MESSAGE

A message which requires recording is about to follow.

MORE TO FOLLOW	Used in Long Message Procedure to indicate that a further portion of the message follows when the transmission is resumed.
NOTHING HEARD	To be used when no reply is received from a called station.
OUT	This is the end of my transmission to you and no answer is required or expected.
OUT TO YOU	Used to indicate that this is the end of my transmission to you and no answer is required or expected. I am about to call another station immediately. No other station is to transmit in the meantime.
OVER	This is the end of my transmission to you and a response is necessary. Go ahead and transmit.
PRIORITY	Precedence; PRIORITY.
RADIO CHECK	What is my signal strength and readability. That is, how do you hear me?
READABLE	Your transmission is readable.
READBACK	Repeat this entire transmission (or portion indicated) back to me exactly as received.
RELAY THROUGH	Relay your message through callsign
RELAY TO	Transmit this message to all addressees (or addressees immediately following this proword).
REQUEST TIME CHECK	I wish to synchronise time. Please transmit a time check.
ROGER	(a) As an answer to normal transmissions - I have received your last transmission satisfactorily. (b) As an answer to a Radio Check - I have received your last transmission satisfactorily. The omission of comment on signal strength and readability is understood to mean that reception is loud and clear.
ROUTINE	Precedence; ROUTINE.
SAY AGAIN	Repeat your last transmission (or portion nominated).
SEND YOUR	I am ready to receive your(message).... , SITREP, etc.

SERVICE	The following message is a service message and relates to net integrity.
SPEAKING	 is speaking.
SPEAK SLOWER	Your spoken transmission is too fast.
THIS IS	This transmission is from the station whose address designator immediately follows.
THIS IS A DIRECTED NET	From now until further notice, this net is directed.
THIS IS A FREE NET	From now until further notice, this net is free.
THROUGH ME	Relay your message through me.
TIME	(a) When passing a formal message. That which follows is the time date-time group of the message. (b) When synchronising time. The time now is
TIME CHECK	The time will be hours when I transmit the proword TIME. Used when answering a request for a time check.
TIME CHECK AT	The time will be hours when I transmit the proword TIME. Used when NCS initiates a time check.
TO	The addressees immediately following are addressed for action.
UNKNOWN STATION	The identity of the station with whom I am attempting to establish communication is unknown.
USE ABBREVIATED CALLSIGNS	Until further notice callsigns are to be abbreviated.
USE ABBREVIATED PROCEDURE	As conditions are normal, all stations are to use abbreviated procedure until further notice.
USE FULL CALLSIGNS	Until further notice callsigns are to be sent in full.
USE FULL PROCEDURE	As conditions are NOT normal, all stations are to use full procedure until further notice.
VERIFY	Verify entire message (or portion indicated) with the originator and send correct version. To be used only at the discretion of, or by, the addressee to which the questioned message was directed.

VERY WEAK	Your signal strength is very weak.
WAIT	I must pause for up to maximum of five seconds. No other station is to transmit during this pause. When used in conjunction with OUT TO YOU, means I will contact you later on this subject.
WAIT - OUT	I must pause (you must wait) for more than five seconds. Any station is free to transmit unless otherwise indicated in this transmission or by the prevailing circumstances, such as a directed net. You must wait until called again.
WEAK	Your signal strength is weak.
WILCO	I have received your signal, understood it and will comply. To be used only by the addressee. Since the meaning of ROGER is included in that of WILCO, the two prowords are never used together.
WORD AFTER	The word of the message to which I have referenced is that which follows.....
WORD BEFORE	The word of the message to which I have referenced is that which precedes.....
WORDS TWICE	Communication is difficult. Transmit each phrase (or each code group) twice. This proword may be used as an order, request or as information.
WRONG	Your last transmission was incorrect. The correct version is

The following prowords and meanings are an abbreviated list.

ACKNOWLEDGE	Instruction to a station to acknowledge that it has heard a message.
ALL AFTER ALL BEFORE	Used for making repetitions.
CANCEL	Cancel a message or part of a message or transmission.
CLOSE DOWN	Stations called are to close down when indicated.
CLOSING DOWN	This station is closing down.
CORRECT	You are correct or what you have transmitted is correct.

CORRECTION	An error has been made in transmission. The correct version follows.
FETCH	Used in conjunction with a name or appointment.
FIGURES	Used before sending figures digit by digit in difficult conditions. Not used for Callsigns, grid references, times, date time groups.
GRID	Used before any grid reference.
SAY AGAIN I SAY AGAIN	Used for repetitions.
I SPELL	Used when spelling out a word.
MESSAGE	Used when a message is to be written down.
NOTHING HEARD	Indication that no signals have been heard from a particular station.
OUT	This is the end of my transmission. No reply is expected.
OUT TO YOU	This is the end of my transmission to you and a call to another station follows immediately.
OVER	This is the end of my transmission to you and a reply is expected.
RADIO CHECK	Report how you receive my transmissions.
READ BACK	Repeat this entire transmission back to me exactly as you received it.
RELAY TO	Instruction to a station to relay a message
ROGER	I have received your last transmission satisfactorily.
SEND	I am ready to receive your message.
VERIFY	Verify portion indicated with originator and send correct version.
WAIT	I must pause for up to five seconds. No other station is to transmit even though I am not.
WAIT OUT	Your transmission is received. A further transmission on the same subject will follow later. Other stations may transmit as normal.
WORD AFTER WORD BEFORE	Used to identify part of a message.
WORDS TWICE	Communication is difficult. Transmit each phrase twice.
WRONG	What you have said is wrong. Correct version is...