

Online Dynamic Resource Allocation with State Constraints

Kamiar Asgari Michael J. Neely

April 11, 2026

Abstract

We study online dynamic resource allocation with state-coupled feasibility constraints under adversarial inflows and convex costs. At each round, the controller chooses an allocation before observing inflow and cost, while maintaining feasibility of the evolving resource state. We introduce *Simplex Disturbance-Action Control* (SDAC), a simplex-constrained disturbance-action policy class that preserves feasibility by construction and supports online convex optimization over policy parameters. We benchmark against the best fixed SDAC policy in hindsight and develop an exponentiated-gradient online controller over SDAC weights. Our regret analysis yields sublinear dependence on horizon and logarithmic dependence on policy dimension, connecting constrained resource dynamics with adversarial online control. The framework is motivated by applications in energy-harvesting battery management and inventory control in supply chains, where decisions must respect state-dependent physical limits in real time.

1 Introduction

1.1 Motivation and Problem Setting

Many dynamic resource systems are governed by a budget state variable that evolves over time and constrains the allocation action at every round. The controller must choose an allocation action from currently available resources before observing the round’s inflow and cost.

This creates an online optimization problem with state coupling: aggressive early allocation can harm later performance, while overly conservative allocation can increase immediate cost. Our objective is to design a policy that remains feasible at every round and competes with the best fixed policy in a structurally tractable comparator class.

1.2 Model and Information Structure

We study a discrete-time storage-allocation system with state $b_t \geq 0$, where b_t represents the currently available resource. At each time t , the controller chooses an allocation action u_t under the *feasibility constraints* such as

$$0 \leq u_t \leq b_t,$$

which means the controller cannot allocate more than the currently available resource or any negative amount. After the action is chosen, an adversarial inflow a_t arrives, and the state evolves according to

$$b_{t+1} = b_t - u_t + a_t,$$

with inflow a_t .

Unlike stochastic application models that rely on distributional assumptions, our formulation is adversarial. Inflows a_t and convex costs $c_t(b, u)$ may vary arbitrarily over time, and the controller chooses u_t before observing either object at round t . The goal is low cumulative cost relative to the best fixed policy in a later-defined comparator class, while maintaining feasibility throughout.

1.3 Application Domains

This abstraction captures a broad set of domains:

- **Energy Harvesting and Battery Management:** b_t is battery state of charge, a_t is harvested energy, and u_t is discharge or consumption.
- **Water Reservoir and Dam Management:** b_t is stored water, a_t is inflow, and u_t is controlled release under storage limits.
- **Inventory Control and Supply Chains:** b_t is on-hand inventory, a_t is replenishment, and u_t is allocation/sales under stock constraints.
- **Queueing Networks and Buffer Management:** b_t is queue/buffer occupancy, a_t is arrivals, and u_t is service rate constrained by current backlog.
- **Investments and Bank Accounts:** b_t is liquid capital/balance, a_t is incoming cash flow, and u_t is capital deployment or withdrawal under budget limits.

1.4 Related Work and Research Gap

Prior Work on State-Constrained Allocation. State-constrained dynamic allocation has long been studied in several domain traditions. Queueing and buffer-management models, for example, study how a budget-like state evolves under arrivals and service decisions, and this viewpoint underlies much of network control and performance analysis [13, 15]. Related interpretations appear in energy-harvesting communication systems and Lyapunov-drift control [19, 25, 23, 26]. Classical dam/storage-process theory and inventory-control models provide parallel formulations for inflow-release and supply-demand dynamics [17, 21, 3, 22, 30, 20]. In parallel, competitive-analysis and inventory-constrained online optimization have developed worst-case and online guarantees for storage and allocation systems [5, 28, 27, 16, 6, 18], with related formulations in one-way trading and online knapsack [4, 7]. Control-side approaches based on drift and online optimization hybrids further characterize utility-budget tradeoffs in constrained state systems [12, 29]. Positive-systems theory is also close in spirit, since it emphasizes state nonnegativity and constrained control, although it is not an exact match to our adversarial online-learning setting; still, it provides useful structural intuition for budgeted dynamics [8, 9].

Prior Work on Adversarial Online Control. A major recent stream in online learning studies online control under adversarial disturbances and costs, with regret measured against the best policy in hindsight [1, 2, 10, 24, 11]. Within this stream, Disturbance-Action Control (DAC) parameterizations are central because they convert policy search into tractable online optimization over disturbance-response filters; extensions include partial observability and bandit feedback [14, 10].

Research Gap and Paper Scope. Adversarial online control provides a strong foundation for our problem class: it accommodates arbitrary time-varying disturbances and unknown convex costs, with regret guarantees against hindsight comparators and tractable online updates. DAC is central in this literature because it turns policy search into online convex optimization. However, for budget-coupled allocation dynamics, vanilla DAC does not enforce per-round feasibility by construction. Our framework fills this gap by replacing raw DAC with SDAC, a simplex-constrained DAC-style family that preserves feasibility defined by (1) while retaining adversarial online-learning tractability. We benchmark against the best fixed SDAC policy in hindsight.

1.5 Contributions

The contributions are organized in two layers:

- **Modeling and policy-class contribution.** We formulate adversarial online dynamic resource allocation with state-coupled feasibility, and we introduce *Simplex Disturbance-Action Control* (SDAC), a DAC-inspired simplex-constrained policy class that enforces feasibility by construction while preserving DAC-style expressiveness.
- **Algorithmic and analytical contribution.** We develop an exponentiated-gradient online controller over SDAC weights and analyze regret against the best fixed SDAC comparator in hindsight, highlighting sublinear horizon dependence with logarithmic dependence on policy dimension.

1.6 Paper Organization

Section 3 formalizes the adversarial allocation model, assumptions, and regret benchmark. Section 4 introduces the SDAC policy class and summarizes its structural properties. Section 5 presents the online controller, Section 6 develops regret guarantees, and Section 7 reports experiments.

2 Notation

We denote by $t \in \{1, 2, \dots, T\}$ the time index (total horizon T). The system state $b_t \in \mathbb{R}_{\geq 0}$ is the available resource, and the action $u_t \in \mathbb{R}_{\geq 0}$ satisfies $0 \leq u_t \leq b_t$. The exogenous inflow is $a_t \in [0, 1]$, and the cost function is $c_t : \mathbb{R}_{\geq 0}^2 \rightarrow \mathbb{R}$. The online algorithm is $\mathcal{A}$, and π (or $\pi(w)$ when parameterized by w) denotes a policy from the comparator class $\Pi = \text{SDAC}_H^\kappa$. The parameters $\kappa \in (0, 1]$ (gain) and $H \in \mathbb{N}$ (memory horizon) are fixed design parameters. The weight vector w lies in the simplex $\Delta_H = \{w \in \mathbb{R}_{\geq 0}^H : \sum_i w^{(i)} = 1\}$. The Lipschitz constants for the cost function are $L_b, L_u > 0$. The inner product is denoted $\langle x, y \rangle = x^T y$.

3 Model and Problem Setup

We consider a discrete-time allocation process over rounds $t \in \{1, 2, \dots, T\}$. The system state is denoted by $b_t \in \mathbb{R}_{\geq 0}$, where b_t represents the available budget at the beginning of round t . The initial state is given as

$$b_1 = 0.$$

At each round, the controller chooses an allocation action $u_t \in \mathbb{R}_{\geq 0}$ subject to state feasibility:

$$0 \leq u_t \leq b_t. \quad (1)$$

The system then receives an exogenous inflow $a_t \in [0, 1]$ and evolves according to

$$b_{t+1} = b_t - u_t + a_t. \quad (2)$$

After the action is selected, a convex cost function

$$c_t : \mathbb{R}_{\geq 0}^2 \rightarrow \mathbb{R}$$

is revealed, and the incurred cost is $c_t(b_t, u_t)$. We assume each c_t is convex in (b, u) and satisfies a Lipschitz condition on the relevant domain. There exist constants $L_b, L_u > 0$ such that for all admissible (b, u) and (b', u') ,

$$|c_t(b, u) - c_t(b', u')| \leq L_b |b - b'| + L_u |u - u'|. \quad (3)$$

The information pattern is adversarial and non-anticipatory. At time t , the controller chooses u_t before observing a_t and c_t . Hence both the inflow sequence $\{a_t\}_{t=1}^T$ and the cost sequence $\{c_t\}_{t=1}^T$ may be arbitrary.

Assumptions Equations (1)–(3) define the model. For analysis, we collect the remaining standing assumptions as follows:

1. **Inflow bounds:** $a_t \in [0, 1]$ for all t .
2. **Adversarial timing:** at round t , u_t is chosen before observing a_t and c_t .
3. **Cost regularity:** each c_t is convex in (b, u) and obeys (3).
4. **Feasible policy class:** both the online policy and comparator policies are required to satisfy (1) under dynamics (2).

For an online algorithm $\mathcal{A}$ producing trajectory $\{(b_t^{\mathcal{A}}, u_t^{\mathcal{A}})\}_{t=1}^T$, define cumulative cost

$$J_T(\mathcal{A}) \triangleq \sum_{t=1}^T c_t(b_t^{\mathcal{A}}, u_t^{\mathcal{A}}). \quad (4)$$

For fixed (κ, H) , let the comparator class be $\Pi \triangleq \text{SDAC}_H^\kappa$ (defined in Section 4). For each $\pi \in \Pi$, let $\{(b_t^\pi, u_t^\pi)\}_{t=1}^T$ be the induced feasible trajectory under the same inflow sequence. Regret is defined by

$$\text{Regret}(T) \triangleq \sum_{t=1}^T c_t(b_t^A, u_t^A) - \min_{\pi \in \Pi} \sum_{t=1}^T c_t(b_t^\pi, u_t^\pi). \quad (5)$$

While the online learner may update its SDAC weights over time, the benchmark in (5) is the best single fixed SDAC policy chosen in hindsight. The objective is to design an online policy that preserves feasibility in (1) for all t and achieves sublinear regret as defined in (5).

4 Simplex Disturbance-Action Control (SDAC)

4.1 From Disturbance-Action Control to SDAC

Disturbance-Action Control (DAC) parameterizes the action as a linear function of the current state and a finite window of past disturbances. This representation is central in adversarial online control because it accommodates arbitrary disturbance and cost sequences, yields robust regret guarantees, and enables efficient online convex-optimization updates. In our setting, a representative DAC form is

$$u_t = \kappa b_t + \sum_{i=1}^H m^{(i)} a_{t-i}, \quad (6)$$

where $\kappa \in \mathbb{R}$ is a gain, $H \in \mathbb{N}$ is the memory horizon, and $m \in \mathbb{R}^H$ is a disturbance filter.

For our constrained allocation model, raw DAC is insufficient: (6) does not generally enforce (1) at every round. In particular, the action can violate either bound, with $u_t > b_t$ or $u_t < 0$. We therefore introduce *Simplex Disturbance-Action Control* (SDAC), which replaces unconstrained DAC filters by a simplex-constrained family tailored to budget dynamics. SDAC is designed to keep the DAC advantages above (adversarial robustness, regret-based comparison, and tractable online updates) while adding feasibility by construction.

4.2 SDAC Definition

Fix $\kappa \in (0, 1]$ and memory horizon $H \in \mathbb{N}$. Let

$$\Delta_H \triangleq \left\{ w \in \mathbb{R}_{\geq 0}^H : \sum_{i=1}^H w^{(i)} = 1 \right\} \quad (7)$$

be the probability simplex. For any $w \in \Delta_H$, define the policy $\pi(w)$ by

$$u_t^{\pi(w)} \triangleq \kappa b_t^{\pi(w)} + \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i}, \quad a_\tau \equiv 0 \text{ for } \tau \leq 0. \quad (8)$$

The induced state trajectory satisfies

$$b_{t+1}^{\pi(w)} = b_t^{\pi(w)} - u_t^{\pi(w)} + a_t, \quad b_1^{\pi(w)} = 0. \quad (9)$$

The resulting class is

$$\text{SDAC}_H^\kappa \triangleq \{\pi(w) : w \in \Delta_H\},$$

with Δ_H defined in (7).

First, feasibility is preserved within the class: for any fixed $w \in \Delta_H$, the induced trajectory under (8)–(9) satisfies $0 \leq u_t^{\pi(w)} \leq b_t^{\pi(w)}$ for all t (see Lemma 3 in Appendix A).

Second, SDAC is compatible with online convex optimization. For fixed inflows, both $b_t^{\pi(w)}$ and $u_t^{\pi(w)}$ are linear in w . Therefore, since each c_t is convex in (b, u) , the induced cost is convex in w (see Lemma 4 in Appendix A). Regret minimization against the best fixed SDAC comparator thus becomes online convex optimization over the simplex.

5 Online Algorithm

We now define an online controller over SDAC weights using exponentiated-gradient updates on the simplex.

For each round t , let

$$\tilde{a}_t \triangleq ((1 - \kappa)^1 a_{t-1}, \dots, (1 - \kappa)^H a_{t-H})^\top \in \mathbb{R}^H,$$

and let $w_t \in \Delta_H$ be the online weight vector.

Action selection The controller first forms the unconstrained SDAC-style action

$$\hat{u}_t \triangleq \kappa b_t^A + \langle w_t, \tilde{a}_t \rangle, \quad (10)$$

then enforces feasibility by clipping:

$$u_t^A \triangleq \min\{\hat{u}_t, b_t^A\}. \quad (11)$$

The state update is

$$b_{t+1}^A = b_t^A - u_t^A + a_t, \quad b_1^A = 0. \quad (12)$$

Feasibility of the online trajectory We verify that the algorithm satisfies the state-action constraints at every round. Since $w_t \in \Delta_H$, $\tilde{a}_t \geq 0$ componentwise, and $\kappa \in (0, 1]$, equation (10) gives $\hat{u}_t \geq 0$. By (11),

$$u_t^A = \min\{\hat{u}_t, b_t^A\} \in [0, b_t^A],$$

so the action feasibility constraint holds whenever $b_t^A \geq 0$. It remains to prove $b_t^A \geq 0$ for all t . The base case is $b_1^A = 0$. If $b_t^A \geq 0$, then $u_t^A \leq b_t^A$ and $a_t \in [0, 1]$, so from (12),

$$b_{t+1}^A = b_t^A - u_t^A + a_t \geq 0.$$

Thus, by induction, $b_t^A \geq 0$ and $0 \leq u_t^A \leq b_t^A$ for all t .

Surrogate cost and gradient step Define the surrogate cost at round t by

$$\ell_t(w) \triangleq c_t(b_t^{\pi(w)}, u_t^{\pi(w)}), \quad w \in \Delta_H, \quad (13)$$

which is convex and Lipschitz by Lemma 4. Let $g_t \in \partial \ell_t(w_t)$ be a subgradient.

The exponentiated-gradient update is

$$\tilde{w}_{t+1}^{(i)} \triangleq w_t^{(i)} \exp(-\eta g_t^{(i)}), \quad i = 1, \dots, H, \quad (14)$$

followed by simplex normalization:

$$w_{t+1}^{(i)} \triangleq \frac{\tilde{w}_{t+1}^{(i)}}{\sum_{j=1}^H \tilde{w}_{t+1}^{(j)}}, \quad i = 1, \dots, H. \quad (15)$$

This yields a feasible online trajectory by (11) and performs online convex optimization over Δ_H through (13)–(15).

6 Regret Analysis

7 Experiments

A Appendix: Deferred Proofs

This appendix collects the deferred proofs for structural SDAC properties used in Section 4.

Lemma 1 (State decomposition under SDAC). *Fix $\kappa \in (0, 1]$, $H \in \mathbb{N}$, and $w \in \Delta_H$. Let $\pi(w)$ be defined by (8) and (9). Then for all $t \geq 2$,*

$$b_t^{\pi(w)} = \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^i (1 - \kappa)^{j-1} a_{t-j} \right) = \langle w, \psi_t \rangle, \quad (16)$$

where

$$\psi_t^{(i)} \triangleq \sum_{j=1}^i (1 - \kappa)^{j-1} a_{t-j}, \quad i = 1, \dots, H.$$

In particular, $0 \leq \psi_t^{(i)} \leq 1/\kappa$. Consequently, since $w \in \Delta_H$ and $b_t^{\pi(w)} = \langle w, \psi_t \rangle$, we also have $b_t^{\pi(w)} \geq 0$ for all $t \geq 2$.

Proof. We use induction on t . For $t = 2$, $b_1^{\pi(w)} = 0$ and $a_{1-i} = 0$ for all $i \geq 1$. By the policy definition (8), $u_1^{\pi(w)} = \kappa b_1^{\pi(w)} + \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{1-i} = 0$. Then, using the state update (9), $b_2^{\pi(w)} = b_1^{\pi(w)} - u_1^{\pi(w)} + a_1 = a_1$, which is exactly (16) at time $t = 2$.

Assume the claim holds at time $t \geq 2$. Using (8) and (9),

$$b_{t+1}^{\pi(w)} = (1 - \kappa) b_t^{\pi(w)} - \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i} + a_t.$$

Substituting the induction hypothesis gives

$$\begin{aligned}
b_{t+1}^{\pi(w)} &= (1 - \kappa) \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^i (1 - \kappa)^{j-1} a_{t-j} \right) - \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i} + a_t \\
&= \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^i (1 - \kappa)^j a_{t-j} \right) - \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i} + a_t \\
&= \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^{i-1} (1 - \kappa)^j a_{t-j} \right) + a_t \\
&= \sum_{i=1}^H w^{(i)} \left(a_t + \sum_{j=1}^{i-1} (1 - \kappa)^j a_{t-j} \right) \\
&= \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^i (1 - \kappa)^{j-1} a_{t+1-j} \right),
\end{aligned}$$

which is exactly (16) at time $t + 1$. The bound $\psi_t^{(i)} \leq 1/\kappa$ follows from $a_\tau \in [0, 1]$ and the geometric series. $\square$

Lemma 2 (Linearity of SDAC action in w). *Under the setup of Lemma 1, for each t ,*

$$u_t^{\pi(w)} = \langle w, \phi_t \rangle,$$

where

$$\phi_t^{(i)} \triangleq \kappa \psi_t^{(i)} + (1 - \kappa)^i a_{t-i} = \sum_{j=1}^i (1 - \kappa)^{j-1} a_{t-j}.$$

Moreover, $0 \leq \phi_t^{(i)} \leq 1$ for all i .

Proof. From (8),

$$u_t^{\pi(w)} = \kappa b_t^{\pi(w)} + \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i}.$$

Applying Lemma 1, we substitute $b_t^{\pi(w)} = \langle w, \psi_t \rangle = \sum_{i=1}^H w^{(i)} \psi_t^{(i)}$, so

$$\begin{aligned} u_t^{\pi(w)} &= \kappa \sum_{i=1}^H w^{(i)} \psi_t^{(i)} + \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i} \\ &= \sum_{i=1}^H w^{(i)} (\kappa \psi_t^{(i)} + (1 - \kappa)^i a_{t-i}) \\ &= \sum_{i=1}^H w^{(i)} \phi_t^{(i)} = \langle w, \phi_t \rangle. \end{aligned}$$

The lower bound on $\phi_t^{(i)}$ is immediate from $a_{t-i} \geq 0$ and $\kappa \leq 1$. For the upper bound, use $a_\tau \in [0, 1]$:

$$\phi_t^{(i)} \leq \kappa \sum_{j=1}^i (1 - \kappa)^{j-1} + (1 - \kappa)^i = 1.$$

□

Lemma 3 (Feasibility of SDAC policies). *For every fixed $w \in \Delta_H$, the trajectory induced by (8)–(9) satisfies*

$$0 \leq u_t^{\pi(w)} \leq b_t^{\pi(w)} \quad \text{for all } t \geq 1.$$

Proof. Nonnegativity of $u_t^{\pi(w)}$ follows from (8), because each term in the sum is nonnegative: $\kappa b_t^{\pi(w)} \geq 0$ since $\kappa > 0$ and $b_t^{\pi(w)} \geq 0$ (by Lemma 1 for $t \geq 2$, and $b_1^{\pi(w)} = 0$ by (9)), while $w^{(i)} \geq 0$, $(1 - \kappa)^i \geq 0$, and $a_{t-i} \geq 0$ for every i .

For the upper bound, Lemma 1 implies

$$(1 - \kappa) b_t^{\pi(w)} = (1 - \kappa) \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^i (1 - \kappa)^{j-1} a_{t-j} \right) = \sum_{i=1}^H w^{(i)} \left(\sum_{j=1}^i (1 - \kappa)^j a_{t-j} \right).$$

Now rewrite the inner sum by collecting the coefficient of each a_{t-i} . Since all weights are nonnegative, for every i we have

$$\sum_{j=i}^H w^{(j)} \geq w^{(i)}.$$

Therefore,

$$(1 - \kappa)b_t^{\pi(w)} = \sum_{i=1}^H \left(\sum_{j=i}^H w^{(j)} \right) (1 - \kappa)^i a_{t-i} \geq \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i},$$

since $\sum_{j=i}^H w^{(j)} \geq w^{(i)}$ and $a_{t-i} \geq 0$. Therefore,

$$u_t^{\pi(w)} = \kappa b_t^{\pi(w)} + \sum_{i=1}^H w^{(i)} (1 - \kappa)^i a_{t-i} \leq \kappa b_t^{\pi(w)} + (1 - \kappa)b_t^{\pi(w)} = b_t^{\pi(w)}.$$

□

Lemma 4 (Convexity and Lipschitz continuity of surrogate cost). *Define*

$$\ell_t(w) \triangleq c_t(b_t^{\pi(w)}, u_t^{\pi(w)}), \quad w \in \Delta_H.$$

Then ℓ_t is convex on Δ_H , and for all $w, w' \in \Delta_H$,

$$|\ell_t(w) - \ell_t(w')| \leq \left(\frac{L_b}{\kappa} + L_u \right) \|w - w'\|_1.$$

Proof. By Lemma 1 and Lemma 2,

$$\ell_t(w) = c_t(\langle w, \psi_t \rangle, \langle w, \phi_t \rangle).$$

The map $w \mapsto (\langle w, \psi_t \rangle, \langle w, \phi_t \rangle)$ is affine, and c_t is convex, so ℓ_t is convex.

Using (3),

$$\begin{aligned} |\ell_t(w) - \ell_t(w')| &= |c_t(\langle w, \psi_t \rangle, \langle w, \phi_t \rangle) - c_t(\langle w', \psi_t \rangle, \langle w', \phi_t \rangle)| \\ &\leq L_b |\langle w - w', \psi_t \rangle| + L_u |\langle w - w', \phi_t \rangle| \\ &\leq L_b \|w - w'\|_1 \|\psi_t\|_\infty + L_u \|w - w'\|_1 \|\phi_t\|_\infty \\ &= (L_b \|\psi_t\|_\infty + L_u \|\phi_t\|_\infty) \|w - w'\|_1. \end{aligned}$$

Lemma 1 gives $\|\psi_t\|_\infty \leq 1/\kappa$, and Lemma 2 gives $\|\phi_t\|_\infty \leq 1$, which yields the claim. □

References

- [1] Naman Agarwal, Brian Bullins, Elad Hazan, Sham Kakade, and Karan Singh. Online control with adversarial disturbances. In *International Conference on Machine Learning*, pages 111–119. PMLR, 2019.

- [2] Naman Agarwal, Elad Hazan, and Karan Singh. Logarithmic regret for online control. *Advances in Neural Information Processing Systems*, 32, 2019.
- [3] Kenneth J. Arrow, Samuel Karlin, and Herbert Scarf. *Studies in the Mathematical Theory of Inventory and Production*. Stanford University Press, 1958.
- [4] Ying Cao, Bo Sun, and Danny HK Tsang. Optimal online algorithms for one-way trading and online knapsack problems: A unified competitive analysis. *arXiv preprint arXiv:2004.10358*, 2020.
- [5] Chi-Kin Chau, Guanglin Zhang, and Minghua Chen. Cost minimizing online algorithms for energy storage management with worst-case guarantee. *IEEE Transactions on Smart Grid*, 7(6):2691–2702, 2016.
- [6] Chi-Kin Chau, Guanglin Zhang, and Minghua Chen. Cost minimizing online algorithms for energy storage management with worst-case guarantee. *IEEE Transactions on Smart Grid*, 7(6):2691–2702, 2016.
- [7] Ran El-Yaniv, Amos Fiat, Richard M Karp, and Gordon Turpin. Optimal search and one-way trading online algorithms. *Algorithmica*, 30(1):101–139, 2001.
- [8] Lorenzo Farina and Sergio Rinaldi. *Positive Linear Systems: Theory and Applications*. Wiley-Interscience, 2000.
- [9] Wassim M. Haddad, VijaySekhar Chellaboina, and Qing Hui. *Non-negative and Compartmental Dynamical Systems*. Princeton University Press, 2010.
- [10] Elad Hazan, Sham M. Kakade, Karan Singh, and Abhishek Sidford. Nonstochastic control with bandit feedback. *Advances in Neural Information Processing Systems (NeurIPS)*, 33:16774–16785, 2020.
- [11] Elad Hazan and Karan Singh. Introduction to Online Control, April 2025. arXiv:2211.09619 [cs].
- [12] Longbo Huang and Michael J. Neely. Utility optimal scheduling in energy-harvesting networks. *IEEE/ACM Transactions on Networking*, 21(4):1117–1130, 2013.
- [13] Leonard Kleinrock. *Queueing Systems, Volume 1: Theory*. Wiley, New York, 1975.

- [14] Sahin Lale, Kamyar Azizzadenesheli, Babak Hassibi, and Anima Anandkumar. Logarithmic regret bound in partially observable linear dynamical systems. *Advances in Neural Information Processing Systems*, 33:20876–20888, 2020.
- [15] Jean-Yves Le Boudec and Patrick Thiran. *Network Calculus: A Theory of Deterministic Queuing Systems for the Internet*. Springer, Berlin, 2001.
- [16] Qiulin Lin, Hanling Yi, John Pang, Minghua Chen, Adam Wierman, Michael Honig, and Yuanzhang Xiao. Competitive online optimization under inventory constraints. *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, 3(1):1–28, 2019.
- [17] P. A. P. Moran. A probability theory of dams and storage systems. *Australian Journal of Applied Science*, 5(2):116–124, 1954.
- [18] M. J. Neely and L. Huang. Dynamic product assembly and inventory control for maximum profit. *Proc. IEEE Conf. on Decision and Control (CDC)*, Atlanta, GA, Dec. 2010.
- [19] Michael J. Neely. *Stochastic Network Optimization with Application to Communication and Queueing Systems*. Morgan & Claypool Publishers, 2010.
- [20] Evan L. Porteus. *Foundations of Stochastic Inventory Theory*. Stanford Business Books, 2002.
- [21] N. U. Prabhu. *Stochastic Storage Processes*. Springer New York, New York, NY, 1998.
- [22] Herbert Scarf. The optimality of (s, s) policies in the dynamic inventory problem. In *Mathematical Methods in the Social Sciences*, pages 196–202. Stanford University Press, 1960.
- [23] Vinod Sharma, Uday B. Mukherji, Vinay A. Joseph, and Sudeep Gupta. Optimal energy management policies for energy harvesting sensor nodes. *IEEE Transactions on Wireless Communications*, 9(4):1326–1336, 2010.
- [24] Max Simchowitz, Karan Singh, and Elad Hazan. Improper learning for non-stochastic control. In *Conference on Learning Theory*, pages 3320–3436. PMLR, 2020.

- [25] S. Sudevalayam and P. Kulkarni. Energy harvesting sensor nodes: Survey and implications. *IEEE Communications Surveys & Tutorials*, 13(3):443–461, 2011.
- [26] Jing Yang and Sennur Ulukus. Optimal packet scheduling in an energy harvesting communication system. *IEEE Transactions on Communications*, 60(1):220–230, 2011.
- [27] Lin Yang, Mohammad H Hajiesmaili, Ramesh Sitaraman, Adam Wierman, Enrique Mallada, and Wing S Wong. Online linear optimization with inventory management constraints. *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, 4(1):1–29, 2020.
- [28] Lin Yang, Mohammad H. Hajiesmaili, Ramesh K. Sitaraman, Adam Wierman, Enrique Mallada, and Wing S. Wong. Online linear optimization with inventory management constraints. *Proc. ACM Meas. Anal. Comput. Syst.*, 4(1):16:1–16:29, 2020.
- [29] Hao Yu and Michael J. Neely. Learning-aided optimization for energy-harvesting devices with outdated state information. *IEEE/ACM Transactions on Networking*, 27(4):1501–1514, 2019.
- [30] Paul H. Zipkin. *Foundations of Inventory Management*. McGraw-Hill, 2000.