

Online Constrained Control of Storage Systems via Simplex Disturbance-Action Policies

Kamiar Asgari and Michael J. Neely

Abstract—We study online control of a scalar storage system with nonnegative adversarial resource arrivals and state-dependent action constraints. The adversarial, time-varying cost depends on both the state and the action. At each time, the controller selects a feasible action before the current resource arrival and cost are revealed. To handle the resulting coupling between feasibility and online learning, we introduce *Simplex Disturbance-Action Control* (SDAC), a policy class specified by H nonnegative parameters whose sum is at most one. The key feature of SDAC is that every fixed policy in the class is feasible by construction. Our online SDAC controller updates these parameters using entropic online mirror descent while preserving feasibility along the time-varying trajectory. We prove a regret bound of $O(\sqrt{T \log(H+1)})$ relative to the best fixed SDAC policy. We also derive a minimax lower bound showing that the dependence on T is tight. We then show that SDAC geometrically approximates a decreasing-allocation policy class that spreads each arrival over time according to a common decreasing allocation sequence, a structure that arises in stochastic energy-harvesting control. With $H = \Theta(\log T)$, the resulting regret against the decreasing-allocation class is $O(\sqrt{T \log \log T})$. The framework applies to energy-harvesting batteries and other storage-constrained resource systems.

Index Terms—Online control, disturbance-action policies, storage systems, energy harvesting, regret minimization, state-dependent action constraints.

I. INTRODUCTION

A. Motivation and Problem Setting

MANY resource-allocation systems have a storage state that changes over time and limits the control action at each time. An action that lowers the current cost may leave less resource for future decisions, while conserving the resource may increase the current cost. The controller must balance these effects while satisfying this constraint at every step.

We study this problem for a scalar storage system that loses a fixed fraction of its stored resource each period. At each time, the controller observes the current state and all past arrivals and cost functions, chooses a control action, and then observes the current arrival and cost function. The arrival and cost sequences may be chosen adversarially, so we do not assume a known probability model. Our goal is to construct an online SDAC controller whose cumulative cost is close to that of the best fixed policy, chosen in hindsight, from a specified benchmark class.

One difficulty is that the current action affects the next state. In online control, *Disturbance-Action Control* (DAC)

parameterizes actions using a linear filter of past disturbances, thereby yielding a tractable algorithm with bounded regret. In our storage model, however, some DAC policies can produce negative actions or actions larger than the available resource.

We address this issue by introducing *Simplex Disturbance-Action Control* (SDAC). SDAC restricts the filter parameters to a subprobability simplex and includes powers of the retention coefficient in the filter. These choices ensure that every fixed SDAC policy satisfies the action constraint. The state and action components of each fixed-policy trajectory are also affine in the policy parameter. Thus, a convex state–action cost is convex as a function of that parameter. This structure permits the parameter to be updated using online convex optimization.

B. Model and Information Pattern

The storage state $x_t \geq 0$ evolves according to

$$x_{t+1} = \alpha x_t - u_t + w_t,$$

where $\alpha \in (0, 1)$ is a fixed retention coefficient, u_t is the control action, and $w_t \in [0, 1]$ is a nonnegative resource arrival. The action must satisfy

$$0 \leq u_t \leq \alpha x_t.$$

Thus, the controller cannot use more than the amount remaining after storage loss.

At time t , the controller chooses u_t using the current state and the information available through time $t-1$. The arrival w_t and the convex cost function c_t are revealed after the action is selected, and the controller incurs the cost $c_t(x_t, u_t)$. Both the online trajectory and every fixed-policy trajectory used as a benchmark must satisfy the same dynamics and action constraint. The formal model and assumptions are given in Section III.

Energy-harvesting battery management is our main application. In this case, x_t is the battery state of charge, w_t is the harvested energy, u_t is the energy used, and $1-\alpha$ is the fraction of stored energy lost during one period. Similar dynamics arise in perishable inventory systems, water reservoirs with storage loss, and queues with abandonment. In many standard queueing models, $\alpha = 1$; that case is outside our main results and is discussed in Section VIII.

C. Contributions

Our contributions are as follows:

- **Policy class.** We introduce SDAC, a finite-memory policy class parameterized by a subprobability simplex. We

K. Asgari and M. J. Neely are with the Department of Electrical and Computer Engineering, University of Southern California, Los Angeles, CA 90089 USA (e-mail: kamiaras@usc.edu; mjneely@usc.edu).

Corresponding author: K. Asgari.

prove that every fixed SDAC policy is feasible for every arrival sequence with entries in $[0, 1]$.

We further show that SDAC approximates the decreasing-allocation policy class defined in Section IV-C. This class allocates each arrival over future periods according to the same decreasing sequence. It contains every feasible proportional state-feedback policy $u_t = kx_t$, with $k \in [0, \alpha]$, and the approximation error decreases geometrically with the memory horizon H .

- **Online control and regret.** We develop an online SDAC controller that updates its parameter using entropic online mirror descent (OMD) over the subprobability simplex. We prove that the controller remains feasible and achieves

$$O\left(\sqrt{T \log(H+1)}\right)$$

regret against the best fixed SDAC policy. For $H = \Theta(\log T)$, the regret against the decreasing-allocation class is $O(\sqrt{T \log \log T})$. The same bound holds against the best proportional state-feedback policy.

- **Minimax lower bound.** We prove a lower bound of order $\sqrt{T}$ for the expected regret of every causal feasible controller, including randomized controllers; see Theorem 2. When T is at least on the order of $(1 - \alpha)^{-1}$, the lower bound scales as $\Omega((1 - \alpha)^{-1} \sqrt{T})$ near $\alpha = 1$. The upper and lower bounds differ by a factor of $(1 - \alpha)^{-1/2}$ in their dependence on $1 - \alpha$. Closing this gap is left for future work.

D. Related Work

a) *Online nonstochastic control:* Online nonstochastic control studies dynamical systems with adversarial disturbances and costs. Performance is measured by regret against a policy chosen in hindsight, under suitable stability conditions [1], [2]; see [3] for an overview. For known linear systems, Simchowitz et al. establish the optimal $\sqrt{T}$ dependence on the horizon while leaving some dependence on the system's stability parameters unresolved [4]. Related work also considers partial observability [5] and bandit feedback [6].

A central idea in this literature is DAC. A DAC policy combines a stabilizing state-feedback action with a finite linear filter of past disturbances. The action is therefore described by finitely many policy parameters that can be updated using online methods. SDAC uses the same basic idea but restricts the parameters in a way suited to storage systems with nonnegative arrivals.

Online control with affine or more general constraints on states and actions has been studied in [7], [8]. The constraint $u_t \leq \alpha x_t$ is affine in the state and action, but the range of allowed actions depends on the current storage state. Our approach uses the structure of the storage dynamics to ensure that every fixed SDAC policy is feasible and that the online SDAC controller remains feasible while its parameter changes.

Our analysis also considers how regret depends on the retention coefficient α . Kumar et al. study online convex optimization in which past decisions can affect all later costs, and derive bounds that depend on how quickly those effects decay [9]. In their model with geometrically decaying memory,

the lower bound scales as $\sqrt{T}$ divided by one minus the decay factor, paralleling our $\Omega(\sqrt{T}/(1 - \alpha))$ lower bound for sufficiently long horizons; see Remark 1. Our lower bound is proved directly for state-action costs under the state-dependent action constraint.

b) *Energy harvesting:* Several energy-harvesting policies adjust energy use according to the available battery level. Shaviv and Özgür [10] study a policy that uses a fixed fraction of the available energy and prove guarantees under independent and identically distributed (i.i.d.) energy arrivals. Arafa et al. [11] consider more general sequences for spending energy after a recharge. Zibaeenejad and Chen [12] derive a related decreasing spending rule when future arrivals are known in advance.

These works motivate the *decreasing-allocation policy class* defined in this paper. Under such a policy, each arrival is allocated over future periods according to the same decreasing sequence. In our model, this allocation begins one period after the arrival because the controller does not observe the current arrival before choosing the action.

The models in [10]–[12] use random arrivals from a fixed model, reveal the current harvested energy before allocation, and optimize a fixed reward that depends on the allocated power. In our setting, the arrival and cost sequences may be chosen adversarially, the controller acts before observing the current arrival and cost, the cost can depend on both the storage state and the action, and performance is measured by regret against a fixed SDAC policy.

Yu and Neely [13] study expected utility maximization under i.i.d. system states. Asgari and Neely [14] obtain an $O(\sqrt{T})$ regret-battery-capacity tradeoff for arbitrary loss sequences while retaining i.i.d. energy arrivals. Both works use objectives that depend only on the action and compare against a fixed action. Here, the arrivals may be chosen adversarially, the cost depends on the state and action, and the comparator is a fixed SDAC policy rather than a fixed action.

Lin et al. [15] study online age-of-information optimization in an energy-harvesting system with related battery dynamics. They compare their controller with an unrestricted offline optimum using a competitive ratio. Their objective depends on the energy allocation but not directly on the battery state, and the current arrival is observed before the allocation. Our online SDAC controller acts before observing the current arrival, and our benchmark is a fixed SDAC policy chosen in hindsight.

c) *Queueing and network optimization:* Queueing control also involves states that change through arrivals and service decisions. Classical work studies throughput and queue stability [16]–[18], while stochastic network optimization studies tradeoffs between time-average objectives and queue backlog [19]. Our setting instead allows adversarial arrival sequences and convex state-action costs, and measures regret against a fixed SDAC policy chosen in hindsight.

In many queueing models, $\alpha = 1$ because stored packets do not disappear over time. Such models are not direct examples of the $\alpha \in (0, 1)$ system studied here. A queue with abandonment or expiration can have $\alpha < 1$ and is more closely related to our model. Section VIII discusses the case $\alpha \geq 1$.

Khojastepour and Sabharwal [20] study a fixed scheduler that can be written as a linear filter of past arrivals. Their scheduler minimizes average transmit power subject to a maximum-delay guarantee. In contrast, our controller updates its filter parameters online in response to convex state-action costs revealed after each decision.

d) *Inventory and reservoir management*: Yang et al. [21] study online procurement under inventory constraints. Their controller observes the current demand and price and then chooses how much supply to purchase. Performance is measured by a competitive ratio for the total procurement cost. Our online SDAC controller instead chooses how much stored resource to use before observing the current arrival and cost.

Hihat and Fermanian [22] consider inventory systems with more general state-transition functions and study policies that replenish inventory up to a target level. Their model is broader in its transition dynamics, but it has a different decision order and a different policy class. Our scalar linear dynamics allow explicit feasibility, approximation, and regret guarantees.

Classical reservoir models also use storage dynamics with random inflows and controlled releases [23], [24]. That literature mainly studies long-run performance under stochastic inflows. It provides another example of control under storage constraints, although physical reservoir models may also include capacity and overflow effects that are not part of our main model.

E. Paper Organization

Section III states the storage dynamics, information pattern, cost assumptions, feasible domain, and regret benchmark. Section IV introduces the SDAC policy class and proves its feasibility and convexity properties. It also shows how SDAC approximates decreasing-allocation policies and proportional state-feedback policies. Section V presents the online SDAC controller based on action clipping and entropic OMD. Section VI proves the regret upper bounds and extends them to the larger policy classes. Section VII gives the minimax regret lower bound. Section VIII discusses extensions to $\alpha \geq 1$, vector actions, and multiple storage states. Section IX provides concluding remarks. Appendices A–D contain the deferred proofs, grouped by the section in which the corresponding results are stated or used.

II. NOTATION

For every positive integer n , we write $[n] \triangleq \{1, \dots, n\}$ and $[z]_+ \triangleq \max\{z, 0\}$. For $\mathbf{v} \in \mathbb{R}^n$, the i -th coordinate is denoted by v_i . If the vector already carries a subscript, the coordinate is appended after a comma: the i -th coordinate of $\mathbf{v}_t$ is $v_{t,i}$. We write $\mathbf{1}$ for the all-ones vector, with its dimension clear from context, and $\langle \cdot, \cdot \rangle$ for the Euclidean inner product. We use $\log$ for the natural logarithm and set $w_\tau \equiv 0$ for $\tau \leq 0$.

A fixed SDAC policy with parameter $\mathbf{m}$ is denoted by $\pi_{\mathbf{m}}$. The associated fixed-policy trajectory has state and action components $x_t(\mathbf{m})$ and $u_t(\mathbf{m})$. A feasible proportional state-feedback policy with gain $k \in [0, \alpha]$ induces $x_t(k)$ and $u_t(k)$, while a decreasing allocation sequence $\mathbf{q}$ induces $x_t(\mathbf{q})$ and $u_t(\mathbf{q})$. After the online SDAC controller is introduced, x_t and u_t without arguments denote the online trajectory.

III. MODEL AND REGRET BENCHMARK

Fix a positive integer T and a known retention coefficient $\alpha \in (0, 1)$. The state $x_t \in \mathbb{R}_{\geq 0}$ is the resource level at the beginning of time t . The system starts empty:

$$x_1 = 0. \quad (1)$$

At each time $t \in [T]$, the controller chooses an action $u_t \in \mathbb{R}_{\geq 0}$ satisfying

$$0 \leq u_t \leq \alpha x_t. \quad (2)$$

The system then receives an arrival $w_t \in [0, 1]$ and evolves according to

$$x_{t+1} = \alpha x_t - u_t + w_t. \quad (3)$$

Here, $1 - \alpha$ is the fraction of the stored resource lost during one period. The constraint (2) ensures that the action does not exceed the amount remaining after this loss.

Although w_t is commonly called a disturbance in the online-control literature, we call it an *arrival* because it is nonnegative. We retain the standard names Disturbance-Action Control and Simplex Disturbance-Action Control. The nonnegativity of w_t is important both for the storage interpretation and for the feasibility properties of SDAC.

At time t , the pair (w_t, c_t) may depend on the observations through time $t-1$, but not on the current action or any random choice made by the controller at time t . The controller chooses u_t before observing w_t or c_t . After the action is selected, the arrival and the entire cost function are revealed, the controller incurs $c_t(x_t, u_t)$, and the state is updated according to (3).

For every feasible trajectory,

$$0 \leq x_{t+1} \leq \alpha x_t + 1.$$

Since $x_1 = 0$, induction gives

$$0 \leq x_t \leq \frac{1 - \alpha^{t-1}}{1 - \alpha} \leq \frac{1}{1 - \alpha}, \quad t \in [T + 1].$$

Thus, the storage state is uniformly bounded. In particular, a storage device with capacity $1/(1 - \alpha)$ is sufficient to realize every feasible trajectory without overflow. The state and action constraints imply that every feasible state-action pair belongs to the compact set

$$\mathcal{D}_\alpha \triangleq \left\{ (x, u) : 0 \leq x \leq \frac{1}{1 - \alpha}, 0 \leq u \leq \alpha x \right\}. \quad (4)$$

Each revealed cost function has the form

$$c_t : \mathbb{R}_{\geq 0}^2 \rightarrow \mathbb{R}$$

and is convex in (x, u) . We assume that each c_t satisfies the following Lipschitz condition on $\mathcal{D}_\alpha$: there are constants $L_x, L_u > 0$, independent of t , such that

$$|c_t(x, u) - c_t(x', u')| \leq L_x |x - x'| + L_u |u - u'| \quad (5)$$

for all $(x, u), (x', u') \in \mathcal{D}_\alpha$. We also assume access, at every $(x, u) \in \mathcal{D}_\alpha$, to a cost subgradient

$$\zeta_t(x, u) = (\zeta_t^x(x, u), \zeta_t^u(x, u)) \in \partial c_t(x, u)$$

satisfying

$$|\zeta_t^x(x, u)| \leq L_x, \quad |\zeta_t^u(x, u)| \leq L_u.$$

These subgradient bounds hold, for example, when (5) extends to an open neighborhood of $\mathcal{D}_\alpha$; see [25, Thm. 9.13].

Let $\{(x_t, u_t)\}_{t=1}^T$ denote the trajectory generated by the online controller. Its cumulative cost is

$$J_T^{\text{on}} \triangleq \sum_{t=1}^T c_t(x_t, u_t). \quad (6)$$

Fix a positive integer H , and let $\mathbf{m}$ range over the SDAC parameter set $\mathcal{M}_H$, defined in Section IV. For each $\mathbf{m} \in \mathcal{M}_H$, the *fixed-policy trajectory associated with $\mathbf{m}$* is the unique state-action sequence $\{(x_t(\mathbf{m}), u_t(\mathbf{m}))\}_{t=1}^T$ obtained under the same arrival sequence by holding $\mathbf{m}$ constant at every time and applying $\pi_{\mathbf{m}}$. Precisely, with $w_\tau = 0$ for $\tau \leq 0$, it is defined by

$$\begin{aligned} x_1(\mathbf{m}) &= 0, \\ u_t(\mathbf{m}) &= \sum_{i=1}^H m_i \alpha^i w_{t-i}, \\ x_{t+1}(\mathbf{m}) &= \alpha x_t(\mathbf{m}) - u_t(\mathbf{m}) + w_t, \quad t \in [T]. \end{aligned} \quad (7)$$

Define the cumulative cost of this fixed-policy trajectory by

$$J_T(\mathbf{m}) \triangleq \sum_{t=1}^T c_t(x_t(\mathbf{m}), u_t(\mathbf{m})).$$

Both the online trajectory and every fixed-policy trajectory used as a benchmark are required to satisfy (2) under (3). The regret against the best fixed SDAC policy is defined by

$$\text{Reg}_T^{\text{SDAC}} \triangleq J_T^{\text{on}} - \min_{\mathbf{m} \in \mathcal{M}_H} J_T(\mathbf{m}). \quad (8)$$

The online SDAC controller may update its parameter over time, while the benchmark in (8) is the best fixed SDAC policy chosen in hindsight. Here, fixed means that $\mathbf{m}$ is held constant; the policy's actions still respond to past arrivals. Our objective is to satisfy (2) at every time and achieve sublinear regret.

IV. SIMPLEX DISTURBANCE-ACTION CONTROL (SDAC)

A. From Disturbance-Action Control to SDAC

DAC combines a stabilizing state-feedback term with a finite linear filter of past disturbances. Under standard conditions, this parameterization yields convex surrogate costs and efficient online updates. In our scalar storage model, specializing the baseline feedback term to zero gives the representative form

$$u_t = \sum_{i=1}^H \theta_i w_{t-i}, \quad (9)$$

where H is a positive integer (the memory horizon) and $\theta = (\theta_1, \dots, \theta_H)^\top \in \mathbb{R}^H$ is a linear filter.

For our constrained model, an unrestricted filter does not ensure feasibility: its action can exceed αx_t or become negative. We therefore introduce *Simplex Disturbance-Action Control* (SDAC), which uses a simplex-constrained filter tailored to the storage dynamics. This restriction ensures that every fixed SDAC policy is feasible while preserving convex surrogate costs and tractable online updates.

B. Policy Definition and Structural Properties

Fix a memory horizon $H \in \mathbb{N}_{>0}$. Let

$$\mathcal{M}_H \triangleq \{\mathbf{m} \in \mathbb{R}_{\geq 0}^H : \|\mathbf{m}\|_1 \leq 1\} \quad (10)$$

be the subprobability simplex. For any $\mathbf{m} \in \mathcal{M}_H$, define the policy $\pi_{\mathbf{m}}$ by

$$u_t(\mathbf{m}) \triangleq \sum_{i=1}^H m_i \alpha^i w_{t-i} = \langle \phi_t^u, \mathbf{m} \rangle, \quad (11)$$

where

$$\phi_t^u \triangleq (\alpha w_{t-1}, \alpha^2 w_{t-2}, \dots, \alpha^H w_{t-H})^\top \in \mathbb{R}^H. \quad (12)$$

The state component of the fixed-policy trajectory satisfies

$$x_{t+1}(\mathbf{m}) = \alpha x_t(\mathbf{m}) - u_t(\mathbf{m}) + w_t, \quad x_1(\mathbf{m}) = 0. \quad (13)$$

The SDAC policy class is

$$\Pi_H^{\text{SDAC}} \triangleq \{\pi_{\mathbf{m}} : \mathbf{m} \in \mathcal{M}_H\}. \quad (14)$$

The weights α^i align the arrival filter with the retention coefficient α in (3).

We now establish the two structural properties that make SDAC useful. The induced control action always satisfies the feasibility constraint (2), and the induced cost is convex and Lipschitz in $\mathbf{m}$. Thus, regret minimization against the best fixed SDAC policy is an instance of online convex optimization over the simplex. Both properties follow from an explicit decomposition of the state trajectory that isolates its dependence on $\mathbf{m}$.

Lemma 1 (State decomposition under SDAC). *Fix a positive integer H and $\mathbf{m} \in \mathcal{M}_H$. For each $t \in [T]$, define*

$$r_t(i) \triangleq \sum_{j=1}^i \alpha^{j-1} w_{t-j}, \quad i \in [H], \quad r_t \triangleq \sum_{j=1}^{t-1} \alpha^{j-1} w_{t-j}.$$

Then the state component of the fixed-policy trajectory satisfies, for every $t \in [T]$,

$$x_t(\mathbf{m}) = \sum_{i=1}^H m_i r_t(i) + \left(1 - \sum_{i=1}^H m_i\right) r_t. \quad (15)$$

Equivalently, define

$$\phi_t^x \triangleq (r_t(1) - r_t, \dots, r_t(H) - r_t)^\top.$$

Then

$$x_t(\mathbf{m}) = r_t + \langle \phi_t^x, \mathbf{m} \rangle.$$

Moreover,

$$0 \leq r_t(i) \leq r_t \leq \frac{1}{1 - \alpha},$$

for every $t \in [T]$ and $i \in [H]$. Consequently, $\mathbf{m} \mapsto x_t(\mathbf{m})$ is affine for every $t \in [T]$.

The proof is given in Appendix A.

The first consequence of this decomposition is that every fixed SDAC policy is feasible.

Lemma 2 (Feasibility of SDAC policies). *For every $\mathbf{m} \in \mathcal{M}_H$, the fixed-policy trajectory defined by (11) and (13) satisfies the action constraint (2). Explicitly,*

$$0 \leq u_t(\mathbf{m}) \leq \alpha x_t(\mathbf{m}) \quad \text{for all } t \in [T]. \quad (16)$$

Proof. Because m_i , α , and w_{t-i} are nonnegative,

$$u_t(\mathbf{m}) = \sum_{i=1}^H m_i \alpha^i w_{t-i} \geq 0.$$

For every $i \in \{1, \dots, H\}$,

$$\alpha r_t(i) = \sum_{j=1}^i \alpha^j w_{t-j} \geq \alpha^i w_{t-i}. \quad (17)$$

Because $\mathbf{m} \in \mathcal{M}_H$ and $r_t \geq 0$ by Lemma 1,

$$\begin{aligned} \alpha x_t(\mathbf{m}) &= \sum_{i=1}^H m_i \alpha r_t(i) + \alpha \left(1 - \sum_{i=1}^H m_i\right) r_t \\ &\geq \sum_{i=1}^H m_i \alpha r_t(i) \\ &\geq \sum_{i=1}^H m_i \alpha^i w_{t-i} = u_t(\mathbf{m}), \end{aligned} \quad (18)$$

where the second inequality uses (17). $\square$

For any realized arrival history, both components of the fixed-policy trajectory are affine in $\mathbf{m}$. The following lemma records the resulting convexity and the constants used by the online update.

Lemma 3 (Convexity and Lipschitz continuity of surrogate cost). *Define*

$$\ell_t(\mathbf{m}) \triangleq c_t(x_t(\mathbf{m}), u_t(\mathbf{m})), \quad \mathbf{m} \in \mathcal{M}_H,$$

and

$$G_\alpha \triangleq \alpha \left(\frac{L_x}{1-\alpha} + L_u \right). \quad (19)$$

Then ℓ_t is convex on $\mathcal{M}_H$, and, for all $\mathbf{m}, \mathbf{m}' \in \mathcal{M}_H$,

$$|\ell_t(\mathbf{m}) - \ell_t(\mathbf{m}')| \leq G_\alpha \|\mathbf{m} - \mathbf{m}'\|_1.$$

Moreover, at every $\mathbf{m} \in \mathcal{M}_H$, one can select $\mathbf{g}_t \in \partial \ell_t(\mathbf{m})$ such that $\|\mathbf{g}_t\|_\infty \leq G_\alpha$.

For the online update, let (ζ_t^x, ζ_t^u) be the bounded cost subgradient at the state-action pair of the fixed-policy trajectory associated with $\mathbf{m}$ and use the explicit choice

$$\mathbf{g}_t = \zeta_t^x \phi_t^x + \zeta_t^u \phi_t^u.$$

This choice belongs to $\partial \ell_t(\mathbf{m})$ and satisfies $\|\mathbf{g}_t\|_\infty \leq G_\alpha$, as stated in Lemma 3. The proof is given in Appendix A.

C. Approximation of Decreasing-Allocation Policies

We next show that finite-memory SDAC policies approximate a class of policies that spread each resource arrival over all subsequent periods. Given a fixed decreasing sequence $(q_i)_{i \geq 1}$, an arrival w_τ contributes $q_i w_\tau$ to the expenditure at time $\tau + i$. The one-period delay reflects that w_τ is observed only after u_τ is chosen. Such allocation-sequence policies have been studied for Bernoulli recharges [11], [12].

Define the set of feasible decreasing allocation sequences

$$\mathcal{Q}_\alpha \triangleq \left\{ \mathbf{q} = (q_i)_{i \geq 1} : q_1 \geq q_2 \geq \dots \geq 0, \sum_{i=1}^{\infty} \frac{q_i}{\alpha^i} \leq 1 \right\}. \quad (20)$$

For $\mathbf{q} \in \mathcal{Q}_\alpha$, define

$$u_t(\mathbf{q}) \triangleq \sum_{i=1}^{t-1} q_i w_{t-i}, \quad (21)$$

$$x_{t+1}(\mathbf{q}) = \alpha x_t(\mathbf{q}) - u_t(\mathbf{q}) + w_t, \quad x_1(\mathbf{q}) = 0.$$

Here, $q_i w_s$ is the amount from arrival w_s allocated i periods later. The weighted budget in (20) accounts for leakage: reserving q_i units for expenditure i periods after an arrival requires q_i / α^i units at the arrival time. Let

$$\Pi_\alpha^{\text{alloc}} \triangleq \{\pi_{\mathbf{q}} : \mathbf{q} \in \mathcal{Q}_\alpha\}.$$

Lemma 4 (Finite-memory approximation of decreasing-allocation policies). *Every policy in $\Pi_\alpha^{\text{alloc}}$ is feasible. Fix $\mathbf{q} \in \mathcal{Q}_\alpha$ and $H \geq 1$, and define*

$$m_{H,i}(\mathbf{q}) \triangleq \frac{q_i}{\alpha^i}, \quad i \in [H]. \quad (22)$$

Then $\mathbf{m}_H(\mathbf{q}) \in \mathcal{M}_H$. With

$$\text{Tail}_H(\mathbf{q}) \triangleq \sum_{i=H+1}^{\infty} q_i,$$

the corresponding trajectories satisfy, for every arrival sequence in $[0, 1]$,

$$0 \leq u_t(\mathbf{q}) - u_t(\mathbf{m}_H(\mathbf{q})) \leq \text{Tail}_H(\mathbf{q}), \quad (23)$$

$$0 \leq x_t(\mathbf{m}_H(\mathbf{q})) - x_t(\mathbf{q}) \leq \frac{\text{Tail}_H(\mathbf{q})}{1-\alpha}. \quad (24)$$

If each c_t satisfies (5), then

$$\begin{aligned} &\left| \sum_{t=1}^T [c_t(x_t(\mathbf{m}_H(\mathbf{q})), u_t(\mathbf{m}_H(\mathbf{q}))) - c_t(x_t(\mathbf{q}), u_t(\mathbf{q}))] \right| \\ &\leq \left(L_u + \frac{L_x}{1-\alpha} \right) \text{Tail}_H(\mathbf{q}) T \\ &\leq \left(L_u + \frac{L_x}{1-\alpha} \right) \alpha^{H+1} T. \end{aligned} \quad (25)$$

Corollary 1 (Proportional state feedback as a geometric allocation). *Fix $k \in [0, \alpha]$, set $\lambda_k \triangleq \alpha - k$, and define*

$$q_i(k) = k \lambda_k^{i-1}, \quad i \geq 1, \quad (26)$$

where $\lambda_k^0 \triangleq 1$. Then $\mathbf{q}(k) \in \mathcal{Q}_\alpha$ and $\pi_{\mathbf{q}(k)}$ is exactly the feasible proportional state-feedback policy $u_t(k) = k x_t(k)$. Its SDAC truncation is

$$\mathbf{m}_H^{\text{prop}}(k) \triangleq \mathbf{m}_H(\mathbf{q}(k)),$$

with coordinates

$$m_{H,i}(\mathbf{q}(k)) = \frac{k\lambda_k^{i-1}}{\alpha^i}, \quad i \in [H],$$

and its tail is

$$\text{Tail}_H(\mathbf{q}(k)) = \frac{k\lambda_k^H}{1 - \lambda_k}.$$

Therefore, (25) specializes to

$$\begin{aligned} & \left| \sum_{t=1}^T [c_t(x_t(\mathbf{m}_H^{\text{prop}}(k)), u_t(\mathbf{m}_H^{\text{prop}}(k))) - c_t(x_t(k), u_t(k))] \right| \\ & \leq \left(L_u + \frac{L_x}{1 - \alpha} \right) \frac{k\lambda_k^H}{1 - \lambda_k} T. \end{aligned} \quad (27)$$

The proofs of Lemma 4 and Corollary 1 are given in Appendix A.

Thus, $\Pi_\alpha^{\text{alloc}}$ contains every feasible proportional state-feedback policy. Together with Theorem 1, the tail bound in (25) yields a no-regret guarantee against $\Pi_\alpha^{\text{alloc}}$ and, consequently, against feasible proportional state-feedback policies.

V. ONLINE SDAC CONTROLLER

We now present our online SDAC controller. It updates its parameter over the subprobability simplex $\mathcal{M}_H \subset \mathbb{R}^H$ using OMD with unnormalized negentropy (equivalently, the exponentiated-gradient method) and a fixed step size $\eta > 0$ [26]. Let

$$\Psi(\mathbf{m}) \triangleq \sum_{i=1}^H (m_i \log m_i - m_i), \quad \mathbf{m} \in \mathbb{R}_{\geq 0}^H, \quad (28)$$

denote the unnormalized negentropy (with the convention $0 \log 0 \triangleq 0$). Its Bregman divergence is the generalized Kullback–Leibler divergence

$$D_\Psi(\mathbf{m} \parallel \mathbf{v}) \triangleq \sum_{i=1}^H \left(m_i \log \frac{m_i}{v_i} - m_i + v_i \right), \quad (29)$$

defined for

$$\mathbf{m} \in \mathbb{R}_{\geq 0}^H, \quad \mathbf{v} \in \mathbb{R}_{> 0}^H.$$

For each time $t \in [T]$, let $\mathbf{m}_t \in \mathcal{M}_H$ be the online parameter. We initialize at

$$\mathbf{m}_1 \triangleq \frac{1}{H+1} \mathbf{1} \quad (30)$$

so that $\sup_{\mathbf{m} \in \mathcal{M}_H} D_\Psi(\mathbf{m} \parallel \mathbf{m}_1) \leq \log(H+1)$ (see the proof of Theorem 1).

a) *Control-action selection:* At the start of round t , the controller has the current online parameter $\mathbf{m}_t$. For $t = 1$, it is given by the initialization (30), and for $t \geq 2$, it is the output of the OMD update (33) from round $t-1$. The controller then forms the nominal SDAC action

$$\hat{u}_t \triangleq \langle \phi_t^u, \mathbf{m}_t \rangle, \quad (31)$$

and clips it to the admissible interval in (2):

$$u_t \triangleq \min\{\hat{u}_t, \alpha x_t\}. \quad (32)$$

The state then evolves according to (3). Because $\hat{u}_t \geq 0$, the clipping rule and induction on (3), starting from (1) with $w_t \in [0, 1]$, give $x_t \geq 0$ for all $t \in [T+1]$. Thus, the online trajectory satisfies (2).

The clipping step also has a geometric interpretation. We use $\mathbf{m}_t^{\text{exec}}$ to denote the execution vector obtained by projecting $\mathbf{m}_t$ onto the parameters compatible with the current state x_t , using the negentropy Bregman divergence. Lemma 6 formalizes this projection and shows that $\mathbf{m}_t^{\text{exec}}$ induces exactly the clipped action u_t .

b) *Surrogate cost and OMD update:* After observing (w_t, c_t) , choose $\mathbf{g}_t \in \partial \ell_t(\mathbf{m}_t)$. We define the OMD update

$$\mathbf{m}_{t+1} \triangleq \arg \min_{\mathbf{m} \in \mathcal{M}_H} \{ \eta \langle \mathbf{g}_t, \mathbf{m} \rangle + D_\Psi(\mathbf{m} \parallel \mathbf{m}_t) \}. \quad (33)$$

By Lemma 8, the minimizer in (33) is obtained in two steps. First, apply the multiplicative step,

$$\tilde{\mathbf{m}}_{t+1,i} \triangleq m_{t,i} \exp(-\eta g_{t,i}), \quad i \in [H], \quad (34)$$

where $g_{t,i}$ is the i -th coordinate of $\mathbf{g}_t$. Next, apply the Bregman projection onto $\mathcal{M}_H$:

$$\mathbf{m}_{t+1} \triangleq \text{Proj}_{\mathcal{M}_H}^\Psi(\tilde{\mathbf{m}}_{t+1}) = \frac{\tilde{\mathbf{m}}_{t+1}}{\max\{1, \|\tilde{\mathbf{m}}_{t+1}\|_1\}}, \quad (35)$$

where the projection operator is defined and derived in Lemma 7 of Appendix B.

VI. REGRET UPPER BOUNDS

The following theorem states that the online SDAC controller achieves sublinear regret relative to every fixed SDAC policy $\pi_{\mathbf{m}} \in \Pi_H^{\text{SDAC}}$. The proof combines a standard online convex optimization bound for the surrogate costs ℓ_t with the stability bound under online parameter updates stated below. The complete proofs are deferred to Appendix C.

Theorem 1 (Regret against fixed SDAC policies). *Suppose the cost functions satisfy the regularity and bounded-subgradient assumptions of Section III. Then the controller from Section V, initialized as in (30) and using step size $\eta > 0$, satisfies, for the regret defined in (8),*

$$\text{Reg}_T^{\text{SDAC}} \leq \frac{\log(H+1)}{\eta} + \eta T \Gamma_\alpha, \quad (36)$$

where

$$\Gamma_\alpha \triangleq \frac{G_\alpha^2}{2} + \frac{\alpha G_\alpha (L_x + \alpha L_u)}{(1 - \alpha)^2}, \quad (37)$$

and $G_\alpha = \alpha \left(\frac{L_x}{1 - \alpha} + L_u \right)$ as in (19). In particular, the choice

$$\eta^* = \sqrt{\frac{\log(H+1)}{T \Gamma_\alpha}}$$

gives

$$\text{Reg}_T^{\text{SDAC}} \leq 2\sqrt{\Gamma_\alpha T \log(H+1)}.$$

For fixed $L_x, L_u > 0$, the leading factor obeys

$$\sqrt{\Gamma_\alpha} = \Theta(\alpha) \quad \text{as } \alpha \downarrow 0,$$

and

$$\sqrt{\Gamma_\alpha} = \Theta\left((1 - \alpha)^{-3/2}\right) \quad \text{as } \alpha \uparrow 1.$$

The nonstandard step is to control the difference between the realized online trajectory and the fixed-policy trajectory associated with the current online parameter $\mathbf{m}_t$.

Lemma 5 (Stability under online parameter updates). *For the online trajectory and the fixed-policy trajectory associated with the current online parameter $\mathbf{m}_t$, one has, for every $t \in [T]$,*

$$|x_t - x_t(\mathbf{m}_t)| \leq \frac{\alpha\eta G_\alpha}{(1-\alpha)^2}, \quad (38)$$

$$0 \leq u_t(\mathbf{m}_t) - u_t \leq \frac{\alpha^2\eta G_\alpha}{(1-\alpha)^2}. \quad (39)$$

By definition of the fixed-policy trajectory, $x_t(\mathbf{m}_t)$ is generated by holding $\mathbf{m}_t$ constant from time 1 through time t . Consequently,

$$\sum_{t=1}^T (c_t(x_t, u_t) - \ell_t(\mathbf{m}_t)) \leq \frac{\alpha\eta T G_\alpha (L_x + \alpha L_u)}{(1-\alpha)^2}. \quad (40)$$

The proof of Lemma 5 is given in Appendix C. The proof of Theorem 1 then has three steps. First, the OMD bound for the surrogate costs gives

$$\sum_{t=1}^T \ell_t(\mathbf{m}_t) - \min_{\mathbf{m} \in \mathcal{M}_H} \sum_{t=1}^T \ell_t(\mathbf{m}) \leq \frac{\log(H+1)}{\eta} + \frac{\eta G_\alpha^2 T}{2}.$$

Second, (40) controls the difference between the realized and surrogate costs. Third, adding the two bounds and using (37) gives (36); optimizing over η gives the stated choice η^* .

Theorem 1 and Lemma 4 give the following comparator guarantee.

Corollary 2 (No-regret against decreasing-allocation policies). *Set*

$$H_T \triangleq \max \left\{ 1, \left\lceil \frac{\log T}{\log(1/\alpha)} \right\rceil \right\},$$

and run the online SDAC controller with action clipping, memory horizon $H = H_T$, and the step size η^ of Theorem 1. For $\mathbf{q} \in \mathcal{Q}_\alpha$, let*

$$J_T(\mathbf{q}) \triangleq \sum_{t=1}^T c_t(x_t(\mathbf{q}), u_t(\mathbf{q}))$$

and

$$\text{Reg}_T^{\text{alloc}} \triangleq J_T^{\text{on}} - \inf_{\mathbf{q} \in \mathcal{Q}_\alpha} J_T(\mathbf{q}).$$

Then

$$\begin{aligned} \text{Reg}_T^{\text{alloc}} &\leq 2\sqrt{\Gamma_\alpha T \log(H_T + 1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha} \right) \alpha^{H_T+1} T. \end{aligned} \quad (41)$$

Here Γ_α is defined in (37). Since $\alpha^{H_T} \leq 1/T$ and $\log(H_T + 1) = O(\log \log T)$ as $T \rightarrow \infty$, the approximation term is $O(1)$. Consequently,

$$\text{Reg}_T^{\text{alloc}} = O\left(\sqrt{T \log \log T}\right) = o(T).$$

Because geometric allocation sequences induce proportional state feedback, the controller also satisfies a gain-dependent bound for that policy family.

Corollary 3 (No-regret against proportional state-feedback policies). *Run the online SDAC controller in Corollary 2. For $k \in [0, \alpha]$, let $J_T(k) \triangleq \sum_{t=1}^T c_t(x_t(k), u_t(k))$, where $u_t(k) = kx_t(k)$, and define*

$$\text{Reg}_T^{\text{prop}} \triangleq J_T^{\text{on}} - \min_{k \in [0, \alpha]} J_T(k).$$

For every $k \in [0, \alpha]$, with $\lambda_k = \alpha - k$,

$$\begin{aligned} J_T^{\text{on}} - J_T(k) &\leq 2\sqrt{\Gamma_\alpha T \log(H_T + 1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha} \right) \frac{k\lambda_k^{H_T}}{1-\lambda_k} T. \end{aligned} \quad (42)$$

Moreover,

$$\begin{aligned} \text{Reg}_T^{\text{prop}} &\leq 2\sqrt{\Gamma_\alpha T \log(H_T + 1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha} \right) \alpha^{H_T+1} T \\ &= O\left(\sqrt{T \log \log T}\right) = o(T). \end{aligned}$$

The proofs of Corollaries 2 and 3 are given in Appendix C.

VII. MINIMAX REGRET LOWER BOUND

The next result shows that the $\sqrt{T}$ dependence is unavoidable and quantifies the necessary dependence on $1-\alpha$ for any causal feasible controller. Its proof is deferred to Appendix D.

Theorem 2 (Minimax SDAC regret lower bound). *Fix $H \geq 1$ and $T \geq 2$. For every causal feasible online controller $\mathcal{A}$, possibly randomized, there exists a deterministic oblivious sequence of arrivals and costs satisfying the assumptions of Section III such that*

$$\mathbb{E}_{\mathcal{A}}[\text{Reg}_T^{\text{SDAC}}] \geq \frac{1}{2\sqrt{2}} \sqrt{\sum_{t=2}^T \beta_t^2}, \quad (43)$$

where

$$\beta_t \triangleq \alpha \left(L_u + \frac{L_x(1-\alpha^{t-2})}{1-\alpha} \right). \quad (44)$$

The expectation is only over the internal randomization of $\mathcal{A}$; the adversarial sequence is deterministic and fixed before the interaction.

Corollary 4 (Lower bound beyond the mixing time). *Define*

$$t_{\text{mix}}(\alpha) \triangleq \left\lceil \frac{\log 2}{\log(1/\alpha)} \right\rceil. \quad (45)$$

If $T \geq 2t_{\text{mix}}(\alpha) + 2$, then every causal feasible controller $\mathcal{A}$ admits a deterministic oblivious sequence for which

$$\mathbb{E}_{\mathcal{A}}[\text{Reg}_T^{\text{SDAC}}] \geq \frac{G_\alpha}{8} \sqrt{T}, \quad (46)$$

where $G_\alpha = \alpha(L_x/(1-\alpha) + L_u)$ as in (19).

Remark 1 (Large- α regime). As $\alpha \uparrow 1$, stored arrivals persist longer and $t_{\text{mix}}(\alpha) = \Theta((1-\alpha)^{-1})$. Hence, Corollary 4 yields

$$\mathbb{E}_{\mathcal{A}}[\text{Reg}_T^{\text{SDAC}}] = \Omega\left(\frac{\sqrt{T}}{1-\alpha}\right) \quad (47)$$

whenever $T \geq 2t_{\text{mix}}(\alpha) + 2$. The upper bound in Theorem 1 is $O((1 - \alpha)^{-3/2} \sqrt{T \log(H+1)})$, leaving a factor of $(1 - \alpha)^{-1/2}$ between the two bounds.

The condition $T \geq 2t_{\text{mix}}(\alpha) + 2$ is essential for interpreting the large- α asymptotic. If T is fixed while $\alpha \uparrow 1$, then

$$\frac{1 - \alpha^{t-2}}{1 - \alpha} \rightarrow t - 2,$$

and the right-hand side of (43) converges to the finite quantity

$$\frac{1}{2\sqrt{2}} \sqrt{\sum_{t=2}^T (L_u + L_x(t-2))^2}.$$

Thus, for fixed T , the exact finite-horizon bound in (43) applies instead of the long-horizon scaling in (47).

VIII. DISCUSSION AND EXTENSIONS

We briefly discuss three extensions. In each case, the feasibility, convexity, and stability arguments used above continue to apply after the corresponding changes to the policy domain and the Lipschitz constants. We state these changes but omit the resulting regret bounds, whose form is unchanged up to the modified constants and, in the vector settings, the chosen product norm.

a) Retention $\alpha \geq 1$: For $\alpha \geq 1$, fix k such that $\bar{\alpha} \triangleq \alpha - k \in (0, 1)$ and write $u_t = kx_t + v_t$. Then

$$x_{t+1} = \bar{\alpha}x_t - v_t + w_t.$$

An SDAC filter for v_t uses the powers $\bar{\alpha}^i$. If $0 \leq v_t \leq \bar{\alpha}x_t$, then

$$kx_t \leq u_t = kx_t + v_t \leq (k + \bar{\alpha})x_t = \alpha x_t,$$

so the original feasibility constraint (2) is satisfied. Since

$$x_{t+1} \leq \bar{\alpha}x_t + 1, \quad x_1 = 0,$$

induction gives $x_t \leq 1/(1 - \bar{\alpha})$. The transformed cost $c_t(x, kx + v)$ remains convex in (x, v) . Thus the analysis applies when the costs satisfy the corresponding Lipschitz and bounded-subgradient assumptions on the bounded domain

$$0 \leq x \leq \frac{1}{1 - \bar{\alpha}}, \quad kx \leq u \leq \alpha x.$$

For a fixed k , the comparator class is correspondingly restricted to policies whose actions satisfy $u_t \geq kx_t$. Selecting k , either in advance or online, remains an interesting direction for future work.

b) Vector actions and multi-task allocation: Consider a single storage state x_t with a vector action $\mathbf{u}_t \in \mathbb{R}_{\geq 0}^n$ that allocates resources across n tasks, subject to $\sum_{a=1}^n u_{t,a} \leq \alpha x_t$. Thus, the total drain from storage is the sum of the task allocations. The dynamics remain $x_{t+1} = \alpha x_t - \sum_{a=1}^n u_{t,a} + w_t$, and the cost $c_t(x_t, \mathbf{u}_t)$ is convex in $(x, \mathbf{u})$. Replace $\mathbf{m} \in \mathcal{M}_H$ with a matrix $\mathbf{M} \in \mathbb{R}_{\geq 0}^{n \times H}$ satisfying

$$\sum_{a=1}^n \sum_{i=1}^H M_{a,i} \leq 1, \quad u_{t,a}(\mathbf{M}) = \sum_{i=1}^H M_{a,i} \alpha^i w_{t-i}.$$

Set $m_i = \sum_{a=1}^n M_{a,i}$. Then

$$m_i \geq 0, \quad \sum_{i=1}^H m_i = \sum_{a=1}^n \sum_{i=1}^H M_{a,i} \leq 1,$$

so $\mathbf{m} \in \mathcal{M}_H$. Moreover,

$$\sum_{a=1}^n u_{t,a}(\mathbf{M}) = \sum_{i=1}^H m_i \alpha^i w_{t-i} \leq \alpha x_t(\mathbf{M}),$$

where the inequality is the scalar SDAC feasibility bound. Both the state and vector action are affine in $\mathbf{M}$. Therefore,

$$c_t(x_t(\mathbf{M}), \mathbf{u}_t(\mathbf{M}))$$

is convex in $\mathbf{M}$. For the online SDAC controller, a nominal vector that exceeds the available total resource can be scaled proportionally so that its entries remain nonnegative and sum to αx_t . Under an ℓ_1 Lipschitz bound in the action, the size of this correction equals the excess total action, and the stability proof proceeds with the corresponding matrix norm. OMD then runs over the matrix subprobability simplex above.

c) Multiple storage states with diagonal dynamics: Suppose the state is $\mathbf{x}_t \in \mathbb{R}_{\geq 0}^d$ and evolves according to $\mathbf{x}_{t+1} = \mathbf{A}\mathbf{x}_t - \mathbf{u}_t + \mathbf{w}_t$, where $\mathbf{A} = \text{diag}(\alpha_1, \dots, \alpha_d)$, $\alpha_s \in (0, 1)$ for $s \in [d]$, the arrivals satisfy $\mathbf{w}_t \in [0, 1]^d$, and the per-storage constraints are $0 \leq u_{t,s} \leq \alpha_s x_{t,s}$. Assign one SDAC parameter in $\mathcal{M}_H$ to each storage and use the powers α_s^i in coordinate s . The dynamics and feasibility constraints then decouple by storage, and the SDAC parameter domain is a product of subprobability simplices, with $x_{t,s} \leq 1/(1 - \alpha_s)$ for every $s \in [d]$. The online SDAC controller clips each nominal action to $\alpha_s x_{t,s}$. If the cost is jointly convex and satisfies compatible Lipschitz and bounded-subgradient assumptions on the resulting bounded product domain, the surrogate cost is jointly convex in all SDAC parameters and OMD applies on the product set. The update separates by storage only when the cost is coordinate-separable; otherwise it is a joint update. Cross-coupled storage systems (nondiagonal $\mathbf{A}$) require additional analysis and remain an interesting direction for future work.

IX. CONCLUSION

We studied adversarial online control of a storage system under a state-dependent action constraint. We introduced SDAC so that every fixed-policy trajectory is feasible and developed an online SDAC controller with $O(\sqrt{T \log(H+1)})$ regret against the best fixed SDAC policy. Once T is at least on the order of $(1 - \alpha)^{-1}$, the minimax lower bound gives $\Omega((1 - \alpha)^{-1} \sqrt{T})$ regret as $\alpha \uparrow 1$; hence, a factor of $(1 - \alpha)^{-1/2}$ between the upper and lower bounds remains open. The SDAC approximation results further give $O(\sqrt{T \log \log T})$ regret against the best decreasing-allocation policy when $H = \Theta(\log T)$. The model applies directly to energy-harvesting battery management and related settings in which storage limits must be respected in real time.

APPENDIX A

PROOFS FOR SIMPLEX DISTURBANCE-ACTION CONTROL

We collect the deferred proofs of the structural and approximation results from Section IV.

Proof of Lemma 1. The auxiliary quantities satisfy

$$r_{t+1} = \alpha r_t + w_t, \quad r_1 = 0, \quad (48)$$

and, for every $i \in \{1, \dots, H\}$,

$$\begin{aligned} \alpha r_t(i) - \alpha^i w_{t-i} &= \sum_{j=1}^{i-1} \alpha^j w_{t-j} \\ &= r_{t+1}(i) - w_t. \end{aligned} \quad (49)$$

For $i = 1$, the sum in the first line is empty.

At $t = 1$, since $w_\tau \equiv 0$ for $\tau \leq 0$,

$$\begin{aligned} r_1(i) &= \sum_{j=1}^i \alpha^{j-1} w_{1-j} = 0, \\ r_1 &= 0, \\ x_1(\mathbf{m}) &= 0, \end{aligned}$$

so (15) holds. Suppose it holds at time t . Using (13) and (11),

$$\begin{aligned} x_{t+1}(\mathbf{m}) &= \alpha \left(\sum_{i=1}^H m_i r_t(i) + \left(1 - \sum_{i=1}^H m_i\right) r_t \right) \\ &\quad - \sum_{i=1}^H m_i \alpha^i w_{t-i} + w_t \\ &= \sum_{i=1}^H m_i (\alpha r_t(i) - \alpha^i w_{t-i}) \\ &\quad + \alpha \left(1 - \sum_{i=1}^H m_i\right) r_t + w_t. \end{aligned} \quad (50)$$

Substituting (48) and (49) into (50),

$$\begin{aligned} x_{t+1}(\mathbf{m}) &= \sum_{i=1}^H m_i (r_{t+1}(i) - w_t) \\ &\quad + \left(1 - \sum_{i=1}^H m_i\right) (r_{t+1} - w_t) + w_t \\ &= \sum_{i=1}^H m_i r_{t+1}(i) + \left(1 - \sum_{i=1}^H m_i\right) r_{t+1}, \end{aligned} \quad (51)$$

The total coefficient of w_t in the first line is

$$-\sum_{i=1}^H m_i - \left(1 - \sum_{i=1}^H m_i\right) + 1 = 0.$$

Therefore, (15) follows by induction.

All summands defining $r_t(i)$ and r_t are nonnegative. Since $w_\tau = 0$ for $\tau \leq 0$, $r_t(i)$ is a truncation of r_t ; hence

$$0 \leq r_t(i) \leq r_t \leq \sum_{j=1}^{\infty} \alpha^{j-1} = \frac{1}{1-\alpha}.$$

Finally,

$$x_t(\mathbf{m}) = r_t + \sum_{i=1}^H m_i (r_t(i) - r_t) = r_t + \langle \phi_t^x, \mathbf{m} \rangle,$$

which is affine in $\mathbf{m}$. $\square$

Proof of Lemma 3. Lemma 1 and (11) give

$$x_t(\mathbf{m}) = r_t + \langle \phi_t^x, \mathbf{m} \rangle, \quad u_t(\mathbf{m}) = \langle \phi_t^u, \mathbf{m} \rangle. \quad (52)$$

For every $i \in \{1, \dots, H\}$, the definitions of $r_t(i)$ and r_t give

$$\begin{aligned} \phi_{t,i}^x &= r_t(i) - r_t \\ &= - \sum_{j=i+1}^{t-1} \alpha^{j-1} w_{t-j}, \end{aligned} \quad (53)$$

where the sum is empty when $i \geq t-1$. Hence

$$\begin{aligned} |\phi_{t,i}^x| &\leq \sum_{j=i+1}^{\infty} \alpha^{j-1} = \frac{\alpha^i}{1-\alpha}, \\ 0 \leq \phi_{t,i}^u &= \alpha^i w_{t-i} \leq \alpha^i. \end{aligned} \quad (54)$$

Taking the maximum over the coordinates and noting that both upper bounds are largest at $i = 1$ yields

$$\|\phi_t^x\|_{\infty} \leq \frac{\alpha}{1-\alpha}, \quad \|\phi_t^u\|_{\infty} \leq \alpha. \quad (55)$$

Since the state-action pair in (52) is affine in $\mathbf{m}$ and c_t is convex, ℓ_t is convex.

By (5) and (52),

$$\begin{aligned} |\ell_t(\mathbf{m}) - \ell_t(\mathbf{m}')| &\leq L_x |\langle \phi_t^x, \mathbf{m} - \mathbf{m}' \rangle| + L_u |\langle \phi_t^u, \mathbf{m} - \mathbf{m}' \rangle| \\ &\leq (L_x \|\phi_t^x\|_{\infty} + L_u \|\phi_t^u\|_{\infty}) \|\mathbf{m} - \mathbf{m}'\|_1 \\ &\leq \alpha \left(\frac{L_x}{1-\alpha} + L_u \right) \|\mathbf{m} - \mathbf{m}'\|_1 \\ &= G_{\alpha} \|\mathbf{m} - \mathbf{m}'\|_1. \end{aligned} \quad (56)$$

Let (ζ_t^x, ζ_t^u) denote the components of the bounded subgradient $\zeta_t(x_t(\mathbf{m}), u_t(\mathbf{m}))$ from Section III, and set

$$\mathbf{g}_t \triangleq \zeta_t^x \phi_t^x + \zeta_t^u \phi_t^u. \quad (57)$$

For every $\mathbf{m}' \in \mathcal{M}_H$, the subgradient inequality and (52) yield

$$\begin{aligned} \ell_t(\mathbf{m}') &\geq \ell_t(\mathbf{m}) + \zeta_t^x \langle \phi_t^x, \mathbf{m}' - \mathbf{m} \rangle + \zeta_t^u \langle \phi_t^u, \mathbf{m}' - \mathbf{m} \rangle \\ &= \ell_t(\mathbf{m}) + \langle \mathbf{g}_t, \mathbf{m}' - \mathbf{m} \rangle. \end{aligned}$$

Thus $\mathbf{g}_t \in \partial \ell_t(\mathbf{m})$. For each $i \in \{1, \dots, H\}$, the exact coordinate decay in (54) gives

$$\begin{aligned} |g_{t,i}| &\leq |\zeta_t^x| |\phi_{t,i}^x| + |\zeta_t^u| \phi_{t,i}^u \\ &\leq \alpha^i \left(\frac{L_x}{1-\alpha} + L_u \right) \\ &\leq \alpha \left(\frac{L_x}{1-\alpha} + L_u \right) = G_{\alpha}. \end{aligned} \quad (58)$$

Taking the maximum over i proves

$$\|\mathbf{g}_t\|_{\infty} \leq G_{\alpha}. \quad (59)$$

$\square$

Proof of Lemma 4. Fix $\mathbf{q} \in \mathcal{Q}_\alpha$ and set

$$a_i \triangleq \frac{q_i}{\alpha^i}, \quad b_j \triangleq 1 - \sum_{i=1}^{j-1} a_i, \quad j \geq 1.$$

The weighted-budget constraint gives $a_i \geq 0$ and $b_j \geq 0$. We first show that

$$x_t(\mathbf{q}) = \sum_{j=1}^{t-1} \alpha^{j-1} b_j w_{t-j}. \quad (60)$$

The identity is immediate at $t = 1$. If it holds at time t , then

$$\begin{aligned} x_{t+1}(\mathbf{q}) &= w_t + \sum_{j=1}^{t-1} (\alpha^j b_j - q_j) w_{t-j} \\ &= w_t + \sum_{j=1}^{t-1} \alpha^j b_{j+1} w_{t-j}, \end{aligned}$$

because $q_j = \alpha^j a_j$ and $b_{j+1} = b_j - a_j$. Reindexing gives (60) at time $t + 1$.

For each $j \geq 1$,

$$a_j \leq 1 - \sum_{i=1}^{j-1} a_i = b_j.$$

Consequently,

$$\begin{aligned} 0 \leq u_t(\mathbf{q}) &= \sum_{j=1}^{t-1} \alpha^j a_j w_{t-j} \\ &\leq \sum_{j=1}^{t-1} \alpha^j b_j w_{t-j} = \alpha x_t(\mathbf{q}), \end{aligned}$$

which proves (2) for the decreasing-allocation policy.

For the truncated vector in (22),

$$m_{H,i}(\mathbf{q}) = a_i \geq 0, \quad \sum_{i=1}^H m_{H,i}(\mathbf{q}) \leq \sum_{i=1}^\infty a_i \leq 1.$$

Thus, $\mathbf{m}_H(\mathbf{q}) \in \mathcal{M}_H$. Its SDAC action is

$$u_t(\mathbf{m}_H(\mathbf{q})) = \sum_{i=1}^{\min\{H, t-1\}} q_i w_{t-i}.$$

It follows that

$$0 \leq u_t(\mathbf{q}) - u_t(\mathbf{m}_H(\mathbf{q})) = \sum_{i=H+1}^{t-1} q_i w_{t-i} \leq \text{Tail}_H(\mathbf{q}),$$

where the middle sum is empty when $t \leq H + 1$. This proves (23).

Define

$$e_t^x \triangleq x_t(\mathbf{m}_H(\mathbf{q})) - x_t(\mathbf{q}), \quad e_t^u \triangleq u_t(\mathbf{q}) - u_t(\mathbf{m}_H(\mathbf{q})).$$

The two state recursions give

$$e_{t+1}^x = \alpha e_t^x + e_t^u, \quad e_1^x = 0.$$

Since $0 \leq e_t^u \leq \text{Tail}_H(\mathbf{q})$,

$$0 \leq e_t^x = \sum_{\tau=1}^{t-1} \alpha^{t-1-\tau} e_\tau^u \leq \frac{\text{Tail}_H(\mathbf{q})}{1-\alpha},$$

which proves (24). The Lipschitz property now yields

$$\begin{aligned} &|c_t(x_t(\mathbf{m}_H(\mathbf{q})), u_t(\mathbf{m}_H(\mathbf{q}))) \\ &\quad - c_t(x_t(\mathbf{q}), u_t(\mathbf{q}))| \\ &\leq \left(L_u + \frac{L_x}{1-\alpha} \right) \text{Tail}_H(\mathbf{q}). \end{aligned}$$

Finally,

$$\begin{aligned} \text{Tail}_H(\mathbf{q}) &= \sum_{i=H+1}^\infty \alpha^i a_i \\ &\leq \alpha^{H+1} \sum_{i=H+1}^\infty a_i \leq \alpha^{H+1}. \end{aligned}$$

Summing the per-period cost bound proves (25). $\square$

Proof of Corollary 1. Fix $k \in [0, \alpha]$, let $\lambda_k = \alpha - k$, and let $\mathbf{q}(k)$ be defined by (26). The sequence is nonnegative and decreasing. If $k = 0$, then $\mathbf{q}(k) = \mathbf{0} \in \mathcal{Q}_\alpha$. If $k > 0$, then $\lambda_k/\alpha < 1$ and

$$\sum_{i=1}^\infty \frac{q_i(k)}{\alpha^i} = \frac{k}{\alpha} \sum_{j=0}^\infty \left(\frac{\lambda_k}{\alpha} \right)^j = \frac{k}{\alpha - \lambda_k} = 1,$$

so again $\mathbf{q}(k) \in \mathcal{Q}_\alpha$. Substituting $u_t(k) = kx_t(k)$ into the dynamics and unrolling gives

$$u_t(k) = k \sum_{i=1}^{t-1} \lambda_k^{i-1} w_{t-i} = \sum_{i=1}^{t-1} q_i(k) w_{t-i} = u_t(\mathbf{q}(k)).$$

The two policies therefore have identical state and action trajectories. Their SDAC truncations also coincide coordinate-wise, and the omitted geometric tail is

$$\text{Tail}_H(\mathbf{q}(k)) = k \sum_{i=H+1}^\infty \lambda_k^{i-1} = \frac{k \lambda_k^H}{1 - \lambda_k}.$$

Substitution in (25) proves (27). $\square$

APPENDIX B

PROOFS FOR THE ONLINE SDAC CONTROLLER

The following lemmas establish the Bregman-projection interpretation of scalar action clipping, the projection formula, and the equivalent closed-form OMD update used in Section V.

Lemma 6 (Action clipping as a Bregman projection). *At time t , define the parameter set compatible with the available state by*

$$\mathcal{F}_t(x_t) \triangleq \{\mathbf{m} \in \mathcal{M}_H : \langle \phi_t^u, \mathbf{m} \rangle \leq \alpha x_t\}. \quad (61)$$

For the negentropy Ψ in (28), let

$$\mathbf{m}_t^{\text{exec}} \in \arg \min_{\mathbf{m} \in \mathcal{F}_t(x_t)} D_\Psi(\mathbf{m} \| \mathbf{m}_t). \quad (62)$$

Then

$$\langle \phi_t^u, \mathbf{m}_t^{\text{exec}} \rangle = \min\{\langle \phi_t^u, \mathbf{m}_t \rangle, \alpha x_t\} = u_t. \quad (63)$$

Thus the projection formulation and the scalar clipping rule induce exactly the same executed action.

Proof. The set $\mathcal{F}_t(x_t)$ is nonempty because it contains $\mathbf{0}$, and it is compact and convex. By Lemma 8, every coordinate of $\mathbf{m}_t$ is strictly positive. Hence $D_\Psi(\cdot \|\mathbf{m}_t)$ is strictly convex on $\mathcal{M}_H$ and is minimized uniquely at $\mathbf{m}_t$ over any feasible set containing $\mathbf{m}_t$. Consequently, if

$$\langle \phi_t^u, \mathbf{m}_t \rangle \leq \alpha x_t,$$

then $\mathbf{m}_t^{\text{exec}} = \mathbf{m}_t$, which proves (63) in the feasible case.

Suppose instead that $\mathbf{m}_t$ is infeasible. We claim that the action constraint is active at $\mathbf{m}_t^{\text{exec}}$. If it were slack, then

$$\langle \phi_t^u, \mathbf{m}_t^{\text{exec}} \rangle < \alpha x_t < \langle \phi_t^u, \mathbf{m}_t \rangle. \quad (64)$$

For sufficiently small $\lambda \in (0, 1)$, the point

$$\mathbf{m}_\lambda \triangleq (1 - \lambda)\mathbf{m}_t^{\text{exec}} + \lambda\mathbf{m}_t$$

would still belong to $\mathcal{F}_t(x_t)$. Because $D_\Psi(\mathbf{m}_t \|\mathbf{m}_t) = 0$, strict convexity would then give

$$\begin{aligned} D_\Psi(\mathbf{m}_\lambda \|\mathbf{m}_t) &< (1 - \lambda)D_\Psi(\mathbf{m}_t^{\text{exec}} \|\mathbf{m}_t) \\ &< D_\Psi(\mathbf{m}_t^{\text{exec}} \|\mathbf{m}_t), \end{aligned}$$

contradicting (62). Hence

$$\langle \phi_t^u, \mathbf{m}_t^{\text{exec}} \rangle = \alpha x_t$$

in the infeasible case, which completes the proof. $\square$

Lemma 7 (Bregman projection onto $\mathcal{M}_H$). *Let D_Ψ be the Bregman divergence (29) of the unnormalized negentropy (28). Fix $\tilde{\mathbf{m}} \in \mathbb{R}_{>0}^H$. Then the Bregman projection of $\tilde{\mathbf{m}}$ onto $\mathcal{M}_H$,*

$$\text{Proj}_{\mathcal{M}_H}^\Psi(\tilde{\mathbf{m}}) \triangleq \arg \min_{\mathbf{m} \in \mathcal{M}_H} D_\Psi(\mathbf{m} \|\tilde{\mathbf{m}}),$$

is given by

$$\text{Proj}_{\mathcal{M}_H}^\Psi(\tilde{\mathbf{m}}) = \frac{\tilde{\mathbf{m}}}{\max\{1, \|\tilde{\mathbf{m}}\|_1\}}.$$

Proof. The projection objective $\mathbf{m} \mapsto D_\Psi(\mathbf{m} \|\tilde{\mathbf{m}})$ is strictly convex, and, for $m_i > 0$,

$$\frac{\partial}{\partial m_i} D_\Psi(\mathbf{m} \|\tilde{\mathbf{m}}) = \log \frac{m_i}{\tilde{m}_i}. \quad (65)$$

Its unconstrained minimizer is therefore $\mathbf{m} = \tilde{\mathbf{m}}$.

If $\|\tilde{\mathbf{m}}\|_1 \leq 1$, this minimizer belongs to $\mathcal{M}_H$, and hence

$$\text{Proj}_{\mathcal{M}_H}^\Psi(\tilde{\mathbf{m}}) = \tilde{\mathbf{m}}.$$

Suppose $\|\tilde{\mathbf{m}}\|_1 > 1$. The constraint $\|\mathbf{m}\|_1 \leq 1$ is then active. Moreover, the minimizer has no zero coordinate: if $m_i = 0$, transferring an arbitrarily small amount of mass from a positive coordinate to coordinate i has directional derivative $-\infty$, because

$$\lim_{z \downarrow 0} \log \frac{z}{\tilde{m}_i} = -\infty.$$

Thus the nonnegativity constraints are inactive. With $\nu \geq 0$ denoting the multiplier of $\|\mathbf{m}\|_1 \leq 1$, stationarity and complementary slackness give

$$\log \frac{m_i}{\tilde{m}_i} + \nu = 0, \quad \|\mathbf{m}\|_1 = 1. \quad (66)$$

The first relation in (66) implies

$$m_i = \tilde{m}_i \exp(-\nu).$$

Summing over i and using the second relation in (66),

$$1 = \|\tilde{\mathbf{m}}\|_1 \exp(-\nu), \quad \exp(-\nu) = \frac{1}{\|\tilde{\mathbf{m}}\|_1}.$$

Hence $\nu = \log \|\tilde{\mathbf{m}}\|_1 > 0$ and

$$\text{Proj}_{\mathcal{M}_H}^\Psi(\tilde{\mathbf{m}}) = \frac{\tilde{\mathbf{m}}}{\|\tilde{\mathbf{m}}\|_1}.$$

Combining the cases $\|\tilde{\mathbf{m}}\|_1 \leq 1$ and $\|\tilde{\mathbf{m}}\|_1 > 1$ proves the stated formula. $\square$

Lemma 8 (Closed-form solution of the OMD update). *Fix $\mathbf{m}_t \in \mathcal{M}_H \cap \mathbb{R}_{>0}^H$, $\eta > 0$, and $\mathbf{g}_t \in \mathbb{R}^H$, and let $\tilde{\mathbf{m}}_{t+1}$ be defined coordinatewise by (34), i.e. $\tilde{m}_{t+1,i} = m_{t,i} \exp(-\eta g_{t,i})$. Then*

$$\begin{aligned} \arg \min_{\mathbf{m} \in \mathcal{M}_H} \{ \eta \langle \mathbf{g}_t, \mathbf{m} \rangle + D_\Psi(\mathbf{m} \|\mathbf{m}_t) \} \\ = \arg \min_{\mathbf{m} \in \mathcal{M}_H} D_\Psi(\mathbf{m} \|\tilde{\mathbf{m}}_{t+1}) = \text{Proj}_{\mathcal{M}_H}^\Psi(\tilde{\mathbf{m}}_{t+1}), \end{aligned}$$

where $\text{Proj}_{\mathcal{M}_H}^\Psi$ is the Bregman projection in Lemma 7. Consequently, the OMD update (33) coincides exactly with the closed-form OMD update (34)–(35), and, in particular, $\mathbf{m}_{t+1} \in \mathcal{M}_H \cap \mathbb{R}_{>0}^H$. Thus, the positive initialization (30) keeps every OMD iterate strictly positive.

Proof. Fix $\mathbf{m} \in \mathbb{R}_{\geq 0}^H$ and a coordinate i . Then

$$\begin{aligned} \eta g_{t,i} m_i + m_i \log \frac{m_i}{m_{t,i}} &= m_i \left(\eta g_{t,i} + \log \frac{m_i}{m_{t,i}} \right) \\ &= m_i \log \frac{m_i}{\tilde{m}_{t+1,i}}. \end{aligned} \quad (67)$$

Substitution into the OMD objective gives

$$\begin{aligned} \eta \langle \mathbf{g}_t, \mathbf{m} \rangle + D_\Psi(\mathbf{m} \|\mathbf{m}_t) \\ = D_\Psi(\mathbf{m} \|\tilde{\mathbf{m}}_{t+1}) + \sum_{i=1}^H (m_{t,i} - \tilde{m}_{t+1,i}). \end{aligned} \quad (68)$$

The final sum is independent of $\mathbf{m}$. Hence, the two optimization problems have the same minimizer, and Lemma 7 gives (35). Since $\mathbf{m}_t > 0$ coordinatewise, both the multiplicative step and the subsequent positive rescaling preserve strict positivity. $\square$

APPENDIX C

PROOFS FOR THE REGRET UPPER BOUNDS

The following lemmas establish the OMD and stability estimates used in the proof of Theorem 1. They rely on the state-decomposition, feasibility, and surrogate-cost lemmas established in Section IV (Lemmas 1, 2, and 3).

Lemma 9 (One-step OMD movement bound). *For the OMD update with step size $\eta > 0$ and subgradient $\mathbf{g}_t \in \partial \ell_t(\mathbf{m}_t)$,*

$$\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \leq \eta \|\mathbf{g}_t\|_\infty.$$

In particular, since $\|\mathbf{g}_t\|_\infty \leq G_\alpha$, $\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \leq \eta G_\alpha$.

Proof. First-order optimality of (33), evaluated at the feasible point $\mathbf{m}_t$, gives

$$\begin{aligned} \langle \eta \mathbf{g}_t + \nabla \Psi(\mathbf{m}_{t+1}) - \nabla \Psi(\mathbf{m}_t), \mathbf{m}_t - \mathbf{m}_{t+1} \rangle &\geq 0, \\ D_\Psi(\mathbf{m}_{t+1} \| \mathbf{m}_t) + D_\Psi(\mathbf{m}_t \| \mathbf{m}_{t+1}) & \\ \leq \eta \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle & \\ \leq \eta \|\mathbf{g}_t\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. & \end{aligned} \quad (69)$$

The second line uses the symmetric Bregman identity.

For every $\mathbf{z} \in \mathcal{M}_H \cap \mathbb{R}_{>0}^H$ and $\mathbf{v} \in \mathbb{R}^H$,

$$\begin{aligned} \mathbf{v}^\top \nabla^2 \Psi(\mathbf{z}) \mathbf{v} &= \sum_{i=1}^H \frac{v_i^2}{z_i} \\ &\geq \frac{\|\mathbf{v}\|_1^2}{\sum_{i=1}^H z_i} \\ &\geq \|\mathbf{v}\|_1^2. \end{aligned} \quad (70)$$

The first inequality follows from Cauchy-Schwarz. The segment joining $\mathbf{m}_t$ and $\mathbf{m}_{t+1}$ lies in $\mathcal{M}_H \cap \mathbb{R}_{>0}^H$ by Lemma 8; integrating (70) along this segment yields

$$\begin{aligned} D_\Psi(\mathbf{m}_{t+1} \| \mathbf{m}_t) &\geq \frac{1}{2} \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2, \\ D_\Psi(\mathbf{m}_t \| \mathbf{m}_{t+1}) &\geq \frac{1}{2} \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2. \end{aligned}$$

Combining these inequalities with (69),

$$\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2 \leq \eta \|\mathbf{g}_t\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1.$$

The claim is immediate if $\mathbf{m}_{t+1} = \mathbf{m}_t$; otherwise divide by $\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1$. $\square$

Lemma 10 (OMD regret for the surrogate costs). *For every $\mathbf{m} \in \mathcal{M}_H$, the update (33) satisfies*

$$\sum_{t=1}^T \ell_t(\mathbf{m}_t) - \sum_{t=1}^T \ell_t(\mathbf{m}) \leq \frac{D_\Psi(\mathbf{m} \| \mathbf{m}_1)}{\eta} + \frac{\eta}{2} \sum_{t=1}^T \|\mathbf{g}_t\|_\infty^2. \quad (71)$$

Proof. Convexity of ℓ_t gives

$$\begin{aligned} \ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m}) &\leq \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m} \rangle \\ &= \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle \\ &\quad + \langle \mathbf{g}_t, \mathbf{m}_{t+1} - \mathbf{m} \rangle. \end{aligned} \quad (72)$$

First-order optimality of (33), evaluated at $\mathbf{m} \in \mathcal{M}_H$, yields

$$\begin{aligned} \eta \langle \mathbf{g}_t, \mathbf{m}_{t+1} - \mathbf{m} \rangle &\leq \langle \nabla \Psi(\mathbf{m}_{t+1}) - \nabla \Psi(\mathbf{m}_t), \mathbf{m} - \mathbf{m}_{t+1} \rangle \\ &= D_\Psi(\mathbf{m} \| \mathbf{m}_t) - D_\Psi(\mathbf{m} \| \mathbf{m}_{t+1}) \\ &\quad - D_\Psi(\mathbf{m}_{t+1} \| \mathbf{m}_t). \end{aligned} \quad (73)$$

The equality follows from the three-point Bregman identity. Substituting (73) into (72),

$$\begin{aligned} \ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m}) &\leq \frac{D_\Psi(\mathbf{m} \| \mathbf{m}_t)}{\eta} - \frac{D_\Psi(\mathbf{m} \| \mathbf{m}_{t+1})}{\eta} \\ &\quad + \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle \\ &\quad - \frac{D_\Psi(\mathbf{m}_{t+1} \| \mathbf{m}_t)}{\eta}. \end{aligned} \quad (74)$$

The strong-convexity calculation (70) and Hölder's inequality give

$$\begin{aligned} \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle &- \frac{D_\Psi(\mathbf{m}_{t+1} \| \mathbf{m}_t)}{\eta} \\ &\leq \|\mathbf{g}_t\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 - \frac{\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2}{2\eta} \\ &\leq \frac{\eta}{2} \|\mathbf{g}_t\|_\infty^2. \end{aligned} \quad (75)$$

The last inequality follows from Young's inequality. Combining (74) and (75) and summing over t gives

$$\begin{aligned} \sum_{t=1}^T \ell_t(\mathbf{m}_t) - \sum_{t=1}^T \ell_t(\mathbf{m}) &\leq \frac{D_\Psi(\mathbf{m} \| \mathbf{m}_1)}{\eta} \\ &\quad - \frac{D_\Psi(\mathbf{m} \| \mathbf{m}_{T+1})}{\eta} \\ &\quad + \frac{\eta}{2} \sum_{t=1}^T \|\mathbf{g}_t\|_\infty^2. \end{aligned}$$

Since $D_\Psi(\mathbf{m} \| \mathbf{m}_{T+1}) \geq 0$, this proves (71). $\square$

Lemma 11 (Positive-part representation of the dynamics). *For $\mathbf{m} \in \mathcal{M}_H$, define*

$$F_t(x; \mathbf{m}) \triangleq [\alpha x - \langle \phi_t^u, \mathbf{m} \rangle]_+ + w_t. \quad (76)$$

Then the online state and the state component of every fixed-policy trajectory satisfy

$$x_{t+1} = F_t(x_t; \mathbf{m}_t), \quad x_{t+1}(\mathbf{m}) = F_t(x_t(\mathbf{m}); \mathbf{m}). \quad (77)$$

Moreover, for all $x, x' \geq 0$ and $\mathbf{m}, \mathbf{m}' \in \mathcal{M}_H$,

$$\begin{aligned} |F_t(x; \mathbf{m}) - F_t(x'; \mathbf{m}')| & \\ &\leq |\alpha(x - x') - \langle \phi_t^u, \mathbf{m} - \mathbf{m}' \rangle| \\ &\leq \alpha|x - x'| + \|\phi_t^u\|_\infty \|\mathbf{m} - \mathbf{m}'\|_1. \end{aligned} \quad (78)$$

Proof. For the online trajectory, (32) implies

$$\begin{aligned} \alpha x_t - u_t &= \alpha x_t - \min\{\langle \phi_t^u, \mathbf{m}_t \rangle, \alpha x_t\} \\ &= [\alpha x_t - \langle \phi_t^u, \mathbf{m}_t \rangle]_+. \end{aligned} \quad (79)$$

For a fixed $\mathbf{m}$, Lemma 2 gives

$$\alpha x_t(\mathbf{m}) - \langle \phi_t^u, \mathbf{m} \rangle \geq 0,$$

so inserting a positive part does not change its state update. This proves (77). Finally, the map $z \mapsto [z]_+$ is nonexpansive:

$$|[z]_+ - [z']_+| \leq |z - z'|.$$

Applying this inequality to the two arguments in (76), followed by Hölder's inequality, gives (78). $\square$

Proof of Lemma 5. Define

$$d_t \triangleq |x_t - x_t(\mathbf{m}_t)|.$$

Since $x_1 = x_1(\mathbf{m}_1) = 0$, we have $d_1 = 0$. For $t \in \{1, \dots, T-1\}$, Lemma 11 gives

$$\begin{aligned} d_{t+1} &= |F_t(x_t; \mathbf{m}_t) - F_t(x_t(\mathbf{m}_{t+1}); \mathbf{m}_{t+1})| \\ &\leq \alpha |x_t - x_t(\mathbf{m}_{t+1})| + \|\phi_t^u\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \end{aligned} \quad (80)$$

The affine state representation (52) implies

$$|x_t(\mathbf{m}_t) - x_t(\mathbf{m}_{t+1})| = |\langle \phi_t^x, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle| \leq \|\phi_t^x\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \quad (81)$$

Combining the triangle inequality with (80) and (81) yields

$$d_{t+1} \leq \alpha d_t + (\alpha \|\phi_t^x\|_\infty + \|\phi_t^u\|_\infty) \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \quad (82)$$

By (55),

$$\begin{aligned} \alpha \|\phi_t^x\|_\infty + \|\phi_t^u\|_\infty &\leq \frac{\alpha^2}{1-\alpha} + \alpha \\ &= \frac{\alpha}{1-\alpha}. \end{aligned} \quad (83)$$

Lemma 9 and $\|\mathbf{g}_t\|_\infty \leq G_\alpha$ therefore reduce (82) to

$$d_{t+1} \leq \alpha d_t + \frac{\alpha \eta G_\alpha}{1-\alpha}. \quad (84)$$

Unrolling from $d_1 = 0$ gives

$$\begin{aligned} d_t &\leq \frac{\alpha \eta G_\alpha}{1-\alpha} \sum_{j=0}^{t-2} \alpha^j \\ &\leq \frac{\alpha \eta G_\alpha}{(1-\alpha)^2}, \end{aligned} \quad (85)$$

with an empty sum when $t = 1$. This proves (38).

Finally, $\hat{u}_t = u_t(\mathbf{m}_t)$ and the feasibility of fixed SDAC policies imply

$$\begin{aligned} 0 \leq u_t(\mathbf{m}_t) - u_t &= [u_t(\mathbf{m}_t) - \alpha x_t]_+ \\ &\leq [\alpha x_t(\mathbf{m}_t) - \alpha x_t]_+ \\ &\leq \alpha d_t. \end{aligned} \quad (86)$$

Combining (86) with (38) proves (39).

Both state-action pairs lie in $\mathcal{D}_\alpha$. Hence (5) and the two bounds just proved give

$$\begin{aligned} c_t(x_t, u_t) - \ell_t(\mathbf{m}_t) &\leq L_x |x_t - x_t(\mathbf{m}_t)| + L_u |u_t - u_t(\mathbf{m}_t)| \\ &\leq \frac{\alpha \eta G_\alpha L_x}{(1-\alpha)^2} + \frac{\alpha^2 \eta G_\alpha L_u}{(1-\alpha)^2} \\ &= \frac{\alpha \eta G_\alpha (L_x + \alpha L_u)}{(1-\alpha)^2}. \end{aligned} \quad (87)$$

Summing (87) over $t = 1, \dots, T$ proves (40). $\square$

Proof of Theorem 1. Define the stability term

$$\text{Stab}_T \triangleq \sum_{t=1}^T (c_t(x_t, u_t) - \ell_t(\mathbf{m}_t)).$$

Using $\ell_t(\mathbf{m}) = c_t(x_t(\mathbf{m}), u_t(\mathbf{m}))$, the regret decomposes as

$$\text{Reg}_T^{\text{SDAC}} = \text{Stab}_T + \sum_{t=1}^T \ell_t(\mathbf{m}_t) - \min_{\mathbf{m} \in \mathcal{M}_H} \sum_{t=1}^T \ell_t(\mathbf{m}). \quad (88)$$

We first bound the initial Bregman divergence. Fix $\mathbf{m} \in \mathcal{M}_H$. Since $\mathbf{m}_1 = \frac{1}{H+1} \mathbf{1}$,

$$\begin{aligned} D_\Psi(\mathbf{m} \|\mathbf{m}_1) &= \sum_{i=1}^H m_i \log((H+1)m_i) \\ &\quad - \|\mathbf{m}\|_1 + \frac{H}{H+1} \\ &= \sum_{i=1}^H m_i \log m_i + \|\mathbf{m}\|_1 \log(H+1) \\ &\quad - \|\mathbf{m}\|_1 + \frac{H}{H+1}. \end{aligned} \quad (89)$$

Because $z \log z \leq 0$ for $z \in [0, 1]$,

$$D_\Psi(\mathbf{m} \|\mathbf{m}_1) \leq \|\mathbf{m}\|_1 \log(H+1) - \|\mathbf{m}\|_1 + \frac{H}{H+1}. \quad (90)$$

The right-hand side is affine in $\|\mathbf{m}\|_1 \in [0, 1]$, and its values at the endpoints are

$$\begin{aligned} \frac{H}{H+1} &\leq \log(H+1), \\ \log(H+1) - \frac{1}{H+1} &\leq \log(H+1). \end{aligned}$$

Here the first inequality follows from $\log z \geq 1 - z^{-1}$ for $z \geq 1$. Therefore,

$$D_\Psi(\mathbf{m} \|\mathbf{m}_1) \leq \log(H+1) \quad \text{for every } \mathbf{m} \in \mathcal{M}_H. \quad (91)$$

Lemma 10, $\|\mathbf{g}_t\|_\infty \leq G_\alpha$, and (91) imply, for every $\mathbf{m} \in \mathcal{M}_H$,

$$\begin{aligned} \sum_{t=1}^T (\ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m})) &\leq \frac{D_\Psi(\mathbf{m} \|\mathbf{m}_1)}{\eta} + \frac{\eta}{2} \sum_{t=1}^T \|\mathbf{g}_t\|_\infty^2 \\ &\leq \frac{\log(H+1)}{\eta} + \frac{\eta G_\alpha^2 T}{2}. \end{aligned} \quad (92)$$

Since (92) holds uniformly over $\mathbf{m}$,

$$\sum_{t=1}^T \ell_t(\mathbf{m}_t) - \min_{\mathbf{m} \in \mathcal{M}_H} \sum_{t=1}^T \ell_t(\mathbf{m}) \leq \frac{\log(H+1)}{\eta} + \frac{\eta G_\alpha^2 T}{2}. \quad (93)$$

The stability bound (40) gives

$$\text{Stab}_T \leq \frac{\alpha \eta T G_\alpha (L_x + \alpha L_u)}{(1-\alpha)^2}. \quad (94)$$

Substituting (93) and (94) into (88),

$$\begin{aligned} \text{Reg}_T^{\text{SDAC}} &\leq \frac{\log(H+1)}{\eta} + \frac{\eta T G_\alpha^2}{2} \\ &\quad + \frac{\alpha \eta T G_\alpha (L_x + \alpha L_u)}{(1-\alpha)^2} \\ &= \frac{\log(H+1)}{\eta} + \eta T \Gamma_\alpha. \end{aligned} \quad (95)$$

Differentiating with respect to η yields

$$-\frac{\log(H+1)}{\eta^2} + T \Gamma_\alpha.$$

The unique minimizer is therefore

$$\eta^* = \sqrt{\frac{\log(H+1)}{T \Gamma_\alpha}}. \quad (96)$$

At this value, the two summands in (95) are equal, so

$$\text{Reg}_T^{\text{SDAC}} \leq 2\sqrt{\Gamma_\alpha T \log(H+1)}. \quad (97)$$

It remains to verify the dependence on α . As $\alpha \downarrow 0$,

$$\begin{aligned} \frac{G_\alpha}{\alpha} &= \frac{L_x}{1-\alpha} + L_u \longrightarrow L_x + L_u, \\ \frac{\Gamma_\alpha}{\alpha^2} &= \frac{1}{2} \left(\frac{G_\alpha}{\alpha} \right)^2 + \frac{G_\alpha}{\alpha} \frac{L_x + \alpha L_u}{(1-\alpha)^2} \\ &\longrightarrow \frac{(L_x + L_u)^2}{2} + L_x(L_x + L_u) > 0. \end{aligned}$$

Therefore $\sqrt{\Gamma_\alpha} = \Theta(\alpha)$ as $\alpha \downarrow 0$. As $\alpha \uparrow 1$, write $\varepsilon = 1 - \alpha$. Then

$$\begin{aligned} \varepsilon G_\alpha &= \alpha(L_x + \varepsilon L_u) \longrightarrow L_x, \\ \varepsilon^3 \Gamma_\alpha &= \frac{\varepsilon^3 G_\alpha^2}{2} + \alpha(\varepsilon G_\alpha)(L_x + \alpha L_u) \\ &\longrightarrow L_x(L_x + L_u) > 0. \end{aligned}$$

Thus $\sqrt{\Gamma_\alpha} = \Theta((1-\alpha)^{-3/2})$ as $\alpha \uparrow 1$. $\square$

Proof of Corollary 2. Fix $\mathbf{q} \in \mathcal{Q}_\alpha$ and use the SDAC comparator $\mathbf{m}_{H_T}(\mathbf{q})$ from Lemma 4. Theorem 1 and (25) give

$$\begin{aligned} J_T^{\text{on}} - J_T(\mathbf{q}) &\leq 2\sqrt{\Gamma_\alpha T \log(H_T + 1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha} \right) \text{Tail}_{H_T}(\mathbf{q})T \\ &\leq 2\sqrt{\Gamma_\alpha T \log(H_T + 1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha} \right) \alpha^{H_T+1}T. \end{aligned}$$

The bound is uniform in $\mathbf{q}$, so taking the infimum over $\mathbf{q} \in \mathcal{Q}_\alpha$ proves (41). Finally, $H_T \geq \log T / \log(1/\alpha)$ implies $\alpha^{H_T} \leq 1/T$, while $H_T = \Theta(\log T)$ implies $\log(H_T + 1) = O(\log \log T)$. $\square$

Proof of Corollary 3. For fixed k , Theorem 1 applied to $\mathbf{m}_{H_T}^{\text{prop}}(k)$, followed by (27), gives (42). Corollary 1 shows that the geometric allocation sequence $\mathbf{q}(k)$ belongs to $\mathcal{Q}_\alpha$, so Lemma 4 gives $\text{Tail}_{H_T}(\mathbf{q}(k)) \leq \alpha^{H_T+1}$. This makes the bound uniform in k ; minimizing over k proves the stated finite-time and asymptotic guarantees. $\square$

APPENDIX D

PROOFS FOR THE MINIMAX REGRET LOWER BOUND

Proof of Theorem 2. Fix a causal feasible controller $\mathcal{A}$. Let $\xi_1, \dots, \xi_T$ be independent Rademacher random variables, also independent of the internal randomization of $\mathcal{A}$, with

$$\mathbb{P}(\xi_t = 1) = \mathbb{P}(\xi_t = -1) = \frac{1}{2}.$$

Set

$$w_t = 1 \quad \text{for all } t \in [T], \quad (98)$$

and define the costs by

$$c_t(x, u) = \xi_t(L_x x - L_u u) \quad \text{for all } t \in [T]. \quad (99)$$

Each c_t is affine and hence convex. For any two points in $\mathcal{D}_\alpha$,

$$\begin{aligned} |c_t(x, u) - c_t(x', u')| &= |L_x(x - x') - L_u(u - u')| \\ &\leq L_x|x - x'| + L_u|u - u'|. \end{aligned} \quad (100)$$

Moreover,

$$\nabla c_t = \xi_t(L_x, -L_u), \quad |\partial_x c_t| = L_x, \quad |\partial_u c_t| = L_u,$$

so the required subgradient bounds hold.

We now select two fixed SDAC policies for the benchmark. The parameter $\mathbf{m}^{(0)}$ leaves all mass in the subprobability simplex unused, so its SDAC action is always zero. The parameter $\mathbf{m}^{(1)}$ places all mass on the first lag, so its action is αw_{t-1} . Let

$$\mathbf{m}^{(0)} \triangleq \mathbf{0}, \quad \mathbf{m}^{(1)} \triangleq \mathbf{e}_1 \quad (101)$$

belong to $\mathcal{M}_H$, where $\mathbf{e}_1 = (1, 0, \dots, 0) \in \mathbb{R}^H$. Thus, under (98), $\mathbf{m}^{(0)}$ is the no-release policy, whereas $\mathbf{m}^{(1)}$ releases the retained portion of the preceding arrival. For the no-release policy,

$$u_t(\mathbf{m}^{(0)}) = 0, \quad x_t(\mathbf{m}^{(0)}) = \rho_t \triangleq \frac{1 - \alpha^{t-1}}{1 - \alpha}. \quad (102)$$

This follows by unrolling $x_{t+1} = \alpha x_t + 1$:

$$x_t(\mathbf{m}^{(0)}) = \sum_{s=0}^{t-2} \alpha^s = \frac{1 - \alpha^{t-1}}{1 - \alpha}, \quad t \geq 2,$$

and the closed form also gives $x_1(\mathbf{m}^{(0)}) = 0$. For the one-lag policy, (11) gives

$$u_1(\mathbf{m}^{(1)}) = 0, \quad u_t(\mathbf{m}^{(1)}) = \alpha, \quad t \geq 2. \quad (103)$$

Its state at $t = 2$ is

$$x_2(\mathbf{m}^{(1)}) = \alpha x_1(\mathbf{m}^{(1)}) - u_1(\mathbf{m}^{(1)}) + w_1 = 1.$$

If $x_t(\mathbf{m}^{(1)}) = 1$ for some $t \geq 2$, then

$$\begin{aligned} x_{t+1}(\mathbf{m}^{(1)}) &= \alpha x_t(\mathbf{m}^{(1)}) - u_t(\mathbf{m}^{(1)}) + w_t \\ &= \alpha - \alpha + 1 = 1. \end{aligned}$$

Induction therefore gives

$$x_t(\mathbf{m}^{(1)}) = 1, \quad t \geq 2. \quad (104)$$

For $t \geq 2$, the difference between the two states is

$$\begin{aligned} \Delta_t &\triangleq x_t(\mathbf{m}^{(0)}) - x_t(\mathbf{m}^{(1)}) \\ &= \rho_t - 1 \\ &= \frac{\alpha(1 - \alpha^{t-2})}{1 - \alpha}. \end{aligned} \quad (105)$$

The two policies have the same state and action at $t = 1$. For $t \geq 2$, (103) and (105) give

$$\begin{aligned} J_T(\mathbf{m}^{(0)}) - J_T(\mathbf{m}^{(1)}) &= \sum_{t=2}^T \xi_t(L_x \Delta_t + \alpha L_u) \\ &= \sum_{t=2}^T \xi_t \beta_t, \end{aligned} \quad (106)$$

with β_t as in (44).

Let $\mathcal{F}_t^-$ be the information available immediately before c_t is revealed, including the randomization used to select u_t . By causality, (x_t, u_t) is $\mathcal{F}_t^-$ -measurable, whereas ξ_t is

independent of $\mathcal{F}_t^-$ and has mean zero. Hence, by the tower property,

$$\begin{aligned} \mathbb{E}_{\xi, \mathcal{A}}[J_T^{\text{on}}] &= \sum_{t=1}^T \mathbb{E}_{\xi, \mathcal{A}}[(L_x x_t - L_u u_t) \mathbb{E}[\xi_t | \mathcal{F}_t^-]] \\ &= 0. \end{aligned} \quad (107)$$

The fixed-policy trajectories depend only on the arrival sequence and are therefore independent of the Rademacher variables. Thus, for $j \in \{0, 1\}$,

$$\begin{aligned} \mathbb{E}_{\xi} [J_T(\mathbf{m}^{(j)})] &= \sum_{t=1}^T \mathbb{E}[\xi_t] (L_x x_t(\mathbf{m}^{(j)}) - L_u u_t(\mathbf{m}^{(j)})) \\ &= 0. \end{aligned} \quad (108)$$

Because $\mathbf{m}^{(0)}, \mathbf{m}^{(1)} \in \mathcal{M}_H$, for every realization of the Rademacher variables and every choice made by the controller,

$$\begin{aligned} \text{Reg}_T^{\text{SDAC}} &= J_T^{\text{on}} - \min_{\mathbf{m} \in \mathcal{M}_H} J_T(\mathbf{m}) \\ &\geq J_T^{\text{on}} - \min \{J_T(\mathbf{m}^{(0)}), J_T(\mathbf{m}^{(1)})\}. \end{aligned} \quad (109)$$

Taking expectations in (109) and using $\min\{a, b\} = (a + b - |a - b|)/2$ together with (107) and (108) gives

$$\begin{aligned} \mathbb{E}_{\xi, \mathcal{A}}[\text{Reg}_T^{\text{SDAC}}] &\geq \frac{1}{2} \mathbb{E}_{\xi} [J_T(\mathbf{m}^{(0)}) - J_T(\mathbf{m}^{(1)})] \\ &= \frac{1}{2} \mathbb{E}_{\xi} \left[\sum_{t=2}^T \xi_t \beta_t \right] \\ &\geq \frac{1}{2\sqrt{2}} \left(\sum_{t=2}^T \beta_t^2 \right)^{1/2}. \end{aligned} \quad (110)$$

Khintchine's inequality for Rademacher sums gives the final inequality in (110). It remains to remove the randomization from the adversarial construction. The left-hand side of (110) is the average over all 2^T realizations of the Rademacher vector ξ :

$$\mathbb{E}_{\xi, \mathcal{A}}[\text{Reg}_T^{\text{SDAC}}] = \frac{1}{2^T} \sum_{\xi \in \{-1, 1\}^T} \mathbb{E}_{\mathcal{A}}[\text{Reg}_T^{\text{SDAC}} | \xi].$$

Hence, at least one vector ξ^* makes the conditional expectation at least the right-hand side of (110). Fixing ξ^* in (99), together with the arrivals in (98), produces a deterministic admissible sequence fixed before the interaction. The remaining expectation is only over the internal randomization of $\mathcal{A}$, and (43) follows. $\square$

Proof of Corollary 4. The definition of $t_{\text{mix}}(\alpha)$ gives

$$\alpha^{t_{\text{mix}}(\alpha)} \leq \alpha^{\log 2 / \log(1/\alpha)} = \frac{1}{2}. \quad (111)$$

Therefore, for every $t \geq t_{\text{mix}}(\alpha) + 2$,

$$\begin{aligned} \beta_t &\geq \alpha \left(L_u + \frac{L_x}{2(1-\alpha)} \right) \\ &\geq \frac{\alpha}{2} \left(L_u + \frac{L_x}{1-\alpha} \right) = \frac{G_\alpha}{2}. \end{aligned} \quad (112)$$

There are $T - t_{\text{mix}}(\alpha) - 1$ indices in $\{t_{\text{mix}}(\alpha) + 2, \dots, T\}$. If $T \geq 2t_{\text{mix}}(\alpha) + 2$, then

$$T - t_{\text{mix}}(\alpha) - 1 \geq \frac{T}{2}. \quad (113)$$

Applying Theorem 2 and retaining only these indices,

$$\begin{aligned} \mathbb{E}_{\mathcal{A}}[\text{Reg}_T^{\text{SDAC}}] &\geq \frac{1}{2\sqrt{2}} \left[\frac{T}{2} \left(\frac{G_\alpha}{2} \right)^2 \right]^{1/2} \\ &= \frac{G_\alpha}{8} \sqrt{T}. \end{aligned} \quad (114)$$

This is (46). $\square$

REFERENCES

- [1] N. Agarwal, B. Bullins, E. Hazan, S. Kakade, and K. Singh, "Online control with adversarial disturbances," in *Proceedings of the 36th International Conference on Machine Learning*, ser. Proceedings of Machine Learning Research, vol. 97. PMLR, 2019, pp. 111–119.
- [2] N. Agarwal, E. Hazan, and K. Singh, "Logarithmic regret for online control," *Advances in Neural Information Processing Systems*, vol. 32, 2019.
- [3] E. Hazan and K. Singh, "Introduction to Online Control," Apr. 2026, arXiv:2211.09619, revised April 2026. [Online]. Available: <https://arxiv.org/abs/2211.09619>
- [4] M. Simchowitz, K. Singh, and E. Hazan, "Improper learning for non-stochastic control," in *Proceedings of the Thirty Third Conference on Learning Theory*, ser. Proceedings of Machine Learning Research, vol. 125. PMLR, 2020, pp. 3320–3436.
- [5] S. Lale, K. Azizzadenesheli, B. Hassibi, and A. Anandkumar, "Logarithmic regret bound in partially observable linear dynamical systems," *Advances in Neural Information Processing Systems*, vol. 33, pp. 20876–20888, 2020.
- [6] E. Hazan, S. M. Kakade, K. Singh, and A. Sidford, "Nonstochastic control with bandit feedback," *Advances in Neural Information Processing Systems*, vol. 33, pp. 16774–16785, 2020.
- [7] Y. Li, S. Das, and N. Li, "Online optimal control with affine constraints," *Proceedings of the AAAI Conference on Artificial Intelligence*, vol. 35, no. 10, pp. 8527–8537, 2021. [Online]. Available: <https://ojs.aaai.org/index.php/AAAI/article/view/17035>
- [8] X. Liu, Z. Yang, and L. Ying, "Online nonstochastic control with adversarial and static constraints," in *Proceedings of the 40th International Conference on Machine Learning*, ser. Proceedings of Machine Learning Research, vol. 202. PMLR, 2023, pp. 22277–22288. [Online]. Available: <https://proceedings.mlr.press/v202/liu23at.html>
- [9] R. Kumar, S. Dean, and R. Kleinberg, "Online convex optimization with unbounded memory," 2024, arXiv:2210.09903, version 5. [Online]. Available: <https://arxiv.org/abs/2210.09903>
- [10] D. Shaviv and A. Özgür, "Universally near optimal online power control for energy harvesting nodes," *IEEE Journal on Selected Areas in Communications*, vol. 34, no. 12, pp. 3620–3631, 2016. [Online]. Available: <https://arxiv.org/abs/1511.00353>
- [11] A. Arafat, A. Baknina, and S. Ulukus, "Online fixed fraction policies in energy harvesting communication systems," *IEEE Transactions on Wireless Communications*, vol. 17, no. 5, pp. 2975–2986, 2018.
- [12] A. Zibaeenejad and J. Chen, "The optimal power control policy for an energy harvesting system with look-ahead: Bernoulli energy arrivals," in *2019 IEEE International Symposium on Information Theory (ISIT)*, 2019, extended version: arXiv:1904.12281. [Online]. Available: <https://arxiv.org/abs/1904.12281>
- [13] H. Yu and M. J. Neely, "Learning-aided optimization for energy-harvesting devices with outdated state information," *IEEE/ACM Transactions on Networking*, vol. 27, no. 4, pp. 1501–1514, 2019.
- [14] K. Asgari and M. J. Neely, "Bregman-style online convex optimization with energy harvesting constraints," *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, vol. 4, no. 3, Nov. 2020. [Online]. Available: <https://doi.org/10.1145/3428337>
- [15] Q. Lin, J. Su, and M. Chen, "Optimal algorithms for online Age-of-Information optimization in energy harvesting systems," *IEEE Transactions on Networking*, vol. 33, no. 6, pp. 3146–3161, 2025.

- [16] L. Tassiulas and A. Ephremides, "Stability properties of constrained queueing systems and scheduling policies for maximum throughput in multihop radio networks," in *29th IEEE Conference on Decision and Control*. IEEE, 1990, pp. 2130–2132.
- [17] —, "Dynamic server allocation to parallel queues with randomly varying connectivity," *IEEE Transactions on Information Theory*, vol. 39, no. 2, pp. 466–478, 1993.
- [18] N. McKeown, A. Mekkittikul, V. Anantharam, and J. Walrand, "Achieving 100% throughput in an input-queued switch," *IEEE Transactions on Communications*, vol. 47, no. 8, pp. 1260–1267, 1999.
- [19] M. J. Neely, *Stochastic Network Optimization with Application to Communication and Queueing Systems*. Morgan & Claypool Publishers, 2010.
- [20] M. A. Khojastepour and A. Sabharwal, "Delay-constrained scheduling: Power efficiency, filter design, and bounds," in *IEEE INFOCOM 2004*, vol. 3. IEEE, 2004, pp. 1938–1949.
- [21] L. Yang, M. H. Hajiesmaili, R. Sitaraman, A. Wierman, E. Mallada, and W. S. Wong, "Online linear optimization with inventory management constraints," *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, vol. 4, no. 1, 2020.
- [22] M. Hihat and A. Fermanian, "Online policy selection for inventory problems," *arXiv preprint arXiv:2411.19269*, 2024. [Online]. Available: <https://arxiv.org/abs/2411.19269>
- [23] P. A. P. Moran, "A probability theory of dams and storage systems," *Australian Journal of Applied Science*, vol. 5, no. 2, pp. 116–124, 1954.
- [24] N. U. Prabhu, *Stochastic Storage Processes: Queues, Insurance Risk, Dams, and Data Communication*. New York, NY: Springer New York, 1998. [Online]. Available: <https://doi.org/10.1007/978-1-4612-1742-8>
- [25] R. T. Rockafellar and R. J.-B. Wets, *Variational Analysis*, ser. Grundlehren der mathematischen Wissenschaften. Berlin: Springer, 1998, vol. 317.
- [26] E. Hazan, "Introduction to online convex optimization," *Foundations and Trends in Optimization*, vol. 2, no. 3–4, pp. 157–325, 2016.