Online Constrained Control of Storage Systems via Simplex Disturbance-Action Policies

Kamiar Asgari and Michael J. Neely

***Abstract*—We study online control of a scalar storage system with nonnegative adversarial resource arrivals and state-dependent action constraints. The adversarial, time-varying cost depends on both the state and the action. At each time, the controller selects a feasible action before the current resource arrival and cost are revealed. To handle the resulting coupling between feasibility and online learning, we introduce *Simplex Disturbance-Action Control* (SDAC), a policy class specified by H nonnegative parameters whose sum is at most one. The key feature of SDAC is that every fixed policy in the class is feasible by construction. Our online SDAC controller updates these parameters using entropic online mirror descent while preserving feasibility along the time-varying trajectory. We prove a regret bound of $O\Big(\sqrt{T\log(H+1)}\Big)$ relative to the best fixed SDAC policy. We also derive a minimax lower bound showing that the dependence on T is tight. We then show that SDAC geometrically approximates a decreasing-allocation policy class that spreads each arrival over time according to a common decreasing allocation sequence, a structure that arises in stochastic energy-harvesting control. With $H = \Theta(\log T)$, the resulting regret against the decreasing-allocation class is $O\big(\sqrt{T\log\log T}\big)$. The framework applies to energy-harvesting batteries and other storage-constrained resource systems.**

***Index Terms*—Online control, disturbance-action policies, storage systems, energy harvesting, regret minimization, state-dependent action constraints.**

I. Introduction

A. Motivation and Problem Setting

MANY resource-allocation systems have a storage state that changes over time and limits the control action at each time. An action that lowers the current cost may leave less resource for future decisions, while conserving the resource may increase the current cost. The controller must balance these effects while satisfying this constraint at every step.

We study this problem for a scalar storage system that loses a fixed fraction of its stored resource each period. At each time, the controller observes the current state and all past arrivals and cost functions, chooses a control action, and then observes the current arrival and cost function. The arrival and cost sequences may be chosen adversarially, so we do not assume a known probability model. Our goal is to construct an online SDAC controller whose cumulative cost is close to that of the best fixed policy, chosen in hindsight, from a specified benchmark class.

One difficulty is that the current action affects the next state. In online control, *Disturbance-Action Control* (DAC) parameterizes actions using a linear filter of past disturbances, thereby yielding a tractable algorithm with bounded regret. In our storage model, however, some DAC policies can produce negative actions or actions larger than the available resource.

We address this issue by introducing *Simplex Disturbance-Action Control* (SDAC). SDAC restricts the filter parameters to a subprobability simplex and includes powers of the retention coefficient in the filter. These choices ensure that every fixed SDAC policy satisfies the action constraint. The state and action components of each fixed-policy trajectory are also affine in the policy parameter. Thus, a convex state–action cost is convex as a function of that parameter. This structure permits the parameter to be updated using online convex optimization.

K. Asgari and M. J. Neely are with the Department of Electrical and Computer Engineering, University of Southern California, Los Angeles, CA 90089 USA (e-mail: kamiaras@usc.edu; mjneely@usc.edu).

Corresponding author: K. Asgari.

B. Model and Information Pattern

The storage state $x_t \geq 0$ evolves according to

$$x_{t+1} = \alpha x_t - u_t + w_t,$$

where $\alpha \in (0,1)$ is a fixed retention coefficient, u_t is the control action, and $w_t \in [0,1]$ is a nonnegative resource arrival. The action must satisfy

$$0 \leq u_t \leq \alpha x_t.$$

Thus, the controller cannot use more than the amount remaining after storage loss.

At time t, the controller chooses u_t using the current state and the information available through time $t-1$. The arrival w_t and the convex cost function c_t are revealed after the action is selected, and the controller incurs the cost $c_t(x_t, u_t)$. Both the online trajectory and every fixed-policy trajectory used as a benchmark must satisfy the same dynamics and action constraint. The formal model and assumptions are given in Section II.

Energy-harvesting battery management is our main application. In this case, x_t is the battery state of charge, w_t is the harvested energy, u_t is the energy used, and $1-\alpha$ is the fraction of stored energy lost during one period. Similar dynamics arise in perishable inventory systems, water reservoirs with storage loss, and queues with abandonment. In many standard queueing models, $\alpha = 1$; that case is outside our main results and is discussed in Section VII.

C. Contributions

Our contributions are as follows:

- **Policy class.** We introduce SDAC, a finite-memory policy class parameterized by a subprobability simplex. We

prove that every fixed SDAC policy is feasible for every arrival sequence with entries in $[0, 1]$.
We further show that SDAC approximates the decreasing-allocation policy class defined in Section III-C. This class allocates each arrival over future periods according to the same decreasing sequence. It contains every feasible fixed-fraction policy $u_t = kx_t$ for some fixed $k \in [0, \alpha]$, and the approximation error decreases geometrically with the memory horizon H.

- **Online control and regret.** We develop an online SDAC controller that updates its parameter using entropic online mirror descent (OMD) over the subprobability simplex. We prove that the controller remains feasible and achieves

$$O\Big(\sqrt{T\log(H+1)}\Big)$$

regret against the best fixed SDAC policy. For $H = \Theta(\log T)$, the regret against the decreasing-allocation class is $O\big(\sqrt{T\log\log T}\big)$. The same bound holds against the best fixed-fraction policy.
- **Minimax lower bound.** We prove a lower bound of order $\sqrt{T}$ for the expected regret of every causal feasible controller, including randomized controllers; see Theorem 2. When T is at least on the order of $(1-\alpha)^{-1}$, the lower bound scales as $\Omega((1-\alpha)^{-1}\sqrt{T})$ near $\alpha = 1$. The upper and lower bounds differ by a factor of $(1-\alpha)^{-1/2}$ in their dependence on $1-\alpha$. Closing this gap is left for future work.

D. Related Work

a) Online control: Online control is the main basis for this work. Agarwal et al. use DAC policies to obtain $\widetilde{O}(\sqrt{T})$ regret against strongly stable linear controllers [1]. More closely related to our simplex parameterization, Golowich et al. adapt DAC to population dynamics and search over simplex-structured DAC policy parameters [2]. Their state lies in a probability simplex, and their feasible action set is independent of the current state. Here, the constraint $0 \le u_t \le \alpha x_t$ couples each action to the available resource.

Li et al. consider affine constraints on the state and action [3]. Their action constraint is independent of the current state. They enforce feasibility by restricting and projecting their policy updates onto a tightened parameter set. In our work, the action produced by every fixed SDAC policy is feasible by construction. When the parameter changes online, we clip the nominal action to the current admissible interval as in (24).

Liu et al. consider general convex constraint functions [4]. For their adversarial constraints, the guarantees bound cumulative violation and may permit violations at individual times. Such violations are not permitted here, since (2) must hold at every time.

Kumar et al. introduce online convex optimization with unbounded memory [5]. For their discounted infinite-memory model, the lower bound scales as $\sqrt{T}$ divided by one minus the discount factor. This parallels our $\Omega((1-\alpha)^{-1}\sqrt{T})$ lower bound beyond the mixing time, although ours applies directly to causal feasible controllers under the state-dependent action constraint.

b) Energy harvesting: Fixed-fraction and related allocation policies for stochastic energy arrivals motivate our *decreasing-allocation policy class*. Shaviv and Özgür [6] allocate a fixed fraction of the available energy under i.i.d. arrivals. Arafa et al. [7] extend fixed-fraction policies to general concave utilities under i.i.d. arrivals and, for Bernoulli arrivals, characterize a non-increasing allocation sequence following a full recharge. Zibaeenejad and Chen [8] derive an optimal decreasing allocation sequence under Bernoulli arrivals when the controller observes a fixed look-ahead window. Together, these works motivate allocating each arrival over future periods according to a decreasing sequence. Our allocation begins one period after the arrival because the controller acts before observing the current arrival.

Yu and Neely [9] study expected utility maximization under i.i.d. system states, while Asgari and Neely [10] obtain an $O(\sqrt{T})$ regret–battery-capacity tradeoff for arbitrary loss sequences under i.i.d. energy arrivals. Neither objective depends directly on the battery state. Yu and Neely optimize expected time-average utility, whereas Asgari and Neely measure regret against a fixed action. Lin et al. [11] allow arbitrary energy arrivals and time-varying age-of-information objectives. They observe the current arrival before allocation and compare with an unrestricted offline optimum through a competitive ratio. In our setting, the controller acts before observing the current arrival and cost, the arrival and cost sequences may be chosen adversarially, the cost depends on the storage state and action, and the benchmark is a fixed SDAC policy chosen in hindsight.

c) Queueing and network optimization: Classical queueing control studies throughput and queue stability through dynamic service and scheduling decisions [12]–[14], while stochastic network optimization studies tradeoffs between time-average performance and average queue backlog [15]. Our performance criterion is finite-horizon regret against the best fixed SDAC policy in hindsight.

For their time-invariant class, Khojastepour and Sabharwal [16] represent schedulers satisfying a maximum-delay constraint as fixed linear filters of the current and past arrivals, with nonnegative coefficients summing to one rather than at most one as in SDAC. Under i.i.d. arrivals, they identify the uniform moving-average filter as the minimizer of long-run average transmit power over a Gaussian channel. The connection is limited to the simplex-like filter structure: they solve a stochastic average-power problem with a fixed cost, whereas our algorithm updates the SDAC parameters online under adversarial arrival and cost sequences with general convex state–action costs.

d) Inventory and reservoir management: Yang et al. [17] study online procurement under inventory constraints and obtain optimal competitive ratios relative to an offline optimum. They observe the current demand and price before acting, whereas our controller acts before the current arrival and cost are revealed. Hihat and Fermanian [18] learn a base-stock policy for more general inventory dynamics but do not prove a regret bound for their method. For our scalar linear model, we prove feasibility, approximation, and sublinear regret guarantees. Classical stochastic reservoir models study storage under random inflows and fixed release rules [19], with

an emphasis on steady-state behavior rather than finite-horizon online regret.

II. Model and Regret Benchmark

For every positive integer n, we write $[n] \triangleq \{1, \dots, n\}$. For every $z \in \mathbb{R}$, we define $[z]_+ \triangleq \max\{z, 0\}$. For $\mathbf{v} \in \mathbb{R}^n$, the i-th coordinate is denoted by v_i. If the vector already carries a subscript, the coordinate is appended after a comma: the i-th coordinate of $\mathbf{v}_t$ is $v_{t,i}$. We write $\mathbf{1}$ for the all-ones vector, with its dimension clear from context, and $\langle \cdot, \cdot \rangle$ for the Euclidean inner product. We use $\log$ for the natural logarithm.

Fix a positive integer T and a known retention coefficient $\alpha \in (0, 1)$. The state $x_t \in \mathbb{R}_{\geq 0}$ is the resource level at the beginning of time t. The system starts empty:

$$x_1 = 0. \tag{1}$$

At each time $t \in [T]$, the controller chooses an action $u_t \in \mathbb{R}_{\geq 0}$ satisfying

$$0 \leq u_t \leq \alpha x_t. \tag{2}$$

The system then receives an arrival $w_t \in [0, 1]$ and evolves according to

$$x_{t+1} = \alpha x_t - u_t + w_t. \tag{3}$$

Here, $1 - \alpha$ is the fraction of the stored resource lost during one period. The constraint (2) ensures that the action does not exceed the amount remaining after this loss.

In the online-control literature, w_t is commonly called a disturbance. Here, we call it an *arrival* because it is nonnegative, while retaining the standard names Disturbance-Action Control. The nonnegativity of w_t is important for both the storage interpretation and the feasibility properties of SDAC.

At time t, the controller chooses u_t before observing w_t or c_t. After the action is selected, the arrival and the entire cost function are revealed, the controller incurs $c_t(x_t, u_t)$, and the state is updated according to (3).

For every feasible trajectory, (3) and $w_t \in [0, 1]$ give

$$0 \leq x_{t+1} \leq \alpha x_t + 1.$$

Since $x_1 = 0$, induction gives

$$0 \leq x_t \leq \frac{1 - \alpha^{t-1}}{1 - \alpha} \leq \frac{1}{1 - \alpha}, \qquad t \in [T + 1].$$

Together with (2), this bound places every feasible state–action pair in the compact set

$$\mathcal{D}_\alpha \triangleq \left\{ (x, u) : 0 \leq x \leq \frac{1}{1 - \alpha}, 0 \leq u \leq \alpha x \right\}. \tag{4}$$

Remark 1 (Storage capacity). A storage capacity of $1/(1-\alpha)$ suffices to avoid overflow.

Each revealed cost function has the form

$$c_t : \mathbb{R}^2_{\geq 0} \to \mathbb{R}$$

and is convex in (x, u). We also assume that each c_t satisfies the following Lipschitz condition on $\mathcal{D}_\alpha$: there are constants $L_x, L_u > 0$, such that

$$|c_t(x, u) - c_t(x', u')| \leq L_x |x - x'| + L_u |u - u'| \tag{5}$$

for all $(x, u), (x', u') \in \mathcal{D}_\alpha$. We also assume access, at every $(x, u) \in \mathcal{D}_\alpha$, to a cost subgradient

$$\boldsymbol{\zeta}_t(x, u) = \big(\zeta_t^x(x, u), \zeta_t^u(x, u)\big) \in \partial c_t(x, u) \tag{6}$$

satisfying

$$|\zeta_t^x(x, u)| \leq L_x, \qquad |\zeta_t^u(x, u)| \leq L_u.$$

These subgradient bounds hold, for example, when (5) extends to an open neighborhood of $\mathcal{D}_\alpha$; see [20, Thm. 9.13].

We use x_t and u_t without parameter arguments for the trajectory generated by the online controller. Its cumulative cost is

$$J_T^{\mathrm{on}} \triangleq \sum_{t=1}^{T} c_t(x_t, u_t). \tag{7}$$

For a fixed positive integer H, let $\pi_{\mathbf{m}}$ denote the fixed SDAC policy indexed by $\mathbf{m} \in \mathcal{M}_H$, where $\mathcal{M}_H$ is defined in Section III. The *fixed-policy trajectory associated with* $\mathbf{m}$ is the unique state–action sequence $\{(x_t(\mathbf{m}), u_t(\mathbf{m}))\}_{t=1}^T$ obtained by applying $\pi_{\mathbf{m}}$ with $\mathbf{m}$ held constant at every time. Define the cumulative cost of this fixed-policy trajectory by

$$J_T(\mathbf{m}) \triangleq \sum_{t=1}^{T} c_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big).$$

The regret against the best fixed SDAC policy is defined by

$$\mathrm{Reg}_T^{\mathrm{SDAC}} \triangleq J_T^{\mathrm{on}} - \min_{\mathbf{m} \in \mathcal{M}_H} J_T(\mathbf{m}). \tag{8}$$

Our objective is to satisfy (2) at every time and achieve sublinear regret.

For the other comparator classes considered below, $x_t(k)$ and $u_t(k)$ denote the state and action induced by the feasible fixed-fraction policy $u_t(k) = k x_t(k)$ for $k \in [0, \alpha]$, while $x_t(\mathbf{q})$ and $u_t(\mathbf{q})$ denote those induced by a decreasing allocation sequence $\mathbf{q}$.

III. Simplex Disturbance-Action Control (SDAC)

A. From Disturbance-Action Control to SDAC

DAC uses a finite linear filter of past disturbances. Under standard conditions, this parameterization yields convex surrogate costs and efficient online updates. In our scalar storage model, DAC has the following form:

$$u_t = \sum_{i=1}^{H} \theta_i w_{t-i}, \tag{9}$$

where H is a positive integer (the memory horizon) and $\boldsymbol{\theta} = (\theta_1, \dots, \theta_H)^\top \in \mathbb{R}^H$ is a linear filter.

For our constrained model, an unrestricted filter does not ensure feasibility: its action can exceed αx_t or become negative. We therefore introduce *Simplex Disturbance-Action Control* (SDAC), which uses a simplex-constrained filter tailored to the storage dynamics. This restriction ensures that every fixed SDAC policy is feasible while preserving the convexity of the surrogate costs and enabling us to achieve a tractable online algorithm.

B. Policy Definition and Structural Properties

Fix a memory horizon $H \in \mathbb{N}_{>0}$ and define the subprobability simplex

$$\mathcal{M}_H \triangleq \left\{\mathbf{m} \in \mathbb{R}^H_{\geq 0} : \|\mathbf{m}\|_1 \leq 1\right\}. \tag{10}$$

With the convention $w_\tau \equiv 0$ for $\tau \leq 0$, each $\mathbf{m} \in \mathcal{M}_H$ defines an SDAC policy $\pi_{\mathbf{m}}$ through

$$u_t(\mathbf{m}) \triangleq \sum_{i=1}^{H} m_i \alpha^i w_{t-i} = \langle \boldsymbol{\phi}^u_t, \mathbf{m} \rangle, \tag{11}$$

where

$$\boldsymbol{\phi}^u_t \triangleq \left(\alpha w_{t-1}, \alpha^2 w_{t-2}, \ldots, \alpha^H w_{t-H}\right)^\top \in \mathbb{R}^H. \tag{12}$$

The resulting SDAC policy class is

$$\Pi^{\mathrm{SDAC}}_H \triangleq \{\pi_{\mathbf{m}} : \mathbf{m} \in \mathcal{M}_H\}. \tag{13}$$

We next establish two structural properties of this policy class. Every $\pi_{\mathbf{m}}$ satisfies the feasibility constraint (2), and its induced cost is convex and Lipschitz in $\mathbf{m}$. Proofs omitted from this section are collected in Appendix A.

Lemma 1 (State decomposition under SDAC)**.** *Fix a positive integer H. For $t \in [T]$ and $i \in [H]$, define*

$$r_t(i) \triangleq \sum_{j=1}^{i} \alpha^{j-1} w_{t-j}, \qquad r_t \triangleq \sum_{j=1}^{t-1} \alpha^{j-1} w_{t-j},$$

where the empty sum defining r_1 is zero. Then, for every $\mathbf{m} \in \mathcal{M}_H$ and $t \in [T]$, the fixed-policy state associated with $\mathbf{m}$ satisfies

$$x_t(\mathbf{m}) = \sum_{i=1}^{H} m_i r_t(i) + \big(1 - \sum_{i=1}^{H} m_i\big) r_t. \tag{14}$$

Equivalently, with

$$\boldsymbol{\phi}^x_t \triangleq \big(r_t(1) - r_t, \ldots, r_t(H) - r_t\big)^\top,$$

we have

$$x_t(\mathbf{m}) = r_t + \langle \boldsymbol{\phi}^x_t, \mathbf{m} \rangle.$$

Thus, $\mathbf{m} \mapsto x_t(\mathbf{m})$ is affine.

Lemma 2 (Feasibility of SDAC policies)**.** *For every $\mathbf{m} \in \mathcal{M}_H$, the fixed SDAC policy $\pi_{\mathbf{m}}$ is feasible:*

$$0 \leq u_t(\mathbf{m}) \leq \alpha x_t(\mathbf{m}) \qquad \textit{for every } t \in [T].$$

Proof. Fix $t \in [T]$. For every $i \in [H]$,

$$\alpha r_t(i) - \alpha^i w_{t-i} = \sum_{j=1}^{i-1} \alpha^j w_{t-j} \geq 0.$$

Since $\mathbf{m} \in \mathcal{M}_H$, we have $m_i \geq 0$ for every $i \in [H]$ and $1 - \sum_{i=1}^{H} m_i \geq 0$. Also, $w_{t-i} \geq 0$ for every $i \in [H]$. By the definition of r_t and the nonnegativity of the arrivals,

$$r_t = \sum_{j=1}^{t-1} \alpha^{j-1} w_{t-j} \geq 0.$$

Therefore,

$$\begin{aligned} 0 \leq u_t(\mathbf{m}) &= \sum_{i=1}^{H} m_i \alpha^i w_{t-i} \\ &\leq \sum_{i=1}^{H} m_i \alpha r_t(i) \\ &\leq \sum_{i=1}^{H} m_i \alpha r_t(i) + \alpha \left(1 - \sum_{i=1}^{H} m_i\right) r_t \\ &= \alpha x_t(\mathbf{m}), \end{aligned}$$

where the last equality follows from (14). □

Lemma 3 (Convexity and Lipschitz continuity of surrogate cost)**.** *For $t \in [T]$, define*

$$\ell_t(\mathbf{m}) \triangleq c_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big), \qquad \mathbf{m} \in \mathcal{M}_H,$$

and

$$G_\alpha \triangleq \alpha \left(\frac{L_x}{1-\alpha} + L_u\right). \tag{15}$$

Then ℓ_t is convex on $\mathcal{M}_H$, and, for all $\mathbf{m}, \mathbf{m}' \in \mathcal{M}_H$,

$$|\ell_t(\mathbf{m}) - \ell_t(\mathbf{m}')| \leq G_\alpha \|\mathbf{m} - \mathbf{m}'\|_1.$$

For each $\mathbf{m} \in \mathcal{M}_H$, use the cost subgradient from (6) *to write*

$$\begin{aligned} (\zeta^x_t, \zeta^u_t) &= \boldsymbol{\zeta}_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big), \\ \mathbf{g}_t &\triangleq \zeta^x_t \boldsymbol{\phi}^x_t + \zeta^u_t \boldsymbol{\phi}^u_t. \end{aligned} \tag{16}$$

The resulting vector satisfies

$$\mathbf{g}_t \in \partial \ell_t(\mathbf{m}), \qquad \|\mathbf{g}_t\|_\infty \leq G_\alpha.$$

C. Approximation of Decreasing-Allocation Policies

Define the set of feasible decreasing allocation sequences

$$\mathcal{Q}_\alpha \triangleq \left\{\mathbf{q} = (q_i)_{i \geq 1} : q_1 \geq q_2 \geq \cdots \geq 0, \quad \sum_{i=1}^{\infty} \frac{q_i}{\alpha^i} \leq 1\right\}. \tag{17}$$

For $\mathbf{q} \in \mathcal{Q}_\alpha$, define

$$\begin{aligned} u_t(\mathbf{q}) &\triangleq \sum_{i=1}^{t-1} q_i w_{t-i}, \\ x_{t+1}(\mathbf{q}) &= \alpha x_t(\mathbf{q}) - u_t(\mathbf{q}) + w_t, \qquad x_1(\mathbf{q}) = 0. \end{aligned} \tag{18}$$

Here, $q_i w_s$ is the amount from arrival w_s allocated i periods later. The restriction $i \geq 1$ gives a one-period delay because w_s is observed only after u_s is chosen. Policies of this form have been studied for Bernoulli recharges [7], [8]. Let

$$\Pi^{\mathrm{alloc}}_\alpha \triangleq \{\pi_{\mathbf{q}} : \mathbf{q} \in \mathcal{Q}_\alpha\}.$$

Lemma 4 (Finite-memory approximation of decreasing-allocation policies)**.** *Every policy in $\Pi^{\mathrm{alloc}}_\alpha$ is feasible for every arrival sequence with entries in $[0,1]$. Fix $\mathbf{q} \in \mathcal{Q}_\alpha$ and an integer $H \geq 1$, and define*

$$m_{H,i}(\mathbf{q}) \triangleq \frac{q_i}{\alpha^i}, \qquad i \in [H].$$

Then $\mathbf{m}_H(\mathbf{q}) \in \mathcal{M}_H$. Let

$$\mathrm{Tail}_H(\mathbf{q}) \triangleq \sum_{i=H+1}^{\infty} q_i,$$

so $\mathrm{Tail}_H(\mathbf{q}) \le \alpha^{H+1}$. *If each* c_t *satisfies* (5)*, then, for every such arrival sequence,*

$$\begin{aligned}\left|\sum_{t=1}^{T}\left[c_t\big(x_t(\mathbf{m}_H(\mathbf{q})),u_t(\mathbf{m}_H(\mathbf{q}))\big)-c_t\big(x_t(\mathbf{q}),u_t(\mathbf{q})\big)\right]\right| \\ \le\left(L_u+\frac{L_x}{1-\alpha}\right)\mathrm{Tail}_H(\mathbf{q})T \\ \le\left(L_u+\frac{L_x}{1-\alpha}\right)\alpha^{H+1}T.\end{aligned} \tag{19}$$

Corollary 1 (Fixed-fraction policies as geometric allocations)**.** *Fix* $k\in[0,\alpha]$*, set* $\lambda_k \triangleq \alpha-k$*, and define*

$$q_i(k)=k\lambda_k^{i-1},\qquad i\ge 1,$$

where $\lambda_k^0 \triangleq 1$*. Then* $\mathbf{q}(k)\in\mathcal{Q}_\alpha$ *and, for every arrival sequence with entries in* $[0,1]$*,*

$$\big(x_t(\mathbf{q}(k)),u_t(\mathbf{q}(k))\big)=\big(x_t(k),u_t(k)\big),\qquad t\in[T].$$

Thus, $\pi_{\mathbf{q}(k)}$ *realizes the feasible fixed-fraction policy* $u_t(k)=kx_t(k)$*. For every integer* $H\ge 1$*, define its SDAC truncation by*

$$\mathbf{m}_H^{\mathrm{frac}}(k)\triangleq\mathbf{m}_H\big(\mathbf{q}(k)\big)\in\mathcal{M}_H,$$

whose omitted tail is

$$\mathrm{Tail}_H\big(\mathbf{q}(k)\big)=\frac{k\lambda_k^H}{1-\lambda_k}.$$

If each c_t *satisfies* (5)*, then*

$$\begin{aligned}\left|\sum_{t=1}^{T}\left[c_t\big(x_t(\mathbf{m}_H^{\mathrm{frac}}(k)),u_t(\mathbf{m}_H^{\mathrm{frac}}(k))\big)-c_t\big(x_t(k),u_t(k)\big)\right]\right| \\ \le\left(L_u+\frac{L_x}{1-\alpha}\right)\frac{k\lambda_k^H}{1-\lambda_k}\,T.\end{aligned} \tag{20}$$

IV. Online SDAC Controller

The controller maintains a parameter $\mathbf{m}_t\in\mathcal{M}_H$ and updates it by OMD with unnormalized negentropy and step size $\eta>0$ [21]:

$$\Psi(\mathbf{m})\triangleq\sum_{i=1}^{H}\big(m_i\log m_i-m_i\big),\qquad \mathbf{m}\in\mathbb{R}^H_{\ge 0}, \tag{21}$$

where $0\log 0\triangleq 0$. For $\mathbf{m}\in\mathbb{R}^H_{\ge 0}$ and $\mathbf{v}\in\mathbb{R}^H_{>0}$, its Bregman divergence is

$$D_\Psi(\mathbf{m}\|\mathbf{v})\triangleq\sum_{i=1}^{H}\Big(m_i\log\tfrac{m_i}{v_i}-m_i+v_i\Big). \tag{22}$$

Initialize the online parameter as

$$\mathbf{m}_1\triangleq\frac{1}{H+1}\mathbf{1}. \tag{23}$$

a) Action selection: At the start of round t, the controller has the online parameter $\mathbf{m}_t$. For $t=1$, this parameter is initialized according to (23); for $t\ge 2$, it is the output of the OMD update from round $t-1$. Because $\mathbf{m}_t$ varies with t, the nominal action $\langle\boldsymbol{\phi}_t^u,\mathbf{m}_t\rangle$ may exceed the current upper bound αx_t. The controller therefore selects

$$u_t\triangleq\min\{\langle\boldsymbol{\phi}_t^u,\mathbf{m}_t\rangle,\alpha x_t\}. \tag{24}$$

The state then evolves according to (3). Since $\boldsymbol{\phi}_t^u$ and $\mathbf{m}_t$ are componentwise nonnegative, $\langle\boldsymbol{\phi}_t^u,\mathbf{m}_t\rangle\ge 0$. If $x_t\ge 0$, then (24) gives $0\le u_t\le\alpha x_t$, and (3) gives $x_{t+1}\ge w_t\ge 0$. Since $x_1=0$, induction shows that the online trajectory is feasible.

The clipping step also has an interesting interpretation. Lemma 6 shows that the D_Ψ-projection of $\mathbf{m}_t$ onto the parameters compatible with x_t induces exactly the clipped action u_t.

b) Surrogate cost and OMD update: After w_t and c_t are revealed, the controller evaluates the subgradient $\mathbf{g}_t$ in (16) at $\mathbf{m}_t$ and sets

$$\mathbf{m}_{t+1}\triangleq\operatorname*{arg\,min}_{\mathbf{m}\in\mathcal{M}_H}\{\eta\langle\mathbf{g}_t,\mathbf{m}\rangle+D_\Psi(\mathbf{m}\|\mathbf{m}_t)\}. \tag{25}$$

Lemma 8 gives a two-step implementation. First, take the coordinatewise multiplicative step

$$\widetilde{m}_{t+1,i}\triangleq m_{t,i}\exp\big(-\eta g_{t,i}\big),\qquad i\in[H]. \tag{26}$$

Next, project onto $\mathcal{M}_H$, which here amounts to rescaling if needed:

$$\mathbf{m}_{t+1}\triangleq\mathrm{Proj}^{\Psi}_{\mathcal{M}_H}(\widetilde{\mathbf{m}}_{t+1})=\frac{\widetilde{\mathbf{m}}_{t+1}}{\max\{1,\|\widetilde{\mathbf{m}}_{t+1}\|_1\}}, \tag{27}$$

where the equality follows from Lemma 7.

V. Regret Upper Bounds

The following theorem states that the online SDAC controller achieves sublinear regret relative to every fixed SDAC policy $\pi_{\mathbf{m}}\in\Pi_H^{\mathrm{SDAC}}$. Proofs omitted from this section are collected in Appendix C.

Theorem 1 (Regret against fixed SDAC policies)**.** *Suppose the cost functions satisfy the regularity and bounded-subgradient assumptions of Section II. Then the controller from Section IV, initialized as in* (23) *and using step size* $\eta>0$*, satisfies, for the regret defined in* (8)*,*

$$\mathrm{Reg}_T^{\mathrm{SDAC}}\le\frac{\log(H+1)}{\eta}+\eta T\Gamma_\alpha, \tag{28}$$

where

$$\Gamma_\alpha\triangleq\frac{G_\alpha^2}{2}+\frac{\alpha G_\alpha(L_x+\alpha L_u)}{(1-\alpha)^2}, \tag{29}$$

and $G_\alpha=\alpha\big(\frac{L_x}{1-\alpha}+L_u\big)$ *as in* (15)*. In particular, the choice*

$$\eta^*=\sqrt{\frac{\log(H+1)}{T\Gamma_\alpha}}$$

gives

$$\mathrm{Reg}_T^{\mathrm{SDAC}}\le 2\sqrt{\Gamma_\alpha T\log(H+1)}.$$

For fixed $L_x, L_u > 0$, the leading factor obeys

$$\sqrt{\Gamma_\alpha} = \Theta(\alpha) \quad \text{as } \alpha \downarrow 0,$$

and

$$\sqrt{\Gamma_\alpha} = \Theta\Big((1-\alpha)^{-3/2}\Big) \quad \text{as } \alpha \uparrow 1.$$

The nonstandard step is to control the difference between the realized online trajectory and the fixed-policy trajectory associated with the current online parameter $\mathbf{m}_t$.

Lemma 5 (Stability under online parameter updates)**.** *For the online trajectory and the fixed-policy trajectory associated with the current online parameter $\mathbf{m}_t$, one has, for every $t \in [T]$,*

$$|x_t - x_t(\mathbf{m}_t)| \le \frac{\alpha\eta G_\alpha}{(1-\alpha)^2}, \tag{30}$$

$$0 \le u_t(\mathbf{m}_t) - u_t \le \frac{\alpha^2\eta G_\alpha}{(1-\alpha)^2}. \tag{31}$$

By definition of the fixed-policy trajectory, $x_t(\mathbf{m}_t)$ is generated by holding $\mathbf{m}_t$ constant from time 1 through time t. Consequently,

$$\sum_{t=1}^{T}\Big(c_t(x_t,u_t) - \ell_t(\mathbf{m}_t)\Big) \le \frac{\alpha\eta T G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2}. \tag{32}$$

The proof of Theorem 1 has three steps. First, the OMD bound for the surrogate costs gives

$$\sum_{t=1}^{T}\ell_t(\mathbf{m}_t) - \min_{\mathbf{m}\in\mathcal{M}_H}\sum_{t=1}^{T}\ell_t(\mathbf{m}) \le \frac{\log(H+1)}{\eta} + \frac{\eta G_\alpha^2 T}{2}.$$

Second, (32) controls the difference between the realized and surrogate costs. Third, adding the two bounds and using (29) gives (28); optimizing over η gives the stated choice η^*.

Theorem 1 and Lemma 4 give the following comparator guarantee.

Corollary 2 (No-regret against decreasing-allocation policies)**.** *Set*

$$H_T \triangleq \max\left\{1, \left\lceil \frac{\log T}{\log(1/\alpha)} \right\rceil\right\},$$

and run the online SDAC controller with action clipping, memory horizon $H = H_T$, and the step size η^* of Theorem 1. For $\mathbf{q} \in \mathcal{Q}_\alpha$, let

$$J_T(\mathbf{q}) \triangleq \sum_{t=1}^{T} c_t\big(x_t(\mathbf{q}), u_t(\mathbf{q})\big)$$

and

$$\mathrm{Reg}_T^{\mathrm{alloc}} \triangleq J_T^{\mathrm{on}} - \inf_{\mathbf{q}\in\mathcal{Q}_\alpha} J_T(\mathbf{q}).$$

Then

$$\begin{aligned}\mathrm{Reg}_T^{\mathrm{alloc}} &\le 2\sqrt{\Gamma_\alpha T\log(H_T+1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha}\right)\alpha^{H_T+1}T.\end{aligned} \tag{33}$$

Here Γ_α is defined in (29)*. Since $\alpha^{H_T} \le 1/T$ and $\log(H_T+1) = O(\log\log T)$ as $T \to \infty$, the approximation term is $O(1)$. Consequently,*

$$\mathrm{Reg}_T^{\mathrm{alloc}} = O\Big(\sqrt{T\log\log T}\Big) = o(T).$$

Because geometric allocation sequences induce fixed-fraction policies, the controller also satisfies a corresponding bound for that policy class.

Corollary 3 (No-regret against fixed-fraction policies)**.** *Run the online SDAC controller in Corollary 2. For $k \in [0,\alpha]$, let $J_T(k) \triangleq \sum_{t=1}^{T} c_t\big(x_t(k), u_t(k)\big)$, where $u_t(k) = kx_t(k)$, and define*

$$\mathrm{Reg}_T^{\mathrm{frac}} \triangleq J_T^{\mathrm{on}} - \min_{k\in[0,\alpha]} J_T(k).$$

For every $k \in [0,\alpha]$, with $\lambda_k = \alpha - k$,

$$\begin{aligned}J_T^{\mathrm{on}} - J_T(k) &\le 2\sqrt{\Gamma_\alpha T\log(H_T+1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha}\right)\frac{k\lambda_k^{H_T}}{1-\lambda_k}T.\end{aligned} \tag{34}$$

Moreover,

$$\begin{aligned}\mathrm{Reg}_T^{\mathrm{frac}} &\le 2\sqrt{\Gamma_\alpha T\log(H_T+1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha}\right)\alpha^{H_T+1}T \\ &= O\Big(\sqrt{T\log\log T}\Big) = o(T).\end{aligned}$$

VI. Minimax Regret Lower Bound

The next result shows that the $\sqrt{T}$ dependence is unavoidable and quantifies the necessary dependence on $1-\alpha$ for any causal feasible controller. Proofs omitted from this section are collected in Appendix D.

Theorem 2 (Minimax SDAC regret lower bound)**.** *Fix $H \ge 1$ and $T \ge 2$. For every causal feasible online controller $\mathcal{A}$, possibly randomized, there exists a deterministic oblivious sequence of arrivals and costs satisfying the assumptions of Section II such that*

$$\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}\big] \ge \frac{1}{2\sqrt{2}}\sqrt{\sum_{t=2}^{T}\beta_t^2}, \tag{35}$$

where

$$\beta_t \triangleq \alpha\left(L_u + \frac{L_x(1-\alpha^{t-2})}{1-\alpha}\right). \tag{36}$$

The expectation is only over the internal randomization of $\mathcal{A}$; the adversarial sequence is deterministic and fixed before the interaction.

Corollary 4 (Lower bound beyond the mixing time)**.** *Define*

$$t_{\mathrm{mix}}(\alpha) \triangleq \left\lceil \frac{\log 2}{\log(1/\alpha)} \right\rceil. \tag{37}$$

If $T \ge 2t_{\mathrm{mix}}(\alpha) + 2$, then every causal feasible controller $\mathcal{A}$ admits a deterministic oblivious sequence for which

$$\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}\big] \ge \frac{G_\alpha}{8}\sqrt{T}, \tag{38}$$

where $G_\alpha = \alpha(L_x/(1-\alpha) + L_u)$ as in (15)*.*

Remark 2 (Large-α regime). As $\alpha \uparrow 1$, stored arrivals persist longer and $t_{\mathrm{mix}}(\alpha) = \Theta((1-\alpha)^{-1})$. Hence, Corollary 4 yields

$$\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}\big] = \Omega\left(\frac{\sqrt{T}}{1-\alpha}\right) \tag{39}$$

whenever $T \geq 2t_{\mathrm{mix}}(\alpha) + 2$. The upper bound in Theorem 1 is $O((1-\alpha)^{-3/2}\sqrt{T\log(H+1)})$, leaving a factor of $(1-\alpha)^{-1/2}$ between the two bounds.

The condition $T \geq 2t_{\mathrm{mix}}(\alpha)+2$ is essential for interpreting the large-α asymptotic. If T is fixed while $\alpha \uparrow 1$, then

$$\frac{1-\alpha^{t-2}}{1-\alpha} \longrightarrow t-2,$$

and the right-hand side of (35) converges to the finite quantity

$$\frac{1}{2\sqrt{2}}\sqrt{\sum_{t=2}^{T}\big(L_u + L_x(t-2)\big)^2}.$$

Thus, for fixed T, the exact finite-horizon bound in (35) applies instead of the long-horizon scaling in (39).

VII. Discussion and Extensions

We briefly discuss three extensions. In each case, the feasibility, convexity, and stability arguments used above continue to apply after the corresponding changes to the policy domain and the Lipschitz constants. We state these changes but omit the resulting regret bounds, whose form is unchanged up to the modified constants and, in the vector settings, the chosen product norm.

a) Retention $\alpha \geq 1$: For $\alpha \geq 1$, fix k such that $\bar{\alpha} \triangleq \alpha - k \in (0,1)$ and write $u_t = kx_t + v_t$. Then

$$x_{t+1} = \bar{\alpha}x_t - v_t + w_t.$$

An SDAC filter for v_t uses the powers $\bar{\alpha}^i$. If $0 \leq v_t \leq \bar{\alpha}x_t$, then

$$kx_t \leq u_t = kx_t + v_t \leq (k+\bar{\alpha})x_t = \alpha x_t,$$

so the original feasibility constraint (2) is satisfied. Since

$$x_{t+1} \leq \bar{\alpha}x_t + 1, \qquad x_1 = 0,$$

induction gives $x_t \leq 1/(1-\bar{\alpha})$. The transformed cost $c_t(x, kx+v)$ remains convex in (x,v). Thus the analysis applies when the costs satisfy the corresponding Lipschitz and bounded-subgradient assumptions on the bounded domain

$$0 \leq x \leq \frac{1}{1-\bar{\alpha}}, \qquad kx \leq u \leq \alpha x.$$

For a fixed k, the comparator class is correspondingly restricted to policies whose actions satisfy $u_t \geq kx_t$. Selecting k, either in advance or online, remains an interesting direction for future work.

b) Vector actions and multi-task allocation: Consider a single storage state x_t with a vector action $\mathbf{u}_t \in \mathbb{R}^n_{\geq 0}$ that allocates resources across n tasks, subject to $\sum_{a=1}^n u_{t,a} \leq \alpha x_t$. Thus, the total drain from storage is the sum of the task allocations. The dynamics remain $x_{t+1} = \alpha x_t - \sum_{a=1}^n u_{t,a} + w_t$, and the cost $c_t(x_t, \mathbf{u}_t)$ is convex in $(x, \mathbf{u})$. Replace $\mathbf{m} \in \mathcal{M}_H$ with a matrix $\mathbf{M} \in \mathbb{R}^{n\times H}_{\geq 0}$ satisfying

$$\sum_{a=1}^{n}\sum_{i=1}^{H} M_{a,i} \leq 1, \qquad u_{t,a}(\mathbf{M}) = \sum_{i=1}^{H} M_{a,i}\alpha^i w_{t-i}.$$

Set $m_i = \sum_{a=1}^n M_{a,i}$. Then

$$m_i \geq 0, \qquad \sum_{i=1}^{H} m_i = \sum_{a=1}^{n}\sum_{i=1}^{H} M_{a,i} \leq 1,$$

so $\mathbf{m} \in \mathcal{M}_H$. Moreover,

$$\sum_{a=1}^{n} u_{t,a}(\mathbf{M}) = \sum_{i=1}^{H} m_i\alpha^i w_{t-i} \leq \alpha x_t(\mathbf{M}),$$

where the inequality is the scalar SDAC feasibility bound. Both the state and vector action are affine in $\mathbf{M}$. Therefore,

$$c_t\big(x_t(\mathbf{M}), \mathbf{u}_t(\mathbf{M})\big)$$

is convex in $\mathbf{M}$. For the online SDAC controller, a nominal vector that exceeds the available total resource can be scaled proportionally so that its entries remain nonnegative and sum to αx_t. Under an ℓ_1 Lipschitz bound in the action, the size of this correction equals the excess total action, and the stability proof proceeds with the corresponding matrix norm. OMD then runs over the matrix subprobability simplex above.

c) Multiple storage states with diagonal dynamics: Suppose the state is $\mathbf{x}_t \in \mathbb{R}^d_{\geq 0}$ and evolves according to $\mathbf{x}_{t+1} = \mathbf{A}\mathbf{x}_t - \mathbf{u}_t + \mathbf{w}_t$, where $\mathbf{A} = \mathrm{diag}(\alpha_1, \ldots, \alpha_d)$, $\alpha_s \in (0,1)$ for $s \in [d]$, the arrivals satisfy $\mathbf{w}_t \in [0,1]^d$, and the per-storage constraints are $0 \leq u_{t,s} \leq \alpha_s x_{t,s}$. Assign one SDAC parameter in $\mathcal{M}_H$ to each storage and use the powers α_s^i in coordinate s. The dynamics and feasibility constraints then decouple by storage, and the SDAC parameter domain is a product of subprobability simplices, with $x_{t,s} \leq 1/(1-\alpha_s)$ for every $s \in [d]$. The online SDAC controller clips each nominal action to $\alpha_s x_{t,s}$. If the cost is jointly convex and satisfies compatible Lipschitz and bounded-subgradient assumptions on the resulting bounded product domain, the surrogate cost is jointly convex in all SDAC parameters and OMD applies on the product set. The update separates by storage only when the cost is coordinate-separable; otherwise it is a joint update. Cross-coupled storage systems (nondiagonal $\mathbf{A}$) require additional analysis and remain an interesting direction for future work.

VIII. Conclusion

We studied adversarial online control of a storage system under a state-dependent action constraint. We introduced SDAC so that every fixed-policy trajectory is feasible and developed an online SDAC controller with $O\Big(\sqrt{T\log(H+1)}\Big)$ regret against the best fixed SDAC policy. Once T is at least on the order of $(1-\alpha)^{-1}$, the minimax lower bound gives $\Omega((1-\alpha)^{-1}\sqrt{T})$ regret as $\alpha \uparrow 1$; hence, a factor of $(1-\alpha)^{-1/2}$ between the upper and lower bounds remains open. The SDAC approximation results further give $O\big(\sqrt{T\log\log T}\big)$ regret against the best decreasing-allocation policy when $H = \Theta(\log T)$. The model applies directly to energy-harvesting battery management and related settings in which storage limits must be respected in real time.

APPENDIX A
PROOFS FOR SIMPLEX DISTURBANCE-ACTION CONTROL

Proof of Lemma 1. For $t \in [T]$ and $i \in [H]$, the definitions give

$$\begin{aligned} r_{t+1} &= \sum_{j=1}^{t} \alpha^{j-1} w_{t+1-j} \\ &= w_t + \sum_{j=1}^{t-1} \alpha^j w_{t-j} = w_t + \alpha r_t, \\ r_{t+1}(i) &= \sum_{j=1}^{i} \alpha^{j-1} w_{t+1-j} \\ &= w_t + \sum_{j=1}^{i-1} \alpha^j w_{t-j} = w_t + \alpha r_t(i) - \alpha^i w_{t-i}. \end{aligned}$$

The sum from $j = 1$ to $s - 1$ is empty when $s = 1$.

At $t = 1$, (1) gives $x_1(\mathbf{m}) = 0$, while $r_1(i) = r_1 = 0$ by the arrival and empty-sum conventions. Thus, (14) holds at $t = 1$. Suppose it holds at some t with $1 \le t < T$. By (3) and (11),

$$\begin{aligned} x_{t+1}(\mathbf{m}) &= \alpha x_t(\mathbf{m}) - u_t(\mathbf{m}) + w_t \\ &= \alpha \left[\sum_{i=1}^{H} m_i r_t(i) + \left(1 - \sum_{i=1}^{H} m_i\right) r_t \right] \\ &\quad - \sum_{i=1}^{H} m_i \alpha^i w_{t-i} + w_t \\ &= \sum_{i=1}^{H} m_i \big(\alpha r_t(i) - \alpha^i w_{t-i}\big) \\ &\quad + \left(1 - \sum_{i=1}^{H} m_i\right) \alpha r_t + w_t \\ &= \sum_{i=1}^{H} m_i \big(r_{t+1}(i) - w_t\big) \\ &\quad + \left(1 - \sum_{i=1}^{H} m_i\right) (r_{t+1} - w_t) + w_t \\ &= \sum_{i=1}^{H} m_i r_{t+1}(i) + \left(1 - \sum_{i=1}^{H} m_i\right) r_{t+1}. \end{aligned}$$

Thus, (14) follows by induction. □

Proof of Lemma 3. Lemma 1 and (11) give

$$x_t(\mathbf{m}) = r_t + \langle \boldsymbol{\phi}_t^x, \mathbf{m} \rangle, \qquad u_t(\mathbf{m}) = \langle \boldsymbol{\phi}_t^u, \mathbf{m} \rangle. \tag{40}$$

For $i \in [H]$, Lemma 1 and the definitions of $r_t(i)$ and r_t give

$$\begin{aligned} |\phi_{t,i}^x| = r_t - r_t(i) &= \sum_{j=i+1}^{t-1} \alpha^{j-1} w_{t-j} \\ &\le \sum_{j=i+1}^{\infty} \alpha^{j-1} = \frac{\alpha^i}{1-\alpha} \le \frac{\alpha}{1-\alpha}, \\ 0 \le \phi_{t,i}^u = \alpha^i w_{t-i} &\le \alpha^i \le \alpha. \end{aligned}$$

The sum is empty when $i \ge t - 1$. Taking the maximum over $i \in [H]$ gives

$$\|\boldsymbol{\phi}_t^x\|_\infty \le \frac{\alpha}{1-\alpha}, \qquad \|\boldsymbol{\phi}_t^u\|_\infty \le \alpha. \tag{41}$$

Since the state–action pair in (40) is affine in $\mathbf{m}$ and c_t is convex, ℓ_t is convex.

By Lemma 2, the fixed-policy state–action pairs associated with $\mathbf{m}$ and $\mathbf{m}'$ belong to $\mathcal{D}_\alpha$. Thus, (5), (40), Hölder's inequality, and (41) give

$$\begin{aligned} |\ell_t(\mathbf{m}) - \ell_t(\mathbf{m}')| &\le L_x |x_t(\mathbf{m}) - x_t(\mathbf{m}')| \\ &\quad + L_u |u_t(\mathbf{m}) - u_t(\mathbf{m}')| \\ &= L_x \big|\langle \boldsymbol{\phi}_t^x, \mathbf{m} - \mathbf{m}' \rangle\big| \\ &\quad + L_u \big|\langle \boldsymbol{\phi}_t^u, \mathbf{m} - \mathbf{m}' \rangle\big| \\ &\le \left(\frac{\alpha L_x}{1-\alpha} + \alpha L_u \right) \|\mathbf{m} - \mathbf{m}'\|_1 \\ &= G_\alpha \|\mathbf{m} - \mathbf{m}'\|_1. \end{aligned}$$

Fix $\mathbf{m} \in \mathcal{M}_H$, and let (ζ_t^x, ζ_t^u) and $\mathbf{g}_t$ be defined by (16). For every $\mathbf{m}' \in \mathcal{M}_H$, the subgradient inequality gives

$$\begin{aligned} \ell_t(\mathbf{m}') &= c_t\big(x_t(\mathbf{m}'), u_t(\mathbf{m}')\big) \\ &\ge c_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big) \\ &\quad + \zeta_t^x \big(x_t(\mathbf{m}') - x_t(\mathbf{m})\big) + \zeta_t^u \big(u_t(\mathbf{m}') - u_t(\mathbf{m})\big) \\ &= \ell_t(\mathbf{m}) + \zeta_t^x \langle \boldsymbol{\phi}_t^x, \mathbf{m}' - \mathbf{m} \rangle + \zeta_t^u \langle \boldsymbol{\phi}_t^u, \mathbf{m}' - \mathbf{m} \rangle \\ &= \ell_t(\mathbf{m}) + \langle \mathbf{g}_t, \mathbf{m}' - \mathbf{m} \rangle. \end{aligned}$$

Thus $\mathbf{g}_t \in \partial \ell_t(\mathbf{m})$. The bounded-subgradient assumption and (41) give

$$\begin{aligned} \|\mathbf{g}_t\|_\infty &\le |\zeta_t^x| \|\boldsymbol{\phi}_t^x\|_\infty + |\zeta_t^u| \|\boldsymbol{\phi}_t^u\|_\infty \\ &\le \frac{\alpha L_x}{1-\alpha} + \alpha L_u \\ &= G_\alpha. \end{aligned}$$

□

Proof of Lemma 4. Since $\mathbf{q} \in \mathcal{Q}_\alpha$,

$$m_{H,i}(\mathbf{q}) = \frac{q_i}{\alpha^i} \ge 0, \qquad \|\mathbf{m}_H(\mathbf{q})\|_1 = \sum_{i=1}^{H} \frac{q_i}{\alpha^i} \le 1.$$

Thus $\mathbf{m}_H(\mathbf{q}) \in \mathcal{M}_H$.

We next prove that $\pi_{\mathbf{q}}$ is feasible. For this purpose, take the truncation length to be T. Using $w_\tau = 0$ for $\tau \le 0$, for every $t \in [T]$,

$$u_t\big(\mathbf{m}_T(\mathbf{q})\big) = \sum_{i=1}^{T} \frac{q_i}{\alpha^i} \alpha^i w_{t-i} = \sum_{i=1}^{t-1} q_i w_{t-i} = u_t(\mathbf{q}).$$

The two policies have the same initial state and state recursion, so their state trajectories coincide. Lemma 2 therefore gives

$$0 \le u_t(\mathbf{q}) \le \alpha x_t(\mathbf{q}), \qquad t \in [T].$$

For the approximation error, define

$$e_t^u \triangleq u_t(\mathbf{q}) - u_t\big(\mathbf{m}_H(\mathbf{q})\big), \qquad e_t^x \triangleq x_t\big(\mathbf{m}_H(\mathbf{q})\big) - x_t(\mathbf{q}).$$

Again using $w_\tau = 0$ for $\tau \le 0$,

$$e_t^u = \sum_{i=H+1}^{\infty} q_i w_{t-i}, \qquad 0 \le e_t^u \le \mathrm{Tail}_H(\mathbf{q}).$$

Subtracting the two state recursions gives

$$e^x_{t+1} = \alpha e^x_t + e^u_t, \qquad e^x_1 = 0.$$

Hence, with the sum understood to be zero at $t = 1$,

$$\begin{aligned} 0 \le e^x_t &= \sum_{s=1}^{t-1} \alpha^{t-1-s} e^u_s \le \mathrm{Tail}_H(\mathbf{q}) \sum_{s=1}^{t-1} \alpha^{t-1-s} \\ &= \mathrm{Tail}_H(\mathbf{q}) \frac{1-\alpha^{t-1}}{1-\alpha} \le \frac{\mathrm{Tail}_H(\mathbf{q})}{1-\alpha}. \end{aligned}$$

Both policies are feasible, so their state–action pairs belong to $\mathcal{D}_\alpha$. By (5) and the triangle inequality,

$$\begin{aligned} &\left| \sum_{t=1}^{T} \left[c_t\big(x_t(\mathbf{m}_H(\mathbf{q})), u_t(\mathbf{m}_H(\mathbf{q}))\big) - c_t\big(x_t(\mathbf{q}), u_t(\mathbf{q})\big) \right] \right| \\ &\quad \le \sum_{t=1}^{T} (L_x e^x_t + L_u e^u_t) \le \left(L_u + \frac{L_x}{1-\alpha} \right) \mathrm{Tail}_H(\mathbf{q}) T. \end{aligned}$$

Finally, since $\alpha \in (0,1)$,

$$\mathrm{Tail}_H(\mathbf{q}) = \sum_{i=H+1}^{\infty} \alpha^i \frac{q_i}{\alpha^i} \le \alpha^{H+1} \sum_{i=H+1}^{\infty} \frac{q_i}{\alpha^i} \le \alpha^{H+1}.$$

This proves (19). □

Proof of Corollary 1. Since $0 \le \lambda_k \le \alpha < 1$,

$$q_i(k) \ge 0, \qquad q_{i+1}(k) = \lambda_k q_i(k) \le q_i(k), \qquad i \ge 1.$$

If $k = 0$, then $\mathbf{q}(k) = \mathbf{0} \in \mathcal{Q}_\alpha$. If $k > 0$, then $0 \le \lambda_k/\alpha < 1$ and

$$\begin{aligned} \sum_{i=1}^{\infty} \frac{q_i(k)}{\alpha^i} &= \frac{k}{\alpha} \sum_{j=0}^{\infty} \left(\frac{\lambda_k}{\alpha} \right)^j = \frac{k}{\alpha} \frac{1}{1-\lambda_k/\alpha} \\ &= \frac{k}{\alpha - \lambda_k} = 1. \end{aligned}$$

Thus, $\mathbf{q}(k) \in \mathcal{Q}_\alpha$.

Under the fixed-fraction policy, (3) becomes

$$x_{t+1}(k) = \lambda_k x_t(k) + w_t.$$

Iterating this recursion from $x_1(k) = 0$ gives

$$\begin{aligned} x_t(k) &= \sum_{i=1}^{t-1} \lambda_k^{i-1} w_{t-i}, \\ u_t(k) &= k x_t(k) = \sum_{i=1}^{t-1} q_i(k) w_{t-i} = u_t\big(\mathbf{q}(k)\big). \end{aligned}$$

The two policies have the same actions, initial state, and dynamics. Hence, their state trajectories coincide. Lemma 4 gives $\mathbf{m}^{\mathrm{frac}}_H(k) \in \mathcal{M}_H$. Moreover,

$$\begin{aligned} \mathrm{Tail}_H\big(\mathbf{q}(k)\big) &= k \sum_{i=H+1}^{\infty} \lambda_k^{i-1} = k \lambda_k^H \sum_{j=0}^{\infty} \lambda_k^j \\ &= \frac{k \lambda_k^H}{1-\lambda_k}. \end{aligned}$$

Substituting the trajectory and tail identities into (19) proves (20). □

APPENDIX B
PROOFS FOR THE ONLINE SDAC CONTROLLER

Lemma 6 (Action clipping as a Bregman projection)**.** *For $t \in [T]$, define the set of parameters compatible with the current state by*

$$\mathcal{B}_t(x_t) \triangleq \{\mathbf{m} \in \mathcal{M}_H : \langle \boldsymbol{\phi}^u_t, \mathbf{m} \rangle \le \alpha x_t\}.$$

Let $\mathbf{m}^{\mathrm{exec}}_t$ be the Bregman projection of $\mathbf{m}_t$ onto $\mathcal{B}_t(x_t)$:

$$\mathbf{m}^{\mathrm{exec}}_t \in \operatorname*{arg\,min}_{\mathbf{m} \in \mathcal{B}_t(x_t)} D_\Psi(\mathbf{m} \| \mathbf{m}_t).$$

Then

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle = \min\{\langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle, \alpha x_t\} = u_t.$$

Proof. The online state satisfies $x_t \ge 0$, so $\mathbf{0} \in \mathcal{B}_t(x_t)$. This set is compact and convex because it is the intersection of $\mathcal{M}_H$ and a closed halfspace. By (23) and the update (26)–(27), every coordinate of $\mathbf{m}_t$ is positive. Thus, $D_\Psi(\cdot\|\mathbf{m}_t)$ is continuous and strictly convex on $\mathcal{M}_H$, so the projection exists and is unique. Moreover, $D_\Psi(\mathbf{m}\|\mathbf{m}_t) \ge 0$, with equality only at $\mathbf{m} = \mathbf{m}_t$.

If

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle \le \alpha x_t,$$

then $\mathbf{m}_t \in \mathcal{B}_t(x_t)$ and $\mathbf{m}^{\mathrm{exec}}_t = \mathbf{m}_t$.

Now suppose

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle > \alpha x_t.$$

Since $\mathbf{m}^{\mathrm{exec}}_t \in \mathcal{B}_t(x_t)$,

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle \le \alpha x_t < \langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle.$$

Suppose, for contradiction, that the action constraint is slack at $\mathbf{m}^{\mathrm{exec}}_t$:

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle < \alpha x_t < \langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle.$$

We move a small distance from $\mathbf{m}^{\mathrm{exec}}_t$ toward $\mathbf{m}_t$. The step is chosen to remain in $\mathcal{B}_t(x_t)$; strict convexity will then give a smaller Bregman divergence, contradicting the optimality of $\mathbf{m}^{\mathrm{exec}}_t$. Choose $0 < \delta < 1$ such that

$$\delta\left(\langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle - \langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle\right) < \alpha x_t - \langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle.$$

Such a δ exists because both differences are positive. Set

$$\mathbf{m}_\delta \triangleq (1-\delta)\mathbf{m}^{\mathrm{exec}}_t + \delta \mathbf{m}_t.$$

By convexity, $\mathbf{m}_\delta \in \mathcal{M}_H$, and

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}_\delta \rangle = \langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle + \delta\left(\langle \boldsymbol{\phi}^u_t, \mathbf{m}_t \rangle - \langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle\right) < \alpha x_t.$$

Thus $\mathbf{m}_\delta \in \mathcal{B}_t(x_t)$. Since $\mathbf{m}_t \notin \mathcal{B}_t(x_t)$, $\mathbf{m}^{\mathrm{exec}}_t \ne \mathbf{m}_t$, and hence $D_\Psi(\mathbf{m}^{\mathrm{exec}}_t\|\mathbf{m}_t) > 0$. Strict convexity and $D_\Psi(\mathbf{m}_t\|\mathbf{m}_t) = 0$ give

$$\begin{aligned} D_\Psi(\mathbf{m}_\delta\|\mathbf{m}_t) &< (1-\delta) D_\Psi(\mathbf{m}^{\mathrm{exec}}_t\|\mathbf{m}_t) + \delta D_\Psi(\mathbf{m}_t\|\mathbf{m}_t) \\ &= (1-\delta) D_\Psi(\mathbf{m}^{\mathrm{exec}}_t\|\mathbf{m}_t) \\ &< D_\Psi(\mathbf{m}^{\mathrm{exec}}_t\|\mathbf{m}_t), \end{aligned}$$

contradicting the definition of $\mathbf{m}^{\mathrm{exec}}_t$. Therefore, the constraint is active:

$$\langle \boldsymbol{\phi}^u_t, \mathbf{m}^{\mathrm{exec}}_t \rangle = \alpha x_t.$$

Combining the two cases with (24) proves the result. □

Lemma 7 (Bregman projection onto $\mathcal{M}_H$)**.** *For the Bregman divergence D_Ψ in* (22) *and every $\widetilde{\mathbf{m}} \in \mathbb{R}^H_{>0}$,*

$$\mathrm{Proj}^{\Psi}_{\mathcal{M}_H}(\widetilde{\mathbf{m}}) \triangleq \operatorname*{arg\,min}_{\mathbf{m}\in\mathcal{M}_H} D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}) = \frac{\widetilde{\mathbf{m}}}{\max\{1, \|\widetilde{\mathbf{m}}\|_1\}}.$$

Proof. The function $r \mapsto r\log r - r + 1$ is nonnegative for $r \geq 0$ and vanishes only at $r = 1$. Writing the ith summand in (22) as $v_i(r\log r - r + 1)$, where $r = m_i/v_i$, therefore gives

$$D_\Psi(\mathbf{m}\|\mathbf{v}) \geq 0, \qquad D_\Psi(\mathbf{m}\|\mathbf{v}) = 0 \quad\Longleftrightarrow\quad \mathbf{m} = \mathbf{v}.$$

If $\|\widetilde{\mathbf{m}}\|_1 \leq 1$, then $\widetilde{\mathbf{m}} \in \mathcal{M}_H$, so the equality condition shows that it is the unique minimizer.

Now suppose $\|\widetilde{\mathbf{m}}\|_1 > 1$ and set

$$\mathbf{m}^\star \triangleq \frac{\widetilde{\mathbf{m}}}{\|\widetilde{\mathbf{m}}\|_1}.$$

Then $\mathbf{m}^\star \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$ and

$$\widetilde{\mathbf{m}} = \|\widetilde{\mathbf{m}}\|_1\mathbf{m}^\star, \qquad \|\mathbf{m}^\star\|_1 = 1.$$

For every $i \in [H]$, the first identity gives

$$m_i \log\frac{m_i}{\widetilde{m}_i} = m_i\log\frac{m_i}{m_i^\star} - m_i\log\|\widetilde{\mathbf{m}}\|_1,$$
$$m_i^\star\log\frac{m_i^\star}{\widetilde{m}_i} = -m_i^\star\log\|\widetilde{\mathbf{m}}\|_1.$$

Using these identities in (22), for every $\mathbf{m} \in \mathcal{M}_H$,

$$\begin{aligned}
&D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}) - D_\Psi(\mathbf{m}^\star\|\widetilde{\mathbf{m}})\\
&= \sum_{i=1}^H\left(m_i\log\frac{m_i}{m_i^\star} - m_i + m_i^\star\right) + \sum_{i=1}^H(m_i^\star - m_i)\log\|\widetilde{\mathbf{m}}\|_1\\
&= D_\Psi(\mathbf{m}\|\mathbf{m}^\star) + \big(1 - \|\mathbf{m}\|_1\big)\log\|\widetilde{\mathbf{m}}\|_1 \geq 0.
\end{aligned}$$

The last inequality uses $D_\Psi(\mathbf{m}\|\mathbf{m}^\star) \geq 0$, $\|\mathbf{m}\|_1 \leq 1$, and $\log\|\widetilde{\mathbf{m}}\|_1 > 0$. Equality requires $\mathbf{m} = \mathbf{m}^\star$. Thus, $\mathbf{m}^\star$ is the unique minimizer. □

Lemma 8 (Closed-form solution of the OMD update)**.** *Fix $\mathbf{m}_t \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$, $\eta > 0$, and $\mathbf{g}_t \in \mathbb{R}^H$. Define $\widetilde{m}_{t+1,i} \triangleq m_{t,i}\exp\big(-\eta g_{t,i}\big)$ for $i \in [H]$. Then the OMD update* (25) *has the unique solution*

$$\mathbf{m}_{t+1} = \mathrm{Proj}^{\Psi}_{\mathcal{M}_H}(\widetilde{\mathbf{m}}_{t+1}) = \frac{\widetilde{\mathbf{m}}_{t+1}}{\max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\}}.$$

Moreover, $\mathbf{m}_{t+1} \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$. Hence, the initialization (23) *keeps every OMD iterate strictly positive.*

Proof. Fix $\mathbf{m} \in \mathcal{M}_H$. For each i such that $m_i > 0$,

$$\log\frac{m_i}{\widetilde{m}_{t+1,i}} = \log\frac{m_i}{m_{t,i}} + \eta g_{t,i}.$$

After multiplication by m_i, this identity also holds when $m_i = 0$ under the convention $0\log 0 = 0$. Therefore, (22) gives

$$\begin{aligned}
&\eta\langle\mathbf{g}_t, \mathbf{m}\rangle + D_\Psi(\mathbf{m}\|\mathbf{m}_t)\\
&= \sum_{i=1}^H\left(\eta g_{t,i}m_i + m_i\log\frac{m_i}{m_{t,i}} - m_i + m_{t,i}\right)\\
&= \sum_{i=1}^H\left(m_i\log\frac{m_i}{\widetilde{m}_{t+1,i}} - m_i + m_{t,i}\right)\\
&= D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}_{t+1}) + \sum_{i=1}^H\left(m_{t,i} - \widetilde{m}_{t+1,i}\right).
\end{aligned}$$

The final sum is independent of $\mathbf{m}$. Thus, minimizing the OMD objective is equivalent to minimizing $D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}_{t+1})$ over $\mathcal{M}_H$. Since $\widetilde{\mathbf{m}}_{t+1} > 0$ coordinatewise, Lemma 7 gives the stated unique minimizer and formula. The formula also shows that $\mathbf{m}_{t+1} > 0$ coordinatewise. The last claim follows by induction from (23). □

Appendix C
Proofs for the Regret Upper Bounds

Lemma 9 (One-step OMD movement bound)**.** *The OMD update* (25) *with step size $\eta > 0$ satisfies*

$$\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \leq \eta\|\mathbf{g}_t\|_\infty \leq \eta G_\alpha.$$

Proof. For every $\mathbf{z} \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$ and $\mathbf{v} \in \mathbb{R}^H$, Cauchy–Schwarz and $\sum_i z_i \leq 1$ give

$$\begin{aligned}
\mathbf{v}^\top\nabla^2\Psi(\mathbf{z})\mathbf{v} &= \sum_{i=1}^H\frac{v_i^2}{z_i}\\
&\geq \frac{\|\mathbf{v}\|_1^2}{\sum_{i=1}^H z_i}\\
&\geq \|\mathbf{v}\|_1^2.
\end{aligned} \tag{42}$$

By Lemma 8, both iterates are positive. Integrating (42) along the segment joining them gives

$$D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t) \geq \frac{1}{2}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2,$$
$$D_\Psi(\mathbf{m}_t\|\mathbf{m}_{t+1}) \geq \frac{1}{2}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2.$$

Adding these bounds and using the symmetric Bregman identity,

$$\begin{aligned}
&\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2\\
&\quad\leq D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t) + D_\Psi(\mathbf{m}_t\|\mathbf{m}_{t+1})\\
&\quad= \big\langle\nabla\Psi(\mathbf{m}_{t+1}) - \nabla\Psi(\mathbf{m}_t), \mathbf{m}_{t+1} - \mathbf{m}_t\big\rangle\\
&\quad\leq \eta\langle\mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1}\rangle\\
&\quad\leq \eta\|\mathbf{g}_t\|_\infty\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1.
\end{aligned}$$

The last two inequalities use first-order optimality of (25) at the feasible point $\mathbf{m}_t$ and Hölder's inequality, respectively. If the iterates differ, divide by $\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1$; otherwise the bound is trivial. Finally, $\|\mathbf{g}_t\|_\infty \leq G_\alpha$ gives the stated uniform bound. □

Lemma 10 (OMD regret for the surrogate costs)**.** *For every $\mathbf{m} \in \mathcal{M}_H$, the update* (25) *satisfies*

$$\sum_{t=1}^T\ell_t(\mathbf{m}_t) - \sum_{t=1}^T\ell_t(\mathbf{m}) \leq \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_1)}{\eta} + \frac{\eta}{2}\sum_{t=1}^T\|\mathbf{g}_t\|_\infty^2. \tag{43}$$

Proof. Convexity of ℓ_t gives

$$\begin{aligned}
\ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m}) &\leq \langle\mathbf{g}_t, \mathbf{m}_t - \mathbf{m}\rangle\\
&= \langle\mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1}\rangle\\
&\quad + \langle\mathbf{g}_t, \mathbf{m}_{t+1} - \mathbf{m}\rangle.
\end{aligned} \tag{44}$$

First-order optimality of (25), evaluated at $\mathbf{m} \in \mathcal{M}_H$, yields

$$\begin{aligned}\eta\langle \mathbf{g}_t, \mathbf{m}_{t+1} - \mathbf{m}\rangle &\le \langle \nabla\Psi(\mathbf{m}_{t+1}) - \nabla\Psi(\mathbf{m}_t), \mathbf{m} - \mathbf{m}_{t+1}\rangle \\ &= D_\Psi(\mathbf{m}\|\mathbf{m}_t) - D_\Psi(\mathbf{m}\|\mathbf{m}_{t+1}) \\ &\quad - D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t).\end{aligned} \tag{45}$$

The equality follows from the three-point Bregman identity. Substituting (45) into (44),

$$\begin{aligned}\ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m}) &\le \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_t)}{\eta} - \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_{t+1})}{\eta} \\ &\quad + \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1}\rangle \\ &\quad - \frac{D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t)}{\eta}.\end{aligned} \tag{46}$$

The strong-convexity calculation (42) and Hölder's inequality give

$$\begin{aligned}&\langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1}\rangle - \frac{D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t)}{\eta} \\ &\quad \le \|\mathbf{g}_t\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 - \frac{\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2}{2\eta} \\ &\quad \le \frac{\eta}{2}\|\mathbf{g}_t\|_\infty^2.\end{aligned} \tag{47}$$

The last inequality follows from Young's inequality. Combining (46) and (47) and summing over t gives

$$\begin{aligned}\sum_{t=1}^{T} \ell_t(\mathbf{m}_t) - \sum_{t=1}^{T} \ell_t(\mathbf{m}) &\le \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_1)}{\eta} \\ &\quad - \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_{T+1})}{\eta} \\ &\quad + \frac{\eta}{2}\sum_{t=1}^{T} \|\mathbf{g}_t\|_\infty^2.\end{aligned}$$

Since $D_\Psi(\mathbf{m}\|\mathbf{m}_{T+1}) \ge 0$, this proves (43). □

Lemma 11 (Positive-part representation of the dynamics)**.** *For $\mathbf{m} \in \mathcal{M}_H$, define*

$$F_t(x; \mathbf{m}) \triangleq [\alpha x - \langle \boldsymbol{\phi}_t^u, \mathbf{m}\rangle]_+ + w_t. \tag{48}$$

Then the online state and the state component of every fixed-policy trajectory satisfy

$$x_{t+1} = F_t(x_t; \mathbf{m}_t), \qquad x_{t+1}(\mathbf{m}) = F_t(x_t(\mathbf{m}); \mathbf{m}). \tag{49}$$

Moreover, for all $x, x' \ge 0$ and $\mathbf{m}, \mathbf{m}' \in \mathcal{M}_H$,

$$\begin{aligned}&|F_t(x; \mathbf{m}) - F_t(x'; \mathbf{m}')| \\ &\quad \le |\alpha(x - x') - \langle \boldsymbol{\phi}_t^u, \mathbf{m} - \mathbf{m}'\rangle| \\ &\quad \le \alpha|x - x'| + \|\boldsymbol{\phi}_t^u\|_\infty \|\mathbf{m} - \mathbf{m}'\|_1.\end{aligned} \tag{50}$$

Proof. For the online trajectory, (24) implies

$$\begin{aligned}\alpha x_t - u_t &= \alpha x_t - \min\{\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle, \alpha x_t\} \\ &= [\alpha x_t - \langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle]_+ .\end{aligned} \tag{51}$$

For a fixed $\mathbf{m}$, Lemma 2 gives

$$\alpha x_t(\mathbf{m}) - \langle \boldsymbol{\phi}_t^u, \mathbf{m}\rangle \ge 0,$$

so inserting a positive part does not change its state update. This proves (49). Finally, the map $z \mapsto [z]_+$ is nonexpansive:

$$|[z]_+ - [z']_+| \le |z - z'|.$$

Applying this inequality to the two arguments in (48), followed by Hölder's inequality, gives (50). □

Proof of Lemma 5. Define

$$d_t \triangleq |x_t - x_t(\mathbf{m}_t)|.$$

Since $x_1 = x_1(\mathbf{m}_1) = 0$, we have $d_1 = 0$. For $t \in \{1, \dots, T-1\}$, Lemma 11 gives

$$\begin{aligned}d_{t+1} &= |F_t(x_t; \mathbf{m}_t) - F_t(x_t(\mathbf{m}_{t+1}); \mathbf{m}_{t+1})| \\ &\le \alpha\,|x_t - x_t(\mathbf{m}_{t+1})| + \|\boldsymbol{\phi}_t^u\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1.\end{aligned} \tag{52}$$

The affine state representation (40) implies

$$\begin{aligned}|x_t(\mathbf{m}_t) - x_t(\mathbf{m}_{t+1})| &= |\langle \boldsymbol{\phi}_t^x, \mathbf{m}_t - \mathbf{m}_{t+1}\rangle| \\ &\le \|\boldsymbol{\phi}_t^x\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1.\end{aligned} \tag{53}$$

Combining the triangle inequality with (52) and (53) yields

$$\begin{aligned}d_{t+1} &\le \alpha d_t \\ &\quad + (\alpha\|\boldsymbol{\phi}_t^x\|_\infty + \|\boldsymbol{\phi}_t^u\|_\infty)\,\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1.\end{aligned} \tag{54}$$

By (41),

$$\begin{aligned}\alpha\|\boldsymbol{\phi}_t^x\|_\infty + \|\boldsymbol{\phi}_t^u\|_\infty &\le \frac{\alpha^2}{1-\alpha} + \alpha \\ &= \frac{\alpha}{1-\alpha}.\end{aligned} \tag{55}$$

Lemma 9 and $\|\mathbf{g}_t\|_\infty \le G_\alpha$ therefore reduce (54) to

$$d_{t+1} \le \alpha d_t + \frac{\alpha\eta G_\alpha}{1-\alpha}. \tag{56}$$

Unrolling from $d_1 = 0$ gives

$$\begin{aligned}d_t &\le \frac{\alpha\eta G_\alpha}{1-\alpha}\sum_{j=0}^{t-2}\alpha^j \\ &\le \frac{\alpha\eta G_\alpha}{(1-\alpha)^2},\end{aligned} \tag{57}$$

with an empty sum when $t = 1$. This proves (30).

Finally, $\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle = u_t(\mathbf{m}_t)$, and the feasibility of fixed SDAC policies implies

$$\begin{aligned}0 \le u_t(\mathbf{m}_t) - u_t &= [u_t(\mathbf{m}_t) - \alpha x_t]_+ \\ &\le [\alpha x_t(\mathbf{m}_t) - \alpha x_t]_+ \\ &\le \alpha d_t.\end{aligned} \tag{58}$$

Combining (58) with (30) proves (31).

Both state–action pairs lie in $\mathcal{D}_\alpha$. Hence (5) and the two bounds just proved give

$$\begin{aligned}&c_t(x_t, u_t) - \ell_t(\mathbf{m}_t) \\ &\quad \le L_x\big|x_t - x_t(\mathbf{m}_t)\big| + L_u\big|u_t - u_t(\mathbf{m}_t)\big| \\ &\quad \le \frac{\alpha\eta G_\alpha L_x}{(1-\alpha)^2} + \frac{\alpha^2\eta G_\alpha L_u}{(1-\alpha)^2} \\ &\quad = \frac{\alpha\eta G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2}.\end{aligned} \tag{59}$$

Summing (59) over $t = 1, \dots, T$ proves (32). □

Proof of Theorem 1. Define the stability term

$$\mathrm{Stab}_T \triangleq \sum_{t=1}^{T}\left(c_t(x_t, u_t) - \ell_t(\mathbf{m}_t)\right).$$

Using $\ell_t(\mathbf{m}) = c_t(x_t(\mathbf{m}), u_t(\mathbf{m}))$, the regret decomposes as

$$\mathrm{Reg}_T^{\mathrm{SDAC}} = \mathrm{Stab}_T + \sum_{t=1}^{T} \ell_t(\mathbf{m}_t) - \min_{\mathbf{m}\in\mathcal{M}_H} \sum_{t=1}^{T} \ell_t(\mathbf{m}). \tag{60}$$

We first bound the initial Bregman divergence. Fix $\mathbf{m} \in \mathcal{M}_H$. Since $\mathbf{m}_1 = \frac{1}{H+1}\mathbf{1}$,

$$\begin{aligned} D_\Psi(\mathbf{m}\|\mathbf{m}_1) &= \sum_{i=1}^{H} m_i \log\big((H+1)m_i\big) \\ &\quad - \|\mathbf{m}\|_1 + \frac{H}{H+1} \\ &= \sum_{i=1}^{H} m_i \log m_i + \|\mathbf{m}\|_1 \log(H+1) \\ &\quad - \|\mathbf{m}\|_1 + \frac{H}{H+1}. \end{aligned} \tag{61}$$

Because $z \log z \le 0$ for $z \in [0,1]$,

$$D_\Psi(\mathbf{m}\|\mathbf{m}_1) \le \|\mathbf{m}\|_1 \log(H+1) - \|\mathbf{m}\|_1 + \frac{H}{H+1}. \tag{62}$$

The right-hand side is affine in $\|\mathbf{m}\|_1 \in [0,1]$, and its values at the endpoints are

$$\begin{aligned} \frac{H}{H+1} &\le \log(H+1), \\ \log(H+1) - \frac{1}{H+1} &\le \log(H+1). \end{aligned}$$

Here the first inequality follows from $\log z \ge 1 - z^{-1}$ for $z \ge 1$. Therefore,

$$D_\Psi(\mathbf{m}\|\mathbf{m}_1) \le \log(H+1) \qquad \text{for every } \mathbf{m} \in \mathcal{M}_H. \tag{63}$$

Lemma 10, $\|\mathbf{g}_t\|_\infty \le G_\alpha$, and (63) imply, for every $\mathbf{m} \in \mathcal{M}_H$,

$$\begin{aligned} \sum_{t=1}^{T} \big(\ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m})\big) &\le \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_1)}{\eta} + \frac{\eta}{2}\sum_{t=1}^{T} \|\mathbf{g}_t\|_\infty^2 \\ &\le \frac{\log(H+1)}{\eta} + \frac{\eta G_\alpha^2 T}{2}. \end{aligned} \tag{64}$$

Since (64) holds uniformly over $\mathbf{m}$,

$$\sum_{t=1}^{T} \ell_t(\mathbf{m}_t) - \min_{\mathbf{m}\in\mathcal{M}_H} \sum_{t=1}^{T} \ell_t(\mathbf{m}) \le \frac{\log(H+1)}{\eta} + \frac{\eta G_\alpha^2 T}{2}. \tag{65}$$

The stability bound (32) gives

$$\mathrm{Stab}_T \le \frac{\alpha\eta T G_\alpha (L_x + \alpha L_u)}{(1-\alpha)^2}. \tag{66}$$

Substituting (65) and (66) into (60),

$$\begin{aligned} \mathrm{Reg}_T^{\mathrm{SDAC}} &\le \frac{\log(H+1)}{\eta} + \frac{\eta T G_\alpha^2}{2} \\ &\quad + \frac{\alpha\eta T G_\alpha (L_x + \alpha L_u)}{(1-\alpha)^2} \\ &= \frac{\log(H+1)}{\eta} + \eta T \Gamma_\alpha. \end{aligned} \tag{67}$$

Differentiating with respect to η yields

$$-\frac{\log(H+1)}{\eta^2} + T\Gamma_\alpha.$$

The unique minimizer is therefore

$$\eta^* = \sqrt{\frac{\log(H+1)}{T\Gamma_\alpha}}. \tag{68}$$

At this value, the two summands in (67) are equal, so

$$\mathrm{Reg}_T^{\mathrm{SDAC}} \le 2\sqrt{\Gamma_\alpha T \log(H+1)}. \tag{69}$$

It remains to verify the dependence on α. As $\alpha \downarrow 0$,

$$\begin{aligned} \frac{G_\alpha}{\alpha} &= \frac{L_x}{1-\alpha} + L_u \longrightarrow L_x + L_u, \\ \frac{\Gamma_\alpha}{\alpha^2} &= \frac{1}{2}\left(\frac{G_\alpha}{\alpha}\right)^2 + \frac{G_\alpha}{\alpha}\frac{L_x + \alpha L_u}{(1-\alpha)^2} \\ &\longrightarrow \frac{(L_x + L_u)^2}{2} + L_x(L_x + L_u) > 0. \end{aligned}$$

Therefore $\sqrt{\Gamma_\alpha} = \Theta(\alpha)$ as $\alpha \downarrow 0$. As $\alpha \uparrow 1$, write $\varepsilon = 1 - \alpha$. Then

$$\begin{aligned} \varepsilon G_\alpha &= \alpha(L_x + \varepsilon L_u) \longrightarrow L_x, \\ \varepsilon^3 \Gamma_\alpha &= \frac{\varepsilon^3 G_\alpha^2}{2} + \alpha(\varepsilon G_\alpha)(L_x + \alpha L_u) \\ &\longrightarrow L_x(L_x + L_u) > 0. \end{aligned}$$

Thus $\sqrt{\Gamma_\alpha} = \Theta((1-\alpha)^{-3/2})$ as $\alpha \uparrow 1$. □

Proof of Corollary 2. Fix $\mathbf{q} \in \mathcal{Q}_\alpha$ and use the SDAC comparator $\mathbf{m}_{H_T}(\mathbf{q})$ from Lemma 4. Theorem 1 and (19) give

$$\begin{aligned} J_T^{\mathrm{on}} - J_T(\mathbf{q}) &\le 2\sqrt{\Gamma_\alpha T \log(H_T+1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha}\right) \mathrm{Tail}_{H_T}(\mathbf{q}) T \\ &\le 2\sqrt{\Gamma_\alpha T \log(H_T+1)} \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha}\right) \alpha^{H_T+1} T. \end{aligned}$$

The bound is uniform in $\mathbf{q}$, so taking the infimum over $\mathbf{q} \in \mathcal{Q}_\alpha$ proves (33). Finally, $H_T \ge \log T / \log(1/\alpha)$ implies $\alpha^{H_T} \le 1/T$, while $H_T = \Theta(\log T)$ implies $\log(H_T+1) = O(\log\log T)$. □

Proof of Corollary 3. For fixed k, Theorem 1 applied to $\mathbf{m}_{H_T}^{\mathrm{frac}}(k)$, followed by (20), gives (34). Corollary 1 shows that the geometric allocation sequence $\mathbf{q}(k)$ belongs to $\mathcal{Q}_\alpha$, so Lemma 4 gives $\mathrm{Tail}_{H_T}(\mathbf{q}(k)) \le \alpha^{H_T+1}$. This makes the bound uniform in k; minimizing over k proves the stated finite-time and asymptotic guarantees. □

APPENDIX D
PROOFS FOR THE MINIMAX REGRET LOWER BOUND

Proof of Theorem 2. Fix a causal feasible controller $\mathcal{A}$. Let $\xi_1, \dots, \xi_T$ be independent Rademacher random variables, also independent of the internal randomization of $\mathcal{A}$, with

$$\mathbb{P}(\xi_t = 1) = \mathbb{P}(\xi_t = -1) = \frac{1}{2}.$$

Set

$$w_t = 1 \qquad \text{for all } t \in [T], \tag{70}$$

and define the costs by

$$c_t(x,u) = \xi_t\big(L_x x - L_u u\big) \qquad \text{for all } t \in [T]. \tag{71}$$

Each c_t is affine and hence convex. For any two points in $\mathcal{D}_\alpha$,

$$\begin{aligned} |c_t(x,u) - c_t(x',u')| &= |L_x(x-x') - L_u(u-u')| \\ &\le L_x|x-x'| + L_u|u-u'|. \end{aligned} \tag{72}$$

Moreover,

$$\nabla c_t = \xi_t(L_x, -L_u), \qquad |\partial_x c_t| = L_x, \qquad |\partial_u c_t| = L_u,$$

so the required subgradient bounds hold.

We now select two fixed SDAC policies for the benchmark. The parameter $\mathbf{m}^{(0)}$ leaves all mass in the subprobability simplex unused, so its SDAC action is always zero. The parameter $\mathbf{m}^{(1)}$ places all mass on the first lag, so its action is αw_{t-1}. Let

$$\mathbf{m}^{(0)} \triangleq \mathbf{0}, \qquad \mathbf{m}^{(1)} \triangleq \mathbf{e}_1 \tag{73}$$

belong to $\mathcal{M}_H$, where $\mathbf{e}_1 = (1,0,\dots,0) \in \mathbb{R}^H$. Thus, under (70), $\mathbf{m}^{(0)}$ is the no-release policy, whereas $\mathbf{m}^{(1)}$ releases the retained portion of the preceding arrival. For the no-release policy,

$$u_t(\mathbf{m}^{(0)}) = 0, \qquad x_t(\mathbf{m}^{(0)}) = \rho_t \triangleq \frac{1-\alpha^{t-1}}{1-\alpha}. \tag{74}$$

This follows by unrolling $x_{t+1} = \alpha x_t + 1$:

$$x_t(\mathbf{m}^{(0)}) = \sum_{s=0}^{t-2} \alpha^s = \frac{1-\alpha^{t-1}}{1-\alpha}, \qquad t \ge 2,$$

and the closed form also gives $x_1(\mathbf{m}^{(0)}) = 0$. For the one-lag policy, (11) gives

$$u_1(\mathbf{m}^{(1)}) = 0, \qquad u_t(\mathbf{m}^{(1)}) = \alpha, \quad t \ge 2. \tag{75}$$

Its state at $t = 2$ is

$$x_2(\mathbf{m}^{(1)}) = \alpha x_1(\mathbf{m}^{(1)}) - u_1(\mathbf{m}^{(1)}) + w_1 = 1.$$

If $x_t(\mathbf{m}^{(1)}) = 1$ for some $t \ge 2$, then

$$\begin{aligned} x_{t+1}(\mathbf{m}^{(1)}) &= \alpha x_t(\mathbf{m}^{(1)}) - u_t(\mathbf{m}^{(1)}) + w_t \\ &= \alpha - \alpha + 1 = 1. \end{aligned}$$

Induction therefore gives

$$x_t(\mathbf{m}^{(1)}) = 1, \qquad t \ge 2. \tag{76}$$

For $t \ge 2$, the difference between the two states is

$$\begin{aligned} \Delta_t &\triangleq x_t(\mathbf{m}^{(0)}) - x_t(\mathbf{m}^{(1)}) \\ &= \rho_t - 1 \\ &= \frac{\alpha(1-\alpha^{t-2})}{1-\alpha}. \end{aligned} \tag{77}$$

The two policies have the same state and action at $t = 1$. For $t \ge 2$, (75) and (77) give

$$\begin{aligned} J_T(\mathbf{m}^{(0)}) - J_T(\mathbf{m}^{(1)}) &= \sum_{t=2}^{T} \xi_t(L_x\Delta_t + \alpha L_u) \\ &= \sum_{t=2}^{T} \xi_t \beta_t, \end{aligned} \tag{78}$$

with β_t as in (36).

Let $\mathcal{F}_t^-$ be the information available immediately before c_t is revealed, including the randomization used to select u_t. By causality, (x_t, u_t) is $\mathcal{F}_t^-$-measurable, whereas ξ_t is independent of $\mathcal{F}_t^-$ and has mean zero. Hence, by the tower property,

$$\begin{aligned} \mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}[J_T^{\mathrm{on}}] &= \sum_{t=1}^{T} \mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}\big[\big(L_x x_t - L_u u_t\big)\mathbb{E}[\xi_t \mid \mathcal{F}_t^-]\big] \\ &= 0. \end{aligned} \tag{79}$$

The fixed-policy trajectories depend only on the arrival sequence and are therefore independent of the Rademacher variables. Thus, for $j \in \{0,1\}$,

$$\begin{aligned} \mathbb{E}_{\boldsymbol{\xi}}\Big[J_T(\mathbf{m}^{(j)})\Big] &= \sum_{t=1}^{T} \mathbb{E}[\xi_t]\big(L_x x_t(\mathbf{m}^{(j)}) - L_u u_t(\mathbf{m}^{(j)})\big) \\ &= 0. \end{aligned} \tag{80}$$

Because $\mathbf{m}^{(0)}, \mathbf{m}^{(1)} \in \mathcal{M}_H$, for every realization of the Rademacher variables and every choice made by the controller,

$$\begin{aligned} \mathrm{Reg}_T^{\mathrm{SDAC}} &= J_T^{\mathrm{on}} - \min_{\mathbf{m}\in\mathcal{M}_H} J_T(\mathbf{m}) \\ &\ge J_T^{\mathrm{on}} - \min\Big\{J_T(\mathbf{m}^{(0)}), J_T(\mathbf{m}^{(1)})\Big\}. \end{aligned} \tag{81}$$

Taking expectations in (81) and using $\min\{a,b\} = (a+b-|a-b|)/2$ together with (79) and (80) gives

$$\begin{aligned} \mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}\big] &\ge \frac{1}{2}\mathbb{E}_{\boldsymbol{\xi}}\Big[\Big|J_T(\mathbf{m}^{(0)}) - J_T(\mathbf{m}^{(1)})\Big|\Big] \\ &= \frac{1}{2}\mathbb{E}_{\boldsymbol{\xi}}\left[\left|\sum_{t=2}^{T}\xi_t\beta_t\right|\right] \\ &\ge \frac{1}{2\sqrt{2}}\left(\sum_{t=2}^{T}\beta_t^2\right)^{1/2}. \end{aligned} \tag{82}$$

Khintchine's inequality for Rademacher sums gives the final inequality in (82). It remains to remove the randomization from the adversarial construction. The left-hand side of (82) is the average over all 2^T realizations of the Rademacher vector $\boldsymbol{\xi}$:

$$\mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}\big] = \frac{1}{2^T}\sum_{\boldsymbol{\xi}\in\{-1,1\}^T} \mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}} \,\big|\, \boldsymbol{\xi}\big].$$

Hence, at least one vector $\boldsymbol{\xi}^\star$ makes the conditional expectation at least the right-hand side of (82). Fixing $\boldsymbol{\xi}^\star$ in (71), together with the arrivals in (70), produces a deterministic admissible sequence fixed before the interaction. The remaining expectation is only over the internal randomization of $\mathcal{A}$, and (35) follows. □

Proof of Corollary 4. The definition of $t_{\mathrm{mix}}(\alpha)$ gives

$$\alpha^{t_{\mathrm{mix}}(\alpha)} \le \alpha^{\log 2/\log(1/\alpha)} = \frac{1}{2}. \tag{83}$$

Therefore, for every $t \ge t_{\mathrm{mix}}(\alpha) + 2$,

$$\begin{aligned} \beta_t &\ge \alpha \left(L_u + \frac{L_x}{2(1-\alpha)} \right) \\ &\ge \frac{\alpha}{2} \left(L_u + \frac{L_x}{1-\alpha} \right) = \frac{G_\alpha}{2}. \end{aligned} \tag{84}$$

There are $T - t_{\mathrm{mix}}(\alpha) - 1$ indices in $\{t_{\mathrm{mix}}(\alpha)+2, \dots, T\}$. If $T \ge 2t_{\mathrm{mix}}(\alpha) + 2$, then

$$T - t_{\mathrm{mix}}(\alpha) - 1 \ge \frac{T}{2}. \tag{85}$$

Applying Theorem 2 and retaining only these indices,

$$\begin{aligned} \mathbb{E}_{\mathcal{A}}\left[\mathrm{Reg}_T^{\mathrm{SDAC}}\right] &\ge \frac{1}{2\sqrt{2}} \left[\frac{T}{2} \left(\frac{G_\alpha}{2} \right)^2 \right]^{1/2} \\ &= \frac{G_\alpha}{8}\sqrt{T}. \end{aligned} \tag{86}$$

This is (38). □

REFERENCES

[1] N. Agarwal, B. Bullins, E. Hazan, S. Kakade, and K. Singh, "Online control with adversarial disturbances," in *Proceedings of the 36th International Conference on Machine Learning*, ser. Proceedings of Machine Learning Research, vol. 97. PMLR, 2019, pp. 111–119.

[2] N. Golowich, E. Hazan, Z. Lu, D. Rohatgi, and Y. J. Sun, "Online control in population dynamics," in *Advances in Neural Information Processing Systems*, vol. 37, 2024, pp. 111 571–111 613. [Online]. Available: https://papers.nips.cc/paper_files/paper/2024/hash/ca4f6e86453e4b117dd3263792053cf5-Abstract-Conference.html

[3] Y. Li, S. Das, and N. Li, "Online optimal control with affine constraints," *Proceedings of the AAAI Conference on Artificial Intelligence*, vol. 35, no. 10, pp. 8527–8537, 2021. [Online]. Available: https://ojs.aaai.org/index.php/AAAI/article/view/17035

[4] X. Liu, Z. Yang, and L. Ying, "Online nonstochastic control with adversarial and static constraints," in *Proceedings of the 40th International Conference on Machine Learning*, ser. Proceedings of Machine Learning Research, vol. 202. PMLR, 2023, pp. 22 277–22 288. [Online]. Available: https://proceedings.mlr.press/v202/liu23at.html

[5] R. Kumar, S. Dean, and R. Kleinberg, "Online convex optimization with unbounded memory," 2024, arXiv:2210.09903, version 5. [Online]. Available: https://arxiv.org/abs/2210.09903

[6] D. Shaviv and A. Özgür, "Universally near optimal online power control for energy harvesting nodes," *IEEE Journal on Selected Areas in Communications*, vol. 34, no. 12, pp. 3620–3631, 2016. [Online]. Available: https://arxiv.org/abs/1511.00353

[7] A. Arafa, A. Baknina, and S. Ulukus, "Online fixed fraction policies in energy harvesting communication systems," *IEEE Transactions on Wireless Communications*, vol. 17, no. 5, pp. 2975–2986, 2018.

[8] A. Zibaeenejad and J. Chen, "The optimal power control policy for an energy harvesting system with look-ahead: Bernoulli energy arrivals," in *2019 IEEE International Symposium on Information Theory (ISIT)*, 2019, extended version: arXiv:1904.12281. [Online]. Available: https://arxiv.org/abs/1904.12281

[9] H. Yu and M. J. Neely, "Learning-aided optimization for energy-harvesting devices with outdated state information," *IEEE/ACM Transactions on Networking*, vol. 27, no. 4, pp. 1501–1514, 2019.

[10] K. Asgari and M. J. Neely, "Bregman-style online convex optimization with energy harvesting constraints," *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, vol. 4, no. 3, Nov. 2020. [Online]. Available: https://doi.org/10.1145/3428337

[11] Q. Lin, J. Su, and M. Chen, "Optimal algorithms for online Age-of-Information optimization in energy harvesting systems," *IEEE Transactions on Networking*, vol. 33, no. 6, pp. 3146–3161, 2025.

[12] L. Tassiulas and A. Ephremides, "Stability properties of constrained queueing systems and scheduling policies for maximum throughput in multihop radio networks," in *29th IEEE Conference on Decision and Control*. IEEE, 1990, pp. 2130–2132.

[13] ——, "Dynamic server allocation to parallel queues with randomly varying connectivity," *IEEE Transactions on Information Theory*, vol. 39, no. 2, pp. 466–478, 1993.

[14] N. McKeown, A. Mekkittikul, V. Anantharam, and J. Walrand, "Achieving 100% throughput in an input-queued switch," *IEEE Transactions on Communications*, vol. 47, no. 8, pp. 1260–1267, 1999.

[15] M. J. Neely, *Stochastic Network Optimization with Application to Communication and Queueing Systems*. Morgan & Claypool Publishers, 2010.

[16] M. A. Khojastepour and A. Sabharwal, "Delay-constrained scheduling: Power efficiency, filter design, and bounds," in *IEEE INFOCOM 2004*, vol. 3. IEEE, 2004, pp. 1938–1949.

[17] L. Yang, M. H. Hajiesmaili, R. Sitaraman, A. Wierman, E. Mallada, and W. S. Wong, "Online linear optimization with inventory management constraints," *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, vol. 4, no. 1, 2020.

[18] M. Hihat and A. Fermanian, "Online policy selection for inventory problems," *arXiv preprint arXiv:2411.19269*, 2024. [Online]. Available: https://arxiv.org/abs/2411.19269

[19] P. A. P. Moran, "A probability theory of dams and storage systems," *Australian Journal of Applied Science*, vol. 5, no. 2, pp. 116–124, 1954.

[20] R. T. Rockafellar and R. J.-B. Wets, *Variational Analysis*, ser. Grundlehren der mathematischen Wissenschaften. Berlin: Springer, 1998, vol. 317.

[21] E. Hazan, "Introduction to online convex optimization," *Foundations and Trends in Optimization*, vol. 2, no. 3–4, pp. 157–325, 2016.