Online Constrained Control of Storage Systems via Simplex Disturbance-Action Policies

Kamiar Asgari and Michael J. Neely

***Abstract*—We study online control of a scalar storage system with nonnegative adversarial resource arrivals and state-dependent action constraints. The adversarial, time-varying cost depends on both state and action. At each time, the controller selects a feasible action before the current resource arrival and cost are revealed. To handle the coupling between feasibility and online learning, we introduce *Simplex Disturbance-Action Control* (SDAC), whose policies have H nonnegative parameters summing to at most one. Every fixed SDAC policy is feasible by construction. Our online SDAC controller updates these parameters using entropic online mirror descent while preserving feasibility along the time-varying trajectory. We prove a regret bound of $O\Big(\sqrt{T\log(H+1)}\Big)$ relative to the best fixed SDAC policy, and prove a lower bound showing that the dependence on T is tight for fixed H. We also introduce infinite-memory SDAC policies. SDAC policies approximate this class with an error that decreases geometrically with H. For a suitable choice $H=\Theta(\log T)$, the resulting regret against infinite-memory SDAC policies is $O\big(\sqrt{T\log\log T}\big)$. The framework applies to energy-harvesting batteries and other storage-constrained resource systems.**

***Index Terms*—Online control, disturbance-action policies, storage systems, energy harvesting, regret minimization, state-dependent action constraints.**

I. Introduction

A. Motivation and Problem Setting

MANY resource-allocation systems have a storage state that changes over time and limits the control action at each time. An action that yields an immediate benefit or reward may leave less resource for future decisions. On the other hand, an overly conservative resource allocation policy can miss many opportunities for reward. The controller must balance these effects while satisfying the action constraint at every time.

We study this problem for a scalar storage system that loses a fixed fraction of its stored resource each period. For example, an imperfect battery can lose some of its charge even if it is not used. At each time t, the controller observes the current resource state x_t and chooses an amount u_t to use. This incurs a cost that depends on both x_t and u_t. Rewards can be modeled as negative costs. The cost $c_t(x_t,u_t)$ is revealed *after* the decision u_t is made. The cost sequence and the sequence of new resource arrivals may be chosen adversarially, so we do not assume a known probability model. Our goal is to construct an online controller whose cumulative cost is close to that of the best SDAC policy, chosen in hindsight, from a specified benchmark class.

One difficulty is that the current action affects the next state. In online control, *Disturbance-Action Control* (DAC) parameterizes actions using a linear filter of past disturbances, enabling efficient algorithms with bounded regret. In our storage model, however, some DAC policies can produce negative actions or actions larger than the available resource.

We address this issue by introducing *Simplex Disturbance-Action Control* (SDAC). SDAC restricts the filter parameters to a subprobability simplex and includes powers of the retention coefficient in the filter. These choices ensure that every fixed SDAC policy satisfies the action constraint. The state and action along each SDAC-policy trajectory are also affine in the policy parameter. Thus, a convex state–action cost is convex in that parameter, allowing updates through online convex optimization.

B. Model and Information Pattern

The storage state $x_t \geq 0$ evolves according to

$$x_{t+1} = \alpha x_t - u_t + w_t,$$

where $\alpha \in (0,1)$ is a fixed retention coefficient, u_t is the control action, and $w_t \in [0,1]$ is a nonnegative resource arrival. The action must satisfy

$$0 \leq u_t \leq \alpha x_t.$$

Thus, the controller cannot use more resource than remains after storage loss.

At time t, the controller chooses u_t using the current state and the information available through time $t-1$. The arrival w_t and the convex cost function c_t are revealed after the action is selected, and the controller incurs the cost $c_t(x_t,u_t)$. Both the online trajectory and every SDAC-policy trajectory used as a benchmark must satisfy the same dynamics and action constraint. The formal model and assumptions are given in Section II.

Our main application is energy-harvesting battery management, where x_t is the battery state of charge, w_t is the harvested energy, u_t is the energy used, and $1-\alpha$ is the fraction of stored energy lost per period. Similar dynamics arise in perishable inventory systems, water reservoirs with storage loss, and queues with abandonment. In many standard queueing models, $\alpha = 1$; that case is outside our main results and is discussed in Section VII.

K. Asgari and M. J. Neely are with the Department of Electrical and Computer Engineering, University of Southern California, Los Angeles, CA 90089 USA (e-mail: kamiaras@usc.edu; mjneely@usc.edu).

Corresponding author: K. Asgari.

C. Contributions

Our contributions are:

- **Policy class.** We introduce SDAC policies parameterized by a subprobability simplex. We prove that every such SDAC policy is feasible for every arrival sequence with entries in $[0, 1]$.
  We also introduce infinite-memory SDAC policies in Section III-C. Their parameter domain extends the subprobability simplex to nonnegative sequences whose sum is at most one. This class contains every SDAC policy and every feasible fixed-fraction policy $u_t = kx_t$ with $k \in [0, \alpha]$. Truncating the parameter sequence gives an SDAC policy whose approximation error decreases geometrically with the memory horizon H.
- **Online control and regret.** We develop an online SDAC controller that updates its parameter using entropic online mirror descent (OMD) over the subprobability simplex. We prove that the controller remains feasible and achieves $O\Big(\sqrt{T\log(H+1)}\Big)$ regret against the best fixed SDAC policy. For a suitable choice $H = \Theta(\log T)$, the regret against infinite-memory SDAC policies is $O\big(\sqrt{T\log\log T}\big)$. The same bound holds against the best fixed-fraction policy.
- **Lower bound.** We prove a lower bound of order $\sqrt{T}$ for the expected regret of every causal feasible controller, including randomized controllers; see Theorem 2. When T is at least on the order of $(1-\alpha)^{-1}$, the lower bound scales as $\Omega((1-\alpha)^{-1}\sqrt{T})$ near $\alpha = 1$. The upper bound contains a factor of $\sqrt{\log(H+1)}$ that does not appear in the lower bound. The bounds also differ by a factor of $(1-\alpha)^{-1/2}$ in their dependence on $1-\alpha$. Closing these gaps is left for future work.

D. Related Work

a) Online control: Agarwal et al. use DAC policies to obtain $\widetilde{O}(\sqrt{T})$ regret against strongly stable linear controllers [1]. More closely related to our simplex parameterization, Golowich et al. adapt DAC to population dynamics and search over simplex-structured DAC policy parameters [2]. Their state lies in a probability simplex, and their feasible action set is independent of the current state. This differs from the current paper where our constraint $0 \le u_t \le \alpha x_t$ couples each action to the available resource.

Li et al. impose separate fixed affine constraints on states and actions [3]. Assuming a strictly safe linear controller, they enforce feasibility by projecting DAC updates onto a tightened parameter set. Liu et al. consider adversarial and static convex constraints on the state–action pair [4]. Their main algorithms bound cumulative adversarial violation and per-time static violation; they also describe a projection variant with zero violation for static affine constraints. Our constraint $0 \le u_t \le \alpha x_t$ is itself static and affine. We exploit the storage dynamics to make every fixed SDAC policy feasible on a subprobability-simplex parameter domain, and use the clipping rule (30) to preserve feasibility during online updates.

Kumar et al. introduce online convex optimization with unbounded memory [5]. For their discounted infinite-memory model with a Euclidean history norm, the lower bound scales as $\sqrt{T}$ divided by one minus the discount factor, for horizons beyond the effective memory scale. This parallels our $\Omega((1-\alpha)^{-1}\sqrt{T})$ lower bound for sufficiently large horizons, although ours applies directly to causal feasible controllers under the state-dependent action constraint.

b) Energy harvesting: Fixed-fraction and related allocation policies for stochastic energy arrivals motivate our infinite-memory SDAC policies. Shaviv and Özgür [6] prove constant-gap throughput guarantees for fixed-fraction power allocation under i.i.d. arrivals. Arafa et al. [7] extend the analysis to increasing concave utilities and characterize optimal allocations between full recharges under Bernoulli arrivals. With Bernoulli arrivals and a fixed look-ahead window, Zibaeenejad and Chen [8] characterize an optimal policy that uses a decreasing allocation sequence while no recharge is visible and uniform allocation until the next recharge once it enters the window. For the storage dynamics studied here, Corollary 1 proves that infinite-memory SDAC contains every feasible fixed-fraction policy.

Yu and Neely [9] study expected utility maximization with delayed state information. Their results also cover non-i.i.d. wireless states and independent energy arrivals of constant mean, with performance compared to fixed actions satisfying a mean-energy constraint. Asgari and Neely [10] obtain $O(\sqrt{T})$ expected regret for fixed action dimension using $O(\sqrt{T})$ battery capacity, under i.i.d. energy arrivals and arbitrary convex loss sequences. Their benchmark is the best fixed action satisfying the mean-energy constraint. Neither objective depends directly on the battery state. Lin et al. [11] study online energy allocation with arbitrary arrivals and time-varying functions of age of information. They observe the current arrival and value function before allocation. For increasing concave value functions whose derivatives lie between positive bounds with a known ratio, they establish an optimal competitive ratio against an offline optimum with the same battery-capacity and allocation-rate constraints. Our setting combines adversarial arrivals and costs, decisions before the current arrival and cost are revealed, and convex costs depending on both storage state and action. The benchmark is a fixed SDAC policy evaluated on its own induced trajectory.

c) Queueing and network optimization: Classical queueing control studies throughput and queue stability through dynamic service and scheduling decisions [12]–[14], while stochastic network optimization studies tradeoffs between time-average performance and average queue backlog [15]. Our performance criterion is finite-horizon regret against the best fixed SDAC policy in hindsight.

Khojastepour and Sabharwal [16] connect maximum-delay scheduling to finite-memory filters of current and past arrivals. Their time-invariant filters have nonnegative coefficients summing to one. Under i.i.d. arrivals, the uniform moving average minimizes long-run average transmit power over a Gaussian channel within that class. They also develop a time-varying robust scheduler that does not require source statistics. SDAC uses subprobability parameters together with retention factors and acts before the current arrival is observed. We study regret against a fixed SDAC policy under adversarial convex state–

action costs.

d) Inventory and reservoir management: Yang et al. [17] study online procurement with linear costs and inventory capacity and rate constraints. They obtain optimal competitive ratios relative to an offline optimum. They observe the current demand and price before acting, whereas our controller acts before the current arrival and cost are revealed. Hihat and Fermanian [18] learn a feature-enhanced base-stock policy for inventory systems with multiple products, lost sales, perishability, capacity constraints, and lead times. They evaluate the method empirically and leave regret guarantees open. For our scalar linear model, we prove feasibility, approximation, and sublinear regret guarantees. Classical reservoir theory studies storage under random inflows and prescribed release rules [19].

II. Model and Regret Benchmark

For every positive integer n, we write $[n] \triangleq \{1, \dots, n\}$. For every $z \in \mathbb{R}$, we define $[z]_+ \triangleq \max\{z, 0\}$. For $\mathbf{v} \in \mathbb{R}^n$, the i-th coordinate is denoted by v_i. If the vector already carries a subscript, the coordinate is appended after a comma: the i-th coordinate of $\mathbf{v}_t$ is $v_{t,i}$. We write $\mathbf{1}$ for the all-ones vector, with dimension clear from context, and $\langle \cdot, \cdot \rangle$ for the Euclidean inner product. We use $\log$ for the natural logarithm.

Fix a positive integer T and a known retention coefficient $\alpha \in (0, 1)$. The state $x_t \in \mathbb{R}_{\geq 0}$ is the resource level at the beginning of time t. The system starts empty:

$$x_1 = 0. \tag{1}$$

At each time $t \in [T]$, the controller chooses an action $u_t \in \mathbb{R}_{\geq 0}$ satisfying

$$0 \leq u_t \leq \alpha x_t. \tag{2}$$

The system then receives an arrival $w_t \in [0, 1]$ and evolves according to

$$x_{t+1} = \alpha x_t - u_t + w_t. \tag{3}$$

Here, $1 - \alpha$ is the fraction of stored resource lost per period. The constraint (2) ensures that the action does not exceed the amount remaining after this loss.

In the online-control literature, w_t is commonly called a disturbance. Here, we call it an *arrival* because it is nonnegative, while retaining the standard name Disturbance-Action Control. Nonnegativity is important for both the storage interpretation and the feasibility properties of SDAC.

At time t, the controller chooses u_t before observing w_t or c_t. After the action is selected, the arrival and the entire cost function are revealed, the controller incurs $c_t(x_t, u_t)$, and the state is updated according to (3).

For every feasible trajectory, (2), (3), and $w_t \in [0, 1]$ give

$$0 \leq x_{t+1} \leq \alpha x_t + 1.$$

Since $x_1 = 0$, induction gives

$$\begin{aligned} 0 \leq x_t &\leq \sum_{s=0}^{t-2} \alpha^s = \frac{1 - \alpha^{t-1}}{1 - \alpha} \\ &\leq \frac{1}{1 - \alpha}, \qquad t \in [T + 1]. \end{aligned} \tag{4}$$

Together with (2), this bound places every feasible state–action pair in the compact set

$$\mathcal{D}_\alpha \triangleq \left\{ (x, u) : 0 \leq x \leq \frac{1}{1 - \alpha}, 0 \leq u \leq \alpha x \right\}. \tag{5}$$

Remark 1 (Storage capacity). A storage capacity of $1/(1-\alpha)$ suffices to avoid overflow.

Each revealed cost function $c_t : \mathbb{R}^2_{\geq 0} \to \mathbb{R}$ is convex in (x, u) and satisfies the following Lipschitz condition on $\mathcal{D}_\alpha$: there are constants $L_x, L_u > 0$ such that

$$|c_t(x, u) - c_t(x', u')| \leq L_x |x - x'| + L_u |u - u'| \tag{6}$$

for all $(x, u), (x', u') \in \mathcal{D}_\alpha$. At every $(x, u) \in \mathcal{D}_\alpha$, we also assume access to a cost subgradient

$$\boldsymbol{\zeta}_t(x, u) = \big(\zeta_t^x(x, u), \zeta_t^u(x, u)\big) \in \partial c_t(x, u) \tag{7}$$

satisfying

$$|\zeta_t^x(x, u)| \leq L_x, \qquad |\zeta_t^u(x, u)| \leq L_u. \tag{8}$$

These subgradient bounds hold, for example, when c_t has a convex extension to an open neighborhood of $\mathcal{D}_\alpha$ satisfying (6); see [20, Thm. 9.13].

We use x_t and u_t without parameter arguments for the trajectory generated by the online controller. Its cumulative cost is

$$J_T^{\mathrm{on}} \triangleq \sum_{t=1}^{T} c_t(x_t, u_t). \tag{9}$$

The superscript on stands for online.

Section III defines a class of SDAC policies characterized by a parameter $\mathbf{m}$ in a parameter set $\mathcal{M}_H$. For a fixed $\mathbf{m} \in \mathcal{M}_H$, the corresponding *SDAC-policy trajectory* is the state–action sequence $\{(x_t(\mathbf{m}), u_t(\mathbf{m}))\}_{t=1}^T$ obtained by applying the SDAC policy with parameter $\mathbf{m}$ at every time, starting from $x_1(\mathbf{m}) = 0$. Its cumulative cost is

$$J_T(\mathbf{m}) \triangleq \sum_{t=1}^{T} c_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big). \tag{10}$$

The online policy in (9) and the fixed SDAC policy in (10) are evaluated on the same arrival sequence $\{w_t\}_{t=1}^T$ and cost function sequence $\{c_t\}_{t=1}^T$. For a fixed positive integer H, the regret against the best fixed SDAC policy is

$$\mathrm{Reg}_T^{\mathrm{SDAC}}(H) \triangleq J_T^{\mathrm{on}} - \min_{\mathbf{m} \in \mathcal{M}_H} J_T(\mathbf{m}). \tag{11}$$

Our objective is to satisfy (2) at every time and achieve sublinear regret.

III. Simplex Disturbance-Action Control (SDAC)

A. From Disturbance-Action Control to SDAC

DAC uses a finite linear filter of past disturbances. Under standard conditions, this parameterization yields convex surrogate costs and efficient online updates. In our scalar storage model, DAC has the following form:

$$u_t = \sum_{i=1}^{H} \theta_i w_{t-i}, \tag{12}$$

where H is a positive integer (the memory horizon) and $\boldsymbol{\theta} = (\theta_1, \dots, \theta_H)^\top \in \mathbb{R}^H$ is the vector of filter coefficients.

For our constrained model, an unrestricted filter does not ensure feasibility: its action can exceed αx_t or become negative. We therefore introduce *Simplex Disturbance-Action Control* (SDAC), which uses a simplex-constrained filter tailored to the storage dynamics. This restriction makes every fixed SDAC policy feasible while keeping surrogate costs convex and online updates efficient.

B. Policies and Structural Properties

Fix a memory horizon $H \in \mathbb{N}_{>0}$ and define the subprobability simplex

$$\mathcal{M}_H \triangleq \left\{ \mathbf{m} \in \mathbb{R}^H : m_i \geq 0, \quad \sum_{i=1}^{H} m_i \leq 1 \right\}. \tag{13}$$

The inequalities $m_i \geq 0$ hold for every $i \in [H]$. We write $\|\mathbf{m}\|_1 = \sum_{i=1}^{H} |m_i|$ for the ℓ_1 norm. With the convention $w_\tau \equiv 0$ for $\tau \leq 0$, each $\mathbf{m} \in \mathcal{M}_H$ defines an SDAC policy through

$$u_t(\mathbf{m}) \triangleq \sum_{i=1}^{H} m_i \alpha^i w_{t-i}. \tag{14}$$

Here, $m_i \alpha^i w_s$ is the amount from arrival w_s used i periods later.

The following state decomposition yields two structural properties: every fixed SDAC policy satisfies the feasibility constraint (2), and its induced cost is convex and Lipschitz in $\mathbf{m}$. Omitted proofs appear in Appendix A.

Lemma 1 (State decomposition under SDAC)**.** *Fix a positive integer H. For $t \in [T]$ and $i \in [H]$, define*

$$\begin{aligned} r_t(i) &\triangleq \sum_{j=1}^{i} \alpha^{j-1} w_{t-j}, \\ r_t &\triangleq \sum_{j=1}^{t-1} \alpha^{j-1} w_{t-j}, \end{aligned} \tag{15}$$

where the empty sum defining r_1 is zero. Then, for every $\mathbf{m} \in \mathcal{M}_H$ and $t \in [T]$, the SDAC-policy state associated with $\mathbf{m}$ satisfies

$$x_t(\mathbf{m}) = \sum_{i=1}^{H} m_i r_t(i) + \big(1 - \sum_{i=1}^{H} m_i\big) r_t. \tag{16}$$

By (16) and (14), the state and action of an SDAC policy can be written together as

$$\begin{aligned} x_t(\mathbf{m}) &= r_t + \langle \boldsymbol{\phi}_t^x, \mathbf{m} \rangle, \\ u_t(\mathbf{m}) &= \langle \boldsymbol{\phi}_t^u, \mathbf{m} \rangle, \end{aligned}$$

where the coefficient vectors in $\mathbb{R}^H$ are

$$\begin{aligned} \boldsymbol{\phi}_t^x &\triangleq \big(r_t(1) - r_t, \dots, r_t(H) - r_t\big)^\top, \\ \boldsymbol{\phi}_t^u &\triangleq \big(\alpha w_{t-1}, \alpha^2 w_{t-2}, \dots, \alpha^H w_{t-H}\big)^\top. \end{aligned} \tag{17}$$

The superscripts x and u identify the coefficients for the state and action, respectively. Both vectors and r_t depend only on past arrivals and α, so they are independent of $\mathbf{m}$. Thus, both the state and action are affine in $\mathbf{m}$.

Lemma 2 (Feasibility of SDAC policies)**.** *For every $\mathbf{m} \in \mathcal{M}_H$, the fixed SDAC policy indexed by $\mathbf{m}$ is feasible:*

$$0 \leq u_t(\mathbf{m}) \leq \alpha x_t(\mathbf{m}) \qquad \text{for every } t \in [T].$$

Proof. Fix $t \in [T]$. By (15), for every $i \in [H]$,

$$\alpha r_t(i) - \alpha^i w_{t-i} = \sum_{j=1}^{i-1} \alpha^j w_{t-j} \geq 0.$$

Since $\mathbf{m} \in \mathcal{M}_H$, we have $m_i \geq 0$ for every $i \in [H]$ and $1 - \sum_{i=1}^{H} m_i \geq 0$. Also, $w_{t-i} \geq 0$ for every $i \in [H]$ and $r_t \geq 0$. Therefore, using (14),

$$\begin{aligned} 0 \leq u_t(\mathbf{m}) &= \sum_{i=1}^{H} m_i \alpha^i w_{t-i} \\ &\overset{\text{(A)}}{\leq} \sum_{i=1}^{H} m_i \alpha r_t(i) \\ &\overset{\text{(B)}}{\leq} \sum_{i=1}^{H} m_i \alpha r_t(i) + \alpha \left(1 - \sum_{i=1}^{H} m_i\right) r_t \\ &= \alpha x_t(\mathbf{m}). \end{aligned}$$

Step (A) multiplies $\alpha^i w_{t-i} \leq \alpha r_t(i)$ by $m_i \geq 0$ and sums over i. Step (B) adds the nonnegative term $\alpha(1 - \sum_i m_i) r_t$. The final equality uses (16). □

Lemma 3 (Convexity and Lipschitz continuity of the surrogate cost)**.** *For $t \in [T]$, define*

$$\ell_t(\mathbf{m}) \triangleq c_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big), \qquad \mathbf{m} \in \mathcal{M}_H, \tag{18}$$

and

$$G_\alpha \triangleq \alpha \left(\frac{L_x}{1 - \alpha} + L_u \right). \tag{19}$$

Then ℓ_t is convex on $\mathcal{M}_H$ and, for all $\mathbf{m}, \mathbf{m}' \in \mathcal{M}_H$,

$$|\ell_t(\mathbf{m}) - \ell_t(\mathbf{m}')| \leq G_\alpha \|\mathbf{m} - \mathbf{m}'\|_1.$$

For $\mathbf{m} \in \mathcal{M}_H$, use (7) *to define*

$$\begin{aligned} (\zeta_t^x, \zeta_t^u) &= \boldsymbol{\zeta}_t\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big), \\ \mathbf{g}_t &\triangleq \zeta_t^x \boldsymbol{\phi}_t^x + \zeta_t^u \boldsymbol{\phi}_t^u. \end{aligned} \tag{20}$$

Then

$$\mathbf{g}_t \in \partial \ell_t(\mathbf{m}), \qquad \|\mathbf{g}_t\|_\infty \leq G_\alpha.$$

C. Approximation of Infinite-Memory SDAC Policies

Define the infinite-memory parameter domain

$$\mathcal{M}_\infty \triangleq \left\{ \mathbf{m} = (m_i)_{i \geq 1} : m_i \geq 0, \quad \sum_{i=1}^{\infty} m_i \leq 1 \right\}. \tag{21}$$

Each $\mathbf{m} \in \mathcal{M}_\infty$ defines an infinite-memory SDAC policy through

$$u_t(\mathbf{m}) \triangleq \sum_{i=1}^{t-1} m_i \alpha^i w_{t-i}. \tag{22}$$

The state $x_t(\mathbf{m})$ follows (3) with initial condition (1). We use (10) to define $J_T(\mathbf{m})$ for $\mathbf{m} \in \mathcal{M}_\infty$ as well. After extending vectors in $\mathcal{M}_H$ by zeros, SDAC policies with horizon H are exactly the infinite-memory SDAC policies with $m_i = 0$ for every $i > H$.

Lemma 4 (Approximation of infinite-memory SDAC policies)**.** *Every infinite-memory SDAC policy is feasible for every arrival sequence with entries in* $[0,1]$*. Fix* $\mathbf{m} \in \mathcal{M}_\infty$ *and an integer* $H \geq 1$*, and define its truncation by*

$$\mathbf{m}_H(\mathbf{m}) \triangleq (m_1, \dots, m_H)^\top. \tag{23}$$

Then $\mathbf{m}_H(\mathbf{m}) \in \mathcal{M}_H$*. If each* c_t *satisfies* (6)*, then, for every such arrival sequence,*

$$\begin{aligned} &\left|J_T\big(\mathbf{m}_H(\mathbf{m})\big) - J_T(\mathbf{m})\right| \\ &\qquad \leq \left(L_u + \frac{L_x}{1-\alpha}\right)\alpha^{H+1}T. \end{aligned} \tag{24}$$

A *fixed-fraction policy*, parameterized by $k \in [0, \alpha]$, chooses $u_t = kx_t$ at every time. We denote its trajectory by $\{(x_t(k), u_t(k))\}_{t=1}^T$, where

$$\begin{aligned} u_t(k) &= kx_t(k), \qquad x_1(k) = 0, \\ x_{t+1}(k) &= (\alpha - k)x_t(k) + w_t. \end{aligned} \tag{25}$$

Since $\alpha - k \geq 0$ and $w_t \geq 0$, induction gives $x_t(k) \geq 0$. Thus, $0 \leq u_t(k) = kx_t(k) \leq \alpha x_t(k)$, so every such policy is feasible.

Corollary 1 (Fixed-fraction policies as infinite-memory SDAC policies)**.** *For* $k \in [0, \alpha]$*, define*

$$m_i(k) = \frac{k}{\alpha}\left(1 - \frac{k}{\alpha}\right)^{i-1}, \qquad i \geq 1, \tag{26}$$

where $0^0 = 1$*. Then* $\mathbf{m}(k) \in \mathcal{M}_\infty$ *and, for every arrival sequence with entries in* $[0,1]$*, the infinite-memory SDAC policy indexed by* $\mathbf{m}(k)$ *coincides with the feasible fixed-fraction policy* $u_t(k) = kx_t(k)$*:*

$$\big(x_t(\mathbf{m}(k)), u_t(\mathbf{m}(k))\big) = \big(x_t(k), u_t(k)\big), \qquad t \in [T].$$

IV. Online SDAC Controller

The controller maintains a parameter $\mathbf{m}_t \in \mathcal{M}_H$ and updates it by OMD [21] with step size $\eta > 0$ and unnormalized negentropy:

$$\Psi(\mathbf{m}) \triangleq \sum_{i=1}^{H}\big(m_i \log m_i - m_i\big), \qquad \mathbf{m} \in \mathbb{R}^H_{\geq 0}, \tag{27}$$

where $0 \log 0 \triangleq 0$. For $\mathbf{m} \in \mathbb{R}^H_{\geq 0}$ and $\mathbf{v} \in \mathbb{R}^H_{>0}$, the associated Bregman divergence is

$$D_\Psi(\mathbf{m}\|\mathbf{v}) \triangleq \sum_{i=1}^{H}\Big(m_i \log \tfrac{m_i}{v_i} - m_i + v_i\Big). \tag{28}$$

Initialize the online parameter as

$$\mathbf{m}_1 \triangleq \frac{1}{H+1}\mathbf{1}. \tag{29}$$

a) Action selection: At time t, the controller uses $\mathbf{m}_t$, initialized by (29) for $t = 1$ and produced by the OMD update at time $t-1$ for $t \geq 2$. The feasibility guarantee for an SDAC policy uses the same parameter at every time. When $\mathbf{m}_t$ varies, the nominal action $\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle$ can exceed αx_t. The controller therefore selects

$$u_t \triangleq \min\{\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle, \alpha x_t\}. \tag{30}$$

The state then evolves according to (3). Since $\boldsymbol{\phi}_t^u$ and $\mathbf{m}_t$ are componentwise nonnegative, $\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle \geq 0$. If $x_t \geq 0$, then (30) gives $0 \leq u_t \leq \alpha x_t$, and (3) gives $x_{t+1} \geq w_t \geq 0$. Since $x_1 = 0$, induction shows that the online trajectory is feasible.

Lemma 7 shows that the D_Ψ-projection of $\mathbf{m}_t$ onto the parameters compatible with x_t induces exactly the clipped action u_t.

b) Surrogate cost and OMD update: After w_t and c_t are revealed, the controller evaluates the subgradient $\mathbf{g}_t$ in (20) at $\mathbf{m}_t$ and sets

$$\mathbf{m}_{t+1} \triangleq \operatorname*{arg\,min}_{\mathbf{m} \in \mathcal{M}_H}\{\eta\langle \mathbf{g}_t, \mathbf{m}\rangle + D_\Psi(\mathbf{m}\|\mathbf{m}_t)\}. \tag{31}$$

Lemma 8 gives a two-step implementation. First, take the coordinatewise multiplicative step

$$\widetilde{m}_{t+1,i} \triangleq m_{t,i}\exp\big(-\eta g_{t,i}\big), \qquad i \in [H]. \tag{32}$$

Next, project onto $\mathcal{M}_H$ by rescaling if needed:

$$\begin{aligned} \mathbf{m}_{t+1} &= \operatorname*{arg\,min}_{\mathbf{m} \in \mathcal{M}_H} D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}_{t+1}) \\ &= \frac{\widetilde{\mathbf{m}}_{t+1}}{\max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\}}. \end{aligned} \tag{33}$$

V. Regret Upper Bounds

The next theorem bounds the regret of the online SDAC controller against the best fixed SDAC policy. Proofs appear in Appendix C.

Theorem 1 (Regret against fixed SDAC policies)**.** *Suppose the costs satisfy the assumptions of Section II. For any step size* $\eta > 0$*, the controller in Section IV, initialized by* (29)*, satisfies*

$$\mathrm{Reg}_T^{\mathrm{SDAC}}(H) \leq \frac{\log(H+1)}{\eta} + \eta T \Gamma_\alpha, \tag{34}$$

where

$$\Gamma_\alpha \triangleq \frac{G_\alpha^2}{2} + \frac{\alpha G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2}, \tag{35}$$

and $G_\alpha = \alpha\big(\frac{L_x}{1-\alpha} + L_u\big)$ *as in* (19)*.*

Choosing

$$\eta^* = \sqrt{\frac{\log(H+1)}{T\Gamma_\alpha}} \tag{36}$$

gives

$$\mathrm{Reg}_T^{\mathrm{SDAC}}(H) \leq 2\sqrt{\Gamma_\alpha T \log(H+1)}. \tag{37}$$

The proof combines the OMD bound for the surrogate costs (Lemma 10) with the following bound on the difference between realized and surrogate costs.

Lemma 5 (Stability under online parameter updates)**.** *Under the assumptions of Theorem 1, the online SDAC controller satisfies*

$$\sum_{t=1}^{T}\Big(c_t(x_t,u_t)-\ell_t(\mathbf{m}_t)\Big)\le\frac{\alpha\eta TG_\alpha(L_x+\alpha L_u)}{(1-\alpha)^2}. \tag{38}$$

Corollary 2 (No-regret against infinite-memory SDAC policies)**.** *Under the assumptions of Theorem 1, run the online SDAC controller with step size η^* and memory horizon*

$$H=H_T\triangleq\max\left\{1,\left\lceil\frac{\log T}{\log(1/\alpha)}\right\rceil\right\}, \tag{39}$$

where η^* is given by (36) *with $H=H_T$. Define the regret against the best fixed infinite-memory SDAC policy by*

$$\mathrm{Reg}_T^{\mathrm{SDAC}}(\infty)\triangleq J_T^{\mathrm{on}}-\inf_{\mathbf{m}\in\mathcal{M}_\infty}J_T(\mathbf{m}). \tag{40}$$

Then

$$\begin{aligned}\mathrm{Reg}_T^{\mathrm{SDAC}}(\infty)&\le 2\sqrt{\Gamma_\alpha T\log(H_T+1)}\\&\quad+\left(L_u+\frac{L_x}{1-\alpha}\right)\alpha^{H_T+1}T.\end{aligned} \tag{41}$$

For fixed α,L_x,L_u, the right-hand side is $O\big(\sqrt{T\log\log T}\big)=o(T)$. The same bound holds against the best fixed-fraction policy, since Corollary 1 gives

$$J_T^{\mathrm{on}}-\min_{k\in[0,\alpha]}\sum_{t=1}^{T}c_t\big(x_t(k),u_t(k)\big)\le\mathrm{Reg}_T^{\mathrm{SDAC}}(\infty).$$

VI. Regret Lower Bound

The next result shows that the $\sqrt{T}$ dependence is unavoidable and quantifies the necessary dependence on $1-\alpha$ for any causal feasible controller. Omitted proofs appear in Appendix D.

The construction follows the argument in Hazan, Agarwal, and Kale [22, Sec. 2.3, footnote 3]; see also [21, Sec. 3.2, Thm. 3.2]. In that argument, linear costs with independent random signs give every causal decision rule zero expected cost, while the best decision in hindsight has an advantage determined by the absolute sum of the signs. Here, we use constant arrivals and compare two feasible SDAC policies. Their difference in cumulative costs is a weighted Rademacher sum, with coefficients β_t in (43) determined by the storage dynamics. Applying Khintchine's inequality [23] to this sum gives the bound below. Kumar, Dean, and Kleinberg [5, App. D, Thm. D.2] use a related construction with Rademacher signs assigned to blocks for discounted memory. Our construction uses an independent sign at each time and evaluates SDAC policies on their own feasible storage trajectories.

Theorem 2 (SDAC regret lower bound)**.** *Fix $H\ge 1$ and $T\ge 2$. For every causal feasible online controller $\mathcal{A}$, possibly randomized, there is a deterministic oblivious sequence of arrivals and costs satisfying the assumptions of Section II such that*

$$\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}(H)\big]\ge\frac{1}{2\sqrt{2}}\sqrt{\sum_{t=2}^{T}\beta_t^2}, \tag{42}$$

where

$$\beta_t\triangleq\alpha\left(L_u+\frac{L_x(1-\alpha^{t-2})}{1-\alpha}\right),\qquad t=2,\dots,T. \tag{43}$$

The expectation is over the internal randomization of $\mathcal{A}$.

Corollary 3 (Lower bound for sufficiently large horizons)**.** *Fix $H\ge 1$. If*

$$T\ge 2\left\lceil\frac{\log 2}{\log(1/\alpha)}\right\rceil+2, \tag{44}$$

then for every causal feasible controller $\mathcal{A}$, possibly randomized, there is a deterministic oblivious sequence satisfying the model assumptions such that

$$\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}(H)\big]\ge\frac{G_\alpha}{8}\sqrt{T},$$

where $G_\alpha=\alpha(L_x/(1-\alpha)+L_u)$ as in (19).

Remark 2 (Large-α regime). For fixed $L_x,L_u>0$, both the right-hand side of (44) and G_α are of order $(1-\alpha)^{-1}$ as $\alpha\uparrow 1$: here $\log(1/\alpha)/(1-\alpha)\to 1$, and taking a ceiling changes a number by less than one. If (44) holds, then Corollary 3 yields

$$\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}(H)\big]=\Omega\left(\frac{\sqrt{T}}{1-\alpha}\right).$$

For the upper bound, as $\alpha\uparrow 1$,

$$(1-\alpha)G_\alpha=\alpha\big(L_x+(1-\alpha)L_u\big)\longrightarrow L_x,$$

and (35) gives

$$\begin{aligned}(1-\alpha)^3\Gamma_\alpha&=\frac{1-\alpha}{2}\big((1-\alpha)G_\alpha\big)^2\\&\quad+\alpha\big((1-\alpha)G_\alpha\big)(L_x+\alpha L_u)\\&\longrightarrow L_x(L_x+L_u)>0.\end{aligned}$$

Thus,

$$\sqrt{\Gamma_\alpha}=\Theta\Big((1-\alpha)^{-3/2}\Big)\quad\text{as }\alpha\uparrow 1.$$

The upper bound is $O((1-\alpha)^{-3/2}\sqrt{T\log(H+1)})$ by Theorem 1. The factor $\sqrt{\log(H+1)}$ in this upper bound does not appear in the lower bound. The dependence on $1-\alpha$ also differs by a factor of $(1-\alpha)^{-1/2}$. Thus, the bounds match in their $\sqrt{T}$ dependence for fixed H and α, but do not establish matching dependence on H or $1-\alpha$.

The horizon condition (44) requires T to grow at least on the order of $(1-\alpha)^{-1}$ as $\alpha\uparrow 1$. For fixed T,

$$\frac{1-\alpha^{t-2}}{1-\alpha}=\sum_{s=0}^{t-3}\alpha^s\longrightarrow t-2\qquad\text{as }\alpha\uparrow 1,$$

where the sum is empty for $t=2$, so the lower bound in (42) remains finite.

VII. Discussion and Extensions

We discuss three extensions. In each case, the feasibility, convexity, and stability arguments apply with the stated changes to the policy domain and Lipschitz constants. We omit the resulting regret bounds, whose form is unchanged up to these constants and, in the vector settings, the chosen product norm.

a) Retention $\alpha \geq 1$: Here we extend the model beyond the assumption $\alpha \in (0,1)$. The case $\alpha = 1$ has no storage loss, while $\alpha > 1$ represents growth between decisions. Fix k with $\alpha - 1 < k < \alpha$ and set $\bar{\alpha} \triangleq \alpha - k \in (0,1)$. In particular, $k > 0$. Define $v_t \triangleq u_t - kx_t$ as the action beyond kx_t, and restrict v_t to $0 \leq v_t \leq \bar{\alpha} x_t$. The original action is $u_t = kx_t + v_t$, so

$$\begin{aligned} x_{t+1} &= \alpha x_t - (kx_t + v_t) + w_t \\ &= (\alpha - k)x_t - v_t + w_t = \bar{\alpha} x_t - v_t + w_t. \end{aligned}$$

Thus, v_t is the control action for a storage system with retention coefficient $\bar{\alpha} \in (0,1)$. For $\mathbf{m} \in \mathcal{M}_H$, define

$$\begin{aligned} v_t(\mathbf{m}) &= \sum_{i=1}^{H} m_i \bar{\alpha}^i w_{t-i}, \\ u_t(\mathbf{m}) &= kx_t(\mathbf{m}) + v_t(\mathbf{m}), \end{aligned}$$

where $x_1(\mathbf{m}) = 0$ and $x_{t+1}(\mathbf{m}) = \bar{\alpha} x_t(\mathbf{m}) - v_t(\mathbf{m}) + w_t$. Lemma 2, with α replaced by $\bar{\alpha}$, gives $0 \leq v_t(\mathbf{m}) \leq \bar{\alpha} x_t(\mathbf{m})$. For $\mathbf{m}_t \in \mathcal{M}_H$, the online controller instead selects

$$\begin{aligned} v_t &= \min\left\{ \sum_{i=1}^{H} m_{t,i} \bar{\alpha}^i w_{t-i},\ \bar{\alpha} x_t \right\}, \\ u_t &= kx_t + v_t. \end{aligned}$$

In both cases,

$$kx_t \leq u_t = kx_t + v_t \leq (k + \bar{\alpha}) x_t = \alpha x_t,$$

so the original feasibility constraint (2) is satisfied. Equation (4), with α replaced by $\bar{\alpha} \in (0,1)$, gives $0 \leq x_t \leq 1/(1-\bar{\alpha})$. Assume that the original costs $c_t(x,u)$ are convex and satisfy the Lipschitz and subgradient bounds of Section II on

$$0 \leq x \leq \frac{1}{1-\bar{\alpha}}, \qquad kx \leq u \leq \alpha x.$$

The cost in the variables (x,v) is $c_t(x, kx+v)$, which is convex because $(x,v) \mapsto (x, kx+v)$ is affine. For two feasible pairs (x,v) and (x',v'),

$$\begin{aligned} &|c_t(x, kx+v) - c_t(x', kx'+v')| \\ &\quad \overset{\text{(A)}}{\leq} L_x |x - x'| + L_u |k(x-x') + v - v'| \\ &\quad \overset{\text{(B)}}{\leq} (L_x + kL_u)|x - x'| + L_u |v - v'|. \end{aligned}$$

Step (A) uses the assumed form of (6) on the stated domain, with $u = kx + v$ and $u' = kx' + v'$. Step (B) uses the triangle inequality and $k > 0$. If $(\zeta_t^x, \zeta_t^u) = \boldsymbol{\zeta}_t(x, kx+v)$, then

$$\begin{aligned} &c_t(x', kx'+v') - c_t(x, kx+v) \\ &\quad \geq \zeta_t^x (x' - x) + \zeta_t^u \big(k(x'-x) + v' - v \big) \\ &\quad = (\zeta_t^x + k\zeta_t^u)(x' - x) + \zeta_t^u (v' - v). \end{aligned}$$

Hence, $(\zeta_t^x + k\zeta_t^u, \zeta_t^u)$ is a subgradient of the transformed cost, with

$$|\zeta_t^x + k\zeta_t^u| \leq L_x + kL_u, \qquad |\zeta_t^u| \leq L_u.$$

The online controller uses the same OMD update with surrogate cost

$$\mathbf{m} \mapsto c_t\big(x_t(\mathbf{m}), kx_t(\mathbf{m}) + v_t(\mathbf{m})\big).$$

The feasibility and regret upper-bound analysis therefore applies with α replaced by $\bar{\alpha}$ and L_x replaced by $L_x + kL_u$, while L_u is unchanged. Both the online controller and the comparators use the same fixed k. Each comparator is a policy $u_t(\mathbf{m}) = kx_t(\mathbf{m}) + v_t(\mathbf{m})$ with $v_t(\mathbf{m})$ given by the SDAC filter above. The substitution preserves the cost at every time, so it also preserves cumulative costs and regret against this class. Selecting k, either in advance or online, is left for future work.

b) Vector actions and multi-task allocation: Consider a single storage state x_t with a vector action $\mathbf{u}_t \in \mathbb{R}^n_{\geq 0}$ that allocates resources across n tasks, subject to $\sum_{a=1}^n u_{t,a} \leq \alpha x_t$. The dynamics are $x_{t+1} = \alpha x_t - \sum_{a=1}^n u_{t,a} + w_t$, and the cost $c_t(x, \mathbf{u})$ is convex in $(x, \mathbf{u})$. Replace $\mathbf{m} \in \mathcal{M}_H$ with a matrix $\mathbf{M} \in \mathbb{R}^{n \times H}_{\geq 0}$ satisfying

$$\sum_{a=1}^{n} \sum_{i=1}^{H} M_{a,i} \leq 1, \qquad u_{t,a}(\mathbf{M}) = \sum_{i=1}^{H} M_{a,i} \alpha^i w_{t-i}.$$

Set $m_i = \sum_{a=1}^n M_{a,i}$. Then

$$m_i \geq 0, \qquad \sum_{i=1}^{H} m_i = \sum_{a=1}^{n} \sum_{i=1}^{H} M_{a,i} \leq 1,$$

so $\mathbf{m} \in \mathcal{M}_H$. Moreover,

$$\sum_{a=1}^{n} u_{t,a}(\mathbf{M}) = \sum_{i=1}^{H} m_i \alpha^i w_{t-i} \leq \alpha x_t(\mathbf{M}),$$

where the inequality is Lemma 2, applied to $m_i = \sum_a M_{a,i}$. The scalar SDAC trajectory and $x_t(\mathbf{M})$ have the same initial state and total action, so their states coincide. The state and vector action are affine in $\mathbf{M}$, so $c_t\big(x_t(\mathbf{M}), \mathbf{u}_t(\mathbf{M})\big)$ is convex in $\mathbf{M}$. For the online SDAC controller, a nominal vector whose entries sum to more than αx_t can be scaled proportionally so that its entries remain nonnegative and sum to αx_t. Under an ℓ_1 Lipschitz bound in the action, the size of this correction equals the excess total action, and the stability proof proceeds with the corresponding matrix norm. OMD then runs over the matrix subprobability simplex above.

c) Multiple storage states with diagonal dynamics: Suppose the state is $\mathbf{x}_t \in \mathbb{R}^d_{\geq 0}$ and evolves according to $\mathbf{x}_{t+1} = \mathbf{A}\mathbf{x}_t - \mathbf{u}_t + \mathbf{w}_t$, where $\mathbf{A} = \operatorname{diag}(\alpha_1, \ldots, \alpha_d)$, $\alpha_s \in (0,1)$ for $s \in [d]$, the arrivals satisfy $\mathbf{w}_t \in [0,1]^d$, and the per-storage constraints are $0 \leq u_{t,s} \leq \alpha_s x_{t,s}$. Since $\mathbf{A}$ is diagonal,

$$x_{t+1,s} = \alpha_s x_{t,s} - u_{t,s} + w_{t,s}, \qquad s \in [d].$$

Thus, the next state of each storage system depends only on its own current state, action, and arrival. Assign one SDAC parameter in $\mathcal{M}_H$ to each storage state and use the powers α_s^i in coordinate s. The dynamics and feasibility constraints then decouple by storage state, and the SDAC parameter domain is a product of subprobability simplices, with $x_{t,s} \leq 1/(1-\alpha_s)$ for every $s \in [d]$. The online SDAC controller clips each nominal action to $\alpha_s x_{t,s}$. If the cost is jointly convex and satisfies compatible Lipschitz and bounded-subgradient assumptions on the resulting bounded product domain, the surrogate cost is jointly convex in all SDAC

parameters and OMD applies on the product set. With a sum of negentropy regularizers, the OMD minimization separates by storage state, although each subgradient may depend on all storage states and actions. Cross-coupled storage systems (nondiagonal $\mathbf{A}$) require further analysis.

VIII. Conclusion

We studied adversarial online control of a storage system under a state-dependent action constraint. We introduced SDAC policies, which are feasible by construction, and developed an online SDAC controller with $O\Big(\sqrt{T\log(H+1)}\Big)$ regret against the best fixed SDAC policy. Under the horizon condition (44), the lower bound gives $\Omega((1-\alpha)^{-1}\sqrt{T})$ regret as $\alpha \uparrow 1$. A factor of $\sqrt{\log(H+1)}$ remains between the upper and lower bounds in their dependence on H, together with a factor of $(1-\alpha)^{-1/2}$ in their dependence on $1-\alpha$. The SDAC approximation results further give $O\big(\sqrt{T\log\log T}\big)$ regret against the best fixed infinite-memory SDAC policy for a suitable choice $H=\Theta(\log T)$. The model applies directly to energy-harvesting battery management and related settings in which storage limits must be respected in real time.

Disclosure of AI Assistance

The lower-bound construction and proofs in Section VI and Appendix D were developed primarily using ChatGPT (5.6 sol). The construction closely follows the argument based on independent random signs in [22, Sec. 2.3, footnote 3], adapted to the storage dynamics and feasible SDAC policies. The remaining material was originally written by the authors. ChatGPT (5.6 sol) was subsequently used to improve its exposition and to refine constants in the proofs.

Appendix A
Proofs for Simplex Disturbance-Action Control

Proof of Lemma 1. For $1 \le t < T$ and $i \in [H]$, shifting the summation index in (15) gives

$$\begin{aligned} r_{t+1} &= \sum_{j=1}^{t} \alpha^{j-1} w_{t+1-j} = w_t + \sum_{j=1}^{t-1} \alpha^j w_{t-j} \\ &= w_t + \alpha r_t, \\ r_{t+1}(i) &= w_t + \sum_{j=1}^{i-1} \alpha^j w_{t-j} \\ &= w_t + \alpha r_t(i) - \alpha^i w_{t-i}. \end{aligned} \tag{45}$$

The sums with upper limits $t-1$ and $i-1$ are empty when $t=1$ and $i=1$, respectively.

At $t=1$, (1) gives $x_1(\mathbf{m})=0$, while $r_1(i)=r_1=0$ by the arrival and empty-sum conventions. Thus, (16) holds at $t=1$. Suppose it holds for some $1 \le t < T$. Substitute the induction hypothesis and (14) into (3), then use (45):

$$\begin{aligned} x_{t+1}(\mathbf{m}) &= \sum_{i=1}^{H} m_i\big(\alpha r_t(i) - \alpha^i w_{t-i}\big) \\ &\quad + \left(1 - \sum_{i=1}^{H} m_i\right) \alpha r_t + w_t \\ &= \sum_{i=1}^{H} m_i\big(r_{t+1}(i) - w_t\big) \\ &\quad + \left(1 - \sum_{i=1}^{H} m_i\right) (r_{t+1} - w_t) + w_t \\ &= \sum_{i=1}^{H} m_i r_{t+1}(i) + \left(1 - \sum_{i=1}^{H} m_i\right) r_{t+1}. \end{aligned}$$

The coefficients of w_t in the penultimate expression sum to $-\sum_{i=1}^{H} m_i - (1 - \sum_{i=1}^{H} m_i) + 1 = 0$. Thus, (16) follows by induction. □

Proof of Lemma 3. Lemma 1 and (14) give

$$\begin{aligned} x_t(\mathbf{m}) &= r_t + \langle \boldsymbol{\phi}_t^x, \mathbf{m} \rangle, \\ u_t(\mathbf{m}) &= \langle \boldsymbol{\phi}_t^u, \mathbf{m} \rangle. \end{aligned} \tag{46}$$

For $i \in [H]$, (17) and (15) give

$$\begin{aligned} |\phi_{t,i}^x| = r_t - r_t(i) &= \sum_{j=i+1}^{t-1} \alpha^{j-1} w_{t-j} \\ &\overset{\text{(A)}}{\le} \sum_{j=i+1}^{\infty} \alpha^{j-1} = \frac{\alpha^i}{1-\alpha} \overset{\text{(B)}}{\le} \frac{\alpha}{1-\alpha}, \\ 0 \le \phi_{t,i}^u = \alpha^i w_{t-i} &\le \alpha^i \le \alpha. \end{aligned}$$

The finite sum is empty when $i \ge t-1$, since $w_\tau = 0$ for $\tau \le 0$. Step (A) uses $0 \le w_{t-j} \le 1$ and extends a nonnegative sum. Step (B) uses $i \ge 1$ and $0 < \alpha < 1$; the same bounds give the estimate for $\phi_{t,i}^u$. Taking the maximum over $i \in [H]$ gives

$$\|\boldsymbol{\phi}_t^x\|_\infty \le \frac{\alpha}{1-\alpha}, \qquad \|\boldsymbol{\phi}_t^u\|_\infty \le \alpha. \tag{47}$$

Since the state–action pair in (46) is affine in $\mathbf{m}$ and c_t is convex, ℓ_t is convex.

By Lemma 2 and (4), the SDAC-policy state–action pairs associated with $\mathbf{m}$ and $\mathbf{m}'$ belong to $\mathcal{D}_\alpha$. Thus,

$$\begin{aligned} |\ell_t(\mathbf{m}) - \ell_t(\mathbf{m}')| &\overset{\text{(A)}}{\le} L_x |x_t(\mathbf{m}) - x_t(\mathbf{m}')| \\ &\quad + L_u |u_t(\mathbf{m}) - u_t(\mathbf{m}')| \\ &= L_x \big|\langle \boldsymbol{\phi}_t^x, \mathbf{m} - \mathbf{m}' \rangle\big| \\ &\quad + L_u \big|\langle \boldsymbol{\phi}_t^u, \mathbf{m} - \mathbf{m}' \rangle\big| \\ &\overset{\text{(B)}}{\le} \left(\frac{\alpha L_x}{1-\alpha} + \alpha L_u\right) \|\mathbf{m} - \mathbf{m}'\|_1 \\ &= G_\alpha \|\mathbf{m} - \mathbf{m}'\|_1. \end{aligned}$$

Step (A) is (6). The next equality uses (46), and (B) applies $|\langle \mathbf{v}, \mathbf{m} - \mathbf{m}' \rangle| \le \|\mathbf{v}\|_\infty \|\mathbf{m} - \mathbf{m}'\|_1$ to each coefficient vector, followed by (47). The last equality uses (19).

Fix $\mathbf{m} \in \mathcal{M}_H$, and let (ζ_t^x, ζ_t^u) and $\mathbf{g}_t$ be defined by (20). For every $\mathbf{m}' \in \mathcal{M}_H$, step (A) applies the cost subgradient inequality from (7) at $\big(x_t(\mathbf{m}), u_t(\mathbf{m})\big)$ and substitutes the affine differences from (46):

$$\begin{aligned}\ell_t(\mathbf{m}') &\overset{\text{(A)}}{\geq} \ell_t(\mathbf{m}) + \zeta_t^x \langle \boldsymbol{\phi}_t^x, \mathbf{m}' - \mathbf{m}\rangle \\ &\quad + \zeta_t^u \langle \boldsymbol{\phi}_t^u, \mathbf{m}' - \mathbf{m}\rangle \\ &= \ell_t(\mathbf{m}) + \langle \mathbf{g}_t, \mathbf{m}' - \mathbf{m}\rangle.\end{aligned}$$

Thus, $\mathbf{g}_t \in \partial \ell_t(\mathbf{m})$. The triangle inequality gives the following bound, where (A) uses (8) and (47):

$$\begin{aligned}\|\mathbf{g}_t\|_\infty &\leq |\zeta_t^x| \|\boldsymbol{\phi}_t^x\|_\infty + |\zeta_t^u| \|\boldsymbol{\phi}_t^u\|_\infty \\ &\overset{\text{(A)}}{\leq} \frac{\alpha L_x}{1-\alpha} + \alpha L_u \\ &= G_\alpha.\end{aligned}$$

□

Proof of Lemma 4. For the truncation (23), (21) gives $m_i \geq 0$ for every $i \in [H]$ and

$$\|\mathbf{m}_H(\mathbf{m})\|_1 = \sum_{i=1}^{H} m_i \leq \sum_{i=1}^{\infty} m_i \leq 1.$$

Thus, $\mathbf{m}_H(\mathbf{m}) \in \mathcal{M}_H$.

To prove feasibility of the infinite-memory SDAC policy, truncate at length T. Since $w_\tau = 0$ for $\tau \leq 0$, (14) and (22) give, for every $t \in [T]$,

$$\begin{aligned}u_t\big(\mathbf{m}_T(\mathbf{m})\big) &= \sum_{i=1}^{T} m_i \alpha^i w_{t-i} \\ &= \sum_{i=1}^{t-1} m_i \alpha^i w_{t-i} = u_t(\mathbf{m}).\end{aligned}$$

The infinite-memory SDAC policy and its truncation have the same initial state and actions, so their state trajectories coincide. Lemma 2 therefore gives

$$0 \leq u_t(\mathbf{m}) \leq \alpha x_t(\mathbf{m}), \qquad t \in [T].$$

For the approximation error, define

$$\begin{aligned}e_t^u &\triangleq u_t(\mathbf{m}) - u_t\big(\mathbf{m}_H(\mathbf{m})\big), \\ e_t^x &\triangleq x_t\big(\mathbf{m}_H(\mathbf{m})\big) - x_t(\mathbf{m}).\end{aligned} \tag{48}$$

By (14) and (22), for every $t \in [T]$,

$$\begin{aligned}0 \leq e_t^u &= \sum_{i=H+1}^{t-1} \alpha^i m_i w_{t-i} \\ &\overset{\text{(A)}}{\leq} \sum_{i=H+1}^{t-1} \alpha^i m_i \\ &\overset{\text{(B)}}{\leq} \alpha^{H+1} \sum_{i=H+1}^{t-1} m_i \overset{\text{(C)}}{\leq} \alpha^{H+1}.\end{aligned} \tag{49}$$

The sums are empty when $t \leq H+1$. Step (A) uses $w_{t-i} \leq 1$ and $m_i \geq 0$. Step (B) uses $i \geq H+1$ and $0 < \alpha < 1$. Step (C) uses $\sum_{i \geq 1} m_i \leq 1$ from (21).

Subtracting the two instances of (3), with the error signs in (48), gives

$$e_1^x = 0, \qquad e_{t+1}^x = \alpha e_t^x + e_t^u.$$

Iterating this recurrence yields

$$\begin{aligned}0 \leq e_t^x &= \sum_{s=1}^{t-1} \alpha^{t-1-s} e_s^u \\ &\overset{\text{(A)}}{\leq} \alpha^{H+1} \sum_{j=0}^{t-2} \alpha^j \overset{\text{(B)}}{\leq} \frac{\alpha^{H+1}}{1-\alpha}.\end{aligned} \tag{50}$$

Step (A) uses (49) and the change of index $j = t-1-s$. Step (B) extends the nonnegative sum to the geometric series $\sum_{j=0}^{\infty} \alpha^j = (1-\alpha)^{-1}$, valid because $0 < \alpha < 1$. For $t = 1$, both finite sums are empty.

Both policies are feasible, so (4) places their state–action pairs in $\mathcal{D}_\alpha$. Therefore,

$$\begin{aligned}&\big|J_T\big(\mathbf{m}_H(\mathbf{m})\big) - J_T(\mathbf{m})\big| \\ &\overset{\text{(A)}}{\leq} \sum_{t=1}^{T} (L_x e_t^x + L_u e_t^u) \\ &\overset{\text{(B)}}{\leq} \left(L_u + \frac{L_x}{1-\alpha}\right) \alpha^{H+1} T.\end{aligned}$$

Step (A) uses (10), the triangle inequality, and (6); the errors in (48) are nonnegative. Step (B) sums (49) and (50) over $t \in [T]$. This proves (24). □

Proof of Corollary 1. Since $0 \leq k/\alpha \leq 1$,

$$m_i(k) = \frac{k}{\alpha}\left(1 - \frac{k}{\alpha}\right)^{i-1} \geq 0, \qquad i \geq 1.$$

The definition (26) also gives

$$m_i(k) = \left(1 - \frac{k}{\alpha}\right)^{i-1} - \left(1 - \frac{k}{\alpha}\right)^{i}.$$

Summing this difference cancels the terms with exponents $1, \ldots, H-1$. Thus, for every positive integer H,

$$\sum_{i=1}^{H} m_i(k) = 1 - \left(1 - \frac{k}{\alpha}\right)^{H} \leq 1.$$

The nonnegative partial sums increase to $\sum_{i=1}^{\infty} m_i(k) \leq 1$. Hence, $\mathbf{m}(k) \in \mathcal{M}_\infty$ for every $k \in [0, \alpha]$, including both endpoints under the convention $0^0 = 1$.

Iterating the fixed-fraction recursion (25) from $x_1(k) = 0$ gives

$$x_t(k) = \sum_{i=1}^{t-1} (\alpha - k)^{i-1} w_{t-i}.$$

For every $i \geq 1$, (26) and $\alpha > 0$ give

$$\begin{aligned}\alpha^i m_i(k) &= \alpha^i \frac{k}{\alpha}\left(\frac{\alpha - k}{\alpha}\right)^{i-1} \\ &= k(\alpha - k)^{i-1}.\end{aligned}$$

Substituting these two identities into (22),

$$\begin{aligned}u_t(k) = k x_t(k) &= \sum_{i=1}^{t-1} k(\alpha - k)^{i-1} w_{t-i} \\ &= \sum_{i=1}^{t-1} \alpha^i m_i(k) w_{t-i} = u_t\big(\mathbf{m}(k)\big).\end{aligned}$$

Both state trajectories start at zero and follow (3) with the same actions. Hence, $x_t\big(\mathbf{m}(k)\big) = x_t(k)$ for every $t \in [T]$. □

APPENDIX B
PROOFS FOR THE ONLINE SDAC CONTROLLER

The OMD results for unnormalized negentropy and its Bregman divergence on the probability simplex are standard [21]. We prove the corresponding forms for the subprobability simplex $\mathcal{M}_H$ used below.

Lemma 6 (Strong convexity of negentropy on the subprobability simplex)**.** *For every $\mathbf{m} \in \mathcal{M}_H$ and $\mathbf{v} \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$,*

$$D_\Psi(\mathbf{m}\|\mathbf{v}) \geq \frac{1}{2}\|\mathbf{m}-\mathbf{v}\|_1^2. \tag{51}$$

Thus, Ψ is 1-strongly convex with respect to $\|\cdot\|_1$ on $\mathcal{M}_H$.

Proof. First suppose $\mathbf{m} > 0$ coordinatewise. Set $\mathbf{d} \triangleq \mathbf{m}-\mathbf{v}$ and $\mathbf{z}_s \triangleq \mathbf{v} + s\mathbf{d}$ for $s \in [0,1]$. Then $\mathbf{z}_s \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$. By (27), $\nabla^2\Psi(\mathbf{z}_s) = \operatorname{diag}(1/z_{s,1}, \dots, 1/z_{s,H})$. Consequently,

$$\begin{aligned}\|\mathbf{d}\|_1^2 &= \left(\sum_{i=1}^H \frac{|d_i|}{\sqrt{z_{s,i}}}\sqrt{z_{s,i}}\right)^2 \\ &\overset{(A)}{\leq} \left(\sum_{i=1}^H \frac{d_i^2}{z_{s,i}}\right)\left(\sum_{i=1}^H z_{s,i}\right) \\ &\overset{(B)}{\leq} \mathbf{d}^\top \nabla^2\Psi(\mathbf{z}_s)\mathbf{d}.\end{aligned} \tag{52}$$

Here (A) is Cauchy–Schwarz, with $z_{s,i} > 0$, and (B) uses $\sum_i z_{s,i} \leq 1$ from (13) and the Hessian above. Taylor's formula with integral remainder and (52) give

$$\begin{aligned}D_\Psi(\mathbf{m}\|\mathbf{v}) &= \int_0^1 (1-s)\mathbf{d}^\top\nabla^2\Psi(\mathbf{z}_s)\mathbf{d}\,ds \\ &\overset{(A)}{\geq} \|\mathbf{d}\|_1^2 \int_0^1 (1-s)\,ds = \frac{1}{2}\|\mathbf{d}\|_1^2.\end{aligned}$$

In (A), the weight $1-s$ is nonnegative on $[0,1]$. For a general $\mathbf{m} \in \mathcal{M}_H$ and $0 < \varepsilon < 1$, apply the bound to $\mathbf{m}^\varepsilon \triangleq (1-\varepsilon)\mathbf{m}+\varepsilon\mathbf{v}$ and let $\varepsilon \downarrow 0$. The result follows from the convention $0\log 0 = 0$ and continuity in the first argument of D_Ψ. □

Lemma 7 (Action clipping as a Bregman projection)**.** *For $t \in [T]$, define the set of parameters compatible with the current state by*

$$\mathcal{B}_t \triangleq \{\mathbf{m} \in \mathcal{M}_H : \langle \boldsymbol{\phi}_t^u, \mathbf{m}\rangle \leq \alpha x_t\}. \tag{53}$$

Let $\mathbf{m}_t^{\mathrm{exec}}$ be the Bregman projection of $\mathbf{m}_t$ onto $\mathcal{B}_t$:

$$\mathbf{m}_t^{\mathrm{exec}} \in \operatorname*{arg\,min}_{\mathbf{m}\in\mathcal{B}_t} D_\Psi(\mathbf{m}\|\mathbf{m}_t). \tag{54}$$

Then

$$\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle = \min\{\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle, \alpha x_t\} = u_t.$$

Proof. The feasibility argument following (30) gives $x_t \geq 0$, so $\mathbf{0} \in \mathcal{B}_t$ by (53). This set is compact and convex because it is the intersection of $\mathcal{M}_H$ and a closed halfspace. The initialization (29) and update (32)–(33) ensure that every coordinate of $\mathbf{m}_t$ is positive. By (28), $D_\Psi(\cdot\|\mathbf{m}_t)$ is continuous on $\mathcal{M}_H$. By Lemma 6, it is strictly convex and, for every $\mathbf{m} \in \mathcal{M}_H$,

$$D_\Psi(\mathbf{m}\|\mathbf{m}_t) \geq \frac{1}{2}\|\mathbf{m}-\mathbf{m}_t\|_1^2 \geq 0.$$

Thus, the projection exists and is unique, and equality holds only at $\mathbf{m} = \mathbf{m}_t$.

If $\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle \leq \alpha x_t$, then $\mathbf{m}_t \in \mathcal{B}_t$ and $\mathbf{m}_t^{\mathrm{exec}} = \mathbf{m}_t$.

Now suppose $\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle > \alpha x_t$. Assume, for contradiction, that the action constraint is slack:

$$\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle < \alpha x_t < \langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle.$$

Set

$$\delta \triangleq \frac{\alpha x_t - \langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle}{\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle - \langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle}.$$

The strict inequalities above give $0 < \delta < 1$. Define

$$\mathbf{m}_\delta \triangleq (1-\delta)\mathbf{m}_t^{\mathrm{exec}} + \delta\mathbf{m}_t.$$

By convexity, $\mathbf{m}_\delta \in \mathcal{M}_H$, and

$$\begin{aligned}&\langle \boldsymbol{\phi}_t^u, \mathbf{m}_\delta\rangle \\ &= \langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle \\ &\quad + \delta\left(\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t\rangle - \langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle\right) \\ &= \alpha x_t.\end{aligned}$$

The last equality substitutes the definition of δ. Thus, $\mathbf{m}_\delta \in \mathcal{B}_t$ by (53). Since $\mathbf{m}_t \notin \mathcal{B}_t$, $\mathbf{m}_t^{\mathrm{exec}} \neq \mathbf{m}_t$, and hence $D_\Psi(\mathbf{m}_t^{\mathrm{exec}}\|\mathbf{m}_t) > 0$. Using convexity and $D_\Psi(\mathbf{m}_t\|\mathbf{m}_t) = 0$, we obtain

$$\begin{aligned}D_\Psi(\mathbf{m}_\delta\|\mathbf{m}_t) &\overset{(A)}{\leq} (1-\delta)D_\Psi(\mathbf{m}_t^{\mathrm{exec}}\|\mathbf{m}_t) \\ &\quad + \delta D_\Psi(\mathbf{m}_t\|\mathbf{m}_t) \\ &= (1-\delta)D_\Psi(\mathbf{m}_t^{\mathrm{exec}}\|\mathbf{m}_t) \\ &\overset{(B)}{<} D_\Psi(\mathbf{m}_t^{\mathrm{exec}}\|\mathbf{m}_t),\end{aligned}$$

where (A) uses convexity in the first argument, and (B) uses $\delta > 0$ and the strict positivity of the divergence established above. This contradicts (54). Therefore, the constraint is active:

$$\langle \boldsymbol{\phi}_t^u, \mathbf{m}_t^{\mathrm{exec}}\rangle = \alpha x_t.$$

Combining the two cases with (30) proves the result. □

Lemma 8 (Closed-form solution of the OMD update)**.** *Fix $\mathbf{m}_t \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$, $\eta > 0$, and $\mathbf{g}_t \in \mathbb{R}^H$. Define $\widetilde{m}_{t+1,i} \triangleq m_{t,i}\exp(-\eta g_{t,i})$ for $i \in [H]$. Then the OMD update* (31) *has the unique solution*

$$\mathbf{m}_{t+1} = \frac{\widetilde{\mathbf{m}}_{t+1}}{\max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\}}.$$

Moreover, $\mathbf{m}_{t+1} \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$. Thus, the OMD iterates initialized by (29) *remain strictly positive.*

Proof. Since $m_{t,i} > 0$, we have $\widetilde{m}_{t+1,i} > 0$ for every $i \in [H]$. For any $\mathbf{m} \in \mathcal{M}_H$,

$$m_i \log\frac{m_i}{\widetilde{m}_{t+1,i}} = m_i\log\frac{m_i}{m_{t,i}} + \eta g_{t,i}m_i,$$

where the identity at $m_i = 0$ uses the convention $0\log 0 = 0$. Substituting into (28) gives

$$\begin{aligned}&\eta\langle \mathbf{g}_t, \mathbf{m}\rangle + D_\Psi(\mathbf{m}\|\mathbf{m}_t) \\ &= \sum_{i=1}^H \left(m_i\log\frac{m_i}{\widetilde{m}_{t+1,i}} - m_i + m_{t,i}\right) \\ &= D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}_{t+1}) + \sum_{i=1}^H (m_{t,i} - \widetilde{m}_{t+1,i}).\end{aligned}$$

Thus, it suffices to minimize $D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}_{t+1})$ over $\mathcal{M}_H$.

Define

$$\mathbf{m}^\star \triangleq \frac{\widetilde{\mathbf{m}}_{t+1}}{\max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\}}.$$

Then $\mathbf{m}^\star > 0$ coordinatewise and

$$\|\mathbf{m}^\star\|_1 = \frac{\|\widetilde{\mathbf{m}}_{t+1}\|_1}{\max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\}} \le 1.$$

If $\|\widetilde{\mathbf{m}}_{t+1}\|_1 \le 1$, the logarithm below is zero; otherwise, $\|\mathbf{m}^\star\|_1 = 1$. Hence,

$$\big(1 - \|\mathbf{m}^\star\|_1\big) \log \max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\} = 0. \tag{55}$$

For any $\mathbf{m} \in \mathcal{M}_H$ and $i \in [H]$, the definition of $\mathbf{m}^\star$ gives

$$\begin{aligned} m_i \log \frac{m_i}{\widetilde{m}_{t+1,i}} &= m_i \log \frac{m_i}{m_i^\star} \\ &\quad - m_i \log \max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\}. \end{aligned}$$

This identity also holds at $m_i = 0$ under the convention $0 \log 0 = 0$. Substituting it into (28) gives

$$\begin{aligned} &D_\Psi(\mathbf{m}\|\widetilde{\mathbf{m}}_{t+1}) - D_\Psi(\mathbf{m}^\star\|\widetilde{\mathbf{m}}_{t+1}) \\ &= D_\Psi(\mathbf{m}\|\mathbf{m}^\star) \\ &\quad + \big(\|\mathbf{m}^\star\|_1 - \|\mathbf{m}\|_1\big) \log \max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\} \\ &= D_\Psi(\mathbf{m}\|\mathbf{m}^\star) \\ &\quad + \big(1 - \|\mathbf{m}\|_1\big) \log \max\{1, \|\widetilde{\mathbf{m}}_{t+1}\|_1\} \\ &\overset{\text{(A)}}{\ge} D_\Psi(\mathbf{m}\|\mathbf{m}^\star) \overset{\text{(B)}}{\ge} \frac{1}{2}\|\mathbf{m} - \mathbf{m}^\star\|_1^2. \end{aligned}$$

The second equality uses (55). In (A), $1 - \|\mathbf{m}\|_1 \ge 0$ by (13), and the logarithm is nonnegative. Step (B) applies Lemma 6 with $\mathbf{v} = \mathbf{m}^\star \in \mathcal{M}_H \cap \mathbb{R}^H_{>0}$. Thus, the objective is minimized uniquely at $\mathbf{m} = \mathbf{m}^\star$. The minimizer has the stated form and is strictly positive. Induction from (29) proves that every iterate is strictly positive. □

APPENDIX C
PROOFS FOR THE REGRET UPPER BOUNDS

Lemma 9 (One-step OMD movement bound)**.** *The OMD update* (31) *with step size* $\eta > 0$ *satisfies*

$$\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \le \eta \|\mathbf{g}_t\|_\infty \le \eta G_\alpha.$$

Proof. By Lemma 8, both iterates are positive. Applying (51) in both directions gives step (A) below; the equality follows by adding the two instances of (28):

$$\begin{aligned} &\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2 \\ &\overset{\text{(A)}}{\le} D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t) + D_\Psi(\mathbf{m}_t\|\mathbf{m}_{t+1}) \\ &= \big\langle \nabla\Psi(\mathbf{m}_{t+1}) - \nabla\Psi(\mathbf{m}_t), \\ &\qquad \mathbf{m}_{t+1} - \mathbf{m}_t \big\rangle \\ &\overset{\text{(B)}}{\le} \eta \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle \\ &\overset{\text{(C)}}{\le} \eta \|\mathbf{g}_t\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \end{aligned}$$

Step (B) uses the first-order optimality condition for (31) with comparison point $\mathbf{m}_t$ and step (C) uses Hölder's inequality. Dividing by $\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1$ gives the first bound when the iterates differ; when they coincide, its left-hand side is zero. Finally, Lemma 3 gives $\|\mathbf{g}_t\|_\infty \le G_\alpha$ and hence the uniform bound. □

Lemma 10 (OMD regret for the surrogate costs)**.** *For every* $\mathbf{m} \in \mathcal{M}_H$*, the update* (31) *satisfies*

$$\sum_{t=1}^T \ell_t(\mathbf{m}_t) - \sum_{t=1}^T \ell_t(\mathbf{m}) \le \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_1)}{\eta} + \frac{\eta}{2} \sum_{t=1}^T \|\mathbf{g}_t\|_\infty^2. \tag{56}$$

Proof. Lemma 3 gives convexity of ℓ_t and $\mathbf{g}_t \in \partial \ell_t(\mathbf{m}_t)$, so

$$\begin{aligned} \ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m}) &\le \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m} \rangle \\ &= \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle \\ &\quad + \langle \mathbf{g}_t, \mathbf{m}_{t+1} - \mathbf{m} \rangle. \end{aligned} \tag{57}$$

The iterates are positive by Lemma 8. Thus, the first-order optimality condition for (31), with comparison point $\mathbf{m} \in \mathcal{M}_H$, gives (A) below. Expanding (28) gives the subsequent equality, even when the comparison point has zero coordinates:

$$\begin{aligned} &\eta \langle \mathbf{g}_t, \mathbf{m}_{t+1} - \mathbf{m} \rangle \\ &\overset{\text{(A)}}{\le} \big\langle \nabla\Psi(\mathbf{m}_{t+1}) - \nabla\Psi(\mathbf{m}_t), \\ &\qquad \mathbf{m} - \mathbf{m}_{t+1} \big\rangle \\ &= D_\Psi(\mathbf{m}\|\mathbf{m}_t) - D_\Psi(\mathbf{m}\|\mathbf{m}_{t+1}) \\ &\quad - D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t). \end{aligned} \tag{58}$$

Substituting (58) into (57) gives

$$\begin{aligned} \ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m}) &\le \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_t)}{\eta} - \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_{t+1})}{\eta} \\ &\quad + \langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle \\ &\quad - \frac{D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t)}{\eta}. \end{aligned} \tag{59}$$

The last two terms in (59) satisfy

$$\begin{aligned} &\langle \mathbf{g}_t, \mathbf{m}_t - \mathbf{m}_{t+1} \rangle - \frac{D_\Psi(\mathbf{m}_{t+1}\|\mathbf{m}_t)}{\eta} \\ &\overset{\text{(A)}}{\le} \|\mathbf{g}_t\|_\infty \|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \\ &\quad - \frac{\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1^2}{2\eta} \\ &= \frac{\eta}{2}\|\mathbf{g}_t\|_\infty^2 \\ &\quad - \frac{\big(\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 - \eta\|\mathbf{g}_t\|_\infty\big)^2}{2\eta} \\ &\overset{\text{(B)}}{\le} \frac{\eta}{2}\|\mathbf{g}_t\|_\infty^2. \end{aligned} \tag{60}$$

Step (A) uses Hölder's inequality and (51) with $(\mathbf{m}, \mathbf{v}) = (\mathbf{m}_{t+1}, \mathbf{m}_t)$. After completing the square, (B) discards a nonnegative term since $\eta > 0$. Substituting (60) into (59) and summing over t gives

$$\begin{aligned} \sum_{t=1}^T \ell_t(\mathbf{m}_t) - \sum_{t=1}^T \ell_t(\mathbf{m}) &\le \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_1)}{\eta} - \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_{T+1})}{\eta} \\ &\quad + \frac{\eta}{2} \sum_{t=1}^T \|\mathbf{g}_t\|_\infty^2. \end{aligned}$$

The Bregman terms telescope. By (51), $D_\Psi(\mathbf{m}\|\mathbf{m}_{T+1}) \ge 0$, so dropping its negative proves (56). □

Proof of Lemma 5. Let $d_t \triangleq |x_t - x_t(\mathbf{m}_t)|$. Both trajectories start at zero, so $d_1 = 0$. By (3), the clipping rule (30), and feasibility of the fixed policy (Lemma 2), for $1 \le t < T$ we have

$$x_{t+1} = [\alpha x_t - u_t(\mathbf{m}_t)]_+ + w_t,$$
$$x_{t+1}(\mathbf{m}_t) = [\alpha x_t(\mathbf{m}_t) - u_t(\mathbf{m}_t)]_+ + w_t.$$

The triangle inequality and the affine formula (46) therefore yield

$$\begin{aligned} d_{t+1} &\le |x_{t+1} - x_{t+1}(\mathbf{m}_t)| \\ &\quad + |x_{t+1}(\mathbf{m}_t) - x_{t+1}(\mathbf{m}_{t+1})| \\ &\overset{(A)}{\le} \alpha d_t + |\langle \boldsymbol{\phi}^x_{t+1}, \mathbf{m}_t - \mathbf{m}_{t+1}\rangle| \\ &\overset{(B)}{\le} \alpha d_t + \frac{\alpha}{1-\alpha}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \end{aligned} \tag{61}$$

In (A), $|[z]_+ - [z']_+| \le |z - z'|$ is applied with $z = \alpha x_t - u_t(\mathbf{m}_t)$ and $z' = \alpha x_t(\mathbf{m}_t) - u_t(\mathbf{m}_t)$; the common action and arrival cancel. Step (B) uses Hölder's inequality and (47) at time $t+1$. Summing (61) and using $d_1 = 0$ gives

$$\begin{aligned} \sum_{t=1}^{T} d_t &= \sum_{t=1}^{T-1} d_{t+1} \\ &\le \alpha \sum_{t=1}^{T-1} d_t + \frac{\alpha}{1-\alpha}\sum_{t=1}^{T-1}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \\ &\overset{(A)}{\le} \alpha \sum_{t=1}^{T} d_t + \frac{\alpha}{1-\alpha}\sum_{t=1}^{T-1}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \end{aligned}$$

Step (A) uses $\alpha d_T \ge 0$. We subtract $\alpha \sum_{t=1}^{T} d_t$ from both sides and divide by $1 - \alpha > 0$ to obtain

$$\sum_{t=1}^{T} d_t \le \frac{\alpha}{(1-\alpha)^2}\sum_{t=1}^{T-1}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1. \tag{62}$$

When $T = 1$, the movement sum is empty and both sides are zero.

For every $t \in [T]$, the clipping rule (30) gives

$$\begin{aligned} 0 \le u_t(\mathbf{m}_t) - u_t &= [u_t(\mathbf{m}_t) - \alpha x_t]_+ \\ &\overset{(A)}{\le} [\alpha x_t(\mathbf{m}_t) - \alpha x_t]_+ \\ &\le \alpha d_t. \end{aligned} \tag{63}$$

Step (A) uses $u_t(\mathbf{m}_t) \le \alpha x_t(\mathbf{m}_t)$ from Lemma 2 and monotonicity of $[\cdot]_+$. Both state–action pairs are feasible, so (4) places them in $\mathcal{D}_\alpha$. Hence,

$$\begin{aligned} &\sum_{t=1}^{T}\big(c_t(x_t, u_t) - \ell_t(\mathbf{m}_t)\big) \\ &\overset{(A)}{\le} \sum_{t=1}^{T}\big(L_x d_t + L_u|u_t - u_t(\mathbf{m}_t)|\big) \\ &\overset{(B)}{\le} \frac{\alpha(L_x + \alpha L_u)}{(1-\alpha)^2}\sum_{t=1}^{T-1}\|\mathbf{m}_{t+1} - \mathbf{m}_t\|_1 \\ &\overset{(C)}{\le} \frac{\alpha\eta(T-1)G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2} \\ &\le \frac{\alpha\eta T G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2}. \end{aligned}$$

Step (A) uses (18) and (6); (B) uses (63) and (62); (C) applies Lemma 9 to the $T-1$ increments. The last step uses $T-1 \le T$ and nonnegativity of the coefficient, proving (38). □

Proof of Theorem 1. Fix $\mathbf{m} \in \mathcal{M}_H$. We first bound the initial Bregman divergence. Substituting (29) into (28) gives

$$\begin{aligned} D_\Psi(\mathbf{m}\|\mathbf{m}_1) &= \sum_{i=1}^{H} m_i \log m_i \\ &\quad + \|\mathbf{m}\|_1\big(\log(H+1) - 1\big) + \frac{H}{H+1} \\ &\overset{(A)}{\le} (1 - \|\mathbf{m}\|_1)\frac{H}{H+1} \\ &\quad + \|\mathbf{m}\|_1\left(\log(H+1) - \frac{1}{H+1}\right) \\ &\overset{(B)}{\le} \log(H+1). \end{aligned} \tag{64}$$

Step (A) discards $\sum_i m_i \log m_i \le 0$ and regroups the remaining terms, using $0 \log 0 = 0$. In (B), $\|\mathbf{m}\|_1 \in [0,1]$ by (13), and both terms in this convex combination are at most $\log(H+1)$: indeed, $\log(H+1) = \int_1^{H+1} z^{-1}\,dz \ge H/(H+1)$.

Using the surrogate definition (18), we obtain

$$\begin{aligned} J_T^{\mathrm{on}} - J_T(\mathbf{m}) &= \sum_{t=1}^{T}\big(c_t(x_t, u_t) - \ell_t(\mathbf{m}_t)\big) \\ &\quad + \sum_{t=1}^{T}\big(\ell_t(\mathbf{m}_t) - \ell_t(\mathbf{m})\big) \\ &\overset{(A)}{\le} \frac{D_\Psi(\mathbf{m}\|\mathbf{m}_1)}{\eta} + \frac{\eta}{2}\sum_{t=1}^{T}\|\mathbf{g}_t\|_\infty^2 \\ &\quad + \frac{\alpha\eta T G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2} \\ &\overset{(B)}{\le} \frac{\log(H+1)}{\eta} + \frac{\eta T G_\alpha^2}{2} \\ &\quad + \frac{\alpha\eta T G_\alpha(L_x + \alpha L_u)}{(1-\alpha)^2} \\ &= \frac{\log(H+1)}{\eta} + \eta T \Gamma_\alpha. \end{aligned}$$

Step (A) adds (56) and (38). Step (B) uses (64) and the gradient bound in Lemma 3; the last equality is (35). Taking the maximum over $\mathbf{m} \in \mathcal{M}_H$ and using (11) proves (34). Since $H, T \ge 1$ and $\Gamma_\alpha > 0$, the step size (36) is positive and satisfies

$$\frac{\log(H+1)}{\eta^*} = \eta^* T \Gamma_\alpha = \sqrt{\Gamma_\alpha T \log(H+1)},$$

which gives (37). □

Proof of Corollary 2. Fix an infinite-memory SDAC policy $\mathbf{m} \in \mathcal{M}_\infty$. By Lemma 4, its truncation satisfies $\mathbf{m}_{H_T}(\mathbf{m}) \in$

$\mathcal{M}_{H_T}$. Comparing first with this truncation gives

$$\begin{aligned} J_T^{\mathrm{on}} - J_T(\mathbf{m}) &= J_T^{\mathrm{on}} - J_T\big(\mathbf{m}_{H_T}(\mathbf{m})\big) \\ &\quad + J_T\big(\mathbf{m}_{H_T}(\mathbf{m})\big) - J_T(\mathbf{m}) \\ &\overset{\text{(A)}}{\le} \mathrm{Reg}_T^{\mathrm{SDAC}}(H_T) \\ &\quad + J_T\big(\mathbf{m}_{H_T}(\mathbf{m})\big) - J_T(\mathbf{m}) \\ &\overset{\text{(B)}}{\le} \mathrm{Reg}_T^{\mathrm{SDAC}}(H_T) \\ &\quad + \left(L_u + \frac{L_x}{1-\alpha}\right)\alpha^{H_T+1}T. \end{aligned}$$

Step (A) uses (11) with $H = H_T$ and the feasible comparison point $\mathbf{m}_{H_T}(\mathbf{m})$; (B) uses (24) with the same memory horizon. The final bound is independent of $\mathbf{m}$. Taking the supremum over $\mathcal{M}_\infty$, using (40), and applying (37) with $H = H_T$ and the corresponding step size (36) proves (41).

For the asymptotic rate, $T \ge 1$ and $0 < \alpha < 1$ imply $\log T/\log(1/\alpha) \ge 0$. The ceiling in (39) raises this quantity by at most one; the outer maximum with 1 preserves the same upper bound. Hence,

$$\frac{\log T}{\log(1/\alpha)} \le H_T \le 1 + \frac{\log T}{\log(1/\alpha)}. \tag{65}$$

In particular, $H_T = 1$ when $T = 1$. Since $0 < \alpha < 1$, we obtain

$$\begin{aligned} \alpha^{H_T+1}T &\overset{\text{(A)}}{\le} \alpha^{1+\log T/\log(1/\alpha)}T \\ &= \alpha \exp\!\left(\frac{\log\alpha}{\log(1/\alpha)}\log T\right)T \\ &= \alpha e^{-\log T}T = \alpha. \end{aligned}$$

Step (A) uses the lower bound in (65) and the fact that powers of α decrease with the exponent. The final line uses $\log\alpha = -\log(1/\alpha)$. The upper bound in (65) and monotonicity of $\log$ also give, for fixed α as $T \to \infty$,

$$\log(H_T+1) \le \log\!\left(2 + \frac{\log T}{\log(1/\alpha)}\right) = O(\log\log T).$$

Thus, for fixed α, L_x, L_u, the right-hand side of (41) is $O\big(\sqrt{T\log\log T}\big) = o(T)$. For fixed-fraction policies, Corollary 1 gives $\mathbf{m}(k) \in \mathcal{M}_\infty$ for every $k \in [0,\alpha]$. Consequently,

$$\begin{aligned} \inf_{\mathbf{m}\in\mathcal{M}_\infty} J_T(\mathbf{m}) &\le \min_{k\in[0,\alpha]} J_T(\mathbf{m}(k)) \\ &= \min_{k\in[0,\alpha]} \sum_{t=1}^{T} c_t\big(x_t(k), u_t(k)\big). \end{aligned}$$

Subtracting from J_T^{on} yields the stated fixed-fraction regret bound. □

APPENDIX D
PROOFS FOR THE REGRET LOWER BOUND

Proof of Theorem 2. Fix a causal feasible controller $\mathcal{A}$. Let $\xi_1, \dots, \xi_T$ be independent Rademacher random variables, independent of the controller's randomization. Set

$$w_t = 1, \qquad c_t(x,u) = \xi_t(L_x x - L_u u), \qquad t \in [T].$$

Each cost is affine with gradient $\xi_t(L_x, -L_u)$, so it is convex and satisfies (8) because $|\xi_t| = 1$. Also,

$$\begin{aligned} |c_t(x,u) - c_t(x',u')| &= |L_x(x-x') - L_u(u-u')| \\ &\le L_x|x-x'| + L_u|u-u'|. \end{aligned}$$

Thus, every realization satisfies (6) and gives an admissible sequence.

Consider the two fixed SDAC parameters

$$\mathbf{m}^{(0)} = \mathbf{0}, \qquad \mathbf{m}^{(1)} = \mathbf{e}_1 = (1,0,\dots,0) \in \mathcal{M}_H.$$

Both trajectories start at $(x_1,u_1) = (0,0)$. For $t \ge 2$, (14) and (3), with $w_t = 1$, give

$$\begin{aligned} &u_t(\mathbf{m}^{(0)}) = 0, \quad x_t(\mathbf{m}^{(0)}) = \sum_{s=0}^{t-2}\alpha^s = \frac{1-\alpha^{t-1}}{1-\alpha}, \\ &u_t(\mathbf{m}^{(1)}) = \alpha, \quad x_t(\mathbf{m}^{(1)}) = 1. \end{aligned}$$

The last identity follows by induction from $x_2(\mathbf{m}^{(1)}) = 1$ and $\alpha\cdot 1 - \alpha + 1 = 1$. Hence, for $t \ge 2$,

$$x_t(\mathbf{m}^{(0)}) - x_t(\mathbf{m}^{(1)}) = \frac{1-\alpha^{t-1}}{1-\alpha} - 1 = \frac{\alpha(1-\alpha^{t-2})}{1-\alpha}.$$

Since both policies incur zero cost at $t = 1$, (10) and (43) give

$$\begin{aligned} &J_T(\mathbf{m}^{(0)}) - J_T(\mathbf{m}^{(1)}) \\ &\quad = \sum_{t=2}^{T}\xi_t\left(\frac{\alpha L_x(1-\alpha^{t-2})}{1-\alpha} + \alpha L_u\right) \\ &\quad = \sum_{t=2}^{T}\xi_t\beta_t. \end{aligned} \tag{66}$$

By causality, (x_t,u_t) depends only on past signs and the controller's randomization, so it is independent of ξ_t. Since $\mathbb{E}[\xi_t] = 0$,

$$\begin{aligned} &\mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}[J_T^{\mathrm{on}}] \\ &\quad = \sum_{t=1}^{T}\mathbb{E}[\xi_t]\,\mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}[L_x x_t - L_u u_t] = 0. \end{aligned} \tag{67}$$

The two SDAC-policy trajectories are deterministic because $w_t = 1$ at every time and their actions do not depend on the costs. Thus, for $j \in \{0,1\}$,

$$\begin{aligned} &\mathbb{E}_{\boldsymbol{\xi}}[J_T(\mathbf{m}^{(j)})] \\ &\quad = \sum_{t=1}^{T}\mathbb{E}[\xi_t]\big(L_x x_t(\mathbf{m}^{(j)}) - L_u u_t(\mathbf{m}^{(j)})\big) = 0. \end{aligned} \tag{68}$$

Using (11) and $\min\{a,b\} = (a+b-|a-b|)/2$, we obtain

$$\begin{aligned} \mathrm{Reg}_T^{\mathrm{SDAC}}(H) &\overset{\text{(A)}}{\ge} J_T^{\mathrm{on}} - \min\{J_T(\mathbf{m}^{(0)}), J_T(\mathbf{m}^{(1)})\} \\ &= J_T^{\mathrm{on}} - \frac{J_T(\mathbf{m}^{(0)}) + J_T(\mathbf{m}^{(1)})}{2} \\ &\quad + \frac{1}{2}\left|J_T(\mathbf{m}^{(0)}) - J_T(\mathbf{m}^{(1)})\right|. \end{aligned}$$

Step (A) restricts the minimum to two parameters in $\mathcal{M}_H$; this increases the minimum and decreases its negative. Taking expectations gives

$$\begin{aligned}\mathbb{E}_{\boldsymbol{\xi},\mathcal{A}}[\mathrm{Reg}_T^{\mathrm{SDAC}}(H)] &\overset{(A)}{\geq} \frac{1}{2}\mathbb{E}_{\boldsymbol{\xi}}\left|\sum_{t=2}^{T}\xi_t\beta_t\right| \\ &\overset{(B)}{\geq} \frac{1}{2\sqrt{2}}\sqrt{\sum_{t=2}^{T}\beta_t^2}.\end{aligned} \tag{69}$$

Step (A) uses the preceding display, the zero expectations in (67)–(68), and (66). Step (B) applies the $p = 1$ Khintchine inequality [23] to the deterministic real coefficients $\beta_2, \ldots, \beta_T$ and independent Rademacher signs. Its constant $1/\sqrt{2}$, multiplied by $1/2$, gives $1/(2\sqrt{2})$. The left side of (69) is the average of $\mathbb{E}_{\mathcal{A}}[\mathrm{Reg}_T^{\mathrm{SDAC}}(H)]$ over the 2^T sign sequences. At least one sequence $\boldsymbol{\xi}^\star$ attains or exceeds this average, with expectation only over the controller's randomization. Fixing $\boldsymbol{\xi}^\star$ before the interaction gives the required deterministic oblivious sequence. □

Proof of Corollary 3. For $t = \lceil \log 2/\log(1/\alpha)\rceil + 2, \ldots, T$,

$$\begin{aligned}\alpha^{t-2} &\overset{(A)}{\leq} \alpha^{\lceil \log 2/\log(1/\alpha)\rceil} \\ &\overset{(B)}{\leq} \alpha^{\log 2/\log(1/\alpha)} = \frac{1}{2}.\end{aligned}$$

Steps (A) and (B) use that $s \mapsto \alpha^s$ is decreasing for $0 < \alpha < 1$: first $t - 2 \geq \lceil \log 2/\log(1/\alpha)\rceil$, then $\lceil z\rceil \geq z$ with $z = \log 2/\log(1/\alpha)$. The equality uses $\log\alpha = -\log(1/\alpha)$. Thus,

$$\begin{aligned}\beta_t &\overset{(A)}{\geq} \alpha\left(L_u + \frac{L_x}{2(1-\alpha)}\right) \\ &\overset{(B)}{\geq} \frac{\alpha}{2}\left(L_u + \frac{L_x}{1-\alpha}\right) = \frac{G_\alpha}{2}.\end{aligned} \tag{70}$$

Step (A) substitutes $1 - \alpha^{t-2} \geq 1/2$ in (43), using $L_x/(1-\alpha) > 0$. Step (B) uses $L_u \geq L_u/2$; the equality is (19). By (44), the number of these indices satisfies

$$T - \left\lceil \frac{\log 2}{\log(1/\alpha)}\right\rceil - 1 \geq \frac{T}{2}. \tag{71}$$

Theorem 2 therefore gives

$$\begin{aligned}\mathbb{E}_{\mathcal{A}}\big[\mathrm{Reg}_T^{\mathrm{SDAC}}(H)\big] &\overset{(A)}{\geq} \frac{1}{2\sqrt{2}}\sqrt{\sum_{t=2}^{T}\beta_t^2} \\ &\overset{(B)}{\geq} \frac{1}{2\sqrt{2}}\left[\frac{T}{2}\left(\frac{G_\alpha}{2}\right)^2\right]^{1/2} \\ &= \frac{G_\alpha}{8}\sqrt{T}.\end{aligned}$$

Step (A) is (42). Step (B) retains the indices counted in (71) and applies (70); all discarded squares are nonnegative. The last equality uses $(2\sqrt{2})^{-1}(T/2)^{1/2}(G_\alpha/2) = G_\alpha\sqrt{T}/8$ and $G_\alpha > 0$. □

REFERENCES

[1] N. Agarwal, B. Bullins, E. Hazan, S. Kakade, and K. Singh, "Online control with adversarial disturbances," in *Proceedings of the 36th International Conference on Machine Learning*, ser. Proceedings of Machine Learning Research, vol. 97. PMLR, 2019, pp. 111–119.

[2] N. Golowich, E. Hazan, Z. Lu, D. Rohatgi, and Y. J. Sun, "Online control in population dynamics," in *Advances in Neural Information Processing Systems*, vol. 37, 2024, pp. 111 571–111 613. [Online]. Available: https://papers.nips.cc/paper_files/paper/2024/hash/ca4f6e86453e4b117dd3263792053cf5-Abstract-Conference.html

[3] Y. Li, S. Das, and N. Li, "Online optimal control with affine constraints," *Proceedings of the AAAI Conference on Artificial Intelligence*, vol. 35, no. 10, pp. 8527–8537, 2021. [Online]. Available: https://ojs.aaai.org/index.php/AAAI/article/view/17035

[4] X. Liu, Z. Yang, and L. Ying, "Online nonstochastic control with adversarial and static constraints," in *Proceedings of the 40th International Conference on Machine Learning*, ser. Proceedings of Machine Learning Research, vol. 202. PMLR, 2023, pp. 22 277–22 288. [Online]. Available: https://proceedings.mlr.press/v202/liu23at.html

[5] R. Kumar, S. Dean, and R. Kleinberg, "Online convex optimization with unbounded memory," in *Advances in Neural Information Processing Systems*, vol. 36, 2023, pp. 26 229–26 270. [Online]. Available: https://proceedings.neurips.cc/paper_files/paper/2023/hash/531230cfac80c65017ad0f85d3031edc-Abstract-Conference.html

[6] D. Shaviv and A. Özgür, "Universally near optimal online power control for energy harvesting nodes," *IEEE Journal on Selected Areas in Communications*, vol. 34, no. 12, pp. 3620–3631, 2016. [Online]. Available: https://arxiv.org/abs/1511.00353

[7] A. Arafa, A. Baknina, and S. Ulukus, "Online fixed fraction policies in energy harvesting communication systems," *IEEE Transactions on Wireless Communications*, vol. 17, no. 5, pp. 2975–2986, 2018.

[8] A. Zibaeenejad and J. Chen, "The optimal power control policy for an energy harvesting system with look-ahead: Bernoulli energy arrivals," in *2019 IEEE International Symposium on Information Theory (ISIT)*, 2019, pp. 116–120, extended version: arXiv:1904.12281. [Online]. Available: https://arxiv.org/abs/1904.12281

[9] H. Yu and M. J. Neely, "Learning-aided optimization for energy-harvesting devices with outdated state information," *IEEE/ACM Transactions on Networking*, vol. 27, no. 4, pp. 1501–1514, 2019.

[10] K. Asgari and M. J. Neely, "Bregman-style online convex optimization with energy harvesting constraints," *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, vol. 4, no. 3, 2020. [Online]. Available: https://doi.org/10.1145/3428337

[11] Q. Lin, J. Su, and M. Chen, "Optimal algorithms for online Age-of-Information optimization in energy harvesting systems," *IEEE Transactions on Networking*, vol. 33, no. 6, pp. 3146–3161, 2025.

[12] L. Tassiulas and A. Ephremides, "Stability properties of constrained queueing systems and scheduling policies for maximum throughput in multihop radio networks," *IEEE Transactions on Automatic Control*, vol. 37, no. 12, pp. 1936–1948, 1992.

[13] ——, "Dynamic server allocation to parallel queues with randomly varying connectivity," *IEEE Transactions on Information Theory*, vol. 39, no. 2, pp. 466–478, 1993.

[14] N. McKeown, A. Mekkittikul, V. Anantharam, and J. Walrand, "Achieving 100% throughput in an input-queued switch," *IEEE Transactions on Communications*, vol. 47, no. 8, pp. 1260–1267, 1999.

[15] M. J. Neely, *Stochastic Network Optimization with Application to Communication and Queueing Systems*. Morgan & Claypool Publishers, 2010.

[16] M. A. Khojastepour and A. Sabharwal, "Delay-constrained scheduling: Power efficiency, filter design, and bounds," in *IEEE INFOCOM 2004*, vol. 3. IEEE, 2004, pp. 1938–1949.

[17] L. Yang, M. H. Hajiesmaili, R. Sitaraman, A. Wierman, E. Mallada, and W. S. Wong, "Online linear optimization with inventory management constraints," *Proceedings of the ACM on Measurement and Analysis of Computing Systems*, vol. 4, no. 1, 2020.

[18] M. Hihat and A. Fermanian, "Online policy selection for inventory problems," *arXiv preprint arXiv:2411.19269*, 2024. [Online]. Available: https://arxiv.org/abs/2411.19269

[19] P. A. P. Moran, "A probability theory of dams and storage systems," *Australian Journal of Applied Science*, vol. 5, no. 2, pp. 116–124, 1954.

[20] R. T. Rockafellar and R. J.-B. Wets, *Variational Analysis*, ser. Grundlehren der mathematischen Wissenschaften. Berlin: Springer, 1998, vol. 317.

[21] E. Hazan, "Introduction to online convex optimization," *Foundations and Trends in Optimization*, vol. 2, no. 3–4, pp. 157–325, 2016.

[22] E. Hazan, A. Agarwal, and S. Kale, "Logarithmic regret algorithms for online convex optimization," *Machine Learning*, vol. 69, no. 2–3, pp. 169–192, 2007.

[23] S. J. Szarek, "On the best constants in the Khinchin inequality," *Studia Mathematica*, vol. 58, no. 2, pp. 197–208, 1976.